efesotomasyon.com

AC Servo Drives Σ-V Series Product Catalog



YASKAWA™

Certified for ISO9001 and ISO14001

JQA-0422 JQA-EM0202 JQA-EM0924

Build the machine you've dreamed of, today!

AC servo drive

Sigma Five

Σ-V




You want maximum effect quickly and easily,
as does every engineer in the field.
And now the Σ-V series is here with
the practical answer to your dreams!

How many times have you heard people say servos need adjustment to work well? Our new tuning-less function means it works as soon as you hook it up!

And if you want more performance than ever before, the Σ-V series advanced autotuning function lets you set up for it rapidly.

Advanced technology makes possible a host of safety standards compliance for the first time in Japan (as of April 2007), compliance with key international standards, a diverse motor line-up, compact size, high speed and simple maintenance: everything you need to answer today's requirements.



International Standards

c UL us LISTED c UL us CE

Safety Standards


Safety Stop-0 (Standard)

RoHS Directive

RoHS Directive Stands for the EU directive on the Restriction of the Use of Certain Hazardous Substances in Electrical and Electronic Equipment.

Features

Superlative Performance



Operate your machinery faster and with higher precision than ever!

The Σ-V delivers the highest performance in the industry.

The best amplifier response in the industry slashes settling time


In-house comparison: 1/12th

Outstanding frequency response **16 kHz***



* Representative value when using a combination of the SGMAV-02ADA servomotor and SGDV-1R6A SERVOPACK at one time of the load moment of inertia ratio.

● Servo Adjustment Example: When the ball screw slider was run using a combination of the SGMJV-02ADA servomotor and SGDV-1R6A SERVOPACK.



Settling Time 0 to 4 ms !

Enhanced vibration suppression

Existing functions to minimize vibration have been enhanced, and new ones added, improving tracking and further improving settling time. Vibration and noise during driving have also been cut, along with vibration at machine edges when stopping.

Contributing to machine performance in conjunction with a medium-inertia motor

Small Capacity

SGMJV Series



Low Heating

Improved motor constants have reduced both losses and heating.

Better Cycle Time

Instantaneous peak torque has been boosted from 300% to 350%, contributing to shorter cycle times

Ease of Use

Moment of inertia ratio has been doubled in the same motor, reducing the moment of inertia ratio and boosting gain for faster settling

Medium Capacity

SGMGV Series



Compact Design

Smaller package and about 20% lighter, but with the same moment of inertia ratio as the conventional model. A small encoder connector is applied.

Improved Vibration Resistance

New coupling delivers typical 5G vibration resistance

Encoder resolution 1,048,576 pulses/revolution


Simple Start-up

Making servo adjustment quick and simple

Unpacking → Installation and Wiring → Basic Parameter Setting → Trial Operation

Faster setup

SigmaWin+



Setup Wizard
Simple parameter set-up with wizard-aided input

Wiring Check Function
The SigmaWin+ wiring check function checks your wiring in a single operation

USB1.1 Support

Trace Function
Realtime trace of adjustment state means you can check instantly.

Full of handy functions for start-up and more effective operation!

Selection

Servomotor capacity selection software


SigmaJunmaSize+

Optimal selection for your application:
With consideration of moment of inertia, DB resistance, etc.



Let the Σ-V series simplify your life!

Gain and Filter Adjustment → Operation



New Advanced Autotuning Window

Simple Tuning

Get up and running quickly after hooking up the motor
- New Tuning-less Function

Even without servo adjustment and with load changes, oscillation- and vibration-free drive is possible up to 20 times the load moment of inertia.

Settling time: 100 to 150 ms level

Minimize settling time with less vibration
- New Advanced Autotuning

The reference filter and feedback gain adjustment functions have a new automatic feed forward gain adjustment for optimal adjustment performance. The friction compensation function automatically cancels out the effect of friction on machine characteristics.

Settling time: 10 ms level

Fine-tuning is a must
- New "One-parameter" Tuning

Fine-tuning can tweak machine performance to the max.

Settling time: 0 to 4 ms level


Maintenance

Faster Troubleshooting


Engineering tool

SigmaWin+

Alarm diagnostic function:
Presumes possible causes of the alarm and immediately displays suggested corrective actions.



Outstanding Expandability



Use servos that really fit into your system

A rich selection of models and options to match your requirements

- **Extensive variety of motors to match any machine**


  Medium-inertia servomotors ➡ Improved control stability
  Low-inertia servomotors ➡ High-speed acceleration and deceleration

- **Selection of servo actuators**

  Support for direct drive servomotors, linear servomotors and linear sliders

- **Standard support for analog voltage/pulse train reference series or MECHATROLINK-II communications reference series**

- **Wide selection of option modules for various communication interfaces and feedback**




The first in the industry in Japan!
(as of April 2007)

- **Compliant with applicable safety standards**

  Easy compliance with machine safety standards

- **Motor line-up to handle a wide range of markets and applications**



Product Line-up

Servomotors

◆Rotary Servomotors (Small Capacity)



SGMJV
(Medium Inertia, Small Capacity)
50 W to 750 W



SGMAV
(Low Inertia, Small Capacity)
50 W to 1 kW

◆Rotary Servomotors (Medium Capacity)




SGMGV
(Medium Inertia, Medium Capacity)
300 W to 15 kW



SGMSV
(Low Inertia, Medium Capacity)
1.0 kW to 7.0 kW

◆Direct Drive Servomotors



SGMCS (Small Capacity)
2 to 3.5 Nm



SGMCS (Medium Capacity)
45 to 200 Nm

◆Linear Servomotors

Linear Σ Series



SGLGW (Coreless Type)
12.5 to 750 N



SGLFW (With F-type Iron Core)
25 to 1120 N



SGLTW (With T-type Iron Core)
130 to 1300 N

◆Cylinder Type Linear Servomotor

Σ-Stick Series



SGLC
17 to 180 N


◆Linear Slides Σ -Trac Series



SGT1F (Σ-Trac)
47 to 560 N



SGTMM (Σ -Trac-μ)
3.5 to 7 N



SGTMF (Σ -Trac-MAG)
90 to 240 N

SERVOPACKs

◆ Analog Voltage/Pulse Train Reference



SGDV-□□□□01/05 SERVOPACK

◆ MECHATROLINK-II Communications Reference



SGDV-□□□□11/15 SERVOPACK

◆ Command Option Attachable Type



SGDV SERVOPACK with Additional Options

Available Option Modules include:
- EtherCAT (CoE) Communication
- Fully Closed Loop Control
- MP2600iec Single Axis Controller

◆Stock Status Definitions

The product selection tables in this catalog contain stock status codes, which are subject to change. The codes are defined below:

S Stock Item

Normally 3 to 5 days leadtime for most order quantities. 3 to 5 weeks maximum if temporary outages occur. For critical lead time or large quantity shipments, check with your Yaskawa sales representative.

LS Limited Stock Item

Typically small quantites are available from stock. Items may become stock items as demand increases.

NS Non-Stock Item

Non-stock items typically carry a 12 - 16 week delivery time.

GS Global Support Item

Global Support Products are non-stock items that are not promoted in North America. Delivery is typically 14-20 weeks depending on price availability. Local repair and service capabilities may be limited. Customers should consider stock or limited stock substitutes if possible. Global Support Products are found on some machines imported to North America. In many cases the fastest delivery of spare parts can be obtained by contacting the original machine builder. Yaskawa Electric America can make special arrangements for servicing customers on a contract basis.

◆Rotary Servomotors and SERVOPACKs

Rotary Servomotor Model		Capacity	SERVOPACK Model SGDV-□□□□			Stock Status
			Single-phase 100 VAC	Three-phase 200 VAC	Three-phase 400 VAC	
SGMJV (Medium Inertia, Small Capacity) 3000min^{-1}	SGMJV-A5A	50 W	R70F	R70A	—	S
	SGMJV-01A	100 W	R90F	R90A		
	SGMJV-02A	200 W	2R1F	1R6A		
	SGMJV-04A	400 W	2R8F	2R8A		
	SGMJV-08A	750 W	—	5R5A		
SGMAV (Low Inertia, Small Capacity) 3000min^{-1}	SGMAV-A5A	50 W	R70F	R70A	—	S
	SGMAV-01A	100 W	R90F	R90A		
	SGMAV-C2A	150 W	2R1F	1R6A		
	SGMAV-02A	200 W				
	SGMAV-04A	400 W	2R8F	2R8A		
	SGMAV-06A	550 W	—	5R5A		
	SGMAV-08A	750 W				
	SGMAV-10A	1.0 kW		120A*1		
SGMGV (Medium Inertia, Medium Capacity) 1500min^{-1}	SGMGV-03A	300 W	—	3R8A	—	S
	SGMGV-05A	450 W				
	SGMGV-09A	850 W		7R6A		
	SGMGV-13A	1.3 kW		120A		
	SGMGV-20A	1.8 kW		180A		
	SGMGV-30A	2.9 kW		330A/200A*2		
	SGMGV-44A	4.4 kW		330A		
	SGMGV-55A	5.5 kW		470A		
	SGMGV-75A	7.5 kW		550A		
	SGMGV-1AA	11 kW		590A		
	SGMGV-1EA	15 kW		780A		
	SGMGV-03D	300 W	—	—	1R9D	S
	SGMGV-05D	450 W				
	SGMGV-09D	850 W			3R5D	
	SGMGV-13D	1.3 kW			5R4D	
	SGMGV-20D	1.8 kW			8R4D	
	SGMGV-30D	2.9 kW			120D	
	SGMGV-44D	4.4 kW			170D	
	SGMGV-55D	5.5 kW			210D	
	SGMGV-75D	7.5 kW			260D	
	SGMGV-1AD	11 kW			280D	
	SGMGV-1ED	15 kW			370D	
SGMSV (Low Inertia, Medium Capacity) 3000min-1	SGMSV-10A	1.0 kW	—	7R6A	—	S
	SGMSV-15A	1.5 kW		120A		
	SGMSV-20A	2.0 kW		180A		
	SGMSV-25A	2.5 kW		200A		
	SGMSV-30A	3.0 kW				
	SGMSV-40A	4.0 kW		330A		
	SGMSV-50A	5.0 kW				
	SGMSV-70A	7.0 kW		550A		
	SGMSV-10D	1.0 kW		—	3R5D	
	SGMSV-15D	1.5 kW			5R4D	
	SGMSV-20D	2.0 kW			8R4D	
	SGMSV-25D	2.5 kW			120D	
	SGMSV-30D	3.0 kW				
	SGMSV-40D	4.0 kW			170D	
	SGMSV-50D	5.0 kW				

*1: Single-phase 200 VAC SERVOPACKs are also available (SERVOPACK model: SGDV-120A□□A008000,
*2: The combination of the SGDV-200A SERVOPACK and the SGMGV-30A servomotor must be used at the following reduction ratings.

		Reduction Ratings	Ratings
Rated Current	A_{rms}	19.6	23.8
Rated Torque	Nm	15.3	18.6
Allowable Load Moment of Inertia		3 times	5 times

◆Linear Servomotors and SERVOPACKs

Linear Servomotor Model		Rated Force N	Peak Force N	SERVOPACK Model SGDV-□□□□			Stock Staus
				Single-phase 100 VAC	Three-phase 200 VAC	Three-phase 400 VAC	
SGLGW (Coreless Type, With standard magnetic way)	SGLGW-30A050C	12.5	40	R70F	R70A	—	S
	SGLGW-30A080C	25	80	R90F	R90A		
	SGLGW-40A140C	47	140				
	SGLGW-40A253C	93	280	2R1F	1R6A		
	SGLGW-60A140C	70	220				
	SGLGW-40A365C	140	420	2R8F	2R8A		
	SGLGW-60A253C	140	440				
	SGLGW-60A365C	210	660	—	5R5A		
	SGLGW-90A200C	325	1300		120A		
	SGLGW-90A370C	550	2200		180A		
	SGLGW-90A535C	750	3000		200A		
SGLGW (Coreless Type, With high-efficiency magnetic way)	SGLGW-40A140C	57	230	2R1F	1R6A	—	NS
	SGLGW-60A140C	85	360				
	SGLGW-40A253C	114	460	2R8F	2R8A		
	SGLGW-40A365C	171	690	—	3R8A		
	SGLGW-60A253C	170	720				
	SGLGW-60A365C	255	1080		7R6A		
SGLFW (With F-type Iron Core)	SGLFW-20A090A	25	86	2R1F	1R6A	—	S
	SGLFW-20A120A	40	125				
	SGLFW-35A120A	80	220				
	SGLFW-35A230A	160	440	—	3R8A		
	SGLFW-50A200B	280	600		5R5A		
	SGLFW-50A380B	560	1200		120A		
	SGLFW-1ZA200B	560	1200				
	SGLFW-1ZA380B	1120	2400		200A		
	SGLFW-35D120A	80	220		—	1R9D	
	SGLFW-35D230A	160	440				
	SGLFW-50D200B	280	600			3R5D	
	SGLFW-50D380B	560	1200			5R4D	
	SGLFW-1ZD200B	560	1200				
	SGLFW-1ZD380B	1120	2400			120D	
SGLTW (With T-type Iron Core)	SGLTW-20A170A	130	380	—	3R8A	—	NS
	SGLTW-35A170A	220	660		5R5A		
	SGLTW-35A170H	300	600				
	SGLTW-50A170H	450	900				
	SGLTW-20A320A	250	760		7R6A		
	SGLTW-20A460A	380	1140		120A		
	SGLTW-35A320A	440	1320				
	SGLTW-35A320H	600	1200				
	SGLTW-50A320H	900	1800				
	SGLTW-35A460A	670	2000		180A		
	SGLTW-40A400B	670	2600				
	SGLTW-40A600B	1000	4000		330A		
	SGLTW-80A400B	1300	5000				
	SGLTW-35D170H	300	600		—	3R5D	
	SGLTW-50D170H	450	900				
	SGLTW-35D320H	600	1200			8R4D	
	SGLTW-50D320H	900	1800				
	SGLTW-40D400B	670	2600			120D	
	SGLTW-40D600B	1000	4000			170D	
	SGLTW-80D400B	1300	5000				

◆Cylinder Type Servomotors (Σ-Stick) and SERVOPACKs

Linear Servomotor Model		Rated Force N	Peak Force N	SERVOPACK Model SGDV-□□□□		Stock Status
				Single-phase 100 VAC	Three-phase 200 VAC	
SGLC	SGLC-D16A085	17	60	R70F	R70A	GS
	SGLC-D16A115	25	90			
	SGLC-D16A145	34	120	R90F	R90A	
	SGLC-D20A100	30	150	2R1F	1R6A	
	SGLC-D20A135	45	225			
	SGLC-D20A170	60	300		2R8A	
	SGLC-D25A125	70	280		1R6A	
	SGLC-D25A170	105	420	2R8F	2R8A	
	SGLC-D32A165	90	420			
	SGLC-D25A215	140	560	—	5R5A	
	SGLC-D32A225	135	630			
	SGLC-D32A285	180	840			

◆Linear Slides (Σ-Trac) and SERVOPACKs

Linear Slide Model		Rated Force N	Peak Force N	SERVOPACK Model SGDV-□□□□		Stock Status
				Single-phase 100 VAC	Three-phase 200 VAC	
SGT1F (Σ-Trac)	SGT1F31-	80	220	2R1F	1R6A	LS
	SGT1F41-	160	440	—	3R8A	
	SGT1F91-	280	600		5R5A	
	SGT1FA1-	560	1200		120A	
SGTMM (Σ-Trac-μ)	SGTMM-01	3.5	10	R70F	R70A	GS
	SGTMM-03	7	25	R90F	R90A	
SGTMF (Σ-Trac-MAG)	SGTMF-4A	90	270	2R1F	1R6A	GS
	SGTMF-4B	120	360			
	SGTMF-5A	180	540	—	5R5A	
	SGTMF-5B	240	720			

◆Direct Drive Servomotors and SERVOPACKs

Direct Drive Servomotor Model		Rated Torque N m	Peak Torque N m	SERVOPACK Model SGDV-□□□□		Stock Status
				Single-phase 100 VAC	Three-phase 200 VAC	
SGMCS (Small Capacity)	SGMCS-02B	2	6	2R1F	2R8A	S
	SGMCS-05B	5	15			
	SGMCS-07B	7	21			
	SGMCS-04C	4	12	2R8F		
	SGMCS-10C	10	30			
	SGMCS-14C	14	42			
	SGMCS-08D	8	24			
	SGMCS-17D	17	51			
	SGMCS-25D	25	75			
	SGMCS-16E	16	48	—	5R5A	
	SGMCS-35E	35	105			
SGMCS (Medium Capacity)	SGMCS-45M	45	135	—	7R6A	S
	SGMCS-80M	80	240		120A	
	SGMCS-80N	80	240			
	SGMCS-1AM	110	330		180A	
	SGMCS-1EN	150	450		200A	
	SGMCS-2ZN	200	600			

Contents

Σ-V AC SERVODRIVE

Servomotors

Rotary Servomotors 1

Medium inertia, small capacity	SGMJV	1
Low inertia, small capacity	SGMAV	23
Medium inertia, medium capacity	SGMGV	47
Low inertia, medium capacity	SGMSV	71
Rotary Servomotor General Instructions		91

Direct Drive Servomotors 101

Small capacity, medium capacity	SGMCS	101

Linear Servomotors 119

Coreless type	SGLGW	119
With F-type iron core	SGLFW	139
With T-type iron core	SGLTW	159
Cylinder type Σ-Stick	SGLC	187
Linear Servomotor General Instructions		201

Linear Slides 209

Σ-Trac	SGT1F	209
Σ-Trac-μ	SGTMM	217
Σ-Trac-MAG	SGTMF	225

SERVOPACKs

Analog Voltage/Pulse Train Reference Type SERVOPACKs 233

MECHATROLINK-II Communications Reference Type SERVOPACKs 257

SERVOPACK with Additional Options 279

Wiring Main Circuit and Peripheral Devices 325

Others

Selecting Servomotor Capacity and Regenerative Capacity 343

Connection to Host Controller 359

Rotary Servomotors

SGMJV



efesotomasyon.com

Model Designations

● Without Gears

SGMJV - 01 A D A 2 1

Σ-V Series Servomotor SGMJV	1st+2nd digits	3rd digit	4th digit	5th digit	6th digit	7th digit

1st+2nd digits Rated Output

Code	Specifications
A5	50 W
01	100 W
02	200 W
04	400 W
08	750 W

3rd digit Power Supply Voltage

Code	Specifications
A	200 VAC

4th digit Serial Encoder

Code	Specifications
3	20-bit absolute*
D	20-bit incremental
A	13-bit incremental

*: When exporting the servomotors themselves, export restrictions may apply. Follow each country's export restrictions.

5th digit Design Revision Order

Code	Specifications
A	Standard

6th digit Shaft End

Code	Specifications
2	Straight without key
6	Straight with key and tap
B	With two flat seats

7th digit Options

Code	Specifications
1	Without options
C	With holding brake (24 VDC)
E	With oil seal and holding brake (24 VDC)
S	With oil seal

☐ Limited Stock Items ■ Non-Stock Items

Features

- Medium inertia
- Instantaneous peak torque (350% of rated torque)
- Mounted high-resolution serial encoder: 13, 20 bits
- Maximum speed: 6,000 min^{-1}
- Wide Selection: 50 to 750 W capacity, holding brake and gear options

Application Examples

- Semiconductor equipment
- Chip mounters
- PCB drilling stations
- Robots
- Material handling machines
- Food processing equipment

● With Gears (Global Support - Refer to Stock Status Definitions - page viii)

SGMJV - 01 A D A H 1 2 1

Σ-V Series Servomotor SGMJV	1st+2nd digits	3rd digit	4th digit	5th digit	6th digit	7th digit	8th digit	9th digit

1st+2nd digits Rated Output

Code	Specifications
A5	50 W
01	100 W
02	200 W
04	400 W
08	750 W

3rd digit Power Supply Voltage

Code	Specifications
A	200 VAC

4th digit Serial Encoder

Code	Specifications
3	20-bit absolute (standard)*
D	20-bit incremental (standard)
A	13-bit incremental (standard)

*: When exporting the servomotors themselves, export restrictions may apply. Follow each country's export restrictions.

5th digit Design Revision Order

Code	Specifications
A	Standard

6th digit Gear Type

Code	Specifications
H	HDS planetary low-backlash gear

7th digit Gear Ratio

Code	Specifications
B	1/11 (Not available: 50 W)
C	1/21
1	1/5
2	1/9 (Only 50 W)
7	1/33

8th digit Shaft End

Code	Specifications
0	Flange output
2	Straight without key
6	Straight with key and tap

9th digit Options

Code	Specifications
1	Without options
C	With holding brake (24 VDC)

Ratings and Specifications

Time Rating: Continuous
Vibration Class: V15
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40˚C
Excitation: Permanent magnet
Mounting: Flange-mounted
Thermal Class: B


Withstand Voltage: 1500 VAC for one minute
Enclosure: Totally enclosed, self-cooled, IP65 (except for shaft opening)
Ambient Humidity: 20% to 80% (no condensation)
Drive Method: Direct drive
Rotation Direction: Counterclockwise (CCW) with forward run reference when viewed from the load side

Voltage		200 V				
Servomotor Model: SGMJV-□□□		A5A	01A	02A	04A	08A
Rated Output*1	W	50	100	200	400	750
Rated Torque*1, *2	N•m	0.159	0.318	0.637	1.27	2.39
Instantaneous Peak Torque*1	N•m	0.557	1.11	2.23	4.46	8.36
Rated Current*1	A_{rms}	0.61	0.84	1.6	2.7	4.7
Instantaneous Max. Current*1	A_{rms}	2.1	2.9	5.8	9.3	16.9
Rated Speed*1	min^{-1}	3000				
Max. Speed*1	min^{-1}	6000				
Torque Constant	$N•m/A_{rms}$	0.285	0.413	0.435	0.512	0.544
Rotor Moment of Inertia	$\times10^{-4}$ kg•m^2	0.0414 (0.0561)	0.0665 (0.0812)	0.259 (0.323)	0.442 (0.506)	1.57 (1.74)
Rated Power Rate*1	kW/s	6.11	15.2	15.7	36.5	36.3
Rated Angular Acceleration*1	rad/s^2	38400	47800	24600	28800	15200
Applicable SERVOPACK	SGDV-□□□□	R70□	R90□	1R6A,2R1F	2R8□	5R5A

*1: These items and torque-motor speed characteristics quoted in combination with an SGDV SERVOPACK are at an armature winding temperature of 100˚C. Other values quoted are at 20˚C.
*2: Rated torques are continuous allowable torque values at 40˚C with an aluminum heat sink of the following dimensions attached.
SGMJV-A5A, -01A: 200 mm×200 mm×6 mm
SGMJV-02A, -04A, -08A: 250 mm×250 mm×6 mm
Note: The values in parentheses are for servomotors with holding brakes.

●Torque-Motor Speed Characteristics

A : Continuous Duty Zone B : Intermittent Duty Zone(Note3)



Notes: 1 The solid, dotted, and dashed-dotted lines of the intermittent duty zone indicate the characteristics when a servomotor runs with the following combinations:
- The solid line: With a three-phase 200 V or a single-phase 230 V SERVOPACK
- The dotted line: With a single-phase 200 V SERVOPACK
- The dashed-dotted line: With a single-phase 100 V SERVOPACK

An SGMJV-A5A servomotor has the same characteristics in combination with three-phase 200 V and single-phase 200 V SERVOPACKs.
2 The characteristics of the intermittent duty zone differ depending on the supply voltages.
3 When the effective torque during intermittent duty is within the rated torque, the servomotor can be used within the intermittent duty zone.
4 When the main circuit cable length exceeds 20 m, note that the intermittent duty zone of the Torque-Motor Speed Characteristics will shrink as the line-to-line voltage drops.

Ratings and Specifications

●Derating Rate for Servomotor Fitted with an Oil Seal

When a motor is fitted with an oil seal, use the following derating rate because of the higher friction torque.

Servomotor Model SGMJV-	A5A	01A	02A	04A	08A
Derating Rate %	80	90		95	


●Holding Brake Electrical Specifications

Holding Brake Rated Voltage	Servomotor Model	Servomotor Rated Output W	Holding Brake Specifications					
			Capacity W	Holding Torque N·m	Coil Resistance Ω(at 20˚C)	Rated Current A(at 20˚C)	Brake Release Time ms	Brake Operation Time ms
24 VDC$^{+10\%}_{0}$	SGMJV-A5A	50	5.5	0.159	103	0.23	60	100
	SGMJV-01A	100	5.5	0.318	103	0.23	60	100
	SGMJV-02A	200	6	0.637	97.4	0.25	60	100
	SGMJV-04A	400	6	1.27	97.4	0.25	60	100
	SGMJV-08A	750	6.5	2.39	87.7	0.27	80	100

Notes: 1 The holding brake is only used to hold the load and cannot be used to stop the servomotor.
2 The holding brake open time and holding brake operation time vary depending on which discharge circuit is used. Make sure holding brake open time and holding brake operation time are correct for your servomotor.
3 A 24-VDC power supply is provided by customers.

●Overload Characteristics

The overload detection level is set under hot start conditions at a servomotor ambient temperature of 40˚C.



Note: Overload characteristics shown above do not guarantee continuous duty of 100% or more output. Use a servomotor with effective torque within the continuous duty zone of Torque-Motor Speed Characteristics.

Ratings and Specifications

●Allowable Load Moment of Inertia at the Motor Shaft

The rotor moment of inertia ratio is the value for a servomotor without a gear and a holding brake.


Servomotor Model		Servomotor Rated Output	Allowable Load Moment of Inertia (Rotor Moment of Inertia Ratio)
SGMJV-	A5A, 01A	50 ,100 W	20 times
	02A	200 W	15 times
	04A, 08A	400 to 750 W	10 times

●Load Moment of Inertia

- The larger the load moment of inertia, the worse the movement response.
- The allowable load moment of inertia (J_L) depends on motor capacity, as shown above. This value is provided strictly as a guideline and results may vary depending on servomotor drive conditions.
- Use the AC servo drive capacity selection program SigmaJunmaSize+ to check the operation conditions. The program can be downloaded for free from our web site (http://www.e-mechatronics.com/).
- An overvoltage alarm (A.400) is likely to occur during deceleration if the load moment of inertia exceeds the allowable load moment of inertia. SERVOPACKs with a built-in regenerative resistor may generate a regenerative overload alarm (A.320). Take one of the following steps if this occurs.
  - Reduce the torque limit.
  - Reduce the deceleration rate.
  - Reduce the maximum speed.
  - Install an external regenerative resistor if the alarm cannot be cleared using the steps above. Refer to Regenerative Resistors on page 339.
- Regenerative resistors are not built into SERVOPACKs for 400 W motors or less.
- External regenerative resistors are required when this condition is exceeded or if the allowable loss capacity (W) of the built-in regenerative resistor is exceeded due to regenerative drive conditions when a regenerative resistor is already built in.


●Allowable Radial and Thrust Loads

Design the mechanical system so thrust and radial loads applied to the servomotor shaft end during operation fall within the ranges shown in the table.

Servomotor Model		Allowable Radial Load (Fr) N	Allowable Thrust Load (Fs) N	LR mm	Reference Diagram
SGMJV-	A5A	78	54	20	
	01A				
	02A	245	74	25	
	04A				
	08A	392	147	35	

External Dimensions Units: mm

(1) 50 to 100 W




Model SGMJV-	L	LL	LM	Tap × Depth	Key Dimensions QK	U	W	T	Approx. Mass kg
A5A□A21 (A5A□A2C)	94 (139)	69 (114)	37	No tap	No key				0.3 (0.6)
A5A□A61 (A5A□A6C)				M3 × 6L	14	1.8	3	3	
01A□A21 (01A□A2C)	107.5 (152.5)	82.5 (127.5)	50.5	No tap	No key				0.4 (0.7)
01A□A61 (01A□A6C)				M3 × 6L	14	1.8	3	3	

Note: The models and values in parentheses are for servomotors with holding brakes.


<Shaft End and Other Options>

● With Two Flat Seats



Model SGMJV-	Dimensions of Servomotor with Two Flat Seats mm QH	H1	H2
A5A□AB□	15	7.5	7.5
01A□AB□			


● With an Oil Seal



Notes: 1 The 7th digit of the model designation is "S" or "E."
2 Key dimensions are the same as those in the table above.

External Dimensions Units: mm

(2) 200 to 750 W




Model SGMJV-	L	LL	LM	Flange Face Dimensions							S	Tap×Depth	Key Dimensions				MD	MW	MH	Approx. Mass kg
				LR	LE	LG	LC	LA	LB	LZ			QK	U	W	T				
02A□A21 (02A□A2C)	110 (150)	80 (120)	51	30	3	6	60	70	$50^{0}_{-0.025}$	5.5	$14^{0}_{-0.011}$	No tap	No key				8.3	21	13	0.9 (1.5)
02A□A61 (02A□A6C)												M5×8L	14	3	5	5				
04A□A21 (04A□A2C)	128.5 (168.5)	98.5 (138.5)	69.5	30	3	6	60	70	$50^{0}_{-0.025}$	5.5	$14^{0}_{-0.011}$	No tap	No key				8.3	21	13	1.3 (1.9)
04A□A61 (04A□A6C)												M5×8L	14	3	5	5				
08A□A21 (08A□A2C)	155 (200)	115 (160)	85	40	3	8	80	90	$70^{0}_{-0.030}$	7	$19^{0}_{-0.013}$	No tap	No key				13.8	27	15	2.7 (3.6)
08A□A61 (08A□A6C)												M6×10L	22	3.5	6	6				

Note: The models and values in parentheses are for servomotors with holding brakes.


<Shaft End and Other Options>

● With Two Flat Seats



Model SGMJV-	Dimensions of Servomotor with Two Flat Seats mm			
	QH	S	H1	H2
02A□AB□	15	$14^{0}_{-0.011}$	13	13
04A□AB□				
08A□AB□	22	$19^{0}_{-0.013}$	18	18

● With an Oil Seal




Model SGMJV-	Dimensions of Servomotor with an Oil Seal			
	E1	E2	LS1	LS2
02A, 04A	36	48	4	10
08A	49	66	6	11

Notes: 1 The 7th digit of the model designation is “S” or “E.”
2 Key dimensions are the same as those in the table above.

Selecting Cables


●Cables Connections

●Standard Wiring (Max. encoder cable length: 20 m)



●Encoder Cable Extension from 30 to 50 m


(See page 14.)



⚠ CAUTION


- Separate the servomotor main circuit cable wiring from the I/O signal cable and encoder cable at least 30 cm, and do not bundle or run them in the same duct.
- When the cable length exceeds 20 m, be sure to use a relay encoder cable.
- When the main circuit cable length exceeds 20 m, note that the intermittent duty zone of the Torque-Motor Speed Characteristics will shrink as the line-to-line voltage drops.

●Servomotor Main Circuit Cable

Name	Servomotor Rated Output	Length	Order No.		Specifications	Details
			Standard Type	Flexible Type*		
For Servomotor without Holding Brakes	50 to 100 W	3 m	JZSP-CSM01-03-E	JZSP-CSM21-03-E		(1)
		5 m	JZSP-CSM01-05-E	JZSP-CSM21-05-E		
		10 m	JZSP-CSM01-10-E	JZSP-CSM21-10-E		
		15 m	JZSP-CSM01-15-E	JZSP-CSM21-15-E		
		20 m	JZSP-CSM01-20-E	JZSP-CSM21-20-E		
		30 m	JZSP-CSM01-30-E	JZSP-CSM21-30-E		
		40 m	JZSP-CSM01-40-E	JZSP-CSM21-40-E		
		50 m	JZSP-CSM01-50-E	JZSP-CSM21-50-E		
	200 to 400 W	3 m	JZSP-CSM02-03-E	JZSP-CSM22-03-E		
		5 m	JZSP-CSM02-05-E	JZSP-CSM22-05-E		
		10 m	JZSP-CSM02-10-E	JZSP-CSM22-10-E		
		15 m	JZSP-CSM02-15-E	JZSP-CSM22-15-E		
		20 m	JZSP-CSM02-20-E	JZSP-CSM22-20-E		
		30 m	JZSP-CSM02-30-E	JZSP-CSM22-30-E		
		40 m	JZSP-CSM02-40-E	JZSP-CSM22-40-E		
		50 m	JZSP-CSM02-50-E	JZSP-CSM22-50-E		
	750 W	3 m	JZSP-CSM03-03-E	JZSP-CSM23-03-E		
		5 m	JZSP-CSM03-05-E	JZSP-CSM23-05-E		
		10 m	JZSP-CSM03-10-E	JZSP-CSM23-10-E		
		15 m	JZSP-CSM03-15-E	JZSP-CSM23-15-E		
		20 m	JZSP-CSM03-20-E	JZSP-CSM23-20-E		
		30 m	JZSP-CSM03-30-E	JZSP-CSM23-30-E		
		40 m	JZSP-CSM03-40-E	JZSP-CSM23-40-E		
		50 m	JZSP-CSM03-50-E	JZSP-CSM23-50-E		

(Cont'd)

Selecting Cables

Name	Servomotor Rated Output	Length	Order No.		Specifications	Details
			Standard Type	Flexible Type*		
For Servomotor with Holding Brakes	50 to 100 W	3 m	JZSP-CSM11-03-E	JZSP-CSM31-03-E		(2)
		5 m	JZSP-CSM11-05-E	JZSP-CSM31-05-E		
		10 m	JZSP-CSM11-10-E	JZSP-CSM31-10-E		
		15 m	JZSP-CSM11-15-E	JZSP-CSM31-15-E		
		20 m	JZSP-CSM11-20-E	JZSP-CSM31-20-E		
		30 m	JZSP-CSM11-30-E	JZSP-CSM31-30-E		
		40 m	JZSP-CSM11-40-E	JZSP-CSM31-40-E		
		50 m	JZSP-CSM11-50-E	JZSP-CSM31-50-E		
	200 to 400 W	3 m	JZSP-CSM12-03-E	JZSP-CSM32-03-E		
		5 m	JZSP-CSM12-05-E	JZSP-CSM32-05-E		
		10 m	JZSP-CSM12-10-E	JZSP-CSM32-10-E		
		15 m	JZSP-CSM12-15-E	JZSP-CSM32-15-E		
		20 m	JZSP-CSM12-20-E	JZSP-CSM32-20-E		
		30 m	JZSP-CSM12-30-E	JZSP-CSM32-30-E		
		40 m	JZSP-CSM12-40-E	JZSP-CSM32-40-E		
		50 m	JZSP-CSM12-50-E	JZSP-CSM32-50-E		
	750 W	3 m	JZSP-CSM13-03-E	JZSP-CSM33-03-E		
		5 m	JZSP-CSM13-05-E	JZSP-CSM33-05-E		
		10 m	JZSP-CSM13-10-E	JZSP-CSM33-10-E		
		15 m	JZSP-CSM13-15-E	JZSP-CSM33-15-E		
		20 m	JZSP-CSM13-20-E	JZSP-CSM33-20-E		
		30 m	JZSP-CSM13-30-E	JZSP-CSM33-30-E		
		40 m	JZSP-CSM13-40-E	JZSP-CSM33-40-E		
		50 m	JZSP-CSM13-50-E	JZSP-CSM33-50-E		
Servomotor-end Connector Kit	50 to 100 W		JZSP-CSM9-1-E		Crimping Type (A crimp tool is required.) 	(3)
	200 to 400 W		JZSP-CSM9-2-E			(4)
	750 W		JZSP-CSM9-3-E			(5)
Cables	50 to 400 W	5 m	JZSP-CSM90-05-E	JZSP-CSM80-05-E		(6)
		10 m	JZSP-CSM90-10-E	JZSP-CSM80-10-E		
		15 m	JZSP-CSM90-15-E	JZSP-CSM80-15-E		
		20 m	JZSP-CSM90-20-E	JZSP-CSM80-20-E		
		30 m	JZSP-CSM90-30-E	JZSP-CSM80-30-E		
		40 m	JZSP-CSM90-40-E	JZSP-CSM80-40-E		
		50 m	JZSP-CSM90-50-E	JZSP-CSM80-50-E		
	750 W	5 m	JZSP-CSM91-05-E	JZSP-CSM81-05-E		(7)
		10 m	JZSP-CSM91-10-E	JZSP-CSM81-10-E		
		15 m	JZSP-CSM91-15-E	JZSP-CSM81-15-E		
		20 m	JZSP-CSM91-20-E	JZSP-CSM81-20-E		
		30 m	JZSP-CSM91-30-E	JZSP-CSM81-30-E		
		40 m	JZSP-CSM91-40-E	JZSP-CSM81-40-E		
		50 m	JZSP-CSM91-50-E	JZSP-CSM81-50-E		

*: Use flexible cables for movable sections such as robot arms.

(1) Wiring Specifications for Servomotors without Holding Brakes

SERVOPACK-end Leads		Servomotor-end Connector	
Wire Color	Signal	Signal	Pin No.
Green/yellow	FG	FG	1
Blue	Phase W	Phase W	2
White	Phase V	Phase V	3
Red	Phase U	Phase U	4
		–	5
		–	6

Note: This cable is not shielded.

(2) Wiring Specifications for Servomotor with Holding Brakes

SERVOPACK-end Leads		Servomotor-end Connector	
Wire Color	Signal	Signal	Pin No.
Green/yellow	FG	FG	1
Blue	Phase W	Phase W	2
White	Phase V	Phase V	3
Red	Phase U	Phase U	4
Black	Brake	Brake	5
Black	Brake	Brake	6


Note: No polarity for connection to a holding brake.
Note: This cable is not shielded.

Selecting Cables

(3) Servomotor-end Connector Kit Specifications: For 50 to 100 W Servomotors

Items		Specifications
Order No.		JZSP-CSM9-1-E (Cables are not included.)
Applicable Servomotors		SGMJV-A5A, -01A
Manufacturer		J.S.T. Mfg. Co., Ltd.
Receptacle		J17-06FMH-7KL-1-CF
Electrical Contact		SJ1F-01GF-P0.8
Applicable Wire Size		AWG20 to 24
Outer Diameter of Insulating Sheath		1.11 dia. to 1.53 dia. mm
Crimp Tool	Hand tool	YRS-8841
	Applicator	APLMK SJ1F/M-01-08
Mounting Screw		M2 Pan-head screw
Applicable Cable Outer Diameter		7±0.3 dia. mm


External Dimensions mm



(4) Servomotor-end Connector Kit Specifications: For 200 to 400 W Servomotors

Items		Specifications
Order No.		JZSP-CSM9-2-E (Cables are not included.)
Applicable Servomotors		SGMJV-02A, -04A
Manufacturer		J.S.T. Mfg. Co., Ltd.
Receptacle		J27-06FMH-7KL-1-CF
Electrical Contact		SJ2F-01GF-P1.0
Applicable Wire Size		AWG20 to 24
Outer Diameter of Insulating Sheath		1.11 dia. to 1.53 dia. mm
Crimp Tool	Hand tool	YRS-8861
	Applicator	APLMK SJ2F/M-01-08
Mounting Screw		M2 Pan-head screw
Applicable Cable Outer Diameter		7±0.3 dia. mm


External Dimensions mm




(5) Servomotor-end Connector Kit Specifications: For 750 W Servomotors

Items		Specifications	
Order No.		JZSP-CSM9-3-E (Cables are not included.)	
Applicable Servomotors		SGMJV-08A	
Manufacturer		J.S.T. Mfg. Co., Ltd.	
Receptacle		J37-06FMH-8KL-1-CF	
Cable Type		Standard	
Electrical Contact		SJ3F-41GF-P1.8 (For power terminals)	SJ3F-01GF-P1.8 (For brake terminals)
Applicable Wire Size		AWG16 to 20	AWG20 to 24
Outer Diameter of Insulating Sheath		1.53 dia. to 2.5 dia. mm	1.11 dia. to 1.86 dia. mm
Crimp Tool	Hand tool	YRF-880	YRF-881
	Applicator	APLMK SF3F/M-41-20	APLMK SF3F/M-01-20
Mounting Screw		M2.5 Pan-head screw	
Applicable Cable Outer Diameter		8±0.3 dia. mm	

External Dimensions mm




(6) Cable Specifications: For 50 to 400 W Servomotors

Items	Standard Type	Flexible Type
Order No.*	JZSP-CSM90-□□-E (50 m max.)	JZSP-CSM80-□□-E (50 m max.)
Specifications	UL2517 (Max. operating temperature: 105°C) AWG20×6C For power line: AWG20 (0.52 mm^2) Outer diameter of insulating sheath: 1.53 dia. mm For holding brake line: AWG20 (0.52 mm^2) Outer diameter of insulating sheath: 1.53 dia. mm	UL2517 (Max. operating temperature: 105°C) AWG22×6C For power line: AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.37 dia. mm For holding brake line: AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.37 dia. mm
Finished Dimensions	7±0.3 dia. mm	
Internal Configuration and Lead Color		
Yaskawa Standard Specifications (Standard Length)	Cable length: 5 m, 10 m, 15 m, 20 m, 30 m, 40 m, 50 m	

*: Specify the cable length in □□ of order no.
Example: JZSP-CSM90-05-E (5 m)



(7) Cable Specifications: For 750 W Servomotors

Items	Standard Type	Flexible Type
Order No.*	JZSP-CSM91-□□-E (50 m max.)	JZSP-CSM81-□□-E (50 m max.)
Specifications	UL2517 (Max. operating temperature: 105°C) AWG16×4C, AWG20×2C For power line: AWG16 (1.31 mm^2) Outer diameter of insulating sheath: 2.15 dia. mm For holding brake line: AWG20 (0.52 mm^2) Outer diameter of insulating sheath: 1.6 dia. mm	UL2517 (Max. operating temperature: 105°C) AWG16×4C, AWG22×2C For power line: AWG16 (1.31 mm^2) Outer diameter of insulating sheath: 2.35 dia. mm For holding brake line: AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.37 dia. mm
Finished Dimensions	8±0.3 dia. mm	
Internal Configuration and Lead Color		
Yaskawa Standard Specifications (Standard Length)	Cable length: 5 m, 10 m, 15 m, 20 m, 30 m, 40 m, 50 m	

*: Specify the cable length in □□ of order no.
Example: JZSP-CSM91-05-E (5 m)

Selecting Cables

●Encoder Cables (Length: 20 m or less)


Name	Length	Order No.		Specifications	Details
		Standard Type	Flexible Type*		
Cable with Connectors (For Incremental Encoder)	3 m	JZSP-CSP01-03-E	JZSP-CSP21-03-E		(1)
	5 m	JZSP-CSP01-05-E	JZSP-CSP21-05-E		
	10 m	JZSP-CSP01-10-E	JZSP-CSP21-10-E		
	15 m	JZSP-CSP01-15-E	JZSP-CSP21-15-E		
	20 m	JZSP-CSP01-20-E	JZSP-CSP21-20-E		
Cable with Connectors (For Absolute Encoder, with a Battery Case)	3 m	JZSP-CSP05-03-E	JZSP-CSP25-03-E		(2)
	5 m	JZSP-CSP05-05-E	JZSP-CSP25-05-E		
	10 m	JZSP-CSP05-10-E	JZSP-CSP25-10-E		
	15 m	JZSP-CSP05-15-E	JZSP-CSP25-15-E		
	20 m	JZSP-CSP05-20-E	JZSP-CSP25-20-E		
SERVOPACK-end Connector Kit		JZSP-CMP9-1-E		Soldered 	(3)
Encoder-end Connector Kit		JZSP-CSP9-2-E		Crimping Type (A crimping tool is required) 	
Cables	3 m	JZSP-CMP09-03-E	JZSP-CSP39-03-E		(4)
	5 m	JZSP-CMP09-05-E	JZSP-CSP39-05-E		
	10 m	JZSP-CMP09-10-E	JZSP-CSP39-10-E		
	15 m	JZSP-CMP09-15-E	JZSP-CSP39-15-E		
	20 m	JZSP-CMP09-20-E	JZSP-CSP39-20-E		

*: Use flexible cables for movable sections such as robot arms.
Note: When the battery from the host controller is used for the absolute encoder, no battery case is required. In this case, use a cable for the incremental encoders.

(1) Wiring Specifications for Cable with Connectors
(For incremental encoder)

• Standard Type


Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG



Pin No.	Wire Color
5	Light blue/white
4	Light blue
8	Orange/white
9	Orange
3	Black
6	Red
Shell	FG

• Flexible Type

Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG




Pin No.	Wire Color
5	Black/pink
4	Red/pink
8	Black/light blue
9	Red/light blue
3	Green
6	Orange
Shell	FG

(2) Wiring Specifications for Cable with Connectors
(For absolute encoder, with a battery case)

• Standard Type

Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG




Pin No.	Wire Color
5	Light blue/white
4	Light blue
8	Orange/white
9	Orange
3	Black
6	Red
Shell	FG

Battery Case

Pin No.	Signal
2	BAT (–)
1	BAT (+)

• Flexible Type

Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG





Pin No.	Wire Color
5	Black/pink
4	Red/pink
8	Black/light blue
9	Red/light blue
3	Green
6	Orange
Shell	FG

Battery Case



Pin No.	Signal
2	BAT (–)
1	BAT (+)

(3) SERVOPACK-end/Encoder-end Connector Kit Specifications

Items	SERVOPACK-end Connector Kit	Encoder-end Connector Kit
Order No.	JZSP-CMP9-1-E (Cables are not included.)	JZSP-CSP9-2-E (Cables are not included.)
Manufacturer	Molex Japan Co., Ltd.	Molex Japan Co., Ltd.
Specifications	55100-0670 (soldered)	54346-0070 (crimped)* Mounting screw: M2 pan-head screw (× 2) Applicable cable outer diameter of applicable cable: 6.3 dia. to 7.7 dia. mm Applicable wire size: AWG22 to 26 Outer diameter of insulating sheath: 1.05 dia. to 1.4 dia. mm
External Dimensions (Units: mm)		

*: A crimp tool is required.
The following crimp tools are applicable for the cables provided by Yaskawa. When using other wire sizes, contact the respective manufacturer for crimp tools.
Applicable crimp tool for Yaskawa's wire size: Hand Tool Model No. 57175-5000
Applicator Model No. 57175-3000




(4) Cable Specifications

Items	Standard Type	Flexible Type
Order No.*	JZSP-CMP09-□□-E	JZSP-CSP39-□□-E
Cable Length	20 m max.	
Specifications	UL20276 (Max. operating temperature: 80°C) AWG22×2C+AWG24×2P AWG22 (0.33 mm²) Outer diameter of insulating sheath: 1.15 dia. mm AWG24 (0.20 mm²) Outer diameter of insulating sheath: 1.09 dia. mm	UL20276 (Max. operating temperature: 80°C) AWG22×2C+AWG24×2P AWG22 (0.33 mm²) Outer diameter of insulating sheath: 1.35 dia. mm AWG24 (0.20 mm²) Outer diameter of insulating sheath: 1.21 dia. mm
Finished Dimensions	6.5 dia. mm	6.8 dia. mm
Internal Configuration and Lead Color		
Yaskawa Standards Specifications (Standard Length)	Cable length: 5 m, 10 m, 15 m, 20 m	

*: Specify the cable length in □□ of order no.
Example: JZSP-CSP09-05-E (5 m)

Selecting Cables

●Relay Encoder Cables (For extending from 30 to 50 m)

Name	Length	Order No. Standard Type	Specifications	Details
① Encoder-end Cables (For incremental and absolute encoder)	0.3 m	JZSP-CSP11-E		(1)
② Cable with Connectors (For incremental and absolute encoder)	30 m	JZSP-UCMP00-30-E		(2)
	40 m	JZSP-UCMP00-40-E		
	50 m	JZSP-UCMP00-50-E		
③ Cable with a Battery Case (Required when an absolute encoder is used.)	0.3 m	JZSP-CSP12-E*		(3)
④ Cables	30 m	JZSP-CMP19-30-E		(4)
	40 m	JZSP-CMP19-40-E		
	50 m	JZSP-CMP19-50-E		

*: When using an incremental encoder or using an absolute encoder with a battery connected to the host controller, no battery case is required.

(1) Wiring Specifications for Encoder-end Cable

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG

Encoder (Servomotor) End

Pin No.	Wire Color
5	Light blue/white
4	Light blue
8	Orange/white
9	Orange
3	Black
6	Red
Shell	FG

Shield Wire

(2) Wiring Specifications for Cable with Connectors

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG

Encoder (Servomotor) End

Pin No.	Wire Color
6	Light blue/white
5	Light blue
4	Orange/white
3	Orange
2	Black
1	Red
Shell	FG

Shield Wire

(3) Wiring Specifications for Cable with a Battery Case

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG

Encoder (Servomotor) End


Pin No.	Wire Color
6	Light blue/white
5	Light blue
4	Orange/white
3	Orange
2	Black
1	Red
Shell	FG

Shield Wire

Battery Case

Pin No.	Signal
2	BAT (–)
1	BAT (+)

(4) Cable Specifications

Item	Standard Type
Order No.*	JZSP-CMP19-□□-E
Cable Length	50 m max.
Specifications	UL20276 (Max. operating temperature: 80˚C) AWG16×2C+AWG26×2P AWG16 (1.31 mm²) Outer diameter of insulating sheath: 2.0 dia. mm AWG26 (0.13 mm²) Outer diameter of insulating sheath: 0.91 dia. mm
Finished Dimensions	6.8 dia. mm
Internal Configuration and Lead Colors	
Yaskawa Standard Specifications (Standard Length)	Cable length: 30 m, 40 m, 50 m

*: Specify the cable length in □□ of order no.
Example: JZSP-CMP19-30-E (30 m)

Time Rating: Continuous
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40°C
Excitation: Permanent magnet
Mounting: Flange-mounted
Gear Mechanism: Planetary gear mechanism
Thermal Class: B

Withstand Voltage: 1500 VAC for one minute
Enclosure: Totally enclosed, self-cooled, IP55 (except for shaft opening)
Ambient Humidity: 20% to 80% (no condensation)
Drive Method: Direct drive
Rotation Direction: Counterclockwise (CCW) with forward run reference when viewed from the load side

Servomotor Model SGMJV-	Servomotor					Gear					
	Rated Output W	Rated Speed min^{-1}	Max. Speed min^{-1}	Rated Torque N•m	Instantaneous Peak Torque N•m	Gear Ratio	Lost Motion arc-min	Rated Torque / Efficiency*1 N•m /%	Instantaneous Peak Torque N•m	Rated Speed min^{-1}	Max. Speed min^{-1}
A5A□AH1□	50	3000	6000	0.159	0.557	1/5	3 max.	0.433/64*2	2.37	600	1200
A5A□AH2□						1/9		1.12/78	3.78*3	333	667
A5A□AHC□						1/21		2.84/85	10.6	143	286
A5A□AH7□						1/33		3.68/70	15.8	91	182
01A□AH1□	100	3000	6000	0.318	1.11	1/5	3 max.	1.06/78*2	4.96	600	1200
01A□AHB□						1/11		2.52/72	10.7	273	545
01A□AHC□						1/21		5.35/80	20.8	143	286
01A□AH7□						1/33		7.35/70	32.7	91	182
02A□AH1□	200	3000	6000	0.637	2.23	1/5	3 max.	2.39/75	9.80	600	1200
02A□AHB□						1/11		5.74/82	22.1	273	545
02A□AHC□						1/21		10.2/76	42.1	143	286
02A□AH7□						1/33		17.0/81	67.6	91	182
04A□AH1□	400	3000	6000	1.27	4.46	1/5	3 max.	5.35/84	20.1	600	1200
04A□AHB□						1/11		11.5/82	45.1	273	545
04A□AHC□						1/21		23.0/86	87.0	143	286
04A□AH7□						1/33		34.0/81	135	91	182
08A□AH1□	750	3000	6000	2.39	8.36	1/5	3 max.	10.0/84	38.4	600	1200
08A□AHB□						1/11		23.1/88	86.4	273	545
08A□AHC□						1/21		42.1/84	163	143	286
08A□AH7□						1/33		69.3/88	259	91	182

*1: Gear output torque is expressed using the following equation.

$$\text{(Gear output torque)} = \text{(Servomotor output torque)} \times \frac{1}{\text{(gear ratio)}} \times \text{(efficiency)}$$

Gear efficiency depends on operating conditions such as output torque, motor speed, and temperature etc. The values in the table are representative values with rated torque, rated speed, and an ambient temperature of 25°C, and are not guaranteed values.

*2: When using SGMJV-A5A, -01A servomotors with a gear ratio of 1/5, maintain an 85% max. effective load ratio. The values in the table are provided with consideration given to the effective load ratio.

*3: Instantaneous Peak torque is 300%

Notes: 1 The gear mounted to our servomotor has not been broken in. Break in the servomotor if necessary. First, run the motor at low speed with no load. If no problems arise, gradually increase the speed and load.
2 The no-load torque for a servomotor with a gear is high immediately after the servomotor starts, and it then decreases and becomes stable a few minutes later. This is a common phenomenon caused by grease being circulated in the gear and not by a faulty gear.


IMPORTANT The SERVOPACK speed control range is 5000:1. When using servomotors at extremely low speeds (0.02 min^{-1} at gear output shaft), when using servomotors with one pulse feed reference for extended periods and in some other situations, the gear bearing lubrication may be insufficient. That may cause deterioration of bearing or increase the load ratio.
Contact your Yaskawa representative if you are using your servomotor under these conditions.

Global Support Product (see page viii)

With Low-backlash Gears | Ratings and Specifications

●Moment of Inertia and Allowable Radial and Thrust Loads

Servomotor Model SGMJV-	Moment of Inertia×10^{-4} kg•m^2				Servomotors with Low-backlash Gears			Reference Diagram
	Motor + Gear	Gear	Flange Output		Allowable Radial Load (Fr) N	Allowable Thrust Load (Fs) N	LR mm	
			Motor + Gear	Gear				
A5A□AH1□	0.0474	0.006	0.0464	0.005	95	431	37	
A5A□AH2□	0.0444	0.003	0.0444	0.003	113	514	37	
A5A□AHC□	0.0454	0.004	0.0454	0.004	146	663	37	
A5A□AH7□	0.0864	0.045	0.0864	0.045	267	1246	53	
01A□AH1□	0.0725	0.006	0.0715	0.005	95	431	37	
01A□AHB□	0.127	0.060	0.126	0.059	192	895	53	
01A□AHC□	0.117	0.050	0.117	0.050	233	1087	53	
01A□AH7□	0.132	0.065	0.131	0.064	605	2581	75	
02A□AH1□	0.466	0.207	0.460	0.201	152	707	53	
02A□AHB□	0.452	0.193	0.451	0.192	192	895	53	
02A□AHC□	0.749	0.490	0.747	0.488	528	2254	75	
02A□AH7□	0.709	0.450	0.708	0.449	605	2581	75	
04A□AH1□	0.649	0.207	0.643	0.201	152	707	53	
04A□AHB□	1.01	0.570	1.00	0.560	435	1856	75	
04A□AHC□	0.932	0.490	0.930	0.488	528	2254	75	
04A□AH7□	1.06	0.620	1.05	0.610	951	4992	128	
08A□AH1□	2.27	0.700	2.23	0.660	343	1465	75	
08A□AHB□	2.17	0.600	2.16	0.590	435	1856	75	
08A□AHC□	4.57	3.00	4.55	2.98	830	4359	128	
08A□AH7□	4.37	2.80	4.36	2.79	951	4992	128	



IMPORTANT

The gear generates the loss at gear mechanism and oil seal. The loss varies with torque and motor speed conditions. The temperature rise depends on heating conditions. Always check the actual gear and motor temperature. If the temperature is high, take the measures shown below.


·Decrease the load ratio.
·Change the heating conditions.
·Cool the motor with a cooling fan etc.

Rated Output W	Heat Sink Size			
	1/5	1/9 or 1/11	1/21	1/33
50	A			
100				
200			B	
400		C		
750				

A : 250 mm × 250 mm × 6 mm, aluminum
B : 300 mm × 300 mm × 12 mm, aluminum
C : 350 mm × 350 mm × 12 mm, aluminum

Global Support Product (see page viii)

(1) 50 to 100 W



Model SGMJV-	Gear Ratio	L	LL	LM	Flange Face Dimensions LR	LE	LG	B	LD	LB	LC	LA	LZ
A5A□AH1⊛1 (A5A□AH1⊛C)	1/5	150.5 (195.5)	108.5 (153.5)	76.5	42	2.2	5	29	39.5	$40^{0}_{-0.025}$	40	46	3.4
A5A□AH2⊛1 (A5A□AH2⊛C)	1/9												
A5A□AHC⊛1 (A5A□AHC⊛C)	1/21	159.5 (204.5)	117.5 (162.5)	85.5									
A5A□AH7⊛1 (A5A□AH7⊛C)	1/33	191 (236)	133 (178)	101	58	2.5	8	40	55.5	$56^{0}_{-0.030}$	60	70	5.5
01A□AH1⊛1 (01A□AH1⊛C)	1/5	164 (209)	122 (167)	90	42	2.2	5	29	39.5	$40^{0}_{-0.025}$	40	46	3.4
01A□AHB⊛1 (01A□AHB⊛C)	1/11	204.5 (249.5)	146.5 (191.5)	114.5	58	2.5	8	40	55.5	$56^{0}_{-0.030}$	60	70	5.5
01A□AHC⊛1 (01A□AHC⊛C)	1/21												
01A□AH7⊛1 (01A□AH7⊛C)	1/33	229 (274)	149 (194)	117	80	7.5	10	59	84	$85^{0}_{-0.035}$	90	105	9

Model SGMJV-	Flange Face Dimensions L1	L2	L3	Q	C	S	Tap × Depth	Key Dimensions QK	U	W	T	Approx. Mass kg
A5A□AH1⊛1 (A5A□AH1⊛C)	22	20	14.6	–	–	$10^{0}_{-0.015}$	M3 × 6L	15	2.5	4	4	0.6 (0.9)
A5A□AH2⊛1 (A5A□AH2⊛C)												
A5A□AHC⊛1 (A5A□AHC⊛C)												0.7 (1.0)
A5A□AH7⊛1 (A5A□AH7⊛C)	28	30	20	28	20	$16^{0}_{-0.018}$	M4 × 8L	25	3	5	5	1.3 (1.6)
01A□AH1⊛1 (01A□AH1⊛C)	22	20	14.6	–	–	$10^{0}_{-0.015}$	M3 × 6L	15	2.5	4	4	0.7 (1.0)
01A□AHB⊛1 (01A□AHB⊛C)	28	30	20	28	20	$16^{0}_{-0.018}$	M4 × 8L	25	3	5	5	1.4 (1.7)
01A□AHC⊛1 (01A□AHC⊛C)												
01A□AH7⊛1 (01A□AH7⊛C)	36	44	26	42	32	$25^{0}_{-0.021}$	M6 × 12L	36	4	8	7	2.8 (3.1)


*: The asterisk (*) describes the values of the 8th digit of the model designation, “shaft end code 6 (straight with key and tap).” If a key or tap is not necessary, order a servomotor with “shaft end code 2 (without key and tap).”

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 Please note that gear dimensions are different from those of Σ-Ⅰ, Σ-Ⅱ, and Σ-Ⅲ series.

Global Support Product (see page viii)

With Low-backlash Gears | External Dimensions Units: mm

●Flange Output Face




Model SGMJV-	Gear Ratio	L	LR	LJ	F	G	LK	No. of pos Tap ×Depth	Approx. Mass kg
A5A□AH101 (A5A□AH10C)	1/5	123.5 (168.5)	15	18	$5^{+0.012}_{0}$	24	3	3-M4×6L	0.6 (0.9)
A5A□AH201 (A5A□AH20C)	1/9	123.5 (168.5)							
A5A□AHC01 (A5A□AHC0C)	1/21	132.5 (177.5)							
A5A□AH701 (A5A□AH70C)	1/33	154 (199)	21	30	$14^{+0.018}_{0}$	40	5	6-M4×7L	1.2 (1.5)
01A□AH101 (01A□AH10C)	1/5	137 (182)	15	18	$5^{+0.012}_{0}$	24	3	3-M4×6L	0.7 (1.0)
01A□AHB01 (01A□AHB0C)	1/11	167.5 (212.5)	21	30	$14^{+0.018}_{0}$	40	5	3-M4×7L	1.3 (1.6)
01A□AHC01 (01A□AHC0C)	1/21	167.5 (212.5)							
01A□AH701 (01A□AH70C)	1/33	176 (221)	27	45	$24^{+0.021}_{0}$	59	5	6-M6×10L	2.4 (2.7)

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 Dimensions not found in the table above are the same as those in the table on the previous page.


IMPORTANT

Regarding the flange output type shaft end, when the flange "LC" is 40 mm, we recommend designing a servomotor with the dimensions shown in the diagram on the right, in order to secure the gap between the gear oil seal and the parts on the load side.



Global Support Product (see page viii)

(2) 200 to 400 W



Model SGMJV-	Gear Ratio	L	LL	LM	Flange Face Dimensions								
					LR	LE	LG	B	LD	LB	LC	LA	LZ
02A□AH1[*]1 (02A□AH1[*]C)	1/5	202 (242)	144 (184)	115	58	2.5	8	40	55.5	$56^{0}_{-0.030}$	60	70	5.5
02A□AHB[*]1 (02A□AHB[*]C)	1/11												
02A□AHC[*]1 (02A□AHC[*]C)	1/21	231 (271)	151 (191)	122	80	7.5	10	59	84	$85^{0}_{-0.035}$	90	105	9
02A□AH7[*]1 (02A□AH7[*]C)	1/33												
04A□AH1[*]1 (04A□AH1[*]C)	1/5	220.5 (260.5)	162.5 (202.5)	133.5	58	2.5	8	40	55.5	$56^{0}_{-0.030}$	60	70	5.5
04A□AHB[*]1 (04A□AHB[*]C)	1/11	249.5 (289.5)	169.5 (209.5)	140.5	80	7.5	10	59	84	$85^{0}_{-0.035}$	90	105	9
04A□AHC[*]1 (04A□AHC[*]C)	1/21												
04A□AH7[*]1 (04A□AH7[*]C)	1/33	335.5 (375.5)	202.5 (242.5)	173.5	133	12.5	13	84	114	$115^{0}_{-0.035}$	120	135	11

Model SGMJV-	Flange Face Dimensions			Q	C	S	Tap × Depth	Key Dimensions				Approx. Mass kg
	L1	L2	L3					QK	U	W	T	
02A□AH1[*]1 (02A□AH1[*]C)	28	30	20	28	20	$16^{0}_{-0.018}$	M4 × 8L	25	3	5	5	1.9 (2.5)
02A□AHB[*]1 (02A□AHB[*]C)												2.0 (2.6)
02A□AHC[*]1 (02A□AHC[*]C)	36	44	26	42	32	$25^{0}_{-0.021}$	M6 × 12L	36	4	8	7	3.8 (4.4)
02A□AH7[*]1 (02A□AH7[*]C)												
04A□AH1[*]1 (04A□AH1[*]C)	28	30	20	28	20	$16^{0}_{-0.018}$	M4 × 8L	25	3	5	5	2.3 (2.9)
04A□AHB[*]1 (04A□AHB[*]C)	36	44	26	42	32	$25^{0}_{-0.021}$	M6 × 12L	36	4	8	7	4.2 (4.8)
04A□AHC[*]1 (04A□AHC[*]C)												
04A□AH7[*]1 (04A□AH7[*]C)	48	85	33	82	44	$40^{0}_{-0.025}$	M10 × 20L	70	5	12	8	8.8 (9.4)


*: The asterisk (*) describes the values of the 8th digit of the model designation, "shaft end code 6 (straight with key and tap)." If a key or tap is not necessary, order a servomotor with "shaft end code 2 (without key and tap)."

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 Please note that gear dimensions are different from those of Σ-Ⅰ, Σ-Ⅱ, and Σ-Ⅲ series.

Global Support Product (see page viii)

With Low-backlash Gears — External Dimensions Units: mm

●Flange Output Face




Model SGMJV-	Gear Ratio	L	LR	LJ	F	G	No. of pcs Tap × Depth	Approx. Mass kg
02A□AH101 (02A□AH10C)	1/5	165 (205)	21	30	$14^{+0.018}_{0}$	40	6-M4 × 7L	1.8 (2.4)
02A□AHB01 (02A□AHB0C)	1/11							1.9 (2.5)
02A□AHC01 (02A□AHC0C)	1/21	178 (218)	27	45	$24^{+0.021}_{0}$	59	6-M6 × 10L	3.4 (4.0)
02A□AH701 (02A□AH70C)	1/33							
04A□AH101 (04A□AH10C)	1/5	183.5 (223.5)	21	30	$14^{+0.018}_{0}$	40	6-M4 × 7L	2.2 (2.8)
04A□AHB01 (04A□AHB0C)	1/11	196.5 (236.5)	27	45	$24^{+0.021}_{0}$	59	6-M6 × 10L	3.8 (4.4)
04A□AHC01 (04A□AHC0C)	1/21							
04A□AH701 (04A□AH70C)	1/33	237.5 (277.5)	35	60	$32^{+0.025}_{0}$	84	6-M8 × 12L	7.4 (8.0)

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 Dimensions not found in the table above are the same as those in the table on the previous page.

Global Support Product (see page viii)

(3) 750 W



Model SGMJV-	Gear Ratio	L	LL	LM	Flange Face Dimensions								
					LR	LE	LG	B	LD	LB	LC	LA	LZ
08A□AH1□1 (08A□AH1□C)	1/5	273 (318)	193 (238)	163	80	7.5	10	59	84	$85^{0}_{-0.035}$	90	105	9
08A□AHB□1 (08A□AHB□C)	1/11												
08A□AHC□1 (08A□AHC□C)	1/21	352 (397)	219 (264)	189	133	12.5	13	84	114	$115^{0}_{-0.035}$	120	135	11
08A□AH7□1 (08A□AH7□C)	1/33												

Model SGMJV-	Flange Face Dimensions			Q	C	S	Tap × Depth	Key Dimensions				Approx. Mass kg
	L1	L2	L3					QK	U	W	T	
08A□AH1□1 (08A□AH1□C)	36	44	26	42	32	$25^{0}_{-0.021}$	M6 × 12L	36	4	8	7	5.6 (6.5)
08A□AHB□1 (08A□AHB□C)												5.8 (6.7)
08A□AHC□1 (08A□AHC□C)	48	85	33	82	44	$40^{0}_{-0.025}$	M10 × 20L	70	5	12	8	10.5 (11.4)
08A□AH7□1 (08A□AH7□C)												


*: The asterisk (*) describes the values of the 8th digit of the model designation, “shaft end code 6 (straight with key and tap).” If a key or tap is not necessary, order a servomotor with “shaft end code 2 (without key and tap).”

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 Please note that gear dimensions are different from those of Σ-Ⅰ, Σ-Ⅱ, and Σ-Ⅲ series.

Global Support Product (see page viii)

With Low-backlash Gears | External Dimensions Units: mm

● Flange Output Face



Model SGMJV-	Gear Ratio	L	LR	LJ	F	G	No. of pcs Tap × Depth	Approx. Mass kg
08A□AH101 (A8A□AH10C)	1/5	220 (265)	27	45	$24^{+0.021}_{0}$	59	6-M6 × 10L	5.2 (6.1)
08A□AHB01 (A8A□AHB0C)	1/11							5.4 (6.3)
08A□AHC01 (A8A□AHC0C)	1/21	254 (299)	35	60	$32^{+0.025}_{0}$	84	6-M8 × 12L	9.1 (10.0)
08A□AH701 (A8A□AH70C)	1/33							

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 Dimensions not found in the table above are the same as those in the table on the previous page.

Global Support Product (see page viii)

Rotary Servomotors

SGMAV



efesotomasyon.com

Model Designations

● Without Gears

SGMAV - 01 A D A 2 1

Σ-V Series Servomotor SGMAV	1st+2nd digits	3rd digit	4th digit	5th digit	6th digit	7th digit

1st+2nd digits Rated Output

Code	Specifications
A5	50 W
01	100 W
C2	150 W
02	200 W
04	400 W
06	550 W
08	750 W
10	1.0 kW

3rd digit Power Supply Voltage

Code	Specifications
A	200 VAC

4th digit Serial Encoder

Code	Specifications
3	20-bit absolute *
D	20-bit incremental

*: When exporting the servomotors themselves, export restrictions may apply. Follow each country's export restrictions.

5th digit Design Revision Order

Code	Specifications
A	Standard

6th digit Shaft End

Code	Specifications
2	Straight without key
6	Straight with key and tap
B	With two flat seats

NOTE: Shaded items are non-stock.

7th digit Options

Code	Specifications
1	Without options
C	With holding brake (24 VDC)
E	With oil seal and holding brake (24 VDC)
S	With oil seal

Features

- Super high power rate (Extremely low inertia)
- Instantaneous peak torque (300% of rated torque)
- Mounted high-resolution serial encoder: 20 bits
- Maximum speed: 6,000 min^{-1}
- Wide selection: 50 W to 1.0 kW capacity, holding brake and gear options

Application Examples

- Semiconductor equipment
- Chip mounters
- PCB drilling stations
- Robots
- Material handling machines
- Food processing equipment

- With Gears (Global Support - Refer to Stock Status Definitions - page viii)

SGMAV - 01 A D A H 1 2 1

Σ-V Series Servomotor SGMAV	1st+2nd digits	3rd digit	4th digit	5th digit	6th digit	7th digit	8th digit	9th digit

1st+2nd digits Rated Output

Code	Specifications
A5	50 W
01	100 W
C2	150 W
02	200 W
04	400 W
06	550 W
08	750 W
10	1.0 kW

3rd digit Power Supply Voltage

Code	Specifications
A	200 VAC

4th digit Serial Encoder

Code	Specifications
3	20-bit absolute (standard)*
D	20-bit incremental (standard)

*: When exporting the servomotors themselves, export restrictions may apply. Follow each country's export restrictions.

5th digit Design Revision Order

Code	Specifications
A	Standard

6th digit Gear Type

Code	Specifications
H	HDS planetary low-backlash gear

7th digit Gear Ratio

Code	Specifications
B	1/11 (Not available: 50 W)
C	1/21
1	1/5
2	1/9 (Only 50 W)
7	1/33

8th digit Shaft End

Code	Specifications
0	Flange output
2	Straight without key
6	Straight with key and tap

9th digit Options

Code	Specifications
1	Without options
C	With holding brake (24 VDC)

Ratings and Specifications


Time Rating: Continuous
Vibration Class: V15
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40˚C
Excitation: Permanent magnet
Mounting: Flange-mounted
Thermal Class: B

Withstand Voltage: 1500 VAC for one minute
Enclosure: Totally enclosed, self-cooled, IP65 (except for shaft opening)
Ambient Humidity: 20% to 80% (no condensation)
Drive Method: Direct drive
Rotation Direction: Counterclockwise (CCW) with forward run reference when viewed from the load side

Voltage		200 V							
Servomotor Model: SGMAV-□□□		A5A	01A	C2A	02A	04A	06A	08A	10A
Rated Output*1	W	50	100	150	200	400	550	750	1000
Rated Torque*1, *2	N·m	0.159	0.318	0.477	0.637	1.27	1.75	2.39	3.18
Instantaneous Peak Torque*1	N·m	0.477	0.955	1.43	1.91	3.82	5.25	7.16	9.55
Rated Current*1	A_{rms}	0.66	0.91	1.3	1.5	2.6	3.8	5.3	7.4
Instantaneous Max. Current*1	A_{rms}	2.1	2.8	4.2	5.3	8.5	12.2	16.6	23.9
Rated Speed*1	min^{-1}	3000							
Max. Speed*1	min^{-1}	6000							
Torque Constant	$N·m/A_{rms}$	0.265	0.375	0.381	0.450	0.539	0.496	0.487	0.467
Rotor Moment of Inertia	$×10^{-4}$ kg·m²	0.0242 (0.0389)	0.0380 (0.0527)	0.0531 (0.0678)	0.116 (0.180)	0.190 (0.254)	0.326 (0.403)	0.769 (0.940)	1.20 (1.41)
Rated Power Rate*1	kW/s	10.4	26.6	42.8	35.0	84.9	93.9	74.1	84.3
Rated Angular Acceleration*1	rad/s²	65800	83800	89900	54900	67000	53700	31000	26500
Applicable SERVOPACK	SGDV-□□□□	R70□	R90□	1R6A,2R1F		2R8□	5R5A	5R5A	120A

*1: These items and torque-motor speed characteristics quoted in combination with an SGDV SERVOPACK are at an armature winding temperature of 100˚C. Other values quoted are at 20˚C.
*2: Rated torques are continuous allowable torque values at 40˚C with an aluminum heat sink of the following dimensions attached.
SGMAV-A5A, -01A: 200 mm×200 mm×6 mm
SGMAV-C2A, -02A, -04A, -06A, -08A: 250 mm×250 mm×6 mm
SGMAV-10A: 300 mm×300 mm×12 mm
Note: The values in parentheses are for servomotors with holding brakes.

●Torque-Motor Speed Characteristics A: Continuous Duty Zone B: Intermittent Duty Zone(See Note3)



Notes: 1 The solid, dotted, and dashed-dotted lines of the intermittent duty zone indicate the characteristics when a servomotor runs with the following combinations:
· The solid line: With a three-phase 200 V or a single-phase 230 V SERVOPACK
· The dotted line: With a single-phase 200 V SERVOPACK
· The dashed-dotted line: With a single-phase 100 V SERVOPACK
An SGMAV-A5A servomotor has the same characteristics in combination with three-phase 200 V and single-phase 200 V SERVOPACKs.
2 The characteristics of the intermittent duty zone differ depending on the supply voltages.
3 When the effective torque during intermittent duty is within the rated torque, the servomotor can be used within the intermittent duty zone.
4 When the main circuit cable length exceeds 20 m, note that the intermittent duty zone of the Torque-Motor Speed Characteristics will shrink as the line-to-line voltage drops.

Ratings and Specifications

●Derating Rate for Servomotor Fitted with an Oil Seal

When a motor is fitted with an oil seal, use the following derating rate because of the higher friction torque.

Servomotor Model SGMAV-	A5A	01A	C2A	02A	04A	06A	08A	10A
Derating Rate %	80	90			95			


●Holding Brake Electrical Specifications

Holding Brake Rated Voltage	Servomotor Model	Servomotor Rated Output W	Holding Brake Specifications					
			Capacity W	Holding Torque N·m	Coil Resistance Ω(at 20°C)	Rated Current A(at 20°C)	Brake Release Time ms	Brake Operation Time ms
24 VDC$^{+10\%}_{0}$	SGMAV-A5A	50	5.5	0.159	103	0.23	60	100
	SGMAV-01A	100		0.318				
	SGMAV-C2A	150	5.1	0.477	114	0.21	60	100
	SGMAV-02A	200	6	0.637	97.4	0.25	60	100
	SGMAV-04A	400		1.27				
	SGMAV-06A	550	8	1.75	74.3	0.32	80	100
	SGMAV-08A	750	6.5	2.39	87.7	0.27	80	100
	SGMAV-10A	1000	7	3.18	82.8	0.29	80	100

Notes: 1 The holding brake is only used to hold the load and cannot be used to stop the servomotor.
2 The holding brake open time and holding brake operation time vary depending on which discharge circuit is used. Make sure holding brake open time and holding brake operation time are correct for your servomotor.
3 A 24-VDC power supply is provided by customers.

●Overload Characteristics

The overload detection level is set under hot start conditions at a servomotor ambient temperature of 40°C.



Note: Overload characteristics shown above do not guarantee continuous duty of 100% or more output. Use a servomotor with effective torque within the continuous duty zone of Torque-Motor Speed Characteristics.

●Allowable Load Moment of Inertia at the Motor Shaft

The rotor moment of inertia ratio is the value for a servomotor without a gear and a brake.


Servomotor Model		Servomotor Rated Output	Allowable Load Moment of Inertia (Rotor Moment of Inertia Ratio)
SGMAV-	A5A, 01A, C2A, 02A	50 to 200 W	30 times
	04A, 06A, 08A	400 to 750 W	20 times
	10A	1000 W	10 times

●Load Moment of Inertia

- The larger the load moment of inertia, the worse the movement response.
- The allowable load moment of inertia (J_L) depends on motor capacity, as shown above. This value is provided strictly as a guideline and results may vary depending on servomotor drive conditions.
- Use the AC servo drive capacity selection program SigmaJunmaSize+ to check the operation conditions. The program can be downloaded for free from our web site (http://www.e-mechatronics.com/).
- An overvoltage alarm (A.400) is likely to occur during deceleration if the load moment of inertia exceeds the allowable load moment of inertia. SERVOPACKs with a built-in regenerative resistor may generate a regenerative overload alarm (A.320). Take one of the following steps if this occurs.
  - · Reduce the torque limit.
  - · Reduce the deceleration rate.
  - · Reduce the maximum speed.
  - · Install an external regenerative resistor if the alarm cannot be cleared using the steps above. Refer to Regenerative Resistors on page 339.
- Regenerative resistors are not built into SERVOPACKs for 400 W motors or less.
- External regenerative resistors are required when this condition is exceeded or if the allowable loss capacity (W) of the built-in regenerative resistor is exceeded due to regenerative drive conditions when a regenerative resistor is already built in.


●Allowable Radial and Thrust Loads

Design the mechanical system so thrust and radial loads applied to the servomotor shaft end during operation fall within the ranges shown in the table.

Servomotor Model		Allowable Radial Load (Fr) N	Allowable Thrust Load (Fs) N	LR mm	Reference Diagram
SGMAV-	A5A	78	54	20	
	01A				
	C2A				
	02A	245	74	25	
	04A				
	06A				
	08A	392	147	35	
	10A				

External Dimensions Units: mm

(1) 50 to 150 W




Model SGMAV-	L	LL	LM	S	Tap × Depth	Key Dimensions				Approx. Mass kg
						QK	U	W	T	
A5A□A21 (A5A□A2C)	95.5 (140.5)	70.5 (115.5)	38.5	8 0 -0.009 *	No tap	No key				0.3 (0.6)
A5A□A61 (A5A□A6C)					M3 × 6L	14	1.8	3	3	
01A□A21 (01A□A2C)	107.5 (152.5)	82.5 (127.5)	50.5	8 0 -0.009	No tap	No key				0.4 (0.7)
01A□A61 (01A□A6C)					M3 × 6L	14	1.8	3	3	
C2A□A21 (C2A□A2C)	119.5 (164.5)	94.5 (139.5)	62.5	8 0 -0.009	No tap	No key				0.5 (0.8)
C2A□A61 (C2A□A6C)					M3 × 6L	14	1.8	3	3	

Note: The models and values in parentheses are for servomotors with holding brakes.

*: When you need the same shaft diameter as the conventional servomotors, contact your Yaskawa representative.


Shaft End and Other Options

●With Two Flat Seats



Model SGMAV-	Dimensions of Servomotor with Two Flat Seats		
	QH	H1	H2
A5A□AB□	15	7.5	7.5
01A□AB□			
C2A□AB□			


●With an Oil Seal



Note: The 7th digit of the model designation is “S” or “E.”
The key dimensions are the same as those in the table above.

External Dimensions Units: mm

(2) 200 W to 1.0 kW




Model SGMAV-	L	LL	LM	Flange Face Dimensions							S	Tap × Depth	Key Dimensions				MD	MW	MH	Approx. Mass kg
				LR	LE	LG	LC	LA	LB	LZ			QK	U	W	T				
02A□A21 (02A□A2C)	110 (150)	80 (120)	51	30	3	6	60	70	$50^{0}_{-0.025}$	5.5	$14^{0}_{-0.011}$	No tap	No key				8.5	21	13	0.9 (1.5)
02A□A61 (02A□A6C)												M5×8L	14	3	5	5				
04A□A21 (04A□A2C)	128.5 (168.5)	98.5 (138.5)	69.5	30	3	6	60	70	$50^{0}_{-0.025}$	5.5	$14^{0}_{-0.011}$	No tap	No key				8.5	21	13	1.2 (1.8)
04A□A61 (04A□A6C)												M5×8L	14	3	5	5				
06A□A21 (06A□A2C)	154.5 (200.5)	124.5 (170.5)	95.5	30	3	6	60	70	$50^{0}_{-0.025}$	5.5	$14^{0}_{-0.011}$	No tap	No key				8.5	21	13	1.7 (2.4)
06A□A61 (06A□A6C)												M5×8L	14	3	5	5				
08A□A21 (08A□A2C)	155 (200)	115 (160)	85	40	3	8	80	90	$70^{0}_{-0.030}$	7	$19^{0}_{-0.013}$ *	No tap	No key				13.8	27	15	2.6 (3.2)
08A□A61 (08A□A6C)												M6×10L	22	3.5	6	6				
10A□A21 (10A□A2C)	185 (235)	145 (195)	115	40	3	8	80	90	$70^{0}_{-0.030}$	7	$19^{0}_{-0.013}$ *	No tap	No key				13.8	27	15	3.6 (4.6)
10A□A61 (10A□A6C)												M6×10L	22	3.5	6	6				

Note: The models and values in parentheses are for servomotors with holding brakes.
*: When you need the same shaft diameter as the conventional servomotors, contact your Yaskawa representative.


Shaft End and Other Options

● With Two Flat Seats



Model SGMAV-	Dimensions of Servomotor with Two Flat Seats			
	QH	S	H1	H2
02A□AB□	14	$14^{0}_{-0.011}$	13	13
04A□AB□				
06A□AB□				
08A□AB□	22	$19^{0}_{-0.013}$	18	18
10A□AB□				

● With an Oil Seal




Model SGMAV-	Dimensions of Servomotor with an Oil Seal			
	E1	E2	LS1	LS2
02A, 04A, 06A	36	48	4	10
08A,10A	49	66	6	11

Note: The 7th digit of the model designation is “S” or “E.”
The key dimensions are the same as those in the table above.

Selecting Cables


●Cables Connections

●Standard Wiring (Max. encoder cable length: 20 m)



●Encoder Cable Extension from 30 to 50 m


(Example)



⚠CAUTION

- Separate the servomotor main circuit cable wiring from the I/O signal cable and encoder cable at least 30 cm, and do not bundle or run them in the same duct.
- When the cable length exceeds 20 m, be sure to use a relay encoder cable.
- When the main circuit cable length exceeds 20 m, note that the intermittent duty zone of the Torque-Motor Speed Characteristics will shrink as the line-to-line voltage drops.


●Servomotor Main Circuit Cable

Name	Servomotor Rated Output	Length	Order No.		Specifications	Details
			Standard Type	Flexible Type*		
For Servomotor without Holding Brakes	50 to 150 W	3 m	JZSP-CSM01-03-E	JZSP-CSM21-03-E		(1)
		5 m	JZSP-CSM01-05-E	JZSP-CSM21-05-E		
		10 m	JZSP-CSM01-10-E	JZSP-CSM21-10-E		
		15 m	JZSP-CSM01-15-E	JZSP-CSM21-15-E		
		20 m	JZSP-CSM01-20-E	JZSP-CSM21-20-E		
		30 m	JZSP-CSM01-30-E	JZSP-CSM21-30-E		
		40 m	JZSP-CSM01-40-E	JZSP-CSM21-40-E		
		50 m	JZSP-CSM01-50-E	JZSP-CSM21-50-E		
	200 to 550 W	3 m	JZSP-CSM02-03-E	JZSP-CSM22-03-E		
		5 m	JZSP-CSM02-05-E	JZSP-CSM22-05-E		
		10 m	JZSP-CSM02-10-E	JZSP-CSM22-10-E		
		15 m	JZSP-CSM02-15-E	JZSP-CSM22-15-E		
		20 m	JZSP-CSM02-20-E	JZSP-CSM22-20-E		
		30 m	JZSP-CSM02-30-E	JZSP-CSM22-30-E		
		40 m	JZSP-CSM02-40-E	JZSP-CSM22-40-E		
		50 m	JZSP-CSM02-50-E	JZSP-CSM22-50-E		
	750 W, 1.0 kW	3 m	JZSP-CSM03-03-E	JZSP-CSM23-03-E		
		5 m	JZSP-CSM03-05-E	JZSP-CSM23-05-E		
		10 m	JZSP-CSM03-10-E	JZSP-CSM23-10-E		
		15 m	JZSP-CSM03-15-E	JZSP-CSM23-15-E		
		20 m	JZSP-CSM03-20-E	JZSP-CSM23-20-E		
		30 m	JZSP-CSM03-30-E	JZSP-CSM23-30-E		
		40 m	JZSP-CSM03-40-E	JZSP-CSM23-40-E		
		50 m	JZSP-CSM03-50-E	JZSP-CSM23-50-E		

*: Use flexible cables for movable sections such as robot arms.

(Cont'd)

Selecting Cables

Name	Servomotor Rated Output	Length	Order No.		Specifications	Details
			Standard Type	Flexible Type*		
For Servomotor with Holding Brakes	50 to 150 W	3 m	JZSP-CSM11-03-E	JZSP-CSM31-03-E		(2)
		5 m	JZSP-CSM11-05-E	JZSP-CSM31-05-E		
		10 m	JZSP-CSM11-10-E	JZSP-CSM31-10-E		
		15 m	JZSP-CSM11-15-E	JZSP-CSM31-15-E		
		20 m	JZSP-CSM11-20-E	JZSP-CSM31-20-E		
		30 m	JZSP-CSM11-30-E	JZSP-CSM31-30-E		
		40 m	JZSP-CSM11-40-E	JZSP-CSM31-40-E		
		50 m	JZSP-CSM11-50-E	JZSP-CSM31-50-E		
	200 to 550 W	3 m	JZSP-CSM12-03-E	JZSP-CSM32-03-E		
		5 m	JZSP-CSM12-05-E	JZSP-CSM32-05-E		
		10 m	JZSP-CSM12-10-E	JZSP-CSM32-10-E		
		15 m	JZSP-CSM12-15-E	JZSP-CSM32-15-E		
		20 m	JZSP-CSM12-20-E	JZSP-CSM32-20-E		
		30 m	JZSP-CSM12-30-E	JZSP-CSM32-30-E		
		40 m	JZSP-CSM12-40-E	JZSP-CSM32-40-E		
		50 m	JZSP-CSM12-50-E	JZSP-CSM32-50-E		
	750 W, 1.0 kW	3 m	JZSP-CSM13-03-E	JZSP-CSM33-03-E		
		5 m	JZSP-CSM13-05-E	JZSP-CSM33-05-E		
		10 m	JZSP-CSM13-10-E	JZSP-CSM33-10-E		
		15 m	JZSP-CSM13-15-E	JZSP-CSM33-15-E		
		20 m	JZSP-CSM13-20-E	JZSP-CSM33-20-E		
		30 m	JZSP-CSM13-30-E	JZSP-CSM33-30-E		
		40 m	JZSP-CSM13-40-E	JZSP-CSM33-40-E		
		50 m	JZSP-CSM13-50-E	JZSP-CSM33-50-E		
Servomotor-end Connector Kit	50 to 150 W		JZSP-CSM9-1-E		Crimping Type (A crimp tool is required.) 	(3)
	200 to 550 W		JZSP-CSM9-2-E			(4)
	750 W, 1.0 kW		JZSP-CSM9-3-E			(5)
Cables	50 to 550 W	5 m	JZSP-CSM90-05-E	JZSP-CSM80-05-E		(6)
		10 m	JZSP-CSM90-10-E	JZSP-CSM80-10-E		
		15 m	JZSP-CSM90-15-E	JZSP-CSM80-15-E		
		20 m	JZSP-CSM90-20-E	JZSP-CSM80-20-E		
		30 m	JZSP-CSM90-30-E	JZSP-CSM80-30-E		
		40 m	JZSP-CSM90-40-E	JZSP-CSM80-40-E		
		50 m	JZSP-CSM90-50-E	JZSP-CSM80-50-E		
	750 W, 1.0kW	5 m	JZSP-CSM91-05-E	JZSP-CSM81-05-E		(7)
		10 m	JZSP-CSM91-10-E	JZSP-CSM81-10-E		
		15 m	JZSP-CSM91-15-E	JZSP-CSM81-15-E		
		20 m	JZSP-CSM91-20-E	JZSP-CSM81-20-E		
		30 m	JZSP-CSM91-30-E	JZSP-CSM81-30-E		
		40 m	JZSP-CSM91-40-E	JZSP-CSM81-40-E		
		50 m	JZSP-CSM91-50-E	JZSP-CSM81-50-E		

*: Use flexible cables for movable sections such as robot arms.

Selecting Cables

(1) Wiring Specifications for Servomotors without Holding Brakes

SERVOPACK-end Leads		Servomotor-end Connector	
Wire Color	Signal	Signal	Pin No.
Green/yellow	FG	FG	1
Blue	Phase W	Phase W	2
White	Phase V	Phase V	3
Red	Phase U	Phase U	4
		–	5
		–	6


Note: This cable is not shielded.

(2) Wiring Specifications for Servomotor with Holding Brakes


SERVOPACK-end Leads		Servomotor-end Connector	
Wire Color	Signal	Signal	Pin No.
Green/yellow	FG	FG	1
Blue	Phase W	Phase W	2
White	Phase V	Phase V	3
Red	Phase U	Phase U	4
Black	Brake	Brake	5
Black	Brake	Brake	6

Note: No polarity for connection to a holding brake.
Note: This cable is not shielded.


(3) Servomotor-end Connector Kit Specifications: For 50 to 150 W Servomotors

Items		Specifications	External Dimensions mm
Order No.		JZSP-CSM9-1-E (Cables are not included.)	
Applicable Servomotors		SGMAV-A5A, -01A, -C2A	
Manufacturer		J.S.T. Mfg. Co., Ltd.	
Receptacle		J17-06FMH-7KL-1-CF	
Electrical Contact		SJ1F-01GF-P0.8	
Applicable Wire Size		AWG20 to 24	
Outer Diameter of Insulating Sheath		1.11 dia. to 1.53 dia. mm	
Crimp Tool	Hand tool	YRS-8841	
	Applicator	APLMK SJ1F/M-01-08	
Mounting Screw		M2 Pan-head screw	
Applicable Cable Outer Diameter		7±0.3 dia. mm	

(4) Servomotor-end Connector Kit Specifications: For 200 to 550 W Servomotors


Items		Specifications	External Dimensions mm
Order No.		JZSP-CSM9-2-E (Cables are not included.)	
Applicable Servomotors		SGMAV-02A, -04A, -06A	
Manufacturer		J.S.T. Mfg. Co., Ltd.	
Receptacle		J27-06FMH-7KL-1-CF	
Electrical Contact		SJ2F-01GF-P1.0	
Applicable Wire Size		AWG20 to 24	
Outer Diameter of Insulating Sheath		1.11 dia. to 1.53 dia. mm	
Crimp Tool	Hand tool	YRS-8861	
	Applicator	APLMK SJ2F/M-01-08	
Mounting Screw		M2 Pan-head screw	
Applicable Cable Outer Diameter		7±0.3 dia. mm	

(5) Servomotor-end Connector Kit Specifications: For 750 W, 1.0 kW Servomotors

Items		Specifications		External Dimensions mm
Order No.		JZSP-CSM9-3-E (Cables are not included.)		
Applicable Servomotors		SGMAV-08A,-10A		
Manufacturer		J.S.T. Mfg. Co., Ltd.		
Receptacle		J37-06FMH-8KL-1-CF		
Cable Type		Standard		
Electrical Contact		SJ3F-41GF-P1.8 (For power terminals)	SJ3F-01GF-P1.8 (For holding brake terminals)	
Applicable Wire Size		AWG16 to 20	AWG20 to 24	
Outer Diameter of Insulating Sheath		1.53 dia. to 2.5 dia. mm	1.11 dia. to 1.86 dia. mm	
Crimp Tool	Hand tool	YRF-880	YRF-881	
	Applicator	APLMK SF3F/M-41-20	APLMK SF3F/M-01-20	
Mounting Screw		M2.5 Pan-head screw		
Applicable Cable Outer Diameter		8±0.3 dia. mm		


Selecting Cables

(6) Cable Specifications: For 50 to 550 W Servomotors

Items	Standard Type	Flexible Type
Order No.*	JZSP-CSM90-□□-E (50 m max.)	JZSP-CSM80-□□-E (50 m max.)
Specifications	UL2517 (Max. operating temperature: 105°C) AWG20×6C For power line: AWG20 (0.52 mm^2) Outer diameter of insulating sheath: 1.53 dia. mm For holding brake line: AWG20 (0.52 mm^2) Outer diameter of insulating sheath: 1.53 dia. mm	UL2517 (Max. operating temperature: 105°C) AWG22×6C For power line: AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.37 dia. mm For holding brake line: AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.37 dia. mm
Finished Dimensions	7±0.3 dia. mm	
Internal Configuration and Lead Color		
Yaskawa Standard Specifications (Standard Length)	Cable length: 5 m, 10 m, 15 m, 20 m, 30 m, 40 m, 50 m	

*: Specify the cable length in □□ of order no.
Example: JZSP-CSM90-05-E (5 m)

(7) Cable Specifications: For 750 W, 1.0 kW Servomotors

Items	Standard Type	Flexible Type
Order No.*	JZSP-CSM91-□□-E (50 m max.)	JZSP-CSM81-□□-E (50 m max.)
Specifications	UL2517 (Max. operating temperature: 105°C) AWG16×4C, AWG20×2C For power line: AWG16 (1.31 mm^2) Outer diameter of insulating sheath: 2.15 dia. mm For holding brake line: AWG20 (0.52 mm^2) Outer diameter of insulating sheath: 1.6 dia. mm	UL2517 (Max. operating temperature: 105°C) AWG16×4C, AWG22×2C For power line: AWG16 (1.31 mm^2) Outer diameter of insulating sheath: 2.35 dia. mm For holding brake line: AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.37 dia. mm
Finished Dimensions	8±0.3 dia. mm	
Internal Configuration and Lead Color		
Yaskawa Standard Specifications (Standard Length)	Cable length: 5 m, 10 m, 15 m, 20 m, 30 m, 40 m, 50 m	

*: Specify the cable length in □□ of order no.
Example: JZSP-CSM91-15-E (15 m)

Selecting Cables

●Encoder Cables (Length: 20 m or less)

Name	Length	Order No.		Specifications	Details
		Standard Type	Flexible Type*		
Cable with Connectors (For Incremental Encoder)	3 m	JZSP-CSP01-03-E	JZSP-CSP21-03-E	SERVOPACK End L Encoder End Connector (Crimped) (Molex Japan Co., Ltd.) Connector (Molex Japan Co., Ltd.)	(1)
	5 m	JZSP-CSP01-05-E	JZSP-CSP21-05-E		
	10 m	JZSP-CSP01-10-E	JZSP-CSP21-10-E		
	15 m	JZSP-CSP01-15-E	JZSP-CSP21-15-E		
	20 m	JZSP-CSP01-20-E	JZSP-CSP21-20-E		
Cable with Connectors (For Absolute Encoder, with a Battery Case)	3 m	JZSP-CSP05-03-E	JZSP-CSP25-03-E	SERVOPACK End L Encoder End Battery Case (Battery attached) Connector (Crimped) (Molex Japan Co., Ltd.) Connector (Molex Japan Co., Ltd.)	(2)
	5 m	JZSP-CSP05-05-E	JZSP-CSP25-05-E		
	10 m	JZSP-CSP05-10-E	JZSP-CSP25-10-E		
	15 m	JZSP-CSP05-15-E	JZSP-CSP25-15-E		
	20 m	JZSP-CSP05-20-E	JZSP-CSP25-20-E		
SERVOPACK-end Connector Kit		JZSP-CMP9-1-E		Soldered	(3)
Encoder-end Connector Kit		JZSP-CSP9-2-E		Crimping Type (A crimp tool is required.)	
Cables	3 m	JZSP-CMP09-03-E	JZSP-CSP39-03-E		(4)
	5 m	JZSP-CMP09-05-E	JZSP-CSP39-05-E		
	10 m	JZSP-CMP09-10-E	JZSP-CSP39-10-E		
	15 m	JZSP-CMP09-15-E	JZSP-CSP39-15-E		
	20 m	JZSP-CMP09-20-E	JZSP-CSP39-20-E		

*: Use flexible cables for movable sections such as robot arms.
Note: When the battery from the host controller is used for the absolute encoder, no battery case is required. In this case, use a cable for the incremental encoders.

(1) Wiring Specifications for Cable with Connectors (For incremental encoder)

· Standard Type

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG

Shield Wire

Encoder (Servomotor) End

Pin No.	Wire Color
5	Light blue/white
4	Light blue
8	Orange/white
9	Orange
3	Black
6	Red
Shell	FG

· Flexible Type

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG

Shield Wire

Encoder (Servomotor) End

Pin No.	Wire Color
5	Black/pink
4	Red/pink
8	Black/light blue
9	Red/light blue
3	Green
6	Orange
Shell	FG

(2) Wiring Specifications for Cable with Connectors (For absolute encoder, with a battery case)

· Standard Type

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG

Shield Wire

Encoder (Servomotor) End

Pin No.	Wire Color
5	Light blue/white
4	Light blue
8	Orange/white
9	Orange
3	Black
6	Red
Shell	FG

Battery Case

Pin No.	Signal
2	BAT (–)
1	BAT (+)

· Flexible Type

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG

Shield Wire

Encoder (Servomotor) End



Pin No.	Wire Color
5	Black/pink
4	Red/pink
8	Black/light blue
9	Red/light blue
3	Green
6	Orange
Shell	FG

Battery Case

Pin No.	Signal
2	BAT (–)
1	BAT (+)



Selecting Cables

(3) SERVOPACK-end/Encoder-end Connector Kit Specifications

Items	SERVOPACK-end Connector Kit	Encoder-end Connector Kit
Order No.	JZSP-CMP9-1-E (Cables are not included.)	JZSP-CSP9-2-E (Cables are not included.)
Manufacturer	Molex Japan Co., Ltd.	Molex Japan Co., Ltd.
Specifications	55100-0670 (soldered)	54346-0070 (crimped)* Mounting screw: M2 pan-head screw (×2) Outer diameter of applicable cable: 6.3 dia. to 7.7 dia. mm Applicable wire size: AWG22 to 26 Outer diameter of insulating sheath: 1.05 dia. to 1.4 dia. mm
External Dimensions mm		

*: A crimp tool is required.
The following crimp tools are applicable for the cables provided by Yaskawa. When using other wire sizes, contact the respective manufacturer for crimp tools.
Applicable crimp tool for Y askawa's wire size: Hand Tool Model No. 57175-5000
Applicator Model No. 57175-3000




(4) Cable Specifications

Items	Standard Type	Flexible Type
Order No.*	JZSP-CMP09-□□-E	JZSP-CSP39-□□-E
Cable Length	20 m max.	
Specifications	UL20276 (Max. operating temperature: 80˚C) AWG22×2C+AWG24×2P AWG22 (0.33 mm²) Outer diameter of insulating sheath: 1.15 dia. mm AWG24 (0.20 mm²) Outer diameter of insulating sheath: 1.09 dia. mm	UL20276 (Max. operating temperature: 80˚C) AWG22×2C+AWG24×2P AWG22 (0.33 mm²) Outer diameter of insulating sheath: 1.35 dia. mm AWG24 (0.20 mm²) Outer diameter of insulating sheath: 1.21 dia. mm
Finished Dimensions	6.5 dia. mm	6.8 dia. mm
Internal Configuration and Lead Color		
Yaskawa Standards Specifications (Standard Length)	Cable length: 5 m, 10 m, 15 m, 20 m	

*: Specify the cable length in □□ of order no.
Example: JZSP-CSM09-05-E (5 m)

Selecting Cables

●Relay Encoder Cables (For extending from 30 to 50 m)

Name	Length	Order No. Standard Type	Specifications	Datails
① Encoder-end Cables (For incremental and absolute encoder)	0.3 m	JZSP-CSP11-E		(1)
② Cable with Connectors (For incremental and absolute encoder)	30 m	JZSP-UCMP00-30-E		(2)
	40 m	JZSP-UCMP00-40-E		
	50 m	JZSP-UCMP00-50-E		
③ Cable with a Battery Case (Required when an absolute encoder is used.)	0.3 m	JZSP-CSP12-E*		(3)
④ Cables	30 m	JZSP-CMP19-30-E		(4)
	40 m	JZSP-CMP19-40-E		
	50 m	JZSP-CMP19-50-E		

* When using an incremental encoder or using an absolute encoder with a battery connected to the host controller, no battery case is required.

(1) Wiring Specifications for Encoder-end Cable


SERVOPACK End			Encoder (Servomotor) End	
Pin No.	Signal		Pin No.	Wire Color
6	/PS		5	Light blue/white
5	PS		4	Light blue
4	BAT (–)		8	Orange/white
3	BAT (+)		9	Orange
2	PG 0V		3	Black
1	PG 5V		6	Red
Shell	FG	Shield Wire	Shell	FG

(2) Wiring Specifications for Cable with Connectors


SERVOPACK End			Encoder (Servomotor) End	
Pin No.	Signal		Pin No.	Wire Color
6	/PS		6	Light blue/white
5	PS		5	Light blue
4	BAT (–)		4	Orange/white
3	BAT (+)		3	Orange
2	PG 0V		2	Black
1	PG 5V		1	Red
Shell	FG	Shield Wire	Shell	FG

Selecting Cables

(3) Wiring Specifications for Cable with a Battery Case



(4) Cable Specifications

Item	Standard Type
Order No.*	JZSP-CMP19-□□-E
Cable Length	50 m max.
Specifications	UL20276 (Max. operating temperature: 80˚C) AWG16×2C+AWG26×2P AWG16 (1.31 mm^2) Outer diameter of insulating sheath: 2.0 dia. mm AWG26 (0.13 mm^2) Outer diameter of insulating sheath: 0.91 dia. mm
Finished Dimensions	6.8 dia. mm
Internal Configuration and Lead Colors	
Yaskawa Standard Specifications (Standard Length)	Cable length: 30 m, 40 m, 50 m

*: Specify the cable length in □□ of order no.
Example: JZSP-CMP19-30-E (30 m)

Time Rating: Continuous
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40°C
Excitation: Permanent magnet
Mounting: Flange-mounted
Gear Mechanism: Planetary gear mechanism
Thermal Class: B

Withstand Voltage: 1500 VAC for one minute
Enclosure: Totally enclosed, self-cooled, IP55 (except for shaft opening)
Ambient Humidity: 20% to 80% (no condensation)
Drive Method: Direct drive
Rotation Direction: Counterclockwise (CCW) with forward run reference when viewed from the load side

Servomotor Model SGMAV-	Servomotor					Gear					
	Rated Output W	Rated Speed min-1	Max. Speed min-1	Rated Torque N·m	Instantaneous Peak Torque N·m	Gear Ratio	Lost Motion arc-min	Rated Torque / Efficiency*1 N·m /%	Instantaneous Peak Torque N·m	Rated Speed min-1	Max. Speed min-1
A5A□AH1□	50	3000	6000	0.159	0.477	1/5	3 max.	0.433/64*2	1.98	600	1200
A5A□AH2□						1/9		1.12/78	3.8	333	667
A5A□AHC□						1/21		2.84/85	9.0	143	286
A5A□AH7□						1/33		3.68/70	13.4	91	182
01A□AH1□	100	3000	6000	0.318	0.955	1/5	3 max.	1.06/78*2	4.20	600	1200
01A□AHB□						1/11		2.52/72	9.0	273	545
01A□AHC□						1/21		5.35/80	17.8	143	286
01A□AH7□						1/33		7.35/70	27.4	91	182
C2A□AH1□	150	3000	6000	0.477	1.43	1/5	3 max.	1.68/83*2	6.45	600	1200
C2A□AHB□						1/11		3.53/79*2	13.9	273	545
C2A□AHC□						1/21		6.3/70*2	26.2	143	286
C2A□AH7□						1/33		11.2/79*2	42.5	91	182
02A□AH1□	200	3000	6000	0.637	1.91	1/5	3 max.	2.39/75	8.31	600	1200
02A□AHB□						1/11		5.74/82	18.7	273	545
02A□AHC□						1/21		10.2/76	35.7	143	286
02A□AH7□						1/33		17.0/81	57.4	91	182
04A□AH1□	400	3000	6000	1.27	3.82	1/5	3 max.	5.35/84	17.2	600	1200
04A□AHB□						1/11		11.5/82	38.2	273	545
04A□AHC□						1/21		23.0/86	74.6	143	286
04A□AH7□						1/33		34.0/81	115	91	182
06A□AH1□	550	3000	6000	1.75	5.25	1/5	3 max.	6.9/79	23.6	600	1200
06A□AHB□						1/11		16.6/86	53.7	273	545
06A□AHC□						1/21		29.4/80	100	143	286
06A□AHH□						1/33		49.1/85	159	91	182
08A□AH1□	750	3000	6000	2.39	7.16	1/5	3 max.	10.0/84	32.9	600	1200
08A□AHB□						1/11		23.1/88	73.3	273	545
08A□AHC□						1/21		42.1/84	138	143	286
08A□AH7□						1/33		69.3/88	220	91	182
10A□AH1□	1000	3000	6000	3.18	9.55	1/5	3 max.	13.7/86	44.4	600	1200
10A□AHB□						1/11		29.1/83	96.6	273	545
10A□AHC□						1/21		58.2/87	186	143	286
10A□AH7□						1/33		94.5/90	296	91	182

Global Support Product <see page viii>

*1: Gear output torque is expressed using the following equation.

$$\text{(Gear output torque)} = \text{(Servomotor output torque)} \times \frac{1}{\text{(gear ratio)}} \times \text{(efficiency)}$$

Gear efficiency depends on operating conditions such as output torque, motor speed, and temperature etc. The values in the table are representative values with rated torque, rated speed, and an ambient temperature of 25°C, and are not guaranteed values.

*2: When using SGMAV-A5A, -01A, -C2A servomotors with a gear ratio of 1/5, or an SGMAV-C2A servomotor with a gear ratio of 1/11, maintain an 85% max. effective load ratio. For an SGMAV-C2A servomotor with a gear ratio of 1/21 or 1/31, maintain a 90% max. effective load ratio.


Notes: 1 The gear mounted to our servomotor has not been broken in. Break in the servomotor if necessary. First, run the motor at low speed with no load. If no problems arise, gradually increase the speed and load.

2 The no-load torque for a servomotor with a gear is high immediately after the servomotor starts, and it then decreases and becomes stable a few minutes later. This is a common phenomenon caused by grease being circulated in the gear and not by a faulty gear.

IMPORTANT The SERVOPACK speed control range is 5000:1. When using servomotors at extremely low speeds (0.02 min-1 at gear output shaft), or when using servomotors with 1 pulse feed reference for extended periods etc., the gear bearing lubrication may be insufficient. That may cause deterioration of bearing or increase the load ratio. Contact your Yaskawa representative if you are using your servomotor under these conditions.

With Low-backlash Gears | Ratings and Specifications

●Moment of Inertia and Allowable Radial and Thrust Loads

Servomotor Model SGMAV-	Moment of Inertia × 10^{-4} kg·m²				Servomotors with Low-backlash Gears			Reference Diagram
	Motor + Gear	Gear	Flange Output: Motor + Gear	Flange Output: Gear	Allowable Radial Load (Fr) N	Allowable Thrust Load (Fs) N	LR mm	
A5A□AH1□	0.0302	0.006	0.0292	0.005	95	431	37	
A5A□AH2□	0.0272	0.003	0.0272	0.003	113	514	37	
A5A□AHC□	0.0282	0.004	0.0282	0.004	146	663	37	
A5A□AH7□	0.0692	0.045	0.0692	0.045	267	1246	53	
01A□AH1□	0.0430	0.005	0.0420	0.004	95	431	37	
01A□AHB□	0.0980	0.060	0.0970	0.059	192	895	53	
01A□AHC□	0.0880	0.050	0.0880	0.050	233	1087	53	
01A□AH7□	0.1030	0.065	0.1020	0.064	605	2581	75	
C2A□AH1□	0.0581	0.005	0.0571	0.004	95	431	37	
C2A□AHB□	0.1131	0.060	0.1121	0.059	192	895	53	
C2A□AHC□	0.1631	0.110	0.1611	0.108	528	2254	75	
C2A□AH7□	0.1181	0.065	0.1171	0.064	605	2581	75	
02A□AH1□	0.323	0.207	0.317	0.201	152	707	53	
02A□AHB□	0.309	0.193	0.308	0.192	192	895	53	
02A□AHC□	0.606	0.490	0.604	0.480	528	2254	75	
02A□AH7□	0.566	0.450	0.565	0.449	605	2581	75	
04A□AH1□	0.397	0.207	0.391	0.201	152	707	53	
04A□AHB□	0.760	0.570	0.750	0.560	435	1856	75	
04A□AHC□	0.680	0.490	0.678	0.488	528	2254	75	
04A□AH7□	0.810	0.620	0.800	0.610	951	4992	128	
06A□AH1□	1.026	0.700	0.986	0.660	343	1465	75	
06A□AHB□	0.896	0.570	0.886	0.560	435	1856	75	
06A□AHC□	1.166	0.840	1.146	0.820	830	4359	128	
06A□AH7□	0.946	0.620	0.936	0.610	951	4992	128	
08A□AH1□	1.469	0.700	1.429	0.660	343	1465	75	
08A□AHB□	1.369	0.600	1.359	0.590	435	1856	75	
08A□AHC□	3.77	3.000	3.75	2.980	830	4359	128	
08A□AH7□	3.57	2.800	3.56	2.790	951	4992	128	
10A□AH1□	1.90	0.700	1.86	0.660	343	1465	75	
10A□AHB□	4.60	3.400	4.54	3.340	684	3590	128	
10A□AHC□	4.20	3.000	4.18	2.980	830	4359	128	
10A□AH7□	4.00	2.800	3.99	2.790	951	4992	128	

Global Support
Technical Data
(See page viii)

IMPORTANT


The gear generates the loss at gear mechanism and oil seal. The loss varies with torque and motor speed conditions. The temperature rise depends on heating conditions. Always check the actual gear and motor temperature. If the temperature is high, take the measures shown below.

- ·Decrease the load ratio.
- ·Change the heating conditions.
- ·Cool the motor with a cooling fan etc.

Rated Output W	Heat Sink Size			
	1/5	1/9 or 1/11	1/21	1/33
50	A			
100				
150	B			
200				
400	C			
550				
750				
1000				

A : 250 mm × 250 mm × 6 mm, aluminum
B : 300 mm × 300 mm × 12 mm, aluminum
C : 350 mm × 350 mm × 12 mm, aluminum

(1) 50 to 150 W



Model SGMAV-	Gear Ratio	L	LL	LM	Flange Face Dimensions LR	LE	LG	B	LD	LB	LC	LA	LZ
A5A□AH1□1 (A5A□AH1□C)	1/5	152 (197)	110 (155)	78	42	2.2	5	29	39.5	$40^{0}_{-0.025}$	40	46	3.4
A5A□AH2□1 (A5A□AH2□C)	1/9												
A5A□AHC□1 (A5A□AHC□C)	1/21	161 (206)	119 (164)	87									
A5A□AH7□1 (A5A□AH7□C)	1/33	192.5 (237.5)	134.5 (179.5)	102.5	58	2.5	8	40	55.5	$56^{0}_{-0.030}$	60	70	5.5
01A□AH1□1 (01A□AH1□C)	1/5	164 (209)	122 (167)	90	42	2.2	5	29	39.5	$40^{0}_{-0.025}$	40	46	3.4
01A□AHB□1 (01A□AHB□C)	1/11	204.5 (249.5)	146.5 (191.5)	114.5	58	2.5	8	40	55.5	$56^{0}_{-0.030}$	60	70	5.5
01A□AHC□1 (01A□AHC□C)	1/21												
01A□AH7□1 (01A□AH7□C)	1/33	229 (274)	149 (194)	117	80	7.5	10	59	84	$85^{0}_{-0.035}$	90	105	9
C2A□AH1□1 (C2A□AH1□C)	1/5	176 (221)	134 (179)	102	42	2.2	5	29	39.5	$40^{0}_{-0.025}$	40	46	3.4
C2A□AHB□1 (C2A□AHB□C)	1/11	216.5 (261.5)	158.5 (203.5)	126.5	58	2.5	8	40	55.5	$56^{0}_{-0.030}$	60	70	5.5
C2A□AHC□1 (C2A□AHC□C)	1/21	241 (286)	161 (206)	129	80	7.5	10	59	84	$85^{0}_{-0.035}$	90	105	9
C2A□AH7□1 (C2A□AH7□C)	1/33												

Model SGMAV-	Flange Face Dimensions L1	L2	L3	Q	C	S	Tap × Depth	Key Dimensions QK	U	W	T	Approx. Mass kg
A5A□AH1□1 (A5A□AH1□C)	22	20	14.6	–	–	$10^{0}_{-0.015}$	M3×6L	15	2.5	4	4	0.6 (0.9)
A5A□AH2□1 (A5A□AH2□C)												
A5A□AHC□1 (A5A□AHC□C)												0.7 (1.0)
A5A□AH7□1 (A5A□AH7□C)	28	30	20	28	20	$16^{0}_{-0.018}$	M4×8L	25	3	5	5	1.3 (1.6)
01A□AH1□1 (01A□AH1□C)	22	20	14.6	–	–	$10^{0}_{-0.015}$	M3×6L	15	2.5	4	4	0.7 (1.0)
01A□AHB□1 (01A□AHB□C)	28	30	20	28	20	$16^{0}_{-0.018}$	M4×8L	25	3	5	5	1.4 (1.7)
01A□AHC□1 (01A□AHC□C)												
01A□AH7□1 (01A□AH7□C)	36	44	26	42	32	$25^{0}_{-0.021}$	M6×12L	36	4	8	7	2.8 (3.1)
C2A□AH1□1 (C2A□AH1□C)	22	20	14.6	–	–	$10^{0}_{-0.015}$	M3×6L	15	2.5	4	4	0.8 (1.1)
C2A□AHB□1 (C2A□AHB□C)	28	30	20	28	20	$16^{0}_{-0.018}$	M4×8L	25	3	5	5	1.5 (1.8)
C2A□AHC□1 (C2A□AHC□C)	36	44	26									
C2A□AH7□1 (C2A□AH7□C)				42	32	$25^{0}_{-0.021}$	M6×12L	36	4	8	7	2.9 (3.2)


*: The asterisk (*) describes the values of the 8th digit of the model designation, “shaft end code 6 (straight with key and tap).” If a key or tap is not necessary, order a servomotor with “shaft end code 2 (without key and tap).”

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 Please note that gear dimensions are different from those of Σ-I, Σ-II, and Σ-III series.

Global Support Product (see page viii)

With Low-backlash Gears | External Dimensions Units: mm

●Flange Output Face




Model SGMAV-	Gear Ratio	L	LR	LJ	F	G	LK	No. of pcs Tap × Depth	Approx. Mass kg
A5A□AH101 (A5A□AH10C)	1/5	125 (170)	15	18	$5^{+0.012}_{0}$	24	3	3-M4×6L	0.6 (0.9)
A5A□AH201 (A5A□AH20C)	1/9								
A5A□AHC01 (A5A□AHC0C)	1/21	134 (179)							
A5A□AH701 (A5A□AH70C)	1/33	155.5 (200.5)	21	30	$14^{+0.018}_{0}$	40	5	6-M4×7L	1.2 (1.5)
01A□AH101 (01A□AH10C)	1/5	137 (182)	15	18	$5^{+0.012}_{0}$	24	3	3-M4×6L	0.7 (1.0)
01A□AHB01 (01A□AHB0C)	1/11	167.5 (212.5)	21	30	$14^{+0.018}_{0}$	40	5	6-M4×7L	1.3 (1.6)
01A□AHC01 (01A□AHC0C)	1/21								
01A□AH701 (01A□AH70C)	1/33	176 (221)	27	45	$24^{+0.021}_{0}$	59	5	6-M6×10L	2.4 (2.7)
C2A□AH101 (C2A□AH10C)	1/5	149 (194)	15	18	$5^{+0.012}_{0}$	24	3	3-M4×6L	0.8 (1.1)
C2A□AHB01 (C2A□AHB0C)	1/11	179.5 (224.5)	21	30	$14^{+0.018}_{0}$	40	5	6-M4×7L	1.4 (1.7)
C2A□AHC01 (C2A□AHC0C)	1/21	188 (233)	27	45	$24^{+0.021}_{0}$	59	5	6-M6×10L	2.5 (2.8)
C2A□AH701 (C2A□AH70C)	1/33								

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 The dimensions not given on the table above are the same as those in the table on the previous page.


IMPORTANT

Regarding the flange output type shaft end, when the flange "LC" is 40 mm, we recommend designing a servomotor with the dimensions shown in the diagram on the right, in order to secure the gap between the gear oil seal and the parts on the load side.



Global Product Support (see page viii)

(2) 200 to 550 W



Model SGMAV-	Gear Ratio	L	LL	LM	Flange Face Dimensions								
					LR	LE	LG	B	LD	LB	LC	LA	LZ
02A□AH1□1 (02A□AH1□C)	1/5	202 (242)	144 (184)	115	58	2.5	8	40	55.5	$56^{0}_{-0.030}$	60	70	5.5
02A□AHB□1 (02A□AHB□C)	1/11												
02A□AHC□1 (02A□AHC□C)	1/21	231 (271)	151 (191)	122	80	7.5	10	59	84	$85^{0}_{-0.035}$	90	105	9
02A□AH7□1 (02A□AH7□C)	1/33												
04A□AH1□1 (04A□AH1□C)	1/5	220.5 (260.5)	162.5 (202.5)	133.5	58	2.5	8	40	55.5	$56^{0}_{-0.030}$	60	70	5.5
04A□AHB□1 (04A□AHB□C)	1/11	249.5 (289.5)	169.5 (209.5)	140.5	80	7.5	10	59	84	$85^{0}_{-0.035}$	90	105	9
04A□AHC□1 (04A□AHC□C)	1/21												
04A□AH7□1 (04A□AH7□C)	1/33	335.5 (375.5)	202.5 (242.5)	173.5	133	12.5	13	84	114	$115^{0}_{-0.035}$	120	135	11
06A□AH1□1 (06A□AH1□C)	1/5	275.5 (321.5)	195.5 (241.5)	166.5	80	7.5	10	59	84	$85^{0}_{-0.035}$	90	105	9
06A□AHB□1 (06A□AHB□C)	1/11												
06A□AHC□1 (06A□AHC□C)	1/21	361.5 (407.5)	228.5 (274.5)	199.5	133	12.5	13	84	114	$115^{0}_{-0.035}$	120	135	11
06A□AH7□1 (06A□AH7□C)	1/33												

Model SGMAV-	Flange Face Dimensions			Q	C	S	Tap × Depth	Key Dimensions				Approx. Mass kg
	L1	L2	L3					QK	U	W	T	
02A□AH1□1 (02A□AH1□C)	28	30	20	28	20	$16^{0}_{-0.018}$	M4×8L	25	3	5	5	1.9 (2.5)
02A□AHB□1 (02A□AHB□C)												2.0 (2.6)
02A□AHC□1 (02A□AHC□C)	36	44	26	42	32	$25^{0}_{-0.021}$	M6×12L	36	4	8	7	3.8 (4.4)
02A□AH7□1 (02A□AH7□C)												
04A□AH1□1 (04A□AH1□C)	28	30	20	28	20	$16^{0}_{-0.018}$	M4×8L	25	3	5	5	2.2 (2.8)
04A□AHB□1 (04A□AHB□C)	36	44	26	42	32	$25^{0}_{-0.021}$	M6×12L	36	4	8	7	4.1 (4.7)
04A□AHC□1 (04A□AHC□C)												
04A□AH7□1 (04A□AH7□C)	48	85	33	82	44	$40^{0}_{-0.025}$	M10×20L	70	5	12	8	8.7 (9.3)
06A□AH1□1 (06A□AH1□C)	36	44	26	42	32	$25^{0}_{-0.021}$	M6×12L	36	4	8	7	4.4 (5.1)
06A□AHB□1 (06A□AHB□C)												4.6 (5.3)
06A□AHC□1 (06A□AHC□C)	48	85	33	82	44	$40^{0}_{-0.025}$	M10×20L	70	5	12	8	9.2 (9.9)
06A□AH7□1 (06A□AH7□C)												


*: The asterisk (*) describes the values of the 8th digit of the model designation, "shaft end code 6 (straight with key and tap)." If a key or tap is not necessary, order a servomotor with "shaft end code 2 (without key and tap)."

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 Please note that gear dimensions are different from those of Σ-Ⅰ, Σ-Ⅱ, and Σ-Ⅲ series.

Global Support Product (see page viii)

With Low-backlash Gears | External Dimensions Units: mm

●Flange Output Face




Model SGMAV-	Gear Ratio	L	LR	LJ	F	G	No. of pcs Tap × Depth	Approx. Mass kg
02A□AH101 (02A□AH10C)	1/5	165 (205)	21	30	$14^{+0.018}_{0}$	40	6-M4×7L	1.8 (2.4)
02A□AHB01 (02A□AHB0C)	1/11							1.9 (2.5)
02A□AHC01 (02A□AHC0C)	1/21	178 (218)	27	45	$24^{+0.021}_{0}$	59	6-M6×10L	3.4 (4.0)
02A□AH701 (02A□AH70C)	1/33							
04A□AH101 (04A□AH10C)	1/5	183.5 (223.5)	21	30	$14^{+0.018}_{0}$	40	6-M4×7L	2.1 (2.7)
04A□AHB01 (04A□AHB0C)	1/11	196.5 (236.5)	27	45	$24^{+0.021}_{0}$	59	6-M6×10L	3.7 (4.3)
04A□AHC01 (04A□AHC0C)	1/21							
04A□AH701 (04A□AH70C)	1/33	237.5 (277.5)	35	60	$32^{+0.025}_{0}$	84	6-M8×12L	7.3 (7.9)
06A□AH101 (06A□AH10C)	1/5	222.5 (268.5)	27	45	$24^{+0.021}_{0}$	59	6-M6×10L	4.0 (4.7)
06A□AHB01 (06A□AHB0C)	1/11							4.2 (4.9)
06A□AHC01 (06A□AHC0C)	1/21	263.5 (309.5)	35	60	$32^{+0.025}_{0}$	84	6-M8×12L	7.8 (8.5)
06A□AH701 (06A□AH70C)	1/33							

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 The dimensions not given on the table above are the same as those in the table on the previous page.

Global Support Product (see page viii)

(3) 750 W, 1.0 kW



Model SGMAV-	Gear Ratio	L	LL	LM	Flange Face Dimensions								
					LR	LE	LG	B	LD	LB	LC	LA	LZ
08A□AH1[*]1 (08A□AH1[*]C)	1/5	273 (318)	193 (238)	163	80	7.5	10	59	84	85	90	105	9
08A□AHB[*]1 (08A□AHB[*]C)	1/11												
08A□AHC[*]1 (08A□AHC[*]C)	1/21	352 (397)	219 (264)	189	133	12.5	13	84	114	115	120	135	11
08A□AH7[*]1 (08A□AH7[*]C)	1/33												
10A□AH1[*]1 (10A□AH1[*]C)	1/5	303 (353)	223 (273)	193	80	7.5	10	59	84	85	90	105	9
10A□AHB[*]1 (10A□AHB[*]C)	1/11	382 (432)	249 (299)	219	133	12.5	13	84	114	115	120	135	11
10A□AHC[*]1 (10A□AHC[*]C)	1/21												
10A□AH7[*]1 (10A□AH7[*]C)	1/33												

Model SGMAV-	Flange Face Dimensions			Q	C	S	Tap × Depth	Key Dimensions				Approx. Mass kg
	L1	L2	L3					QK	U	W	T	
08A□AH1[*]1 (08A□AH1[*]C)	36	44	26	42	32	25	M6×12L	36	4	8	7	5.2 (6.1)
08A□AHB[*]1 (08A□AHB[*]C)												5.4 (6.3)
08A□AHC[*]1 (08A□AHC[*]C)	48	85	33	82	44	40	M10×20L	70	5	12	8	10.1 (11)
08A□AH7[*]1 (08A□AH7[*]C)												
10A□AH1[*]1 (10A□AH1[*]C)	36	44	26	42	32	25	M6×12L	36	4	8	7	6.5 (7.5)
10A□AHB[*]1 (10A□AHB[*]C)	48	85	33	82	44	40	M10×20L	70	5	12	8	11.4 (12.4)
10A□AHC[*]1 (10A□AHC[*]C)												
10A□AH7[*]1 (10A□AH7[*]C)												


*: The asterisk (*) describes the values of the 8th digit of the model designation, “shaft end code 6 (straight with key and tap).” If a key or tap is not necessary, order a servomotor with “shaft end code 2 (without key and tap).”

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 Please note that gear dimensions are different from those of Σ-Ⅰ, Σ-Ⅱ, and Σ-Ⅲ series.

Global Support Product (See page vii)

With Low-backlash Gears | External Dimensions Units: mm

●Flange Output Face



Model SGMAV-	Gear Ratio	L	LR	LJ	F	G	No. of pcs Tap × Depth	Approx. Mass kg
08A□AH101 (08A□AH10C)	1/5	220 (265)	27	45	$24^{+0.021}_{0}$	59	6-M6×10L	4.8 (5.7)
08A□AHB01 (08A□AHB0C)	1/11							5.0 (5.9)
08A□AHC01 (08A□AHC0C)	1/21	254 (299)	35	60	$32^{+0.025}_{0}$	84	6-M8×12L	8.7 (9.6)
08A□AH701 (08A□AH70C)	1/33							
10A□AH101 (10A□AH10C)	1/5	250 (300)	27	45	$24^{+0.021}_{0}$	59	6-M6×10L	6.1 (7.1)
10A□AHB01 (10A□AHB0C)	1/11	284 (334)	35	60	$32^{+0.025}_{0}$	84	6-M8×12L	10.0 (11.0)
10A□AHC01 (10A□AHC0C)	1/21							
10A□AH701 (10A□AH70C)	1/33							

Notes: 1 The models and values in parentheses are for servomotors with holding brakes.
2 The dimensions not given on the table above are the same as those in the table on the previous page.

Global Support Product (see page viii)

Rotary Servomotors

SGMGV

efesotomasyon.com



Model Designations

SGMGV - 03 A D A 2 1

SGMGV	1st+2nd digits	3rd digit	4th digit	5th digit	6th digit	7th digit
Σ-V Series Servomotor SGMGV	03	A	D	A	2	1

1st+2nd digits Rated Output

Cade	Specifications
03	300 W
05	450 W
09	850 W
13	1.3 kW
20	1.8 kW
30	2.9 kW
44	4.4 kW
55	5.5 kW
75	7.5 kW
1A	11 kW
1E	15 kW

3rd digit Power Supply Voltage

Code	Specifications
A	200 VAC
D	400 VAC

4th digit Serial Encoder

Code	Specifications
3	20-bit absolute
D	20-bit incremental

5th digit Design Revision Order

Code	Specifications
A	Standard

6th digit Shaft End

Code	Specifications
2	Straight without key
6	Straight with key and tap

7th digit Options

Code	Specifications
1	Without options
B	With holding brake (90 VDC)
C	With holding brake (24 VDC)
D	With oil seal and holding brake (90 VDC)
E	With oil seal and holding brake (24 VDC)
S	With oil seal

Limited Stock Items Non-Stock Items

Features

- High-speed driving of feed shafts for various machines
- Wide selection: 300 W to 15 kW capacity, holding brake option
- Mounted serial encoder: 20 bits, high resolution
- Protective structure: IP67

Application Examples

- Machine tools
- Transfer machines
- Material handling machines
- Food processing equipment

Configurations of connectors for the main circuit vary depending on servomotor capacity.



SGMGV-03/-05

- The connectors are used only for Yaskawa servomotors. Order the connectors specified by Yaskawa.
- Both protective structure IP67 and European Safety Standards compliant connectors are available.
- For details, refer to page 59 and 60.



SGMGV-09 to -1E

- The connectors for these models are round. The connectors specified by Yaskawa are required. Note that the connectors vary depending on the operation environment of servomotors.
- Two types of connectors are available.
  - Standard connectors: for details, refer to page 64 and 65.
  - Protective structure IP67 and European Safety Standards compliant connectors: for details, refer to page 66.

Ratings and Specifications

Time Rating: Continuous
Vibration Class: V15
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40°C
Excitation: Permanent magnet
Mounting: Flange-mounted
Thermal Class: F

Withstand Voltage: 1500 VAC for one minute (200-V Class)
1800 VAC for one minute (400-V Class)
Enclosure: Totally enclosed, self-cooled, IP67
(except for shaft opening)
Ambient Humidity: 20% to 80% (no condensation)
Drive Method: Direct drive
Rotation Direction: Counterclockwise (CCW) with forward run reference when viewed from the load side

200 V Class

Servomotor Model: SGMGV-□□□		03A	05A	09A	13A	20A	30A	44A	55A	75A	1AA	1EA
Rated Output*1	kW	0.3	0.45	0.85	1.3	1.8	2.9	4.4	5.5	7.5	11	15
Rated Torque*1	N·m	1.96	2.86	5.39	8.34	11.5	18.6	28.4	35.0	48.0	70.0	95.4
Instantaneous Peak Torque*1	N·m	5.88	8.92	13.8	23.3	28.7	45.1	71.1	87.6	119	175	224
Rated Current*1	A_{rms}	2.8	3.8	6.9	10.7	16.7	23.8	32.8	42.1	54.7	58.6	78
Instantaneous Max. Current*1	A_{rms}	8	11	17	28	42	56	84	110	130	140	170
Rated Speed*1	min^{-1}	1500										
Max. Speed*1	min^{-1}	3000									2000	
Torque Constant	$N·m/A_{rms}$	0.776	0.854	0.859	0.891	0.748	0.848	0.934	0.871	0.957	1.32	1.37
Rotor Moment of Inertia	$\times 10^{-4}$ kg·m²	2.48 (2.73)	3.33 (3.58)	13.9 (16)	19.9 (22)	26 (28.1)	46 (54.5)	67.5 (76.0)	89.0 (97.5)	125 (134)	242 (261)	303 (341)
Rated Power Rate*1	kW/s	15.5 (14.1)	24.6 (22.8)	20.9 (18.2)	35.0 (31.6)	50.9 (47.1)	75.2 (63.5)	119 (106)	138 (126)	184 (172)	202 (188)	300 (283)
Rated Angular Acceleration*1	rad/s²	7900 (7180)	8590 (7990)	3880 (3370)	4190 (3790)	4420 (4090)	4040 (3410)	4210 (3740)	3930 (3590)	3840 (3580)	2890 (2680)	3150 (2960)
Applicable SERVOPACK	SGDV-□□□□	3R8A	3R8A	7R6A	120A	180A	330A 220A*2	330A	470A	550A	590A	780A

*1: These items and torque-motor speed characteristics quoted in combination with a SERVOPACK are at an armature winding temperature of 20°C.
*2: Some restrictions apply when using an SGDV-200A SERVOPACK in combination with an SGMGV-30A servomotor.
Notes: 1 The values in parentheses are for servomotors with holding brakes.
2 The above specifications show the values under the cooling condition when the following heat sinks are mounted on the servomotors.
SGMGV-03A/-05A: 250 mm × 250 mm × 6 mm (aluminum)
SGMGV-09A/-13A/-20A: 400 mm × 400 mm × 20 mm (iron)
SGMGV-30A/-44A/-55A/-75A: 550 mm × 550 mm × 30 mm (iron)
SGMGV-1AA/-1EA: 650 mm × 650 mm × 35 mm (iron)


400 V Class

Servomotor Model: SGMGV-□□□		03D	05D	09D	13D	20D	30D	44D	55D	75D	1AD	1ED
Rated Output*	kW	0.3	0.45	0.85	1.3	1.8	2.9	4.4	5.5	7.5	11	15
Rated Torque*	N·m	1.96	2.86	5.39	8.34	11.5	18.6	28.4	35.0	48.0	70.0	95.4
Instantaneous Peak Torque*	N·m	5.88	8.92	13.8	23.3	28.7	45.1	71.1	87.6	119	175	224
Rated Current*	A_{rms}	1.4	1.9	3.5	5.4	8.4	11.9	16.5	20.8	25.7	28.1	37.2
Instantaneous Max. Current*	A_{rms}	4	5.5	8.5	14	20	28	40.5	52	65	70	85
Rated Speed*	min^{-1}	1500										
Max. Speed*	min^{-1}	3000									2000	
Torque Constant	$N·m/A_{rms}$	1.55	1.71	1.72	1.78	1.50	1.70	1.93	1.80	1.92	2.64	2.74
Rotor Moment of Inertia	$\times 10^{-4}$ kg·m²	2.48 (2.73)	3.33 (3.58)	13.9 (16)	19.9 (22)	26 (28.1)	46 (54.5)	67.5 (76.0)	89.0 (97.5)	125 (134)	242 (261)	303 (341)
Rated Power Rate*	kW/s	15.5 (14.1)	24.6 (22.8)	20.9 (18.2)	35.0 (31.6)	50.9 (47.1)	75.2 (63.5)	119 (106)	138 (126)	184 (172)	202 (188)	300 (283)
Rated Angular Acceleration*	rad/s²	7900 (7180)	8590 (7990)	3880 (3370)	4190 (3790)	4420 (4090)	4040 (3410)	4210 (3740)	3930 (3590)	3840 (3580)	2890 (2680)	3150 (2960)
Applicable SERVOPACK	SGDV-□□□□	1R9D	1R9D	3R5D	5R4D	8R4D	120D	170D	210D	260D	280D	370D

*: These items and torque-motor speed characteristics quoted in combination with a SERVOPACK are at an armature winding temperature of 20°C.
Notes: 1 The values in parentheses are for servomotors with holding brakes.
2 The above specifications show the values under the cooling condition when the following heat sinks are mounted on the servomotors.
SGMGV-03D/-05D: 250 mm × 250 mm × 6 mm (aluminum)
SGMGV-09D/-13D/-20D: 400 mm × 400 mm × 20 mm (iron)
SGMGV-30D/-44D/-55D/-75D: 550 mm × 550 mm × 30 mm (iron)
SGMGV-1AD/-1ED: 650 mm × 650 mm × 35 mm (iron)

Ratings and Specifications

●Torque-Motor Speed Characteristics (200 V/400 V) A: Continuous Duty Zone B: Intermittent Duty Zone Note1



Notes: 1 When the effective torque during intermittent duty is within the rated torque, the servomotor can be used within the intermittent duty zone.
2 When the main circuit cable length exceeds 20 m, note that the intermittent duty zone of the Torque-Motor Speed Characteristics will shrink as the line-to-line voltage drops.

●Holding Brake Electrical Specifications

Servomotor Model	Servomotor Rated Output kW	Holding Brake Specifications				
		Holding Torque N·m	Rated Voltage 24 VDC		Rated Voltage 90 VDC	
			Capacity W	Rated Current A (at 20˚C)	Capacity W	Rated Current A (at 20˚C)
SGMGV-03	0.3	4.5	10	0.42	10	0.11
SGMGV-05	0.45	4.5	10	0.42	10	0.11
SGMGV-09	0.85	12.7	10	0.41	10	0.11
SGMGV-13	1.3	19.6	10	0.41	10	0.11
SGMGV-20	1.8	19.6	10	0.41	10	0.11
SGMGV-30	2.9	43.1	18.5	0.77	18.5	0.21
SGMGV-44	4.4	43.1	18.5	0.77	18.5	0.21
SGMGV-55	5.5	72.6	25	1.05	25	0.28
SGMGV-75	7.5	72.6	25	1.05	25	0.28
SGMGV-1A	11	84.3	32	1.33	32	0.36
SGMGV-1E	15	114.6	35	1.46	35	0.39

Notes: 1 The holding brake is only used to hold the load and cannot be used to stop the servomotor.
2 The holding brake open time and holding brake operation time vary depending on which discharge circuit is used. Make sure holding brake open time and holding brake operation time are correct for your servomotor.
3 A 24-VDC power supply is provided by customers.
4 Refer to page 338 for information on the 90-VDC power supply.

●Allowable Load Moment of Inertia at the Motor Shaft

The rotor moment of inertia ratio is the value for a servomotor without a gear and a holding brake.

Servomotor Model	Servomotor Rated Output	Allowable Load Moment of Inertia (Rotor Moment of Inertia Ratio)
SGMGV-03 to -1E	0.3 to 1.5 kW	5 times


●Load Moment of Inertia

- The larger the load moment of inertia, the worse the movement response of the load.
- The allowable load moment of inertia (JL) depends on motor capacity, as shown above. This value is provided strictly as a guideline and results may vary depending on servomotor drive conditions.
- Use the AC servo drive capacity selection program SigmaJunmaSize+ to check the operation conditions. The program can be downloaded for free from our web site (http://www.e-mechatronics.com/).

- An overvoltage alarm (A.400) is likely to occur during deceleration if the load moment of inertia exceeds the allowable load moment of inertia. SERVOPACKs with a built-in regenerative resistor may generate a regenerative overload alarm (A.320). Take one of the following steps if this occurs.
  - · Reduce the torque limit.
  - · Reduce the deceleration rate.
  - · Reduce the maximum speed.
  - · Install an external regenerative resistor if the alarm cannot be cleared using the steps above. Refer to Regenerative Resistors on page 339.

●Allowable Radial and Thrust Loads


Design the mechanical system so thrust and radial loads applied to the servomotor shaft end during operation fall within the ranges shown in the table.

Servomotor Model		Allowable Radial Load (Fr) N	Allowable Thrust Load (Fs) N	LR mm	Reference Diagram
SGMGV-	03□□A21	490	98	37	
	05□□A21	490	98	40	
	09□□A21	490	98	58	
	13□□A21	686	343	58	
	20□□A21	980	392	58	
	30□□A21	1470	490	79	
	44□□A21	1470	490	79	
	55□□A21	1764	588	113	
	75□□A21	1764	588	113	
	1A□□A21	1764	588	116	
	1E□□A21	4998	2156	116	

External Dimensions Units: mm

●Without Holding Brakes

(1) 300 W, 450 W




Note: For the specifications of the other shaft ends, refer to page 58.

Model SGMGV-	L	LL	LM	LR	KB1	KB2	Shaft End Dimensions		Approx. Mass kg
							S	Q	
03□□A21	163	126	90	37	75	114	$14^{0}_{-0.011}$	25	2.6
05□□A21	179	139	103	40	88	127	$16^{0}_{-0.011}$	30	3.2

Note: Models with oil seals are of the same configuration.

· Cable Specifications for Encoder-end Connector (20-bit Encoder)



Receptacle: CM10-R10P-D
Applicable plug (To be provided by the customer)
Plug: CM10-AP10S-□-D (Angle)
CM10-SP10S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Manufacturer: DDK Ltd.


With an Absolute Encoder

1	PS	6	BAT (+)
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	BAT (–)	10	FG (Frame ground)

With an Incremental Encoder

1	PS	6	–
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	–	10	FG (Frame ground)

· Cable Specifications for Servomotor-end Connector




PE	FG (Frame ground)
5	–
4	–
3	Phase U
2	Phase V
1	Phase W

Manufacturer: Japan Aviation Electronics Industry,Ltd.

External Dimensions Units: mm

(2) 850 W to 7.5 kW




*: When using SGMGV-55 and -75 servomotors

Note: For the specifications of the other shaft ends, refer to page 58.

Model SGMGV-	L	LL	LM	LR	KB1	KB2	IE	KL1	Flange Face Dimensions							Shaft End Dimensions		Approx. Mass
									LA	LB	LC	LE	LG	LH	LZ	S	Q	kg
09□□A21	195	137	101	58	83	125	–	104	145	$110^{0}_{-0.035}$	130	6	12	165	9	$19^{0}_{-0.013}$	40	5.5
13□□A21	211	153	117	58	99	141	–	104	145	$110^{0}_{-0.035}$	130	6	12	165	9	$22^{0}_{-0.013}$	40	7.1
20□□A21	229	171	135	58	117	159	–	104	145	$110^{0}_{-0.035}$	130	6	12	165	9	$24^{0}_{-0.013}$	40	8.6
30□□A21	239	160	124	79	108	148	–	134	200	$114.3^{0}_{-0.025}$	180	3.2	18	230	13.5	$35^{+0.01}_{0}$	76	13.5
44□□A21	263	184	148	79	132	172	–	134	200	$114.3^{0}_{-0.025}$	180	3.2	18	230	13.5	$35^{+0.01}_{0}$	76	17.5
55□□A21	334	221	185	113	163	209	123	144	200	$114.3^{0}_{-0.025}$	180	3.2	18	230	13.5	$42^{0}_{-0.016}$	110	21.5
75□□A21	380	267	231	113	209	255	123	144	200	$114.3^{0}_{-0.025}$	180	3.2	18	230	13.5	$42^{0}_{-0.016}$	110	29.5


Note: Models with oil seals are of the same configuration.

· Cable Specifications for Encoder-end Connector (20-bit Encoder)



Receptacle: CM10-R10P-D
Applicable plug (To be provided by the customer)
Plug: CM10-AP10S-□-D (Angle)
CM10-SP10S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Manufacturer: DDK Ltd.

· Cable Specifications for Servomotor-end Connector



A	Phase U
B	Phase V
C	Phase W
D	FG (Frame ground)

Manufacturer: DDK Ltd.

With an Absolute Encoder


1	PS	6	BAT (+)
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	BAT (–)	10	FG (Frame ground)

With an Incremental Encoder

1	PS	6	–
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	–	10	FG (Frame ground)

External Dimensions Units: mm

(3) 11 kW, 15 kW




Note: For the specifications of the other shaft ends, refer to page 58.

Model SGMGV-	L	LL	LM	LR	KB1	KB2	IE	KL1	Flange Face Dimensions							Shaft End Dimensions		Approx. Mass kg
									LA	LB	LC	LE	LG	LH	LZ	S	S1	
1A□□A21	447	331	295	116	247	319	150	168	235	$200^{0}_{-0.046}$	220	4	20	270	13.5	$42^{0}_{-0.016}$	50	57
1E□□A21	509	393	357	116	309	381	150	168	235	$200^{0}_{-0.046}$	220	4	20	270	13.5	$55^{+0.030}_{+0.011}$	60	67

Note: Models with oil seals are of the same configuration.

· Cable Specifications for Encoder-end Connector (20-bit Encoder)



Receptacle: CM10-R10P-D
Applicable plug (To be provided by the customer)
Plug: CM10-AP10S-□-D (Angle)
CM10-SP10S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Manufacturer: DDK Ltd.


With an Absolute Encoder

1	PS	6	BAT (+)
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	BAT (–)	10	FG (Frame ground)

With an Incremental Encoder

1	PS	6	–
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	–	10	FG (Frame ground)

· Cable Specifications for Servomotor-end Connector




A	Phase U
B	Phase V
C	Phase W
D	FG (Frame ground)

Manufacturer: DDK Ltd.

External Dimensions Units: mm

●With Holding Brakes

(1) 300 W, 450 W




Note: For the specifications of the other shaft ends, refer to page 58.

Model SGMGV-	L	LL	LM	LR	KB1	KB2	Shaft End Dimensions		Approx. Mass
							S	Q	kg
03□□A2□	196	159	123	37	75	147	$14^{0}_{-0.011}$	25	3.6
05□□A2□	212	172	136	40	88	160	$16^{0}_{-0.011}$	30	4.2

Note: Models with oil seals are of the same configuration.

· Cable Specifications for Encoder-end Connector (20-bit Encoder)



Receptacle: CM10-R10P-D
Applicable plug (To be provided by the customer)
Plug: CM10-AP10S-□-D (Angle)
CM10-SP10S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Manufacturer: DDK Ltd.


With an Absolute Encoder

1	PS	6	BAT (+)
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	BAT (–)	10	FG (Frame ground)

With an Incremental Encoder

1	PS	6	–
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	–	10	FG (Frame ground)

· Cable Specifications for Servomotor-end Connector




PE	FG (Frame ground)
5	Brake terminal
4	Brake terminal
3	Phase U
2	Phase V
1	Phase W

Manufacturer: Japan Aviation Electronics Industry,Ltd.

External Dimensions Units: mm

(2) 850 W to 7.5 kW




*: When using SGMGV-55 and -75 servomotors

Note: For the specifications of the other shaft ends, refer to page 58.

Model SGMGV-	L	LL	LM	LR	KB1	KB2	KB3	IE	KL1	KL3	Flange Face Dimensions							Shaft End Dimensions		Approx. Mass kg
											LA	LB	LC	LE	LG	LH	LZ	S	Q	
09□□A2□	231	173	137	58	83	161	115	–	104	80	145	$110^{0}_{-0.035}$	130	6	12	165	9	$19^{0}_{-0.013}$	40	7.5
13□□A2□	247	189	153	58	99	177	131	–	104	80	145	$110^{0}_{-0.035}$	130	6	12	165	9	$22^{0}_{-0.013}$	40	9.0
20□□A2□	265	207	171	58	117	195	149	–	104	80	145	$110^{0}_{-0.035}$	130	6	12	165	9	$24^{0}_{-0.013}$	40	11.0
30□□A2□	287	208	172	79	108	196	148	–	134	110	200	$114.3^{0}_{-0.025}$	180	3.2	18	230	13.5	$35^{+0.01}_{0}$	76	19.5
44□□A2□	311	232	196	79	132	220	172	–	134	110	200	$114.3^{0}_{-0.025}$	180	3.2	18	230	13.5	$35^{+0.01}_{0}$	76	23.5
55□□A2□	378	265	229	113	163	253	205	123	144	110	200	$114.3^{0}_{-0.025}$	180	3.2	18	230	13.5	$42^{0}_{-0.016}$	110	27.5
75□□A2□	424	311	275	113	209	299	251	123	144	110	200	$114.3^{0}_{-0.025}$	180	3.2	18	230	13.5	$42^{0}_{-0.016}$	110	35

Note: Models with oil seals are of the same configuration.

· Cable Specifications for Encoder-end Connector
(20-bit Encoder)



Receptacle: CM10-R10P-D
Applicable plug (To be provided by the customer)
Plug: CM10-AP10S-□-D (Angle)
CM10-SP10S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Manufacturer: DDK Ltd.


With an Absolute Encoder

1	PS	6	BAT (+)
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	BAT (–)	10	FG (Frame ground)

With an Incremental Encoder

1	PS	6	–
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	–	10	FG (Frame ground)


· Cable Specifications for Servomotor-end Connector



A	Phase U
B	Phase V
C	Phase W
D	FG (Frame ground)

Manufacturer: DDK Ltd.

· Cable Specifications for Brake-end Connector




Receptacle: CM10-R2P-D
Applicable plug (To be provided by the customer)
Plug: CM10-AP2S-□-D (Angle)
CM10-SP2S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Manufacturer: DDK Ltd.

Brake terminal
Brake terminal

Note: No polarity for connection to the brake terminals

External Dimensions Units: mm

(3) 11 kW, 15 kW




Note: For the specifications of the other shaft ends, refer to page 82.

Model SGMGV-	L	LL	LM	LR	KB1	KB2	KB3	IE	KL1	KL3	Flange Face Dimensions							Shaft End Dimensions		Approx. Mass
											LA	LB	LC	LE	LG	LH	LZ	S	S1	kg
1A□□A2□	498	382	346	116	247	370	315	150	168	125	235	$200^{0}_{-0.046}$	220	4	20	270	13.5	$42^{0}_{-0.016}$	50	65
1E□□A2□	598	482	446	116	309	470	385	150	168	125	235	$200^{0}_{-0.046}$	220	4	20	270	13.5	$55^{+0.030}_{+0.011}$	60	85

Note: Models with oil seals are of the same configuration.

· Cable Specifications for Encoder-end Connector (20-bit Encoder)



Receptacle: CM10-R10P-D
Applicable plug (To be provided by the customer)
Plug: CM10-AP10S-□-D (Angle)
CM10-SP10S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Manufacturer: DDK Ltd.


With an Absolute Encoder

1	PS	6	BAT (+)
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	BAT (–)	10	FG (Frame ground)

With an Incremental Encoder

1	PS	6	–
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	–	10	FG (Frame ground)


· Cable Specifications for Servomotor-end Connector



A	Phase U
B	Phase V
C	Phase W
D	FG (Frame ground)

Manufacturer: DDK Ltd.

· Cable Specifications for Brake-end Connector



Receptacle: CM10-R2P-D
Applicable plug (To be provided by the customer)
Plug: CM10-AP2S-□-D (Angle)
CM10-SP2S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Manufacturer: DDK Ltd.

Brake terminal
Brake terminal



Note: No polarity for connection to the brake terminals

External Dimensions Units: mm

● Shaft End

SGMGV - □□□□□□□


Code	Specifications	Remarks
2	Straight without key	Standard
6	Straight with key and tap for one location (Key slot is JIS B1301-1996 fastening type)	Optional

Shaft End		Model SGMGV-								
		03	05	09	13	20	30/44	55/75	1A	1E
Code: 2 (Straight without Key)										
	LR	37	40	58	58	58	79	113	116	116
	Q	25	30	40	40	40	76	110	110	110
	S	$14^{\ 0}_{-0.011}$	$16^{\ 0}_{-0.011}$	$19^{\ 0}_{-0.013}$	$22^{\ 0}_{-0.013}$	$24^{\ 0}_{-0.013}$	$35^{+0.01}_{\ 0}$	$42^{\ 0}_{-0.016}$	$42^{\ 0}_{-0.016}$	$55^{+0.030}_{+0.011}$
Code: 6 (Straight with Key and Tap)										
	LR	37	40	58	58	58	79	113	116	116
	Q	25	30	40	40	40	76	110	110	110
	QK	15	20	25	25	25	60	90	90	90
	S	$14^{\ 0}_{-0.011}$	$16^{\ 0}_{-0.011}$	$19^{\ 0}_{-0.013}$	$22^{\ 0}_{-0.013}$	$24^{\ 0}_{-0.013}$	$35^{+0.01}_{\ 0}$	$42^{\ 0}_{-0.016}$	$42^{\ 0}_{-0.016}$	$55^{+0.030}_{+0.011}$
	W	5	5	5	6	8	10	12	12	16
	T	5	5	5	6	7	8	8	8	10
	U	3	3	3	3.5	4	5	5	5	6
	P	M4 Screw, Depth 10	M5 Screw, Depth 12				M12 Screw, Depth 25	M16 Screw, Depth 32		M20 Screw, Depth 40

Selecting Main Circuit Cables (SGMGV-03 / -05)


●Cables Connections

●Standard Wiring (Max. encoder cable length: 20 m)



●Encoder Cable Extension from 30 to 50 m

(See page 69.)



⚠CAUTION

- Separate the servomotor main circuit cable wiring from the I/O signal cable and encoder cable at least 30 cm, and do not bundle or run them in the same duct.
- When the main circuit cable length exceeds 20 m, note that the intermittent duty zone of the Torque-Motor Speed Characteristics will shrink as the line-to-line voltage drops.



●Servomotor Main Circuit Cable

Servomotor Rated Output	Name	Length	Order No. Standard (Flexible) Type*	Order No. Premium (Flex + Shield) Type	Specifications	Details
0.3 kW 0.45 kW	For Servomotor without Holding Brakes	3 m	JZSP-CVM21-03-E	YEA-CVM21-03(A)-E	SERVOPACK End — Servomotor End 50 mm, L Wire Markers M4 Crimped Terminals	(1)
		5 m	JZSP-CVM21-05-E	YEA-CVM21-05(A)-E		
		10 m	JZSP-CVM21-10-E	YEA-CVM21-10(A)-E		
		15 m	JZSP-CVM21-15-E	YEA-CVM21-15(A)-E		
		20 m	JZSP-CVM21-20-E	YEA-CVM21-20(A)-E		
		30 m	JZSP-CVM21-30-E	-		
		40 m	JZSP-CVM21-40-E	-		
		50 m	JZSP-CVM21-50-E	-		
	For Servomotor with Holding Brakes	3 m	JZSP-CVM41-03-E	YEA-CVM41-03(A)-E	SERVOPACK End — Servomotor End 50 mm, L Wire Markers M4 Crimped Terminals	(2)
		5 m	JZSP-CVM41-05-E	YEA-CVM41-05(A)-E		
		10 m	JZSP-CVM41-10-E	YEA-CVM41-10(A)-E		
		15 m	JZSP-CVM41-15-E	YEA-CVM41-15(A)-E		
		20 m	JZSP-CVM41-20-E	YEA-CVM41-20(A)-E		
		30 m	JZSP-CVM41-30-E	-		
		40 m	JZSP-CVM41-40-E	-		
		50 m	JZSP-CVM41-50-E	-		
	Servomotor-end Connector Kit	–	JZSP-CVM9-1-E	-	Crimping Type (A crimp tool is required.)	(3)

*: These flexible cables are provided as standard equipment.

(Cont'd)

Selecting Main Circuit Cables (SGMGV-03 / -05)

Servomotor Rated Output	Name		Length	Order No. Standard (Flexible) Type*	Specifications	Details
0.3 kW 0.45 kW	Cables	For Servomotor without Holding Brakes (4 wires)	5 m	JZSP-CVM29-05-E		(4)
			10 m	JZSP-CVM29-10-E		
			15 m	JZSP-CVM29-15-E		
			20 m	JZSP-CVM29-20-E		
			30 m	JZSP-CVM29-30-E		
			40 m	JZSP-CVM29-40-E		
			50 m	JZSP-CVM29-50-E		
		For Servomotor with Holding Brakes (6 wires)	5 m	JZSP-CVM49-05-E		(4)
			10 m	JZSP-CVM49-10-E		
			15 m	JZSP-CVM49-15-E		
			20 m	JZSP-CVM49-20-E		
			30 m	JZSP-CVM49-30-E		
			40 m	JZSP-CVM49-40-E		
			50 m	JZSP-CVM49-50-E		

(1) Wiring Specifications for Servomotors without Holding Brakes

Standard Type

SERVOPACK-end Leads

Wire Color	Signal
Green/yellow	FG
Blue	Phase W
White	Phase V
Red	Phase U

Servomotor-end Connector

Signal	Pin No.
FG	PE
Phase W	1
Phase V	2
Phase U	3
–	4
–	5

Premium Type

SERVOPACK-end Leads

Wire Color	Signal
Green	FG
Blue	Phase W
White	Phase V
Red	Phase U

Shield Wire

Servomotor-end Connector

Signal	Pin No.
FG	PE
Phase W	1
Phase V	2
Phase U	3
–	4
–	5

(2) Wiring Specifications for Servomotor with Holding Brakes

Standard Type

SERVOPACK-end Leads

Wire Color	Signal
Green/yellow	FG
Blue	Phase W
White	Phase V
Red	Phase U
Black	Brake
Black	Brake

Servomotor-end Connector

Signal	Pin No.
FG	PE
Phase W	1
Phase V	2
Phase U	3
Brake	4
Brake	5

Note: No polarity for connection to a holding brake

Premium Type

SERVOPACK-end Leads

Wire Color	Signal
Green	FG
Blue	Phase W
White	Phase V
Red	Phase U
Black	Brake
Black	Brake


Shield Wire

Servomotor-end Connector



Signal	Pin No.
FG	PE
Phase W	1
Phase V	2
Phase U	3
Brake	4
Brake	5

Note: No polarity for connection to a holding brake

(3) Servomotor-end Connector Kit Specifications

Items		Specifications	External Dimensions mm
Order No.		JZSP-CVM9-1-E (Cables are not included.)	
Applicable Servomotors		SGMGV-03/-05	
Manufacturer		Japan Aviation Electronics Industry, Ltd.	
Plug		JNYFX06SJ3	
Electrical Contact		ST-TMH-S-C1B	
Applicable Wire Size		AWG18 to 22	
Outer Diameter of Insulating Sheath		1.3 dia. to 1.8 dia.	
Crimp Tool	Hand tool	CT160-3-TMH5B	
	Applicator	350-TMH5B-2B	
Mounting Screw		M3 Pan head screw	
Applicable Cable Outer Diameter		6.9 dia. to 8.3 dia.	

(4) Cable Specifications


Items	For Servomotor without Holding Brakes (4 wires)	For Servomotor with Holding Brakes (6 wires)
Order No.*	JZSP-CVM29-□□-E	JZSP-CVM49-□□-E
Cable Length	50 m max.	
Specifications	UL2586 (Max. operating temperature: 105°C) AWG20×4C For power line: AWG20 (0.55 mm²) Outer diameter of insulating sheath: 1.77 dia.	UL2586 (Max. operating temperature: 105°C) AWG20×6C For power line: AWG20 (0.55 mm²) Outer diameter of insulating sheath: 1.77 dia. For holding brake line: AWG20 (0.55 mm²) Outer diameter of insulating sheath: 1.77 dia.
Finished Dimensions	7.3±0.3 dia.	7.4±0.3 dia.
Internal Configuration and Lead Color		
Yaskawa Standard Specifications (Standard Length)	Cable length: 5 m, 10 m, 15 m, 20 m, 30 m, 40 m, 50 m	

*: Specify the cable length in □□ of order no [JZSP-CVM29-□□-05-E (5 m)]

Selecting Main Circuit Cables (SGMGV-09 to -1E)


●Cables Connections

●Standard Wiring (Max. encoder cable length: 20 m)



●Encoder Cable Extension from 30 to 50 m

(See page 69.)






⚠CAUTION

- Separate the servomotor main circuit cable wiring from the I/O signal cable and encoder cable at least 30 cm, and do not bundle or run them in the same duct.
- When the main circuit cable length exceeds 20 m, note that the intermittent duty zone of the Torque-Motor Speed Characteristics will shrink as the line-to-line voltage drops.

Selecting Main Circuit Cables (SGMGV-09 to -1E)

●Servomotor Main Circuit Cables

Voltage	Servomotor Rated Output	Name	Length	Order No.		Specifications	Details
				Value Type	Premium Type *2		
200V	850W, 1.3kW	Servomotor Power Cable *1	3 m	B1EV-03(A)-E	B1EP-03(A)-E		(1)
			5 m	B1EV-05(A)-E	B1EP-05(A)-E		
			10 m	B1EV-10(A)-E	B1EP-10(A)-E		
			15 m	B1EV-15(A)-E	B1EP-15(A)-E		
			20 m	B1EV-20(A)-E	B1EP-20(A)-E		
	2.0kW		3 m	B2EV-03(A)-E	B2EP-03(A)-E		
			5 m	B2EV-05(A)-E	B2EP-05(A)-E		
			10 m	B2EV-10(A)-E	B2EP-10(A)-E		
			15 m	B2EV-15(A)-E	B2EP-15(A)-E		
			20 m	B2EV-20(A)-E	B2EP-20(A)-E		
	3.0 to 4.4kW		3 m	B4EV-03(A)-E	B4EP-03(A)-E		
			5 m	B4EV-05(A)-E	B4EP-05(A)-E		
			10 m	B4EV-10(A)-E	B4EP-10(A)-E		
			15 m	B4EV-15(A)-E	B4EP-15(A)-E		
			20 m	B4EV-20(A)-E	B4EP-20(A)-E		
	5.5 to 7.5kW		3 m	B6EV-03(A)-E	B6EP-03(A)-E		
			5 m	B6EV-05(A)-E	B6EP-05(A)-E		
			10 m	B6EV-10(A)-E	B6EP-10(A)-E		
			15 m	B6EV-15(A)-E	B6EP-15(A)-E		
			20 m	B6EV-20(A)-E	B6EP-20(A)-E		
	11 to 15kW		3 m	B7EV-03(A)-E	B7EP-03(A)-E		
			5 m	B7EV-05(A)-E	B7EP-05(A)-E		
			10 m	B7EV-10(A)-E	B7EP-10(A)-E		
			15 m	B7EV-15(A)-E	B7EP-15(A)-E		
			20 m	B7EV-20(A)-E	B7EP-20(A)-E		
400V	850W, 1.3kW, 2.0kW		3 m	B1EV-03(A)-E	B1EP-03(A)-E		
			5 m	B1EV-05(A)-E	B1EP-05(A)-E		
			10 m	B1EV-10(A)-E	B1EP-10(A)-E		
			15 m	B1EV-15(A)-E	B1EP-15(A)-E		
			20 m	B1EV-20(A)-E	B1EP-20(A)-E		
	3.0 to 4.4kW		3 m	B3EV-03(A)-E	B3EP-03(A)-E		
			5 m	B3EV-05(A)-E	B3EP-05(A)-E		
			10 m	B3EV-10(A)-E	B3EP-10(A)-E		
			15 m	B3EV-15(A)-E	B3EP-15(A)-E		
			20 m	B3EV-20(A)-E	B3EP-20(A)-E		
	5.5 to 7.5kW		3 m	B5EV-03(A)-E	B5EP-03(A)-E		
			5 m	B5EV-05(A)-E	B5EP-05(A)-E		
			10 m	B5EV-10(A)-E	B5EP-10(A)-E		
			15 m	B5EV-15(A)-E	B5EP-15(A)-E		
			20 m	B5EV-20(A)-E	B5EP-20(A)-E		
	11 to 15kW		3 m	B6EV-03(A)-E	B6EP-03(A)-E		
			5 m	B6EV-05(A)-E	B6EP-05(A)-E		
			10 m	B6EV-10(A)-E	B6EP-10(A)-E		
			15 m	B6EV-15(A)-E	B6EP-15(A)-E		
			20 m	B6EV-20(A)-E	B6EP-20(A)-E		
200V and 400V	850W to 15kW	Holding Brake Cable	3 m	BBEV-03(A)-E	-		(2)
			5 m	BBEV-05(A)-E	-		
			10 m	BBEV-10(A)-E	-		
			15 m	BBEV-15(A)-E	-		
			20 m	BBEV-20(A)-E	-		
	850W to 15kW		3 m	-	BBEP-03(A)-E		(3)
			5 m	-	BBEP-05(A)-E		
			10 m	-	BBEP-10(A)-E		
			15 m	-	BBEP-15(A)-E		
			20 m	-	BBEP-20(A)-E		

*1 Servomotors with holding brakes require a holding brake cable in addition to a power cable.

*2 Premium cables have a braided shield and are intended for use in applications that require CE. B1EP through B5EP have a continuous flex and are intended for use in movable sections such as robot arms.

Selecting Main Circuit Cables (SGMGV-09 to -1E)

(1) Wiring Specifications for Servomotors with and without Holding Brakes*

● Value Type

SERVOPACK-end Leads		Servomotor-end Connector	
Wire Label	Signal	Signal	Pin No.
G	FG	FG	D
W	Phase W	Phase W	C
V	Phase V	Phase V	B
U	Phase U	Phase U	A

*For servomotors with holding brakes, the holding brake cable must also be wired.

● Premium Type

SERVOPACK-end Leads		Shield Wire	Servomotor-end Connector	
Wire Label	Signal		Signal	Pin No.
G	FG		FG	D
W	Phase W		Phase W	C
V	Phase V		Phase V	B
U	Phase U		Phase U	A

*For servomotors with holding brakes, the holding brake cable must also be wired.

(2) Wiring Specifications for the Value Type Brake Cable

SERVOPACK-end Leads		Servomotor-end Connector	
Wire Color	Signal	Signal	Pin No.
Black	Brake	Brake	1
Blue	Brake	Brake	2

Note: No polarity for connection to a holding brake.

(3) Wiring Specifications for the Premium Type Brake Cable

SERVOPACK-end Leads		Servomotor-end Connector	
Wire Color	Signal	Signal	Pin No.
Black	Brake	Brake	1
Blue	Brake	Brake	2
Green/Yellow	Shield	Shield Wire	

Note: No polarity for connection to a holding brake.


● Customer Cable Assembly

- Customers may assemble the servomotor's main circuit cables and attach connectors to connect the SERVOPACKs and the SGMGV servomotors.
- The connectors specified by Yaskawa are required. Note that the connectors vary depending on the operation environment of servomotors.
- Two types of connectors are available.
  - Standard connectors
  - Protective structure IP67 and European Safety Standards compliant connectors
- Yaskawa does not specify which cables to use. Use appropriate cables for the connectors.


Selecting Main Circuit Cables (SGMGV-09 to -1E)

●Standard Connectors


● Connector Configuration



(1) Without Holding Brakes



Servomotor-end Connector
For 0.85 to 15 kW




Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not provided by Yaskawa)		
		Straight Plug	L-shaped Plug	Cable Clamp
0.85 1.3 1.8	MS3102A18-10P	MS3106B18-10S	MS3108B18-10S	MS3057-10A
2.9 4.4	MS3102A22-22P	MS3106B22-22S	MS3108B22-22S	MS3057-12A
5.5 to 15	MS3102A32-17P	MS3106B32-17S	MS3108B32-17S	MS3057-20A


Note: Servomotor-end connectors (receptacles) are RoHS-compliant. Contact the respective connector manufacturers for RoHS-compliant cable-end connectors (not provided by Yaskawa).

(2) With Holding Brakes

0.85 to 15 kW servomotors require servomotor-end connector and brake power supply connector.
The servomotor-end connector is the same as is used for servomotors without holding brakes.



Brake Power Supply Connector
0.85 to 15 kW



Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not provided by Yaskawa)		
		Straight Plug	L-shaped Plug	Manufacturer
0.85 to 15	CM10-R2P-D	CM10-SP2S-S-D Applicable Cable: 4.0 dia. to 6.0 dia.	CM10-AP2S-S-D Applicable Cable: 4.0 dia. to 6.0 dia.	DDK Ltd.
		CM10-SP2S-M-D Applicable Cable: 6.0 dia. to 9.0 dia.	CM10-AP2S-M-D Applicable Cable: 6.0 dia. to 9.0 dia.	
		CM10-SP2S-L-D Applicable Cable: 9.0 dia. to 11.6 dia.	CM10-AP2S-L-D Applicable Cable: 9.0 dia. to 11.6 dia.	

To order a brake power supply connector kit (0.85 to 15 kW) with the order no. below, contact your Yaskawa representative.

JZSP - CVB9 - S M S2 - E

- Connector Type
  - S: Straight plug
  - A: L-shaped plug
- Bush Size*1
  - S : Size S (4.0 dia. to 6.0 dia.)
  - M : Size M (6.0 dia. to 9.0 dia.)
  - L : Size L (9.0 dia. to 11.6 dia.)
- Contact Pin Size
  - S2: Soldered
  - C3: Crimping type*2


*1: A size-M connector kit is available as a standard equipment.
*2: A crimp tool (model: 357J-50448T) by DDK Ltd. is required.

Selecting Main Circuit Cables (SGMGV-09 to -1E) Units: mm

● Cable-end Connectors

(1) MS3106B□□-□□S :


Straight Plug



Shell Size	Joint Screw A	Length of Joint Portion J±0.12	Overall Length L max.	Outer Diameter of Joint Nut $Q^{+0}_{-0.38}$	Cable Clamp Set Screw V	Effective Screw Length W min.	Maximum Width Y max.
18	1-1/8-18UNEF	18.26	52.37	34.13	1-20UNEF	9.53	42
22	1-3/8-18UNEF	18.26	55.57	40.48	1-3/16-18UNEF	9.53	50
32	2-18UNS	18.26	61.92	56.33	1-3/4-18UNS	11.13	66


(2) MS3108B□□-□□S :

L-shaped Plug




Shell Size	Joint Screw A	Length of Joint Portion J±0.12	Overall Length L max.	Outer Diameter of Joint Nut $Q^{+0}_{-0.38}$	R ±0.5	U ±0.5	Cable Clamp Set Screw V	Effective Screw Length W min.
18	1-1/8-18UNEF	18.26	68.27	34.13	20.5	30.2	1-20UNEF	9.53
22	1-3/8-18UNEF	18.26	76.98	40.48	24.1	33.3	1-3/16-18UNEF	9.53
32	2-18UNS	18.26	95.25	56.33	32.8	44.4	1-3/4-18UNS	11.13

(3) MS3057-□□A : Cable Clamp with Rubber Bushing




Cable Clamp Type	Applicable Connector Shell Size	Overall Length A±0.7	Effective Screw Length C	E Diameter	G±0.7	H	J Diameter	Set Screw V	Outer Diameter Q±0.7 Dia.	Attached Bushing
MS3057-10A	18	23.8	10.3	15.9	31.7	3.2	14.3	1-20UNEF	30.1	AN3420-10
MS3057-12A	20□22	23.8	10.3	19	37.3	4	15.9	1-3/16-18UNEF	35.0	AN3420-12
MS3057-20A	32	27.8	11.9	31.7	51.6	6.3	23.8	1-3/4-18UNS	51.6	AN3420-20

● Dimensional Drawings of Brake Power Supply



Angled Plug




Straight Plug

Items	Specifications
Connector Order No.	CM10-□P2S-□-D (Cables are not included.)
Protective Structure	IP67
Manufacturer	DDK Ltd.
Instructions	Angled plug (CM10-AP2S-□-D): TC-573, Straight plug (CM10-SP2S-□-D): TC-583
Electrical Contact Order No.	Electrical contact (100 pcs in one bag) □Crimping type: CM10-#22SC(C3)-100, Wire size: AWG16 to 20, Outer diameter of sheath: 1.87 to 2.45 dia., Hand tool: 357J-50448T □Soldered type: CM10-#22SC (S2)-100, Wire size: AWG16 max. Real contact (4000 pcs on one reel) □Crimping type: CM10-#22SC(C3)-4000, Wire size: AWG 16 to 20, Outer diameter of sheath: 1.87 to 2.45 dia., Semi-automatic tool: AP-A50541T (product name for one set), AP-A50541T-1 (product name for applicator) Note: The product name of the semi-automatic tool refers to the product name of the press and applicator (crimper) as a set.

Selecting Main Circuit Cables (SGMGV-09 to -1E)

●Protective Structure IP67 and European Safety Standards Compliant Connector

● Connector Configuration




Note: For the conduit grounding, contact the manufacturer of the conduit being used.

(1) Without Holding Brakes

Servomotor-end Connector
For 0.85 to 15 kW







Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not Provided by Yaskawa)				
		Straight Plug	L-shaped Plug	Cable Clamp	Applicable Cable Diameter (For Reference)	Manufacturer
0.85 1.3 1.8	CE05-2A18-10PD-D	CE05-6A18-10SD-D-BSS	CE05-8A18-10SD-D-BAS	CE3057-10A-1-D	10.5 dia. to 14.1 dia.	DDK Ltd.
				CE3057-10A-2-D	8.5 dia. to 11.0 dia.	
				CE3057-10A-3-D	6.5 dia. to 8.7 dia.	
2.9 4.4	CE05-2A22-22PD-D	CE05-6A22-22SD-D-BSS	CE05-8A22-22SD-D-BAS	CE3057-12A-1-D	12.5 dia. to 16.0 dia.	
				CE3057-12A-2-D	9.5 dia. to 13.0 dia.	
				CE3057-12A-3-D	6.8 dia. to 10.0 dia.	
				CE3057-12A-7-D	14.5 dia. to 17.0 dia.	
5.5 to 15	CE05-2A32-17PD-D	CE05-6A32-17SD-D-BSS	CE05-8A32-17SD-D-BAS	CE3057-20A-1-D	22 dia. to 23.8 dia.	
				CE3057-20A-2-D	24 dia. to 26.6 dia.	
				CE3057-20A-3-D	22 dia. to 22.5 dia.	

(2) With Holding Brakes

0.85 to 15 kW servomotors require servomotor-end connector and brake power supply connector.
The servomotor-end connector is the same as is used for servomotors without holding brakes.



Brake Power Supply Connector
0.85 to 15 kW



Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not provided by Yaskawa)		
		Straight Plug	L-shaped Plug	Manufacturer
0.85	CM10-R2P-D	CM10-SP2S-S-D Applicable Cable: 4.0 dia. to 6.0 dia.	CM10-AP2S-S-D Applicable Cable: 4.0 dia. to 6.0 dia.	DDK Ltd.
to		CM10-SP2S-M-D Applicable Cable: 6.0 dia. to 9.0 dia.	CM10-AP2S-M-D Applicable Cable: 6.0 dia. to 9.0 dia.	
15		CM10-SP2S-L-D Applicable Cable: 9.0 dia. to 11.6 dia.	CM10-AP2S-L-D Applicable Cable: 9.0 dia. to 11.6 dia.	

To order a brake power supply connector kit (0.85 to 15 kW) with the order no. below, contact your Yaskawa representative.

JZSP - CVB9 - S M S2 - E

- Connector Type: S: Straight plug; A: L-shaped plug
- Bush Size*1: S : Size S (4.0 dia. to 6.0 dia.); M : Size M (6.0 dia. to 9.0 dia.); L : Size L (9.0 dia. to 11.6 dia.)
- Contact Pin Size: S2: Soldered; C3: Crimping type*2

*1: A size-M connector kit is available as a standard equipment.
*2: A crimp tool (model: 357J-50448T) by DDK Ltd. is required.

Selecting Encoder Cables

●Encoder Cables (Max. length: 20 m)

■ Non-Stock Items

Name	Length (L)	Order No. Standard Type	Order No. Flexible Type*	Specifications	Details
Encoder Cable with Connectors (For Incremental Encoder)	3 m	JZSP-CVP01-03-E	JZSP-CVP11-03-E	SERVOPACK End — L — Encoder End Connector (Crimped) (Molex Japan Co., Ltd.) — CM10-SP10S-□-D (DDK Ltd.)	(1)
	5 m	JZSP-CVP01-05-E	JZSP-CVP11-05-E		
	10 m	JZSP-CVP01-10-E	JZSP-CVP11-10-E		
	15 m	JZSP-CVP01-15-E	JZSP-CVP11-15-E		
	20 m	JZSP-CVP01-20-E	JZSP-CVP11-20-E		
	3 m	JZSP-CVP02-03-E	JZSP-CVP12-03-E	SERVOPACK End — L — Encoder End Connector (Crimped) (Molex Japan Co., Ltd.) — CM10-AP10S-□-D (DDK Ltd.)	
	5 m	JZSP-CVP02-05-E	JZSP-CVP12-05-E		
	10 m	JZSP-CVP02-10-E	JZSP-CVP12-10-E		
	15 m	JZSP-CVP02-15-E	JZSP-CVP12-15-E		
	20 m	JZSP-CVP02-20-E	JZSP-CVP12-20-E		
Encoder Cable with Connectors (For Absolute Encoder, with a Battery Case)	3 m	JZSP-CVP06-03-E	JZSP-CVP26-03-E	SERVOPACK End — L — Encoder End Battery Case (Battery Attached) Connector (Crimped)(Molex Japan Co., Ltd.) — CM10-SP10S-□-D (DDK Ltd.)	(2)
	5 m	JZSP-CVP06-05-E	JZSP-CVP26-05-E		
	10 m	JZSP-CVP06-10-E	JZSP-CVP26-10-E		
	15 m	JZSP-CVP06-15-E	JZSP-CVP26-15-E		
	20 m	JZSP-CVP06-20-E	JZSP-CVP26-20-E		
	3 m	JZSP-CVP07-03-E	JZSP-CVP27-03-E	SERVOPACK End — L — Encoder End Battery Case (Battery Attached) Connector (Crimped)(Molex Japan Co., Ltd.) — CM10-AP10S-□-D (DDK Ltd.)	
	5 m	JZSP-CVP07-05-E	JZSP-CVP27-05-E		
	10 m	JZSP-CVP07-10-E	JZSP-CVP27-10-E		
	15 m	JZSP-CVP07-15-E	JZSP-CVP27-15-E		
	20 m	JZSP-CVP07-20-E	JZSP-CVP27-20-E		
SERVOPACK-end Connector Kit		JZSP-CMP9-1-E		Soldered (Molex Japan Co., Ltd.)	(3)
Encoder-end Connectors for Protective Structure IP67 Straight Plug		JZSP-CVP9-1-E		Connector Specifications: Plug: CM10-SP10S-M-D; Electrical Contact: (Crimped)** CM10-#22SC(C4)-100; Applicable Cable Diameter: 6.0 dia. to 9.0 dia.	Straight plug + Electrical Contact (DDK Ltd.)	-
		JZSP-CVP9-3-E		Connector Specifications: Plug: CM10-SP10S-M-D; Electrical Contact: (Soldered) CM10-#22SC(S1)-100; Applicable Cable Diameter: 6.0 dia. to 9.0 dia		
Encoder-end Connectors for Protective Structure IP67 L-shaped Plug		JZSP-CVP9-2-E		Connector Specifications: Plug: CM10-AP10S-M-D; Electrical Contact: (Crimped)** CM10-#22SC(C4)-100; Applicable Cable Diameter: 6.0 dia. to 9.0 dia.	L-shaped plug + Electrical Contact (DDK Ltd.)	-
		JZSP-CVP9-4-E		Connector Specifications: Plug: CM10-AP10S-M-D; Electrical Contact: (Soldered) CM10-#22SC(S1)-100; Applicable Cable Diameter: 6.0 dia. to 9.0 dia		
Cables	3 m	JZSP-CMP09-03-E	JZSP-CSP39-03-E			(4)
	5 m	JZSP-CMP09-05-E	JZSP-CSP39-05-E			
	10 m	JZSP-CMP09-10-E	JZSP-CSP39-10-E			
	15 m	JZSP-CMP09-15-E	JZSP-CSP39-15-E			
	20 m	JZSP-CMP09-20-E	JZSP-CSP39-20-E			

* Use flexible cables for movable sections such as robot arms.
** A crimp tool (357J-52667T) is required

Selecting Encoder Cables

(1) Wiring Specifications for Cable with Connectors (For incremental encoder)

· Standard Type

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT(–)
3	BAT(+)
2	PG 0V
1	PG 5V
Shell	FG

Encoder (Servomotor) End

Pin No.	Wire Color
2	Light blue/white
1	Light blue
5	Orange/white
6	Orange
9	Black
4	Red
10	FG

Shield Wire

· Flexible Type

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT(–)
3	BAT(+)
2	PG 0V
1	PG 5V
Shell	FG

Encoder (Servomotor) End

Pin No.	Wire Color
2	Black/pink
1	Red/pink
5	Black/light blue
6	Red/light blue
9	Green
4	Orange
10	FG

Shield Wire

(2) Wiring Specifications for Cable with Connectors (For absolute encoder, with a battery case)

· Standard Type

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT(–)
3	BAT(+)
2	PG 0V
1	PG 5V
Shell	FG

Encoder (Servomotor) End

Pin No.	Wire Color
2	Light blue/white
1	Light blue
5	Orange/white
6	Orange
9	Black
4	Red
10	FG

Shield Wire

Battery Case

Pin No.	Signal
2	BAT(–)
1	BAT(+)

· Flexible Type

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT(–)
3	BAT(+)
2	PG 0V
1	PG 5V
Shell	FG

Encoder (Servomotor) End


Pin No.	Wire Color
2	Black/pink
1	Red/pink
5	Black/light blue
6	Red/light blue
9	Green
4	Orange
10	FG

Shield Wire

Battery Case



Pin No.	Signal
2	BAT(–)
1	BAT(+)

(3) SERVOPACK-end Connector Kit Specifications

Items	Specifications
Order No.	JZSP-CMP9-1-E
Manufacturer	Molex Japan Co., Ltd.
Connector Model (For standard)	55100-0670 (soldered)
External Dimensions (Units: mm)	

Note: The mating connector model on SERVOPACK: 54280-800
The mating connector model on servomotor: 55102-0600

(4) Cable Specifications






Items	Standard Type	Flexible Type
Order No.*	JZSP-CMP09-□□-E	JZSP-CSP39-□□-E
Cable Length	20 m max.	
Specifications	UL20276 (Max. operating temperature: 80˚C) AWG22×2C + AWG24×2P AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.15 dia. AWG24 (0.20 mm^2) Outer diameter of insulating sheath: 1.09 dia.	UL20276 (Max. operating temperature: 80˚C) AWG22×2C + AWG24×2P AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.35 dia. AWG24 (0.20 mm^2) Outer diameter of insulating sheath: 1.21 dia.
Finished Dimensions	6.5 dia.	6.8 dia.
Internal Configuration and Lead Color		
Yaskawa Standards Specifications (Standard Length)	Cable length: 5 m, 10 m, 15 m, 20 m	

*: Specify the cable length in □□ of order no.
Example: JZSP-CMP09-05-E (5 m)

Selecting Encoder Cables

●Encoder Cables (For extending from 30 to 50 m)


Limited Stock Items

Name	Length	Order No.	Specifications	Datails
① Encoder-end Cables (For incremental and absolute encoder)	0.3 m	JZSP-CVP01-E		(1)
		JZSP-CVP02-E		
② Cable with Connectors (For incremental and absolute encoder)	30 m	JZSP-UCMP00-30-E		(2)
	40 m	JZSP-UCMP00-40-E		
	50 m	JZSP-UCMP00-50-E		
③ Cable with a Battery Case (Required when an absolute encoder is used.)	0.3 m	JZSP-CSP12-E*		(3)
④ Cables	30 m	JZSP-CMP19-30-E		(4)
	40 m	JZSP-CMP19-40-E		
	50 m	JZSP-CMP19-50-E		

*: When using an incremental encoder or using an absolute encoder with a battery connected to the host controller, no battery case is required.

Selecting Encoder Cables

(1) Wiring Specifications for Encoder-end Cable
(For incremental and absolute encoder)




SERVOPACK End		Encoder (Servomotor) End	
Pin No.	Signal	Pin No.	Wire Color
6	/PS	2	Light blue/white
5	PS	1	Light blue
4	BAT (–)	5	Orange/white
3	BAT (+)	6	Orange
2	PG 0V	9	Black
1	PG 5V	4	Red
Shell	FG	10	FG

Shield Wire

Note: The signals BAT(+) and BAT(–) are used when using an absolute encoder.


(2) Wiring Specifications for Cable with Connectors
(For incremental and absolute encoder)



SERVOPACK End		Encoder (Servomotor) End	
Pin No.	Signal	Pin No.	Wire Color
6	/PS	6	Light blue/white
5	PS	5	Light blue
4	BAT (–)	4	Orange/white
3	BAT (+)	3	Orange
2	PG 0V	2	Black
1	PG 5V	1	Red
Shell	FG	Shell	FG

Shield Wire

(3) Wiring Specifications for Cable with a Battery Case
(For absolute encoder)




SERVOPACK End		Encoder (Servomotor) End	
Pin No.	Signal	Pin No.	Wire Color
6	/PS	6	Lignt blue/white
5	PS	5	Light blue
4	BAT (–)	4	Orange/white
3	BAT (+)	3	Orange
2	PG 0V	2	Black
1	PG 5V	1	Red
Shell	FG	Shell	FG

Shield Wire

Battery Case

Pin No.	Signal
2	BAT (–)
1	BAT (+)

(4) Cable Specifications

Item	Standard Type
Order No.*	JZSP-CMP19-□□-E
Cable Length	50 m max.
Specifications	UL20276 (Max. operating temperature: 80˚C) AWG16×2C+AWG26×2P AWG16 (1.31 mm²) Outer diameter of insulating sheath: 2.0 dia. AWG26 (0.13 mm²) Outer diameter of insulating sheath: 0.91 dia.
Finished Dimensions	6.8 dia.
Internal Configuration and Lead Colors	
Yaskawa Standard Specifications (Standard Length)	Cable length: 30 m, 40 m, 50 m

*: Specify the cable length in □□ of order no.
Example: JZSP-CMP19-30-E (30 m)

Rotary Servomotors

SGMSV



efesotomasyon.com

Model Designations

SGMSV - 10 A D A 2 1

Σ-V Series Servomotor SGMSV	1st+2nd digits	3rd digit	4th digit	5th digit	6th digit	7th digit

1st+2nd digits Rated Output

Code	Specifications
10	1.0 kW
15	1.5 kW
20	2.0 kW
25	2.5 kW
30	3.0 kW
40	4.0 kW
50	5.0 kW
70	7.0 kW*

*: Available only for 200-VAC models without brake.

3rd digit Power Supply Voltage

Code	Specifications
A	200 VAC
D	400 VAC

4th digit Serial Encoder

Code	Specifications
3	20-bit absolute
D	20-bit incremental

5th digit Design Revision Order

Code	Specifications
A	Standard

6th digit Shaft End

Code	Specifications
2	Straight without key
6	Straight with key and tap

7th digit Options

Code	Specifications
1	Without options
B	With holding brake (90 VDC)
C	With holding brake (24 VDC)
D	With oil seal and holding brake (90 VDC)
E	With oil seal and holding brake (24 VDC)
S	With oil seal

☐ Limited Stock Items ■ Non-Stock Items

Features

- Super high power
- Wide selection: 1.0 kW to 7.0 kW capacity, holding brake option
- Mounted serial encoder: 20 bits, high resolution
- Protective structure: IP67 (Not including the IP22 compliant enclosure for 7.0 kW motor)

Application Examples

- Chip mounters
- PCB drilling stations
- Machine tool feeders

Configurations of connectors for the main circuit



SGMSV-10 to -70

The connectors for these models are round. The connectors specified by Yaskawa are required. Note that the connectors vary depending on the operation environment of servomotors.
Two types of connectors are available.

· Standard connectors
For details, refer to page 83 to 85.

· Protective structure IP67 and European Safety Standards compliant connectors
For details, refer to page 86 and 87.

Note: Connectors are not provided by Yaskawa.

Ratings and Specifications

Time Rating: Continuous
Vibration Class: V15
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40°C
Excitation: Permanent magnet
Mounting: Flange-mounted
Thermal Class: F

Withstand Voltage: 1500 VAC for one minute (200-V class)
1800 VAC for one minute (400-V class)
Enclosure: Totally enclosed, self-cooled, IP67
(except for shaft opening)
Note: IP22 for SGMSV-70 servomotors.
Ambient Humidity: 20% to 80% (no condensation)
Drive Method: Direct drive
Rotation Direction: Counterclockwise (CCW) with forward run reference when viewed from the load side

200-V Class

Servomotor Model: SGMSV-□□□		10A	15A	20A	25A	30A	40A	50A	70A
Rated Output*	kW	1.0	1.5	2.0	2.5	3.0	4.0	5.0	7.0
Rated Torque*	N·m	3.18	4.90	6.36	7.96	9.80	12.6	15.8	22.3
Instantaneous Peak Torque*	N·m	9.54	14.7	19.1	23.9	29.4	37.8	47.6	54
Rated Current*	A_{rms}	5.7	9.3	12.1	13.8	17.9	25.4	27.6	38.3
Instantaneous Max. Current*	A_{rms}	17	28	42	44.5	56	77	84	105
Rated Speed*	min^{-1}	3000							
Max. Speed*	min^{-1}	6000	5000						
Torque Constant	$N·m/A_{rms}$	0.636	0.590	0.561	0.610	0.582	0.519	0.604	0.604
Rotor Moment of Inertia	$\times10^{-4}$ kg·m²	1.74 (1.99)	2.00 (2.25)	2.47 (2.72)	3.19 (3.44)	7.00 (9.2)	9.60 (11.8)	12.3 (14.5)	12.3
Rated Power Rate*	kW/s	58 (51)	120 (107)	164 (149)	199 (184)	137 (104)	165 (135)	203 (172)	404
Rated Angular Acceleration*	rad/s²	18300 (16000)	24500 (21800)	25700 (23400)	25000 (23100)	14000 (10700)	13100 (10700)	12800 (10900)	18100
Applicable SERVOPACK	SGDV-□□□□	7R6A	120A	180A	200A	200A	330A	330A	550A

*: These items and torque-motor speed characteristics quoted in combination with a SERVOPACK are at an armature winding temperature of 20°C.
Notes: 1 The values in parentheses are for servomotors with holding brakes.
2 The above specifications show the values under the cooling condition when the following heat sinks are mounted on the servomotors.
SGMSV-10A/-15A/-20A/-25A : 300 mm×300 mm×12 mm (aluminum)
SGMSV-30A/-40A/-50A/-70A : 400 mm×400 mm×20 mm (aluminum)


400-V Class

Servomotor Model: SGMSV-□□□		10D	15D	20D	25D	30D	40D	50D
Rated Output*	kW	1.0	1.5	2.0	2.5	3.0	4.0	5.0
Rated Torque*	N·m	3.18	4.9	6.36	7.96	9.8	12.6	15.8
Instantaneous Peak Torque*	N·m	9.54	14.7	19.1	23.9	29.4	37.8	47.6
Rated Current*	A_{rms}	2.8	4.7	6.1	7.4	8.9	12.5	13.8
Instantaneous Max. Current*	A_{rms}	8.5	14	20	25	28	38	42
Rated Speed*	min^{-1}	3000						
Max. Speed*	min^{-1}	6000	5000					
Torque Constant	$N·m/A_{rms}$	1.27	1.23	1.18	1.15	1.16	1.06	1.21
Rotor Moment of Inertia	$\times10^{-4}$ kg·m²	1.74 (1.99)	2.00 (2.25)	2.47 (2.72)	3.19 (3.44)	7.00 (9.2)	9.60 (11.8)	12.3 (14.5)
Rated Power Rate*	kW/s	58 (51)	120 (107)	164 (149)	199 (184)	137 (104)	165 (135)	203 (172)
Rated Angular Acceleration*	rad/s²	18300 (16000)	24500 (21800)	25700 (23400)	25000 (23100)	14000 (10700)	13100 (10700)	12800 (10900)
Applicable SERVOPACK	SGDV-□□□□	3R5D	5R4D	8R4D	120D	120D	170D	170D

*: These items and torque-motor speed characteristics quoted in combination with a SERVOPACK are at an armature winding temperature of 20°C.
Notes: 1 The values in parentheses are for servomotors with holding brakes.
2 The above specifications show the values under the cooling condition when the following heat sinks are mounted on the servomotors.
SGMSV-10D/-15D/-20D/-25D : 300 mm×300 mm×12 mm (aluminum)
SGMSV-30D/-40D/-50D : 400 mm×400 mm×20 mm (aluminum)

Ratings and Specifications

●Torque-Motor Speed Characteristics(200 V/400 V) A: Continuous Duty Zone B: Intermittent Duty Zone (Note1)



Note: 1 When the effective torque during intermittent duty is within the rated torque, the servomotor can be used within the intermittent duty zone.
2 When the main circuit cable length exceeds 20 m, note that the intermittent duty zone of the Torque-Motor Speed Characteristics will shrink as the line-to-line voltage drops.

●Holding Brake Electrical Specifications

Servomotor Model	Servomotor Rated Output kW	Holding Brake Specifications				
		Holding Torque N·m	Rated Voltage 24 VDC		Rated Voltage 90 VDC	
			Capacity W	Rated Current A (at 20˚C)	Capacity W	Rated Current A (at 20˚C)
SGMSV-10	1.0	7.84	12	0.5	12	0.13
SGMSV-15	1.5	7.84	12	0.5	12	0.13
SGMSV-20	2.0	7.84	12	0.5	12	0.13
SGMSV-25	2.5	10	12	0.5	12	0.13
SGMSV-30	3.0	20	10	0.41	10	0.11
SGMSV-40	4.0	20	10	0.41	10	0.11
SGMSV-50	5.0	20	10	0.41	10	0.11

Notes: 1 The holding brake is only used to hold the load and cannot be used to stop the servomotor.
2 The holding brake open time and holding brake operation time vary depending on which discharge circuit is used. Make sure holding brake open time and holding brake operation time are correct for your servomotor.
3 A 24 VDC power supply is to be provided by customers.
4 For information on a 90 VDC power supply, refer to page 338.

●Allowable Load Moment of Inertia at the Motor Shaft

The rotor moment of inertia ratio is the value for a servomotor without a gear and a holding brake.

Servomotor Model	Servomotor Rated Output	Allowable Load Moment of Inertia (Rotor Moment of Inertia Ratio)
SGMSV-10 to -70	1.0 to 7.0 kW	5 times

●Load Moment of Inertia


The larger the load moment of inertia, the worse the movement response.
The allowable load moment of inertia (J_L) depends on motor capacity, as shown above. This value is provided strictly as a guideline and results may vary depending on servomotor drive conditions.
Use the AC servo drive capacity selection program SigmaJunmaSize+ to check the operation conditions.
The program can be downloaded for free from our web site (http://www.e-mechatronics.com/).

An overvoltage alarm (A.400) is likely to occur during deceleration if the load moment of inertia exceeds the allowable load moment of inertia. SERVOPACKs with a built-in regenerative resistor may generate a regenerative overload alarm (A.320). Take one of the following steps if this occurs.

- Reduce the torque limit.
- Reduce the deceleration rate.
- Reduce the maximum speed.
- Install an external regenerative resistor if the alarm cannot be cleared using the steps above. Refer to Regenerative Resistors on page 339.

●Allowable Radial and Thrust Loads


Design the mechanical system so thrust and radial loads applied to the servomotor shaft end during operation fall within the ranges shown in the table.


Servomotor Model		Allowable Radial Load (Fr) N	Allowable Thrust Load (Fs) N	LR mm	Reference Diagram
SGMSV-	10□□A21	686	196	45	
	15□□A21				
	20□□A21				
	25□□A21				
	30□□A21	980	392	63	
	40□□A21	1176			
	50□□A21				
	70□□A21				

External Dimensions Units: mm

●Without Holding Brakes

(1) 1.0 to 5.0 kW






Note: For the specifications of the other shaft ends, refer to page 79.

Model SGMSV-	L	LL	LM	LR	KB1	KB2	KL1	Flange Face Dimensions								Shaft End Dimensions		Approx. Mass
								LA	LB	LC	LE	LF	LG	LH	LZ	S	Q	kg
10□□A21	192	147	111	45	76	135	96	115	$95^{0}_{-0.035}$	100	3	3	10	130	7	$24^{0}_{-0.013}$	40	4.1
15□□A21	202	157	121	45	86	145	96	115	$95^{0}_{-0.035}$	100	3	3	10	130	7	$24^{0}_{-0.013}$	40	4.6
20□□A21	218	173	137	45	102	161	96	115	$95^{0}_{-0.035}$	100	3	3	10	130	7	$24^{0}_{-0.013}$	40	5.4
25□□A21	241	196	160	45	125	184	96	115	$95^{0}_{-0.035}$	100	3	3	10	130	7	$24^{0}_{-0.013}$	40	6.8
30□□A21	259	196	160	63	124	184	114	145	$110^{0}_{-0.035}$	130	6	6	12	165	9	$28^{0}_{-0.013}$	55	10.5
40□□A21	296	233	197	63	161	221	114	145	$110^{0}_{-0.035}$	130	6	6	12	165	9	$28^{0}_{-0.013}$	55	13.5
50□□A21	336	273	237	63	201	261	114	145	$110^{0}_{-0.035}$	130	6	6	12	165	9	$28^{0}_{-0.013}$	55	16.5

Note: Models with oil seals are of the same configuration.

· Cable Specifications for Encoder-end Connector (20-bit Encoder)



Receptacle: CM10-R10P-D
Applicable plug (To be provided by the customer)
Plug: CM10-AP10S-□-D (Angle)
CM10-SP10S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Manufacturer: DDK Ltd.


With an Absolute Encoder

1	PS	6	BAT (+)
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	BAT (–)	10	FG (Frame ground)

With an Incremental Encoder

1	PS	6	–
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	–	10	FG (Frame ground)

· Cable Specifications for Servomotor-end Connector




A	Phase U
B	Phase V
C	Phase W
D	FG (Frame ground)

· SGMSV-10 to -25
Manufacturer: DDK Ltd.
· SGMSV-30 to -50
Manufacturer: Japan Aviation Electronics Industry, Ltd.

External Dimensions Units: mm


(2) 7.0 kW (only for 200 V servomotors)

Notes: 1 Leave a minimum space of 70 mm around the servomotor to allow for a sufficient amount of cooling air.
2 Cooling Fan : single-phase 220 V, 50/60Hz, 17/15 W, 0.11/0.09 A




Note: For the specifications of the other shaft ends, refer to page 79.

Approx. Mass: 18.5 kg



· Cable Specifications for Servomotor-end Connector



A	Phase U
B	Phase V
C	Phase W
D	FG (Frame ground)


Manufacturer: Japan Aviation Electronics Industry, Ltd.

· Specifications of Cooling Fan
Single-phase 220 V
50/60 Hz
17/15 W
0.11/0.09 A

· Specifications of rotation error detector
Contact Capacity:
- Max. allowable voltage: 350 V (AC, DC)
- Max. allowable current: 120 mA (AC, DC)
- Max. controllable power: 360 mW

Alarm Contact:
- ON at normal fan rotation.
- OFF at 1680±100 min^{-1} or less.
- (OFF during 3 seconds at start-up)

· Cable Specifications for Fan-end Connector




Receptacle:MS3102A14S-6P
Applicable plug
Plug:MS3108B14S-6S
Cable clamp:MS3057-6A

Note: Servomotor-end connectors (receptacles) are RoHS-compliant. Contact the respective connector manufacturers for RoHS-compliant cable-end connectors.

A	Fan motor
B	Fan motor
C	–
D	Alarm terminal
E	Alarm terminal
F	FG (Frame ground)

· Cable Specifications for Encoder-end Connector
(20-bit Encoder)



Receptacle: CM10-R10P-D
Applicable plug (To be provided by the customer)
Plug: CM10-SP10S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Use straight plugs to avoid interference with the fan cover.
Manufacturer: DDK Ltd.

With an Absolute Encoder

1	PS	6	BAT (+)
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	BAT (–)	10	FG (Frame ground)


With an Incremental Encoder


1	PS	6	–
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	–	10	FG (Frame ground)

External Dimensions Units: mm

●With Holding Brakes

(1) 1.0 to 5.0 kW






Note: For the specifications of the other shaft ends, refer to page 79.

Model SGMSV-	L	LL	LM	LR	KB1 200V	KB1 400V	KB2	KB3* 400V	KL1 200V	KL1 400V	KL3* 400V	Flange Face Dimensions LA	LB	LC	LE	LF	LG	LH	LZ	Shaft End Dimensions S	Q	Approx.Mass
10□□A2□	233	188	152	45	67	76	176	118	102	96	69	115	$95^{0}_{-0.035}$	100	3	3	10	130	7	$24^{0}_{-0.013}$	40	5.5
15□□A2□	243	198	162	45	77	86	186	128	102	96	69	115	$95^{0}_{-0.035}$	100	3	3	10	130	7	$24^{0}_{-0.013}$	40	6
20□□A2□	259	214	178	45	93	102	202	144	102	96	69	115	$95^{0}_{-0.035}$	100	3	3	10	130	7	$24^{0}_{-0.013}$	40	6.8
25□□A2□	292	247	211	45	116	125	225	177	102	96	69	115	$95^{0}_{-0.035}$	100	3	3	10	130	7	$24^{0}_{-0.013}$	40	8.7
30□□A2□	295	232	196	63	114	124	220	176	119	114	81	145	$110^{0}_{-0.035}$	130	6	6	12	165	9	$28^{0}_{-0.013}$	55	13
40□□A2□	332	269	233	63	151	161	257	213	119	114	81	145	$110^{0}_{-0.035}$	130	6	6	12	165	9	$28^{0}_{-0.013}$	55	16
50□□A2□	372	309	273	63	191	201	297	253	119	114	81	145	$110^{0}_{-0.035}$	130	6	6	12	165	9	$28^{0}_{-0.013}$	55	19

*: No brake connector for 200-V models (there are brake terminals on the servomotor-end connectors).
Note: Models with oil seals are of the same configuration.

· Cable Specifications for Encoder-end Connector (20-bit Encoder)



Receptacle: CM10-R10P-D
Applicable plug (To be provided by the customer)
Plug: CM10-AP10S-□-D (Angle)
CM10-SP10S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Manufacturer: DDK Ltd.

With an Absolute Encoder


1	PS	6	BAT (+)
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	BAT (–)	10	FG (Frame ground)

With an Incremental Encoder

1	PS	6	–
2	/PS	7	–
3	–	8	–
4	PG 5V	9	PG 0V
5	–	10	FG (Frame ground)

200-V Class

· Cable Specifications for Servomotor-end Connector




A	Phase U
B	Phase V
C	Phase W
D	FG(Frame ground)
E	Brake terminal
F	Brake terminal
G	–

Manufacturer: Japan Aviation Electronics Industry, Ltd.

Note: No polarity for connection to the brake terminals

400-V Class


· Cable Specifications for Servomotor-end Connector



A	Phase U
B	Phase V
C	Phase W
D	FG (Frame ground)

· SGMSV-10 to -25
Manufacturer: DDK Ltd.
· SGMSV-30 to -50
Manufacturer: Japan Aviation Electronics Industry, Ltd.

· Cable Specifications for Brake-end Connector



Receptacle: CM10-R2P-D
Applicable plug (To be provided by the customer)
Plug: CM10-AP2S-□-D (Angle)
CM10-SP2S-□-D (Straight)
(Boxes (□) indicate a value that varies, depending on cable size.)
Manufacturer: DDK Ltd.

Brake terminal
Brake terminal



Note: No polarity for connection to the brake terminals

External Dimensions Units: mm

● Shaft End

SGMSV - □□□□□□□


Code	Specifications	Remarks
2	Straight without key	Optional/Non-stock
6	Straight with key and tap for one location (Key slot is JIS B1301-1996 fastening type)	Standard/Stock

Code	Specifications	Shaft End		Model SGMSV-							
				10	15	20	25	30	40	50	70
2	Straight without Key		LR	45				63			
			Q	40				55			
			S	$24\ ^{0}_{-0.013}$				$28\ ^{0}_{-0.013}$			
6	Straight with Key and Tap		LR	45				63			
			Q	40				55			
			QK	32				50			
			S	$24\ ^{0}_{-0.013}$				$28\ ^{0}_{-0.013}$			
			W	8							
			T	7							
			U	4							
			P	M8 Screw Depth16							

Selecting Cables


●Cables Connections

●Standard Wiring (Max. encoder cable length: 20 m)



●Encoder Cable Extension from 30 to 50 m

(See page 90.)









⚠CAUTION

- Separate the servomotor main circuit cable wiring from the I/O signal cable and encoder cable at least 30 cm, and do not bundle or run them in the same duct.
- When the main circuit cable length exceeds 20 m, note that the intermittent duty zone of the Torque-Motor Speed Characteristics will shrink as the line-to-line voltage drops.

Selecting Cables

●Servomotor Main Circuit Cables

Voltage	Name	Servomotor Rated Output	Length	Order No.		Specifications	Details
				Value Type	Premium Type *2		
200V	Servomotor Power Cable (for Servomotor without Holding Brake)	1.0kW to 2.5kW	3 m	B1EV-03(A)-E	B1EP-03(A)-E		(1)
			5 m	B1EV-05(A)-E	B1EP-05(A)-E		
			10 m	B1EV-10(A)-E	B1EP-10(A)-E		
			15 m	B1EV-15(A)-E	B1EP-15(A)-E		
			20 m	B1EV-20(A)-E	B1EP-20(A)-E		
		3.0kW	3 m	B3EV-03(A)-E	B3EP-03(A)-E		
			5 m	B3EV-05(A)-E	B3EP-05(A)-E		
			10 m	B3EV-10(A)-E	B3EP-10(A)-E		
			15 m	B3EV-15(A)-E	B3EP-15(A)-E		
			20 m	B3EV-20(A)-E	B3EP-20(A)-E		
		4.0 to 7.0kW *4	3 m	B4EV-03(A)-E	B4EP-03(A)-E		
			5 m	B4EV-05(A)-E	B4EP-05(A)-E		
			10 m	B4EV-10(A)-E	B4EP-10(A)-E		
			15 m	B4EV-15(A)-E	B4EP-15(A)-E		
			20 m	B4EV-20(A)-E	B4EP-20(A)-E		
	Servomotor Power Cable (for Servomotor with Holding Brake) *3	1.0kW to 2.5kW	3 m	BABEV-03(A)-E	BABEP-03(A)-E		(5)
			5 m	BABEV-05(A)-E	BABEP-05(A)-E		
			10 m	BABEV-10(A)-E	BABEP-10(A)-E		
			15 m	BABEV-15(A)-E	BABEP-15(A)-E		
			20 m	BABEV-20(A)-E	BABEP-20(A)-E		
		3.0kW	3 m	BCBEV-03(A)-E	BCBEP-03(A)-E		
			5 m	BCBEV-05(A)-E	BCBEP-05(A)-E		
			10 m	BCBEV-10(A)-E	BCBEP-10(A)-E		
			15 m	BCBEV-15(A)-E	BCBEP-15(A)-E		
			20 m	BCBEV-20(A)-E	BCBEP-20(A)-E		
		4.0 to 5.0kW *4	3 m	BDBEV-03(A)-E	BDBEP-03(A)-E		
			5 m	BDBEV-05(A)-E	BDBEP-05(A)-E		
			10 m	BDBEV-10(A)-E	BDBEP-10(A)-E		
			15 m	BDBEV-15(A)-E	BDBEP-15(A)-E		
			20 m	BDBEV-20(A)-E	BDBEP-20(A)-E		
	Fan Cable	7.0kW	3 m	BFEV-03(A)-E	-		(4)
			5 m	BFEV-05(A)-E			
			10 m	BFEV-10(A)-E			
			15 m	BFEV-15(A)-E			
			20 m	BFEV-20(A)-E			
400V	Servomotor Power Cable (for Servomotor with or without Holding Brake) *1	1.0kW to 2.5kW	3 m	B1EV-03(A)-E	B1EP-03(A)-E		(1)
			5 m	B1EV-05(A)-E	B1EP-05(A)-E		
			10 m	B1EV-10(A)-E	B1EP-10(A)-E		
			15 m	B1EV-15(A)-E	B1EP-15(A)-E		
			20 m	B1EV-20(A)-E	B1EP-20(A)-E		
		3.0 to 5.0kW	3 m	B3EV-03(A)-E	B3EP-03(A)-E		
			5 m	B3EV-05(A)-E	B3EP-05(A)-E		
			10 m	B3EV-10(A)-E	B3EP-10(A)-E		
			15 m	B3EV-15(A)-E	B3EP-15(A)-E		
			20 m	B3EV-20(A)-E	B3EP-20(A)-E		
	Holding Brake Cable	1kW to 5kW	3 m	BBEV-03(A)-E	-		(2)
			5 m	BBEV-05(A)-E	-		
			10 m	BBEV-10(A)-E	-		
			15 m	BBEV-15(A)-E	-		
			20 m	BBEV-20(A)-E	-		
			3 m	-	BBEP-03(A)-E		(3)
			5 m	-	BBEP-05(A)-E		
			10 m	-	BBEP-10(A)-E		
			15 m	-	BBEP-15(A)-E		
			20 m	-	BBEP-20(A)-E		

*1 400V Servomotors with holding brakes require a holding brake cable in addition to a power cable.
*2 Premium cables have a braided cable shield and are intended for use in applications that require CE. Premium cables have a continuous flex rating and are intended for use in movable sections such as robot arms.
*3 200V servomotors with holding brakes use a combined power and brake cable
*4 The 7.0kW, 200V servomotor requires a separate fan cable. 7.0kW units are not available with holding brake.

Selecting Cables

(1) Wiring Specifications for 200V and 400V Servomotors without Holding Brakes*

● Value Type

SERVOPACK-end Leads / Servomotor-end Connector

Wire Label	Signal	Signal	Pin No.
G	FG	FG	D
W	Phase W	Phase W	C
V	Phase V	Phase V	B
U	Phase U	Phase U	A

*400V servomotors with holding brakes require a separate holding brake cable. See (2) and (3).

● Premium Type

SERVOPACK-end Leads / Shield Wire / Servomotor-end Connector

Wire Label	Signal	Signal	Pin No.
G	FG	FG	D
W	Phase W	Phase W	C
V	Phase V	Phase V	B
U	Phase U	Phase U	A

*400V servomotors with holding brakes require a separate holding brake cable. See (2) and (3).

(2) Wiring Specifications for the Value Type Brake Cable for 400V Servomotors

SERVOPACK-end Leads / Servomotor-end Connector

Wire Color	Signal	Signal	Pin No.
Black	Brake	Brake	1
Blue	Brake	Brake	2

Note: No polarity for connection to a holding brake.

(3) Wiring Specifications for the Premium Type Brake Cable for 400V Servomotors

SERVOPACK-end Leads / Servomotor-end Connector

Wire Color	Signal	Signal	Pin No.
Black	Brake	Brake	1
Blue	Brake	Brake	2
Green/Yellow	Shield	Shield Wire	

Note: No polarity for connection to a holding brake.

(4) Wiring Specifications for the Fan on 200V 7.0kW Servomotors

SERVOPACK-end Leads / Servomotor-end Connector

Wire Label	Signal	Signal	Pin No.
FAN	Fan	Fan Motor	A
FAN	Fan	Fan Motor	B
ALM	Alarm	Alarm Terminal	D
ALM	Alarm	Alarm Terminal	E
GND	FG	FG	F

Shield Wire

Notes:
No polarity for connection to a fan.
No polarity for connection to an alarm circuit.

(5) Wiring Specifications for 200V Servomotors with Holding Brakes

● Value Type

SERVOPACK-end Leads / Servomotor-end Connector

Wire Label	Signal	Signal	Pin No.
U	Phase U	Phase U	A
V	Phase V	Phase V	B
W	Phase W	Phase W	C
G	FG	FG	D
BK	Brake	Brake	E
BK	Brake	Brake	F

Note: No polarity for connection to a holding brake.

● Premium Type

SERVOPACK-end Leads / Shield Wire / Servomotor-end Connector

Wire Label	Signal	Signal	Pin No.
U	Phase U	Phase U	A
V	Phase V	Phase V	B
W	Phase W	Phase W	C
G	FG	FG *	D
BK	Brake	Brake	E
BK	Brake	Brake	F

Note: No polarity for connection to a holding brake.
* For 200V Premium Cable, shield is connected to FG wire on the servomotor-end of the cable.

●Customer Cable Assembly

Customers may assemble the servomotor's main circuit cables and attach connectors to connect the SERVOPACKs and the SGMSV servomotors.

The connectors for these models are round. The connectors specified by Yaskawa are required. Note that the connectors vary depending on the operation environment of servomotors.

Two types of connectors are available.


· Standard connectors

· Protective structure IP67 and European Safety Standards compliant connectors


Yaskawa does not specify which cables to use. Use appropriate cables for the connectors.

●Standard Connectors


● Connector Configuration



(1) Without Holding Brakes



Servomotor-end Connector
For 1.0 to 7.0 kW




Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not provided by Yaskawa)		
		Straight Plug	L-shaped Plug	Cable Clamp
1.0 to 2.5	MS3102A18-10P	MS3106B18-10S	MS3108B18-10S	MS3057-10A
3.0 to 7.0	MS3102A22-22P	MS3106B22-22S	MS3108B22-22S	MS3057-12A


Note: Servomotor-end connectors (receptacles) are RoHS-compliant. Contact the respective connector manufacturers for RoHS-compliant cable-end connectors.

(2) With Holding Brakes (200 V)

No brake connector for 200-V models
(there are brake terminals on the servomotor-end connectors).



Servomotor-end Connector
For 1.0 to 5.0 kW




Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not provided by Yaskawa)		
		Straight Plug	L-shaped Plug	Cable Clamp
1.0 to 2.5	MS3102A20-15P	MS3106B20-15S	MS3108B20-15S	MS3057-12A
3.0 to 5.0	MS3102A24-10P	MS3106B24-10S	MS3108B24-10S	MS3057-16A


Note: Servomotor-end connectors (receptacles) are RoHS-compliant. Contact the respective connector manufacturers for RoHS-compliant cable-end connectors.

Selecting Cables

(3) With Holding Brakes (400 V)




Servomotor-end Connector
For 1.0 to 5.0 kW



Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not provided by Yaskawa)		
		Straight Plug	L-shaped Plug	Cable Clamp
1.0 to 2.5	MS3102A18-10P	MS3106B18-10S	MS3108B18-10S	MS3057-10A
3.0 to 5.0	MS3102A22-22P	MS3106B22-22S	MS3108B22-22S	MS3057-12A

Note: Servomotor-end connectors (receptacles) are RoHS-compliant. Contact the respective connector manufacturers for RoHS-compliant cable-end connectors.

Brake Power Supply Connector
For 1.0 to 5.0 kW



Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not provided by Yaskawa)		
		Straight Plug	L-shaped Plug	Manufacturer
1.0 to 5.0	CM10-R2P-D	CM10-SP2S-S-D Applicable Cable: 4.0 dia. to 6.0 dia.	CM10-AP2S-S-D Applicable Cable: 4.0 dia. to 6.0 dia.	DDK Ltd.
		CM10-SP2S-M-D Applicable Cable: 6.0 dia. to 9.0 dia.	CM10-AP2S-M-D Applicable Cable: 6.0 dia. to 9.0 dia.	
		CM10-SP2S-L-D Applicable Cable: 9.0 dia. to 11.6 dia.	CM10-AP2S-L-D Applicable Cable: 9.0 dia. to 11.6 dia.	

To order a brake power supply connecter kit (1.0 to 5.0 kW) with the order no. below, contact your Yaskawa representative.


J Z S P - C V B 9 - S M S2 - E

- Connector Type
  - S: Straight plug
  - A: L-shaped plug
- Bush Size*1
  - S : Size S (4.0 dia. to 6.0 dia.)
  - M: Size M (6.0 dia. to 9.0 dia.)
  - L : Size L (9.0 dia. to 11.6 dia.)
- Contact Pin Size
  - S2: Soldered
  - C3: Crimping type*2

*1: A size-M connector kit is available as standard equipment.
*2: A crimp tool (model: 357J-50448T) by DDK Ltd. is required.


● Cable-end Connectors

(1) MS3106B□□-□□S :
Straight Plug




Shell Size	Joint Screw A	Length of Joint Portion J±0.12	Overall Length L max.	Outer Diameter of Joint Nut Q $^{+0}_{-0.38}$	Cable Clamp Set Screw V	Effective Screw Length W min.	Maximum Width Y max.
18	1-1/8-18UNEF	18.26	52.37	34.13	1-20UNEF	9.53	42
20	1-1/4-18UNEF	18.26	55.57	37.28	1-3/16-18UNEF	9.53	47
22	1-3/8-18UNEF	18.26	55.57	40.48	1-3/16-18UNEF	9.53	50
24	1-1/2-18UNEF	18.26	58.72	43.63	1-7/16-18UNEF	9.53	53

(2) MS3108B□□-□□S :
L-shaped Plug




Shell Size	Joint Screw A	Length of Joint Portion J±0.12	Overall Length L max.	Outer Diameter of Joint Nut Q $^{+0}_{-0.38}$	R ±0.5	U ±0.5	Cable Clamp Set Screw V	Effective Screw Length W min.
18	1-1/8-18UNEF	18.26	68.27	34.13	20.5	30.2	1-20UNEF	9.53
20	1-1/4-18UNEF	18.26	76.98	37.28	22.5	33.3	1-3/16-18UNEF	9.53
22	1-3/8-18UNEF	18.26	76.98	40.48	24.1	33.3	1-3/16-18UNEF	9.53
24	1-1/2-18UNEF	18.26	86.51	43.63	25.6	36.5	1-7/16-18UNEF	9.53

(3) MS3057-□□A : Cable Clamp with Rubber Bushing




Cable Clamp Type	Applicable Connector Shell Size	Overall Length A±0.7	Effective Screw Length C	E Diameter	G±0.7	H	J Diameter	Set Screw V	Outer Diameter Q±0.7 Dia.	Attached Bushing
MS3057-10A	18	23.8	10.3	15.9	31.7	3.2	14.3	1-20UNEF	30.1	AN3420-10
MS3057-12A	20□22	23.8	10.3	19	37.3	4	15.9	1-3/16-18UNEF	35.0	AN3420-12
MS3057-16A	24	26.2	10.3	23.8	42.9	4.8	19.1	1-7/16-18UNEF	42.1	AN3420-16

● Dimensional Drawings of Brake Power Supply



Angled Plug




Straight Plug

Items	Specifications
Connector Order No.	CM10- □P2S-□ -D (Cables are not included.)
Protective Structure	IP67
Manufacturer	DDK Ltd.
Instructions	Angled plug (CM10-AP2S- □ -D): TC-573, Straight plug (CM10-SP2S- □ -D): TC-583
Electrical Contact Order No.	Electrical contact (100 pcs in one bag) · Crimping type: CM10-#22SC(C3)-100, Wire size: AWG16 to 20, Outer diameter of sheath: 1.87 to 2.45 dia., Hand tool: 357J-50448T · Soldered type: CM10-#22SC (S2)-100, Wire size: AWG16 max. Real contact (4000 pcs on one reel) · Crimping type: CM10-#22SC(C3)-4000, Wire size: AWG 16 to 20, Outer diameter of sheath: 1.87 to 2.45 dia., Semi-automatic tool: AP-A50541T (product name for one set), AP-A50541T-1 (product name for applicator) Note: The product name of the semi-automatic tool refers to the product name of the press and applicator (crimper) as a set.

Selecting Cables

●Protective Structure IP67 and European Safety Standards Compliant Connector

● Connector Configuration




Note: For the conduit grounding, contact the manufacturer of the conduit being used.

(1) Without Holding Brakes

Servomotor-end Connector
For 1.0 to 7.0 kW






Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not Provided by Yaskawa)					
		Plug	Straight Plug	L-shaped Plug	Cable Clamp	Applicable Cable Diameter (For Reference)	Manufacturer
1.0 to 2.5	CE05-2A18-10PD-D	CE05-6A18-10SD-D	CE05-6A18-10SD-D-BSS	CE05-8A18-10SD-D-BAS	CE3057-10A-1-D	10.5 dia. to 14.1 dia.	DDK Ltd.
					CE3057-10A-2-D	8.5 dia. to 11.0 dia.	
					CE3057-10A-3-D	6.5 dia. to 8.7 dia.	
3.0 to 7.0	JL04HV-2E22-22PE-B-R	JL04V-6A22-22SE-R	JL04V-6A22-22SE-EB-R or JA06A-22-22S-J1-EB-R*	JL04V-8A22-22SE-EB-R or JA08A-22-22S-J1-EB-R*	JL04-2022CK (09) -R	6.5 Dia. to 9.5 Dia.	Japan Aviation Electronics Industry, Ltd.
					JL04-2022CK (12) -R	9.5 Dia. to 13.0 Dia.	
					JL04-2022CK (14) -R	12.9 Dia. to 15.9 Dia.	


*: Not compliant with European Safety Standards, but compliant with protective structure IP67.

(2) With Holding Brakes (200 V)

No brake connector for 200-V models
(there are brake terminals on the servomotor-end connectors).

Servomotor-end Connector
For 1.0 to 5.0 kW






Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not Provided by Yaskawa)					
		Plug	Straight Plug	L-shaped Plug	Cable Clamp	Applicable Cable Diameter (For Reference)	Manufacturer
1.0 to 2.5	JL04V-2E20-15PE-B-R	JL04V-6A20-15SE-R	JL04V-6A20-15SE-EB-R	JL04V-8A20-15SE-EB-R	JL04-2022CK (09) -R	6.5 Dia. to 9.5 Dia.	Japan Aviation Electronics Industry, Ltd.
					JL04-2022CK (12) -R	9.5 Dia. to 13.0 Dia.	
					JL04-2022CK (14) -R	12.9 Dia. to 15.9 Dia.	
3.0 to 5.0	JL04V-2E24-10PE-B-R	JL04-6A24-10SE-R	JL04V-6A24-10SE-EB-R or JA06A-24-10S-J1-EB-R*	JL04V-8A24-10SE-EB-R or JA08A-24-10S-J1-EB-R*	JL04-2428CK (11) -R	9.0 Dia. to 12.0 Dia.	
					JL04-2428CK (14) -R	12.0 Dia. to 15.0 Dia.	
					JL04-2428CK (17) -R	15.0 Dia. to 18.0 Dia.	
					JL04-2428CK (20) -R	18.0 Dia. to 20.0 Dia.	

*: Not compliant with European Safety Standards, but compliant with protective structure IP67.

(3) With Holding Brakes (400 V)




Servomotor-end Connector
For 1.0 to 5.0 kW



Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not Provided by Yaskawa)					
		Plug	Straight Plug	L-shaped Plug	Cable Clamp	Applicable Cable Diameter (For Reference)	Manufacturer
1.0 to 2.5	CE05-2A18-10PD-D	CE05-6A18-10SD-D	CE05-6A18-10SD-D-BSS	CE05-8A18-10SD-D-BAS	CE3057-10A-1-D	10.5 dia. to 14.1 dia.	DDK Ltd.
					CE3057-10A-2-D	8.5 dia. to 11.0 dia.	
					CE3057-10A-3-D	6.5 dia. to 8.7 dia.	
3.0 to 5.0	JL04HV-2E22-22PE-B-R	JL04V-6A22-22SE-R	JL04V-6A22SE-EB-R or JA06A-22-22S-J1-EB-R*	JL04V-8A22-22SE-EB-R or JA08A-22-22S-J1-EB-R*	JL04-2022CK(09)-R	6.5 Dia. to 9.5 Dia.	Japan Aviation Electronics Industry, Ltd.
					JL04-2022CK(12)-R	9.5 Dia. to 13.0 Dia.	
					JL04-2022CK(14)-R	12.9 Dia. to 15.9 Dia.	

*: Not compliant with European Safety Standards, but compliant with protective structure IP67.

Brake Power Supply Connector
For 1.0 to 5.0 kW



Capacity kW	Servomotor-end Connector (Receptacle)	Cable-end Connector (Not provided by Yaskawa)		
		Straight Plug	L-shaped Plug	Manufacturer
1.0 to 5.0	CM10-R2P-D	CM10-SP2S-S-D Applicable Cable: 4.0 dia. to 6.0 dia.	CM10-AP2S-S-D Applicable Cable: 4.0 dia. to 6.0 dia.	DDK Ltd.
		CM10-SP2S-M-D Applicable Cable: 6.0 dia. to 9.0 dia.	CM10-AP2S-M-D Applicable Cable: 6.0 dia. to 9.0 dia.	
		CM10-SP2S-L-D Applicable Cable: 9.0 dia. to 11.6 dia.	CM10-AP2S-L-D Applicable Cable: 9.0 dia. to 11.6 dia.	

To order a brake power supply connecter kit (1.0 to 5.0 kW)
with the order no. below, contact your Yaskawa representative.

J Z S P - C V B 9 - S M S2 - E

Connector Type
S: Straight plug
A: L-shaped plug

Bush Size*1
S: Size S (4.0 dia. to 6.0 dia.)
M: Size M (6.0 dia. to 9.0 dia.)
L: Size L (9.0 dia. to 11.6 dia.)

Contact Pin Size
S2: Soldered
C3: Crimping type*2

*1: A size-M connector kit is available as standard equipment.
*2: A crimp tool (model: 357J-50448T) by DDK Ltd. is required.

Selecting Cables

●Encoder Cables (Max. length: 20 m)


Non-Stock Items

Name	Length (L)	Order No. Standard Type	Order No. Flexible Type*	Specifications	Details
Encoder Cable with Connectors (For Incremental Encoder)	3 m	JZSP-CVP01-03-E	JZSP-CVP11-03-E	SERVOPACK End — L — Encoder End Connector (Crimped) (Molex Japan Co., Ltd.) CM10-SP10S-□-D (DDK Ltd.)	(1)
	5 m	JZSP-CVP01-05-E	JZSP-CVP11-05-E		
	10 m	JZSP-CVP01-10-E	JZSP-CVP11-10-E		
	15 m	JZSP-CVP01-15-E	JZSP-CVP11-15-E		
	20 m	JZSP-CVP01-20-E	JZSP-CVP11-20-E		
	3 m	JZSP-CVP02-03-E	JZSP-CVP12-03-E	SERVOPACK End — L — Encoder End Connector (Crimped) (Molex Japan Co., Ltd.) CM10-AP10S-□-D (DDK Ltd.)	
	5 m	JZSP-CVP02-05-E	JZSP-CVP12-05-E		
	10 m	JZSP-CVP02-10-E	JZSP-CVP12-10-E		
	15 m	JZSP-CVP02-15-E	JZSP-CVP12-15-E		
	20 m	JZSP-CVP02-20-E	JZSP-CVP12-20-E		
Encoder Cable with Connectors (For Absolute Encoder, with a Battery Case)	3 m	JZSP-CVP06-03-E	JZSP-CVP26-03-E	SERVOPACK End — L — Encoder End Battery Case (Battery Attached) Connector (Crimped)(Molex Japan Co., Ltd.) CM10-SP10S-□-D (DDK Ltd.)	(2)
	5 m	JZSP-CVP06-05-E	JZSP-CVP26-05-E		
	10 m	JZSP-CVP06-10-E	JZSP-CVP26-10-E		
	15 m	JZSP-CVP06-15-E	JZSP-CVP26-15-E		
	20 m	JZSP-CVP06-20-E	JZSP-CVP26-20-E		
	3 m	JZSP-CVP07-03-E	JZSP-CVP27-03-E	SERVOPACK End — L — Encoder End Battery Case (Battery Attached) Connector (Crimped)(Molex Japan Co., Ltd.) CM10-AP10S-□-D (DDK Ltd.)	
	5 m	JZSP-CVP07-05-E	JZSP-CVP27-05-E		
	10 m	JZSP-CVP07-10-E	JZSP-CVP27-10-E		
	15 m	JZSP-CVP07-15-E	JZSP-CVP27-15-E		
	20 m	JZSP-CVP07-20-E	JZSP-CVP27-20-E		
SERVOPACK-end Connector Kit		JZSP-CMP9-1-E		Soldered (Molex Japan Co., Ltd.)	(3)
Encoder-end Connectors for Protective Structure IP67 Straight Plug		JZSP-CVP9-1-E: Connector Specifications Plug: CM10-SP10S-M-D Electrical Contact: (Crimped)** CM10-#22SC(C4)-100 Applicable Cable Diameter: 6.0 dia. to 9.0 dia.		+ Electrical Contact (DDK Ltd.)	-
		JZSP-CVP9-3-E: Connector Specifications Plug: CM10-SP10S-M-D Electrical Contact: (Soldered) CM10-#22SC(S1)-100 Applicable Cable Diameter: 6.0 dia. to 9.0 dia			
Encoder-end Connectors for Protective Structure IP67 L-shaped Plug		JZSP-CVP9-2-E: Connector Specifications Plug: CM10-AP10S-M-D Electrical Contact: (Crimped)** CM10-#22SC(C4)-100 Applicable Cable Diameter: 6.0 dia. to 9.0 dia.		+ Electrical Contact (DDK Ltd.)	-
		JZSP-CVP9-4-E: Connector Specifications Plug: CM10-AP10S-M-D Electrical Contact: (Soldered) CM10-#22SC(S1)-100 Applicable Cable Diameter: 6.0 dia. to 9.0 dia			
Cables	3 m	JZSP-CMP09-03-E	JZSP-CSP39-03-E		(4)
	5 m	JZSP-CMP09-05-E	JZSP-CSP39-05-E		
	10 m	JZSP-CMP09-10-E	JZSP-CSP39-10-E		
	15 m	JZSP-CMP09-15-E	JZSP-CSP39-15-E		
	20 m	JZSP-CMP09-20-E	JZSP-CSP39-20-E		

* Use flexible cables for movable sections such as robot arms.
** A crimp tool (357J-52667T) is required

(1) Wiring Specifications for Cable with Connectors
(For incremental encoder)


· Standard Type



Pin No.	Signal
6	/PS
5	PS
4	BAT(–)
3	BAT(+)
2	PG 0V
1	PG 5V
Shell	FG

Pin No.	Wire Color
2	Light blue/white
1	Light blue
5	Orange/white
6	Orange
9	Black
4	Red
10	FG

· Flexible Type




Pin No.	Signal
6	/PS
5	PS
4	BAT(–)
3	BAT(+)
2	PG 0V
1	PG 5V
Shell	FG

Pin No.	Wire Color
2	Black/pink
1	Red/pink
5	Black/light blue
6	Red/light blue
9	Green
4	Orange
10	FG

(2) Wiring Specifications for Cable with Connectors
(For absolute encoder, with a battery case)

· Standard Type




Pin No.	Signal
6	/PS
5	PS
4	BAT(–)
3	BAT(+)
2	PG 0V
1	PG 5V
Shell	FG

Pin No.	Wire Color
2	Light blue/white
1	Light blue
5	Orange/white
6	Orange
9	Black
4	Red
10	FG

Pin No.	Signal
2	BAT(–)
1	BAT(+)

· Flexible Type




Pin No.	Signal
6	/PS
5	PS
4	BAT(–)
3	BAT(+)
2	PG 0V
1	PG 5V
Shell	FG

Pin No.	Wire Color
2	Black/pink
1	Red/pink
5	Black/light blue
6	Red/light blue
9	Green
4	Orange
10	FG



Pin No.	Signal
2	BAT(–)
1	BAT(+)

(3) SERVOPACK-end Connector Kit Specifications

Items	Specifications
Order No.	JZSP-CMP9-1-E
Manufacturer	Molex Japan Co., Ltd.
Connector Model (For standard)	55100-0670 (soldered)
External Dimensions (Units: mm)	

Note: The mating connector model on SERVOPACK: 54280-800
The mating connector model on servomotor: 55102-0600

(4) Cable Specifications

Items	Standard Type	Flexible Type
Order No.*	JZSP-CMP09-□□-E	JZSP-CSP39-□□-E
Cable Length	20 m max.	
Specifications	UL20276 (Max. rating temperature: 80˚C) AWG22×2C + AWG24×2P AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.15 dia. AWG24 (0.20 mm^2) Outer diameter of insulating sheath: 1.09 dia.	UL20276 (Max. rating temperature: 80˚C) AWG22×2C + AWG24×2P AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.35 dia. AWG24 (0.20 mm^2) Outer diameter of insulating sheath: 1.21 dia.
Finished Dimensions	6.5 dia.	6.8 dia.
Internal Configuration and Lead Color		
Yaskawa Standards Specifications (Standard Length)	Cable length: 5 m, 10 m, 15 m, 20 m	

*: Specify the cable length in □□ of order no.
Example: JZSP-CMP09-05-E (5 m)

Selecting Cables

●Encoder Cables (For extending from 30 to 50 m)

■ Limited Stock Items

Name	Length	Order No.	Specifications	Datails
① Encoder-end Cables (For incremental and absolute encoder)	0.3 m	JZSP-CVP01-E	SERVOPACK End — 0.3 m — Encoder End Plug Connector (Crimped) (Molex Japan Co., Ltd.) CM10-SP10S-□-D (DDK Ltd.)	(1)
		JZSP-CVP02-E	SERVOPACK End — 0.3 m — Encoder End Plug Connector (Crimped) (Molex Japan Co., Ltd.) CM10-AP10S-□-D (DDK Ltd.)	
② Cable with Connectors (For incremental and absolute encoder)	30 m	JZSP-UCMP00-30-E	SERVOPACK End — L — Encoder End Connector (Crimped) (Molex Japan Co., Ltd.) Socket Connector (Soldered) (Molex Japan Co., Ltd.)	(2)
	40 m	JZSP-UCMP00-40-E		
	50 m	JZSP-UCMP00-50-E		
③ Cable with a Battery Case (For absolute encoder)	0.3 m	JZSP-CSP12-E*	SERVOPACK End — 0.3 m — Encoder End Battery Case (Battery attachesl) Connector (Crimped) (Molex Japan Co., Ltd.) Socket Connector (Soldered) (Molex Japan Co., Ltd.)	(3)
④ Relay Cables	30 m	JZSP-CMP19-30-E		(4)
	40 m	JZSP-CMP19-40-E		
	50 m	JZSP-CMP19-50-E		

*: When using an incremental encoder or using an absolute encoder with a battery connected to the host controller, no battery case is required.

(1) Wiring Specifications for Encoder-end Cable (For incremental and absolute encoder)

SERVOPACK End		Encoder (Servomotor) End	
Pin No.	Signal	Pin No.	Wire Color
6	/PS	2	Light blue/white
5	PS	1	Light blue
4	BAT (–)	5	Orange/white
3	BAT (+)	6	Orange
2	PG 0V	9	Black
1	PG 5V	4	Red
Shell	FG	10	FG

Shield Wire

Note: The signals BAT(+) and BAT(–) are used when using an absolute encoder.

(2) Wiring Specifications for Cable with Connectors (For incremental and absolute encoder)

SERVOPACK End		Encoder (Servomotor) End	
Pin No.	Signal	Pin No.	Wire Color
6	/PS	6	Light blue/white
5	PS	5	Light blue
4	BAT (–)	4	Orange/white
3	BAT (+)	3	Orange
2	PG 0V	2	Black
1	PG 5V	1	Red
Shell	FG	Shell	FG

Shield Wire

(3) Wiring Specifications for Cable with a Battery Case (For absolute encoder)

SERVOPACK End		Encoder (Servomotor) End	
Pin No.	Signal	Pin No.	Wire Color
6	/PS	6	Lignt blue/white
5	PS	5	Light blue
4	BAT (–)	4	Orange/white
3	BAT (+)	3	Orange
2	PG 0V	2	Black
1	PG 5V	1	Red
Shell	FG	Shell	FG

Shield Wire

Battery Case

Pin No.	Signal
2	BAT (–)
1	BAT (+)

(4) Relay Encoder Cable Specifications

Item	Standard Type
Order No.*	JZSP-CMP19-□□-E
Cable Length	50 m max.
Specifications	UL20276 (Max. rating temperature: 80˚C) AWG16×2C+AWG26×2P AWG16 (1.31 mm²) Outer diameter of insulating sheath: 2.0 dia. mm AWG26 (0.13 mm²) Outer diameter of insulating sheath: 0.91 dia. mm
Finished Dimensions	6.8 dia.
Internal Configuration and Lead Colors	Orange, Orange /white, Black, Red, Light Blue, Light Blue /white
Yaskawa Standard Specifications (Standard Length)	Cable length: 30 m, 40 m, 50 m

*: Specify the cable length in □□ of order no.
Example: JZSP-CMP19-30-E (30 m)

efesotomasyon.com


Precautions on Servomotor Installation

Servomotors can be installed either horizontally or vertically.

The service life of the servomotor will be shortened or unexpected problems will occur if the servomotor is installed incorrectly or in an inappropriate location. Always observe the following installation instructions.

⚠ CAUTION

Do not connect the servomotor directly to a commercial power line. This will damage the servomotor.
The servomotor cannot operate without the proper SERVOPACK.



(1) Installation Environment


Items	Condition
Ambient Temperature	0 to 40°C (no freezing)
Ambient Humidity	20% to 80%RH (no condensation)
Installation Site	· Free of corrosive or explosive gases. · Well-ventilated and free of dust and moisture. · Facilitates inspection and cleaning. · Elevation :1,000 m max. · Free of high magnetic field
Storage Environment	Store the servomotor in the following environment if it is stored with the power cable disconnected. Ambient temperature during storage: −20 to +60°C (no freezing) Ambient humidity during storage: 20% to 80%RH (no condensation)

(2) Enclosure

The servomotor enclosure* is described table as follows.

Model	Without Gears	With Gears
SGMAV□SGMJV	IP65	IP55
SGMPS	IP55 IP67 (optional)	IP55
SGMGV	IP67	–
SGMSV	IP67 (SGMSV-70 servomotor only: IP22)	–

*: Except through shaft section. The enclosure specification can be satisfied only when using a specified cable.




- Do not use servomotors in a location that is subject to oil. If the servomotor is used in a location that is subject to water or oil mist, order a servomotor with an oil seal to seal the through shaft section.

Precautions on Using Servomotor with Oil Seal:

- Put the oil surface under the oil seal lip.
- Use an oil seal in favorably lubricated condition.
- When using a servomotor with its shaft upward direction, be sure that oil will not stay in the oil seal lips.

(3) Orientation

- Servomotors can be installed either horizontally or vertically. When installing servomotors vertically, make cable traps to keep out water. When mounting servomotors with the shaft up, take measures with the connected machine to prevent oil from getting into the servomotors through gear boxes etc.




(4) Alignment


Align the shaft of the servomotor with the shaft of the equipment, and then couple the shafts.

IMPORTANT


1 Install the servomotor so that alignment accuracy falls within the following range.
Vibration that will damage the bearings and encoders if the shafts are not properly aligned.



2 Do not allow any direct impact to the shafts when installing the couplings. Do not hit the area near encoders with a hammer etc., as impacts may damage the encoders.



3 Before installation, thoroughly remove the anticorrosive paint from the end of the motor shaft. Only after removing the paint can servomotors be installed on the machines.



(5) Cable Stress

- Make sure there is no bending or tension on the cables themselves, the connections, or the cable lead inlets.
  Be especially careful to wire encoder cables so that they are not subject to stress because the core wires of encoder cables and main circuit cables are very thin at only 0.2 to 0.3 $mm^{2.}$

(6) Connectors

Observe the following precautions:


- When the connectors are connected to the motor, be sure to connect the end of motor main circuit cables before connecting the encoder cable's end.
  If the encoder cable's end is connected, the encoder may break because of the voltage differences between FG.
- Make sure there is no foreign matters such as dust and metal chips in the connector before connecting.
- Do not apply shock to resin connectors. Otherwise, they may be damaged.
- Make sure of the pin arrangement.
- Be sure not to apply stress on the connector, when using flexible cables. The connector may be damaged by stress.
- When handling a servomotor with its cables connected, hold the servomotor or the connectors and cables will be damaged.
- Fix the cable connector to SGMJV, SGMAV, SGMPS-01/-02/-04 or SGMGV-03/-05 servomotors with screws. Refer to "Cable connections to SGMJV, SGMAV and SGMPS servomotors" or "Cable connections to SGMGV-03/-05 servomotors."Make sure that the connector is securely fixed with screws.
- If connectors are not connected properly, the protective structure specifications may not be satisfied.

Cable Connections to SGMJV, SGMAV and SGMPS Servomotors


Connect the main circuit cable and encoder cable to SGMJV, SGMAV or SGMPS-01/-02/-04 servomotor in the following manner.

> **⚠ CAUTION**
>
> Do not directly touch the connector pins provided with the servomotor. Particularly, the encoder may be damaged by static electricity, etc.

STEP1 Remove the protective tape and cap from the servomotor connector.



STEP2 Mount the cable connector on the servomotor and fix it with screws as shown in the figure below.



IMPORTANT

- First, connect the servomotor to the servomotor main circuit cable end.
- Do not remove the rubber packing. Mount the connector so that the rubber packing is seated properly.


  If the rubber packing is not seated properly, the requirements for the protective structure specifications may not be met.

Cable Connections to SGMGV-03/-05 Servomotors


Connect the main circuit cable and encoder cable to SGMGV-03/-05 servomotor in the following manner.

> **⚠ CAUTION**
>
> Do not directly touch the connector pins provided with the servomotor. Particularly, the encoder may be damaged by static electricity, etc.

STEP1 Remove the protective cap from the servomotor connector.



STEP2 Mount the cable connector on the servomotor and fix it with screws as shown in the figure below.




IMPORTANT
- First, connect the servomotor to the servomotor main circuit cable end.
- Do not remove the O-ring. Mount the connector so that the O-ring is seated properly. If the O-ring is not seated properly, the requirements for the protective structure specifications may not be met.


Mechanical Specifications

●Mechanical Tolerance(T.I.R. : Total Indicator Reading)

The following figure shows tolerances for the servomotor's output shaft and installation area. For more details on tolerances, refer to the external dimensions of the individual servomotor.




●Direction of Servomotor Rotation



Positive rotation of the servomotor without a gear is counterclockwise when viewed from the load.

Refer to Ratings and Specifications for each series regarding rotation direction of the servomotor with a gear. The direction of rotation can be reversed by changing the SERVOPACK parameters.

●Shock Resistance




Impact Applied to the Servomotor

Mount the servomotor with the axis horizontal. The servomotor will withstand the following vertical impacts:

- Impact Acceleration: 490 m/s^2
- Impact occurrences: 2

●Vibration Resistance



Impact Applied to the Servomotor

Mount the servomotor with the axis horizontal. The servomotor will withstand the following vibration acceleration in three directions: Vertical, side to side, and front to back.

Servomotor Model	Vibration Acceleration at Flange
SGMJV, SGMAV, SGMPS	49 m/s^2
SGMGV -03 to -44, SGMSV -10 to -50	49 m/s^2 (Front to back direction: 24.5 m/s^2)
SGMGV -55 to -1E	24.5 m/s^2
SGMSV -70	14.7 m/s^2

IMPORTANT

The amount of vibration the servomotor endures will vary depending on the application. Check the vibration acceleration being applied to your servomotor for each application.

●Vibration Class

The vibration class for the servomotors at rated motor speed is V15.

(A vibration class of V15 indicates a total vibration amplitude of 15 μm maximum on the servomotor during rated rotation.)

Rotor Moment of Inertia


Small-capacity servomotors come in a medium inertia series "SGMJV servomotor," "SGMPS servomotor" and low inertia series "SGMAV servomotor." The rotor moment of inertia of SGMJV servomotor and SGMPS servomotor are twice as large as that of SGMAV. Select servomotors based on the specifications of your devices, such as load moment of inertia or machine rigidity.

- When the rotor moment of inertia is large:
  Servomotors are capable of corresponding load changes. This has the benefit of reducing settling time and speed ripple. This should also improve control stability of machines with low rigidity.
- When mounting the servomotor with low rotor moment of inertia to devices with load moment of inertia:
  Acceleration/deceleration torque increases and effective load ratio increases. Check the effective load ratio when you select motor capacity.

Servomotor Heating Conditions

The motor rated specifications are continuous allowable values at an ambient temperature of 40˚C when servomotors are installed with heat sinks. When the motor is mounted on a small surface, the motor temperature may rise considerably because of the limited heat radiating abilities of the surface. See the following graph for the relation between heat sink size and derating (derating ratio).

IMPORTANT The actual temperature rise depends on how the heat sink (servomotor mounting section) is fixed on the installation surface, what material is used for the motor mounting section, and motor speed. Always check the actual motor temperature.



Holding Brake Delay Time

Holding brakes have motion delay time that varies depending on when the brake is open and when the brake is operating. The following table shows the brake delay time of each servomotor.

IMPORTANT Make sure the holding brake delay time is correct for your servomotor.

- Example, switching the holding brakes on the DC side

Model	Voltage	Brake Open Time ms	Brake Operation Time ms	Model	Voltage	Brake Open Time ms	Brake Operation Time ms
SGMAV-A5 to -04	24 V	60	100	SGMGV-03 to -20	24 V, 90 V	100	80
SGMAV-06 to -10		80	100	SGMGV-30,-44		170	100 (24 V), 80 (90 V)
SGMJV-A5 to -04	24 V	60	100	SGMGV-55,-75,-1A		170	80
SGMJV-08		80	100	SGMGV-1E		250	80
SGMPS-01, -08	24 V	20	100	SGMSV-10 to -25		170	80
SGMPS-02, -04, -15		40	100	SGMSV-30 to -50		100	80

Rotary Cables with Model Numbers Beginning with "JZSP"

●Standard Cables


Standard servomotor main circuit cables, encoder cables, and relay cables cannot be used in cases where high flexibility is needed, as when the cables themselves move or are twisted or turned.
Recommended minimum bend radius of standard cables: R = radius (of cable) x 15. Use flexible cables for flexible applications.

●Flexible Cables

(1) Life of Flexible Cable

The flexible cable supports 10,000,000 or more operations of bending life with the recommended bending radius R = 90 mm under the following test conditions.

- Conditions
  1. Repeat moving one end of the cable forward and backward for 320 mm using the test equipment shown in the following figure.
  2. Connect the lead wires in parallel, and count the number of cable return motion times until a lead wire is disconnected. Note that one reciprocation is counted as one test.



Notes: 1 The life of flexible cable differs largely depending on the amount of mechanical shocks, mounting to the cable, and fixing methods.
The life of flexible cable is limited under the specified conditions.
2 The life of flexible cable indicates the number of bending times in which lead wires are electrically conducted and by which no cracks and damages that affects the performance of cable sheathing are caused. Disconnecting the shield wire is not taken into account.

(2) Wiring Precautions

Even if the recommended bending radius R is followed in the mechanical design, incorrect wiring may cause the early disconnection. Observe the following precautions when wiring.

(a) Cable twisting

Straighten the flexible cables wiring.
Twisted cables cause the early disconnection. Check the indication on the cable surface to make sure that the cable is not twisted.

(b) Fixing method

Do not fix the moving points of the flexible cable, or stress on the fixed points may cause early disconnection. Fix the cable at the minimum number of points. Do not put stress on the servomotor-end and SERVOPACK-end connectors.

(c) Cable length

If the cable length is too long, it may result the cable sagging. If the cable length is too short, excessive tension on the fixed points will cause the early disconnection. Use a flexible cable with the optimum length.

(d) Interference between cables

Avoid interference between cables.
Interference limits the motion of flexible cable, which causes early disconnection. Keep enough distance between cables, or provide a partition when wiring.

Rotary Cables with Model Numbers NOT Beginning with "JZSP"

●Standard Cables

Standard servomotor main circuit cables, encoder cables, and relay cables cannot be used in cases where high flexibility is needed, as when the cables themselves move or are twisted or turned. Use flexible cables for flexible applications.
For bend radius, refer to the following chart.

Model	B1EV	B2EV	B3EV	B4EV	B5EV	B6EV	B7EV	B6EP	B7EP	BABEV	BCBEV	BDBEV	BBEV	BFEV
Recommended Bend Radius (mm)	72	82		119.5	89.5	191.8	226.1	151.2	201.6	87.65	94.6	107.3	35.2	47.24
Outer Diameter (mm)	14.4	16.4		23.9	17.9	27.4	32.3	25.2	33.6	17.53	18.92	21.46	8.8	11.81

Note: All models in the chart refer to the first set of characters of the cable's model number.


●Flexible Cables

(1) Life of Flexible Cable

The flexible cable supports several million cycles or more of bending life with the recommended bending radius under the following test conditions.

● Conditions

1 Repeat moving one end of the cable forward and backward for 500 mm using the test equipment shown in the following figure.
2 Connect the lead wires in parallel, and count the number of cable return motion times until a lead wire is disconnected. Note that one reciprocation is counted as one cycle.



Notes: 1 The life of flexible cable differs largely depending on the amount of mechanical shocks, mounting to the cable, and fixing methods.
The life of flexible cable is limited under the specified conditions.
2 The life of flexible cable indicates the number of bending times in which lead wires are electrically conducted and by which no cracks and damages that affect the performance of cable sheathing are caused. Disconnecting the shield wire is not taken into account.

(2) Specific Cable Details

The following chart contains details for each flexible cable with model not beginning with "JZSP"

Model	B1EP	B2EP	B3EP	B4EP	B5EP	BABEP	BCBEP	BDBEP	BBEP
Recommended Bend Radius (mm)	140	165		224	191	180	177.1	190.3	50
Outer Diameter (mm)	14.0	16.5		22.4	19.1	15.0	16.1	17.3	7.7
Cycles (million)	8-20					9			10

Note: All models in the chart refer to the first set of characters of the cable's model number..

(3) Wiring Precautions

Even if the recommended bending radius is followed in the mechanical design, incorrect wiring may cause early disconnection. Observe the following precautions when wiring.

(a) Cable twisting

Straighten the flexible cables wiring.

Twisted cables cause early disconnection. Check the indication on the cable surface to make sure the cable is not twisted.

(b) Fixing method

Do not fix the moving points of the flexible cable, or stress on the fixed points may cause early disconnection. Fix the cable at the minimum number of points. Do not put stress on the servomotor-end and SERVOPACK-end connectors.

(c) Cable length

If the cable length is too long, it may result in the cable sagging. If the cable length is too short, excessive tension on the fixed points will cause early disconnection. Use a flexible cable with the optimum length.

(d) Interference between cables

Avoid interference between cables.

Interference limits the motion of flexible cable, which causes early disconnection. Keep enough distance between cables, or provide a partition when wiring.


Battery Case

●Battery Case (Model: JUSP-BA01-E)

Use this battery case if your battery case needs replacing due to damage etc.. This battery case cannot be used with an incremental encoder cable.


IMPORTANT

1 The battery case (JUSP-BA01-E) is not provided with a battery. A battery must be purchased separately.
2 Install the battery case where the ambient temperature is between 0˚C to 55˚C.



(1) Mounting a Battery in a Battery Case


Prepare a lithium battery (JZSP-BA01) and mount in a battery case.



ER3 V Lithium Battery
(3.6 V, 1000 mAh, manufactured by Toshiba Battery Co., Ltd.)

(2) Connecting a Battery to the Host Controller

Use a battery that meets the specifications of the host controller. Use an ER6VC3N (3.6 V, 2000 mAh, manufactured by Toshiba Battery Co., Ltd.) or equivalent battery.




Terms for Servomotors with Gears

(1) Terminology for Servomotors with Low-backlash Gears

Item	Measurement Method/Definition	Typical Value
Rated Torque (N·m)	The rated output torque of the motor is the gear input torque. The rated torque is this value multiplied by the inverse of the gear ratio and efficiency.	–
Lost Motion (arc-min)*	Angular difference in a screw with a ± 5% rated torque load. (Maximum value at any four positions during output.)	3 max.
Torsion Rigidity (arc-min)*	Highest torsion angle value on one side with a ± rated torque load.	10 max.
Angular Transmission Error Accuracy (arc-min)	Difference in absolute accuracy for one rotation under load and no-load conditions during output.	6 max.


*: See the following graph for lost motion and torsion rigidity.



(2) Noise Data


The following noise data for a servomotor with a gear is for reference only. The data may vary slightly depending on the capacity and gear ratio of the servomotor.

Measurement Conditions
- Scale A: 50 cm
- Ground Noise: 28 dB



(3) Efficiency

The output torque and motor speed produce the following trends in efficiency. The values in the tables, Ratings and Specifications of SGM□□ Servomotors with Gears, are at the rated motor torque and rated motor speed.



Direct Drive Servomotors

SGMCS

efesotomasyon.com



Model Designations

SGMCS - 02 B 3 C 1 1

Direct Drive Servomotor SGMCS	1st+2nd digits	3rd digit	4th digit	5th digit	6th digit	7th digit

1st+2nd digits Rated Torque

●Small-capacity

Code	Specifications
02	2.0 N·m
04	4.0 N·m
05	5.0 N·m
07	7.0 N·m
08	8.0 N·m
10	10 N·m
14	14 N·m
16	16 N·m
17	17 N·m
25	25 N·m
35	35 N·m

●Medium-capacity

Code	Specifications
45	45 N·m
80	80 N·m
1A	110 N·m
1E	150 N·m
2Z	200 N·m

3th digit Motor Outer Diameter

Code	Specifications
B	135 dia. mm
C	175 dia. mm
D	230 dia. mm
E	290 dia. mm
M	280 dia. mm
N	360 dia. mm

4th digit Encoder Specifications

Code	Specifications
3	20-bit absolute (without multiturn data) (standard)
D	20-bit incremental (option)

NOTE: Shaded items are non-stock.

5th digit Design Revision Order

Code	Specifications
A	Model of servomotor outer diameter code M, N
B	Model of servomotor outer diameter code E
C	Model of servomotor outer diameter code B, C, D

6th digit Flange Specifications

Code	Flange Specifications		Motor Outer Diameter Code (3rd digit)					
	Specifications	Mounted Side	B	C	D	E	M	N
1	C-face	Non-load side	○	○	○	○	–	–
		load end	–	–	–	–	○	○
3	C-face	Non-load side	–	–	–	–	○	○
4	C-face	Non-load side (with cable on side)	○	○	○	○	–	–

○ : Applicable Model

7th digit Option

Code	Specifications
1	Without options

Features


- Directly coupled to a load without a mechanical transmission such as a gear.
- Powerful and smooth operation throughout the speed range from low to high.
  (Instantaneous peak torque: 6 to 600 N·m
  maximum speed: 250 to 500 min^{-1})
- High-resolution, 20-bit encoder for highly precise indexing.
- Easy wiring and piping with the hollow structure.

Application Examples


- Semiconductor equipment
- LCD manufacturing equipment
- Units for inspection and testing
- Electronic parts assembling machines
- IC handlers
- Inspection units for integrated circuits
- Automated machines
- Robots

Rated Torque / Peak Torque


●Small-capacity




Outer Diameter 135 mm, Inner Diameter 20 mm




Outer Diameter 175 mm, Inner Diameter 35 mm



Outer Diameter 230 mm, Inner Diameter 60 mm




Outer Diameter 290 mm, Inner Diameter 75 mm




●Medium-capacity



Outer Diameter 280 mm, Inner Diameter 75 mm



Outer Diameter 360 mm, Inner Diameter 118 mm



●Small-capacity Series

Time Rating: Continuous
Vibration Class: V15
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40˚C
Excitation: Permanent magnet
Mounting: Flange method
Thermal Class: A

Withstand Voltage: 1500 VAC for one minute
Enclosure: Totally enclosed, self-cooled, IP42 (except for gaps on the rotating section of the shaft)
Ambient Humidity: 20% to 80% (no condensation)
Drive Method: Direct drive
Rotation Direction: Counterclockwise (CCW) with forward run reference when viewed from the load side


Voltage		200 V										
Servomotor Model SGMCS-□□□□□		02B□C	05B□C	07B□C	04C□C	10C□C	14C□C	08D□C	17D□C	25D□C	16E□B	35E□B
Rated Output*1	W	42	105	147	84	209	293	168	356	393	335	550
Rated Torque*1, *2	N·m	2.0	5.0	7.0	4.0	10.0	14.0	8.0	17.0	25.0	16.0	35.0
Instantaneous Peak Torque*1	N·m	6.0	15.0	21.0	12.0	30.0	42.0	24.0	51.0	75.0	48.0	105
Stall Torque*1	N·m	2.05	5.15	7.32	4.09	10.1	14.2	8.23	17.4	25.4	16.5	35.6
Rated Current*1	A_{rms}	1.8	1.7	1.4	2.2	2.2	2.8	1.9	2.5	2.6	3.3	3.5
Instantaneous Max. Current*1	A_{rms}	5.4	5.1	4.1	7.0	7.0	8.3	5.6	7.5	8.0	9.4	10.0
Rated Speed*1	min^{-1}	200			200			200		150	200	150
Max. Speed*1	min^{-1}	500			500	400	300	500	350	250	500	250
Torque Constant	$N·m/A_{rms}$	1.18	3.17	5.44	2.04	5.05	5.39	5.1	7.8	10.8	5.58	11.1
Rotor Moment of Inertia	$×10^{-4}$ kg·m²	28	51	77	77	140	220	285	510	750	930	1430
Rated Power Rate*1	kW/s	1.4	4.9	6.4	2.1	7.1	8.9	2.2	5.7	8.3	2.75	8.57
Rated Angular Acceleration*1	rad/s²	710	980	910	520	710	640	280	330	330	170	240
Absolute Accuracy	second	±15			±15			±15			±15	
Repeatability	second	±1.3			±1.3			±1.3			±1.3	
Applicable SERVOPACK	SGDV-□□□□	2R8A			2R8A			2R8A			5R5A	

*1: These items and torque-motor speed characteristics quoted in combination with an SGDV SERVOPACK are at an armature winding temperature of 100˚C. Other values quoted at 20˚C.
*2: Rated torques are continuous allowable torque values at 40˚C with a steel heat sink attached.
Heat sink: SGMCS-□□B : 350 mm × 350 mm × 12 mm SGMCS-□□C : 450 mm × 450 mm × 12 mm
SGMCS-□□D : 550 mm × 550 mm × 12 mm SGMCS-□□E : 650 mm × 650 mm × 12 mm

Notes: 1 SGMCS servomotor with holding brake is not available.
2 For the bearings used in SGMCS servomotors, loss varies according to the bearing temperature. At low temperatures, the amount of heat loss will be large.

●Small-capacity Series: Torque-Motor Speed Characteristics

A : Continuous Duty Zone B : Intermittent Duty Zone(Note2)



Notes: 1 The solid, dotted lines of the intermittent duty zone indicate the characteristics when a servomotor runs with the following combinations:
· The solid line: With a three-phase 200 V SERVOPACK
· The dotted line: With a single-phase 100 V SERVOPACK
2 When the effective torque during intermittent duty is within the rated torque, the servomotor can be used within the intermittent duty zone.
3 When the main circuit cable length exceeds 20 m, note that the intermittent duty zone of the Torque-Motor Speed Characteristics will shrink as the line-to-line voltage drops.

Ratings and Specifications

●Medium-capacity Series


Time Rating: Continuous
Vibration Class: V15
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40°C
Excitation: Permanent magnet
Mounting: Flange method
Thermal Class: F
Withstand Voltage: 1500 VAC for one minute
Enclosure: Totally enclosed, self-cooled, IP44 (except for shaft opening)
Ambient Humidity: 20% to 80% (no condensation)
Drive Method: Direct drive
Rotation Direction: Counterclockwise (CCW) with forward run reference when viewed from the load side

Voltage		200 V					
Servomotor Model SGMCS-□□□□□		45M□□	80M□□	1AM□□	80N□□	1EN□□	2ZN□□
Rated Output*1	W	707	1260	1730	1260	2360	3140
Rated Torque*1, *2	N·m	45	80	110	80	150	200
Instantaneous Peak Torque*1	N·m	135	240	330	240	450	600
Stall Torque*1	N·m	45	80	110	80	150	200
Rated Current*1	A_{rms}	5.80	9.74	13.4	9.35	17.4	18.9
Instantaneous Max. Current*1	A_{rms}	17	28	42	28	56	56
Rated Speed*1	min^{-1}	150					
Max. Speed*1	min^{-1}	300				250	
Torque Constant	$N·m/A_{rms}$	8.39	8.91	8.45	9.08	9.05	11.5
Rotor Moment of Inertia	$\times 10^{-4}$ kg·m²	388	627	865	1360	2470	3060
Rated Power Rate*1	kW/s	52.2	102	140	47.1	91.1	131
Rated Angular Acceleration*1	rad/s²	1160	1280	1270	588	607	654
Applicable SERVOPACK	SGDV-□□□□	7R6A	120A	180A	120A	200A	200A

*1: These items and torque-motor speed characteristics quoted in combination with an SGDV SERVOPACK are at an armature winding temperature of 20°C.
*2: Rated torques are continuous allowable torque values at 40°C with a steel heat sink attached.
Heat sink: 750 mm × 750 mm × 45 mm
Notes: 1 SGMCS servomotor with holding brake is not available.
2 For the bearings used in SGMCS servomotors, loss varies according to the bearing temperature. At low temperatures, the amount of heat loss will be large.

●Medium-capacity Series: Torque-Motor Speed Characteristics

A : Continuous Duty Zone B : Intermittent Duty Zone(Note1)



Notes: 1 When the effective torque during intermittent duty is within the rated torque, the servomotor can be used within the intermittent duty zone.
2 When the main circuit cable length exceeds 20 m, note that the intermittent duty zone of the Torque-Motor Speed Characteristics will shrink as the line-to-line voltage drops.

●Allowable Load Moment of Inertia at the Motor Shaft

Servomotor Model		Rated Torque N·m	Allowable Load Moment of Inertia (Rotor Moment of Inertia Ratio)
SGMCS-	02B□C, 05B□C, 07B□C, 04C□C	2.0, 5.0, 7.0, 4.0	10 times
	10C□C	10.0	5 times
	14C□C, 08D□C, 17D□C, 25D□C, 16E□B, 35E□B	14.0, 8.0, 17.0, 25.0, 16.0, 35.0	3 times
	45M□A, 80M□A, 1AM□A, 80N□A, 1EN□A, 2ZN□A	45, 80, 110, 150, 200	3 times

●Load Moment of Inertia

The larger the load moment of inertia, the worse the movement response.

The allowable load moment of inertia (J_L) depends on motor capacity, as shown above. This value is provided strictly as a guideline and results may vary depending on servomotor drive conditions.

Use the AC servo drive capacity selection program SigmaJunmaSize+ to check the operation conditions. The program can be downloaded for free from our web site (http://www.e-mechatronics.com/).


An overvoltage alarm (A.400) is likely to occur during deceleration if the load moment of inertia exceeds the allowable load moment of inertia. SERVOPACKs with a built-in regenerative resistor may generate a regenerative overload alarm (A.320). Take one of the following steps if this occurs.

- Reduce the torque limit.
- Reduce the deceleration rate.
- Reduce the maximum speed.
- Install an external regenerative resistor if the alarm cannot be cleared using the steps above. Refer to Regenerative Resistors on page 339.


Mechanical Specifications

●Allowable Loads


The loads applied while a servomotor is running are roughly classified in the following patterns. Design the machine so that the thrust load and moment load will not exceed the values in the table.



Where F is external force,
Thrust load: Fa=F+Load mass
Moment load: M=0



Where F is external force,
Thrust load: Fa=F+Load mass
Moment load: M=F×L



(See the table below for the dimension A of each servomotor model.)

Where F is external force,
Thrust load: Fa=Load mass
Moment load: M=F×(L+A)


Servomotor Model SGMCS-□		02B	05B	07B	04C	10C	14C	08D	17D	25D	16E	35E	45M	80M	1AM	80N	1EN	2ZN
Dimension A	mm	0			0			0			0		33			37.5		
Allowable Thrust Load (Fa)	N	1500			3300			4000			11000		9000			16000		
Allowable Moment Load (M)	N·m	40	50	64	70	75	90	93	103	135	250	320	180			350		

Note: SGMCS-02B to -35E servomotors, set dimensions A to 0 (zero).

●Mechanical Tolerance


The following table shows tolerances for the servomotor's output shaft and installation area.
See the dimensional drawing of the individual servomotor for more details on tolerances.

(1) Small-capacity Series



Tolerance T.I.R. (Total Indicator Reading) Units: mm	Servomotor Model SGMCS-									
	02B	05B	07B	04C	10C	14C	08D	17D	25D	16E	35E
Run-out of the Surface of the Shaft	0.02			0.02			0.02			0.02	
Run-out at the End of the Shaft	0.04			0.04			0.04			0.04	
Perpendicularity between the Flange Face and Output Shaft	0.07			0.07			0.08			0.08	
Coaxiality of Output Axis and Mounting Socket Joint	0.07			0.07			0.08			0.08	


(2) Medium-capacity Series



Tolerance T.I.R. (Total Indicator Reading) Units: mm	Servomotor Model SGMCS-					
	45M	80M	1AM	80N	1EN	2ZN
Run-out of the Surface of the Shaft	0.02			0.02		
Run-out at the End of the Shaft	0.04			0.04		
Perpendicularity between the Flange Face and Output Shaft	–			–		
Coaxiality of Output Axis and Mounting Socket Joint	0.08			0.08		
Right angle between Flange Face and Output Shaft	0.08			0.08		


●Direction of Rotation

Positive rotation of the servomotor is counterclockwise when viewed from the load.



●Impact Resistance


Mount the servomotor with the axis horizontal. The servomotor will withstand the following vertical impacts:
· Impact Acceleration: 490 m/s²
· Number of Impacts: 2



●Vibration Resistance

Mount the servomotor with the axis horizontal. The servomotor will withstand the following vibration acceleration in three directions: Vertical, side to side, and front to back.

Servomotor Type	Vibration Acceleration at Flange
Small-capacity Series	49 m/s²
Medium-capacity Series	24.5 m/s²



●Vibration Class

The vibration class at rated motor speed is V15. (A vibration class of V15 indicates a total vibration amplitude of 15 μm maximum on the servomotor during rated rotation.)

●Enclosure


Servomotor Type	Enclosure
Small-capacity Series	IP42 (except for gaps on the rotating section of the shaft)
Medium-capacity Series	IP44

External Dimensions Units: mm

●Small-capacity Series

(1) Rated Torque 2.0 to 7.0 N·m (Outer Diameter 135 mm Inner Diameter 20 mm)


· Applicable Flange: 1



*1 The shaded section shows the rotating section.
*2 The hatched section shows the non-rotating section.

Model SGMCS-	L	(LL)	Approx. Mass kg
02B□C11	59	51	4.8
05B□C11	88	80	5.8
07B□C11	128	120	8.2

· Applicable Flange: 4




*1 The shaded section shows the rotating section.
*2 The hatched section shows the non-rotating section.

Model SGMCS-	L	(LL)	Approx. Mass kg
02B□C41	59	51	4.8
05B□C41	88	80	5.8
07B□C41	128	120	8.2

●Servomotor Connector for Small-capacity Series Servomotors (Applicable Flange: 1)


Servomotor-end Connector Specifications



Model: JN1AS04MK2
Manufacturer: Japan Aviation Electronics Industry, Ltd.
Applicable plug: JN1DS04FK1
(Provided by the customer.)

1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG (Frame ground)	Green (yellow)

Encoder-end Connector Specifications




Model: JN1AS10ML1
Manufacturer: Japan Aviation Electronics Industry, Ltd.
Applicable plug: JN1DS10SL1
(Provided by the customer.)

1	PS	Light blue	6	–	–
2	/PS	Light blue/ white	7	FG (Frame ground)	Shield
3	–	–	8	–	–
4	PG5V	Red	9	PG0V	Black
5	–	–	10	–	–

External Dimensions Units: mm

(2) Rated Torque 4.0 to 14.0 N·m (Outer Diameter 175 mm Inner Diameter 35 mm)


· Applicable Flange: 1



*1 The shaded section shows the rotating section.
*2 The hatched section shows the non-rotating section.

Model SGMCS-	L	(LL)	Approx. Mass kg
04C□C11	69	59	7.2
10C□C11	90	80	10.2
14C□C11	130	120	14.2

· Applicable Flange: 4




*1 The shaded section shows the rotating section.
*2 The hatched section shows the non-rotating section.

Model SGMCS-	L	(LL)	Approx. Mass kg
04C□C41	69	59	7.2
10C□C41	90	80	10.2
14C□C41	130	120	14.2

● Servomotor Connector (Applicable Flange: 4)


Servomotor-end Connector Specifications



Model
· Plug : 350779-1
· Pin : 350561-3 or 350690-3 (No.1 to 3)
· Ground pin : 350654-1or 350669-1 (No.4)
Manufacturer: Tyco Electronics AMP K.K.
Applicable plug
· Cap : 350780-1
· Socket : 350536-6 or 350550-6

1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG (Frame ground)	Green (yellow)

Encoder-end Connector Specifications




Model : 55102-0600
Manufacturer : Molex Japan Co., Ltd
Applicable plug : 54280-0600

1	PG5V	Red
2	PG0V	Black
3	–	–
4	–	–
5	PS	Light blue
6	/PS	Light blue/ white
Connector Case	FG (Frame ground)	Shield

External Dimensions Units: mm

(3) Rated Torque 8.0 to 25.0 N·m (Outer Diameter 230 mm Inner Diameter 60 mm)


· Applicable Flange: 1



*1 The shaded section shows the rotating section.
*2 The hatched section shows the non-rotating section.

Model SGMCS-	L	(LL)	Approx. Mass kg
08D□C11	74	64	14.0
17D□C11	110	100	22.0
25D□C11	160	150	29.7

· Applicable Flange: 4




*1 The shaded section shows the rotating section.
*2 The hatched section shows the non-rotating section.

Model SGMCS-	L	(LL)	Approx. Mass kg
08D□C41	74	64	14.0
17D□C41	110	100	22.0
25D□C41	160	150	29.7

External Dimensions Units: mm

(4) Rated Torque 16.0 to 35.0 N·m (Outer Diameter 290 mm Inner Diameter 75 mm)


· Applicable Flange: 1



*1 The shaded section shows the rotating section.
*2 The hatched section shows the non-rotating section.

Model SGMCS-	L	(LL)	Approx. Mass kg
16E□B11	88	76	26.0
35E□B11	112	100	34.0

· Applicable Flange: 4



*1 The shaded section shows the rotating section.
*2 The hatched section shows the non-rotating section.


Model SGMCS-	L	(LL)	Approx. Mass kg
16E□B41	88	76	26.0
35E□B41	112	100	34.0

External Dimensions Units: mm

●Medium-capacity Series

(1) Rated Torque 45 to 110 N·m (Outer Diameter 280 mm, Inner Diameter 75 mm)


· Applicable Flange: 1



*: The shaded section shows the rotating section.

Model SGMCS-	LL	KB1	KB2	Approx. Mass kg
45M□A11	141	87.5	122	38
80M□A11	191	137.5	172	45
1AM□A11	241	187.5	222	51

· Applicable Flange: 3




*: The shaded section shows the rotating section.

Model SGMCS-	L	LL	KB1	KB2	Approx. Mass kg
45M□A31	150	135	102.5	137	38
80M□A31	200	185	152.5	187	45
1AM□A31	250	235	202.5	237	51

●Servomotor Connector for Medium-capacity Series Servomotors (Applicable Flange: 1, 3)


Servmotor-end Connector Specifications
(Same for All Medium-capacity Models)



Model : CE05-2A18-10PD
Manufacturer : DDK Ltd.
Applicable plug and cable clamp
Plug : CE05-6A18-10SD-B-BSS
Cable clamp : CE3057-10A-□(D265)

A	Phase U
B	Phase V
C	Phase W
D	FG (Frame ground)

Encoder-end Connector Specifications
(Same for All Medium-capacity Models)




Model : JN1AS10ML1
Manufacturer : Japan Aviation Electronics Industry, Ltd.
Applicable plug : JN1DS10SL1

1	PS	6	–
2	/PS	7	FG (Frame ground)
3	–	8	–
4	PG5V	9	PG0V
5	–	10	–

External Dimensions Units: mm

(2) Rated Torque 80 to 200 N·m (Outer Diameter 360 mm, Inner Diameter 118 mm)


· Applicable Flange: 1



*: The shaded section shows the rotating section.

Model SGMCS-	LL	KB1	KB2	Approx. Mass kg
80N□A11	151	98	132	50
1EN□A11	201	148	182	68
2ZN□A11	251	198	232	86

· Applicable Flange: 3




*: The shaded section shows the rotating section.

Model SGMCS-	L	LL	KB1	KB2	Approx. Mass kg
80N□A31	160	145	113	147	50
1EN□A31	210	195	163	197	68
2ZN□A31	260	245	213	247	86

Selecting Cables

●Cables Connections



●Servomotor Main Circuit Cables

Name		Length (L)	Order No. Standard Type	Order No. Flexible Type*1	Specifications	Details
Small Capacity (02B-35E)	Cable with Loose Wire at SERVOPACK End	3 m	JZSP-CMM60-03-E	JZSP-CSM60-03-E	Applicable Flange*2 : 1 SERVOPACK End 50 mm L Servomotor End M4 Crimped Terminals	(1)
		5 m	JZSP-CMM60-05-E	JZSP-CSM60-05-E		
		10 m	JZSP-CMM60-10-E	JZSP-CSM60-10-E		
		15 m	JZSP-CMM60-15-E	JZSP-CSM60-15-E		
		20 m	JZSP-CMM60-20-E	JZSP-CSM60-20-E		
		3 m	JZSP-CMM00-03-E	JZSP-CMM01-03-E	Applicable Flange*2 : 4 SERVOPACK End 8.5±0.5 (Exposed core wire) 50 L Servomotor End 35 Sheath to Bind Core Wires Heat-shrinkable Tube M4 Crimped Terminals Cable: UL2517 (AWG20×4C) Cap : 350780-1(4-pole) Socket : 350536-6(Chained)	
		5 m	JZSP-CMM00-05-E	JZSP-CMM01-05-E		
		10 m	JZSP-CMM00-10-E	JZSP-CMM01-10-E		
		15 m	JZSP-CMM00-15-E	JZSP-CMM01-15-E		
		20 m	JZSP-CMM00-20-E	JZSP-CMM01-20-E		
	Servomotor-end Connector		JN1DS04FK1		Soldered	(3)
	Cables	5 m	JZSP-CSM90-05-E	JZSP-CSM80-05-E		(4)
		10 m	JZSP-CSM90-10-E	JZSP-CSM80-10-E		
		15 m	JZSP-CSM90-15-E	JZSP-CSM80-15-E		
		20 m	JZSP-CSM90-20-E	JZSP-CSM80-20-E		
		50 m	JZSP-CSM90-50-E	JZSP-CSM80-50-E		
			Value Type	Premium Type*3*		
Medium Capacity (45M, 80M, 80N, 1AM)	Cable with Loose Wire at SERVOPACK End	3 m	B1EV-03(A)-E	B1EP-03(A)-E	L 125 mm	(2)
		5 m	B1EV-05(A)-E	B1EP-05(A)-E		
		10 m	B1EV-10(A)-E	B1EP-10(A)-E		
		15 m	B1EV-15(A)-E	B1EP-15(A)-E		
		20 m	B1EV-20(A)-E	B1EP-20(A)-E		
Medium Capacity (1EN, 2ZN)		3 m	B2EV-03(A)-E	B2EP-03(A)-E		
		5 m	B2EV-05(A)-E	B2EP-05(A)-E		
		10 m	B2EV-10(A)-E	B2EP-10(A)-E		
		15 m	B2EV-15(A)-E	B2EP-15(A)-E		
		20 m	B2EV-20(A)-E	B2EP-20(A)-E		

*1: Use flexible cables for movable sections such as robot arms.
*2: For applicable flanges, see model designations on page 101.
*3 Premium cables are intended for use in applications that require CE. They have a continuous flex rating and are intended for use in movable sections such as robot arms.

NOTES:
Shaded items are non-stock.
SGMCS servomotors with holding brakes are not available.

Selecting Cables

(1) Small Capacity Series: Wiring Specifications for Cables

· Applicable Flange: 1

SERVOPACK End		Servomotor End	
Wire Color	Signal	Signal	Pin No.
Red	Phase U	Phase U	1
White	Phase V	Phase V	2
Blue	Phase W	Phase W	3
Green/(yellow)	FG	FG	4

· Applicable Flange: 4


SERVOPACK End		Servomotor End	
Wire Color	Signal	Signal	Pin No.
Red	Phase U	Phase U	1
White	Phase V	Phase V	2
Blue	Phase W	Phase W	3
Green/(yellow)	FG	FG	4

(2) Medium Capacity Series: Wiring Specifications for Cables


SERVOPACK-end Leads		Servomotor-end Connector	
Wire Label	Signal	Signal	Pin No.
G	FG	FG	D
W	Phase W	Phase W	C
V	Phase V	Phase V	B
U	Phase U	Phase U	A

*For servomotors with holding brakes, the holding brake cable must also be wired.

(3) Small-capacity Series: Servomotor-end Connector Specifications


Items		Specifications
Manufacturer		Tyco Electronics AMP K.K.
Order No.		JZSP-CMM9-3-E
Cap		350780-1
Socket		350550-6
Applicable Wire Size		AWG20 to 14
Crimp Tool	Hand tool	90296-2
	Applicator	687763-2
External Dimensions mm		

(4) Small-capacity Series: Cable Specifications

Items	Standard Type	Flexible Type
Order No.*	JZSP-CSM90-□□-E (50 m max.)	JZSP-CSM80-□□-E (50 m max.)
Specifications	UL2517 (Max. operating temperature: 105°C) AWG20×6C For power line: AWG20 (0.52 mm^2) Outer diameter of insulating sheath: 1.53 dia. mm For holding brake line: AWG20 (0.52 mm^2) Outer diameter of insulating sheath: 1.53 dia.mm	UL2517 (Max. operating temperature: 105°C) AWG22×6C For power line: AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.37 dia. mm For holding brake line: AWG22 (0.33 mm^2) Outer diameter of insulating sheath: 1.37 dia. mm
Finished Dimensions	7±0.3 mm	
Internal Configuration and Lead Color		
Yaskawa Standard Specifications (Standard Length)	Cable length : 5 m, 10 m, 15 m, 20 m, 50 m	


*: Specify the cable length □□ of order no.
Example: JZSP-CSM90-15-E (15 m)

(Medium-capacity Series (SGMCS-□□M and N): Connector Specifications



Servomotor-end Connector (Receptacle)	Cable-end Connector		
	L-shaped Plug	Straight Plug	Cable Clamp
MS3102A18-10P	MS3108B18-10S	MS3106B18-10S	MS3057-10A


· Dimensional Drawings: MS3108B L-shaped Plug Shell



Units: mm

Model No.	Shell Size	Joint Screw A	Length of Joint Portion ±0.12	Overall Length L Max.	Outer Diameter of Joint Nut Q $^{+0}_{-0.38}$	R ±0.5	U ±0.5	Cable Clamp Set Screw V	Effective Screw Length W Min.
MS 3108B	18	1 1/8-18UNEF	18.26	68.27	34.13	20.5	30.2	1-20UNEF	9.53


· Dimensional Drawings: MS3106B Straight Plug Shell



Units: mm

Model No.	Shell Size	Joint Screw A	Length of Joint Portion ±0.12	Overall Length L Max.	Outer Diameter of Joint Nut Q $^{+0}_{-0.38}$	Cable Clamp Set Screw V	Effective Screw Length W Min.	Maximum Width Y Max.
MS 3106B	18	1 1/8-18UNEF	18.26	52.37	34.13	1-20UNEF	9.53	42

· Dimensional Drawings: MS3057-10A Cable Clamp with Rubber Bushing



Units: mm

Model No.	Applicable Connector Shell Size	Overall Length A±0.7	Effective Screw Length C	E	G±0.7	H	J	Set Screw V	Outer Diameter Q±0.7	Attached Bushing
MS3057-10A	18	23.8	10.3	15.9	31.7	3.2	14.3	1-20UNEF	30.1	AN3420-10

Selecting Cables

●Encoder Cables and Connectors (Max. length: 20 m)

Name	Length (L)	Order No.		Specifications	Details
		Standard Type	Flexible Type*1		
Cable with Connectors (For Incremental and Absolute Encoder)	3 m	JZSP-CMP60-03-E	JZSP-CSP60-03-E	Applicable Flange*2: 1, 3 SERVOPACK End L Encoder (Servomotor) End Connector (Crimped) (Molex Japan Co., Ltd.) Straight Plug (Crimped) (Japan Aviation Electronics Industry, Ltd.)	(1)
	5 m	JZSP-CMP60-05-E	JZSP-CSP60-05-E		
	10 m	JZSP-CMP60-10-E	JZSP-CSP60-10-E		
	15 m	JZSP-CMP60-15-E	JZSP-CSP60-15-E		
	20 m	JZSP-CMP60-20-E	JZSP-CSP60-20-E		
	3 m	JZSP-CMP00-03-E	JZSP-CMP10-03-E	Applicable Flange*2 : 4 SERVOPACK End L Encoder End Connector (Molex Japan Co., Ltd.) Socket Connector (Molex Japan Co., Ltd.)	(2)
	5 m	JZSP-CMP00-05-E	JZSP-CMP10-05-E		
	10 m	JZSP-CMP00-10-E	JZSP-CMP10-10-E		
	15 m	JZSP-CMP00-15-E	JZSP-CMP10-15-E		
	20 m	JZSP-CMP00-20-E	JZSP-CMP10-20-E		
Cable with Loose Wire at Encoder End (For Incremental and Absolute Encoder)	3 m	JZSP-CMP03-03-E	JZSP-CMP13-03-E	SERVOPACK End L Encoder End 60 mm 1 2 3 4 5 6 Connector (Crimped) (Molex Japan Co., Ltd.) Wire Markers	(3)
	5 m	JZSP-CMP03-05-E	JZSP-CMP13-05-E		
	10 m	JZSP-CMP03-10-E	JZSP-CMP13-10-E		
	15 m	JZSP-CMP03-15-E	JZSP-CMP13-15-E		
	20 m	JZSP-CMP03-20-E	JZSP-CMP13-20-E		
SERVOPACK-end Connector Kit		JZSP-CMP9-1-E		Soldered (Molex Japan Co., Ltd.)	(4)
Encoder-end Connector (Straight Plug)		JN1DS10SL1		Crimping Type (A crimp tool is required.) (Japan Aviation Electronics Industry, Ltd.)	
Encoder-end Connector (Socket Contact)		JN1-22-22S-PKG100			
Cables	5 m	JZSP-CMP09-05-E	JZSP-CSP39-05-E		(5)
	10 m	JZSP-CMP09-10-E	JZSP-CSP39-10-E		
	15 m	JZSP-CMP09-15-E	JZSP-CSP39-15-E		
	20 m	JZSP-CMP09-20-E	JZSP-CSP39-20-E		

*1: Use flexible cables for movable sections such as robot arms.
*2: For applicable flanges, see model designations on page 101.

NOTE: Shaded items are non-stock.

(1) Wiring Specifications for Cable with Connectors

· Applicable Flange: 1, 3

(Standard type)

SERVOPACK End			Encoder (Servomotor) End	
Pin No.	Signal		Pin No.	Wire Color
1	PG5V		4	Red
2	PG0V		9	Black
5	PS		1	Light blue
6	/PS		2	Light blue/white
Shell	FG	Shield Wire	7	FG Shield wire

(Flexible type)

SERVOPACK End			Encoder End	
Pin No.	Signal		Pin No.	Wire Color
1	PG5V		4	Orange
2	PG0V		9	Green
5	PS		1	Black/light blue
6	/PS		2	Red/light blue
Shell	FG	Shield Wire	7	FG Shield wire

Note: Be sure to connect the shield wire of encoder cable to the connector case (shell).

(2) Wiring Specifications for Cable with Connectors

· Applicable Flange: 4

(Standard type)

SERVOPACK End			Encoder (Servomotor) End	
Pin No.	Signal		Pin No.	Wire Color
1	PG5V		1	Red
2	PG0V		2	Black
5	PS		5	Light blue
6	/PS		6	Light blue/white
Shell	FG	Shield Wire	7	FG Shield wire

(Flexible type)

SERVOPACK End			Encoder End	
Pin No.	Signal		Pin No.	Wire Color
1	PG5V		1	Orange
2	PG0V		2	Green
5	PS		5	Red/light blue
6	/PS		6	Black/light blue
Shell	FG	Shield Wire	7	FG Shield wire

Note: Be sure to connect the shield wire of encoder cable to the connector case (shell).

(3) Wiring Specifications for Cable with Loose Wire at Encoder End

(Standard type)

SERVOPACK End

Pin No.	Signal
6	/PS
5	PS
4	BAT(−)
3	BAT(+)
2	PG0V
1	PG5V
Shell	FG

Encoder (Servomotor) End

Wire Color	Marker
Light blue/white	6
Light blue	5
Orange/white	4
Orange	3
Black	2
Red	1

Shield Wire

(Flexible type)

SERVOPACK End

Pin No.	Signal
1	PG5V
2	PG0V
3	BAT(+)
4	BAT(−)
5	PS
6	/PS
Shell	FG



Encoder (Servomotor) End

Wire Color	Marker
Orange	1
Green	2
Red/pink	3
Black/pink	4
Red/light blue	5
Black/light blue	6



Shield Wire

Notes: 1 The signals BAT (+) and BAT (-) are not needed when using single turn absolute feedback.
2 Be sure to connect the shield wire of encoder cable to the connector case (shell).

(4) SERVOPACK-end Connector Specifications

Items	SERVOPACK End	Encoder End
Order No.	JZSP-CMP9-1-E	Tools are not included.
Manufacturer	Molex Japan Co., Ltd.	Japan Aviation Electronics Industry, Ltd.
Connector	55100-0670 (soldered) Note: 55100-0670 (soldered) when using a connector kit	Straight plug: JN1DS10SL1 (crimped) Socket contact type: JN1-22-22S-PKG100 Outer diameter of applicable cable : 5.7 dia. to 7.3 dia. mm Applicable wire size: AWG21 to 25 Outer diameter of insulating sheath: 0.8 dia. to 1.5 dia. mm Crimp tool (hand tool) model: CT150-2-JN
External Dimensions (Units: mm)		



(5) Cable Specifications

Items	Standard Type	Flexible Type
Order No.*	JZSP-CMP09-□□-E	JZSP-CSP39-□□-E
Cable Length	20 m max.	
Specifications	UL20276 (Rated temperature: 80°C) AWG22×2C+AWG24×2P AWG22 (0.33 mm²) Outer diameter of insulating sheath: 1.15 dia. mm AWG24 (0.20 mm²) Outer diameter of insulating sheath: 1.09 dia. mm	UL20276 (Rated temperature: 80°C) AWG22×2C+AWG24×2P AWG22 (0.33 mm²) Outer diameter of insulating sheath: 1.35 dia. mm AWG24 (0.20 mm²) Outer diameter of insulating sheath: 1.21 dia. mm
Finished Dimensions	6.5 dia. mm	6.8 dia. mm
Internal Configuration and Lead Colors		
Yaskawa Standard Specifications (Standard Length)	Cable length: 5 m, 10 m, 15 m, 20 m	

* Specify the cable length in □□ of order no.
Example: JZSP-CMP09-05-E (5 m)

Selecting Cables

●Relay Encoder Cables (For extending from 30 to 50 m)

Name	Length	Order No. Standard Type	Specifications	Details
Encoder-end Cables (For incremental and absolute encoder)	0.3 m	JZSP-CSP15-E		(1)
Cable with Connectors (For incremental and absolute encoder)	30 m	JZSP-UCMP00-30-E		(2)
	40 m	JZSP-UCMP00-40-E		
	50 m	JZSP-UCMP00-50-E		
Cables	30 m	JZSP-CMP19-30-E		(3)
	40 m	JZSP-CMP19-40-E		
	50 m	JZSP-CMP19-50-E		

(1) Wiring Specifications for Encoder-end Cable

SERVOPACK End

Pin No.	Signal
1	PG 5V
2	PG 0V
5	PS
6	/PS
Shell	FG

Encoder (Servomotor) End

Pin No.	Wire Color
4	Red
9	Black
1	Light blue
2	Light blue/white
7	FG Shield wire

Shield Wire

Note: Be sure to connect the shield wire of encoder cable to the connector case (shell).

(2) Wiring Specifications for Cable with Connectors

SERVOPACK End


Pin No.	Signal
6	/PS
5	PS
4	BAT (–)
3	BAT (+)
2	PG 0V
1	PG 5V
Shell	FG

Encoder (Servomotor) End

Pin No.	Wire Color
6	Light blue/white
5	Light blue
4	Orange/white
3	Orange
2	Black
1	Red
Shell	FG

Shield Wire

(3) Cable Specifications


Items	Standard Type
Order No.*	JZSP-CMP19-□□-E
Cable Length	50 m max.
Specifications	UL20276 (Rated temperature: 80˚C) AWG16×2C+AWG26×2P AWG16 (1.31 mm^2) Outer diameter of insulating sheath: 2.0 dia.mm AWG26 (0.13 mm^2) Outer diameter of insulating sheath: 0.91 dia. mm
Finished Dimensions	6.8 dia. mm
Internal Configuration and Lead Colors	
Yaskawa Standard Specifications (Standard Length)	Cable length: 30 m, 40 m, 50 m

* Specify the cable length in □□ of order no.
Example: JZSP-CMP19-30-E (30 m)

Linear Servomotors

SGLGW

(Coreless Type)



efesotomasyon.com

Model Designations

● Moving Coil

SGL G W - 30 A 050 C P □

Linear Σ Series
Linear Servomotor

Servomotor Type

Code	Specifications
G	Coreless

W : Moving Coil

Magnet Height

Voltage
A: 200 VAC

Length of Moving Coil

Design Revision Order
A, B, C...

Connector for Main Circuit Cable

Code	Specifications	Applicable Model
Blank	Connector by Tyco Electronics AMP K.K.	All models
D	Connector by Interconnectron GmbH	SGLGW -30A, -40A, -60A

Hall Sensor/Cooling Method

Code	Specifications	Applicable Model
P	With hall sensor	All models
C	Forced cooling	SGLGW-40A, -60A, -90A
H	With hall sensor and forced cooling	
Blank	Without hall sensor	All models

● Magnetic Way

SGL G M - 30 108 A □

Linear Σ Series
Linear Servomotor

Servomotor Type

Code	Specifications
G	Coreless

M: Magnetic Way

Magnet Height

Length of Magnetic Way

Options

Code	Specifications	Applicable Model
Blank	(standard)	All models
-M	High force	SGLGM-40, -60

Design Revision Order
A, B, C*...

*: The coreless linear servomotor has revision CT.
C = without mounting holes on the bottom
CT = with mounting holes on the bottom

NOTE: Shaded items are non-stock.

- Direct-feed mechanism for high-speed and high-precision positioning.
- Lack of magnetic attraction force helps extend the life of linear motion guides and minimizes noise.
- Zero cogging for minimal force ripple.


- Feeders and loaders
- Semiconductor equipment
- LCD manufacturing equipment

● Precautions on Moving Coil with Hall Sensor


When using a moving coil with a hall sensor, the magnetic way must completely cover the bottom of the hall sensor. Refer to the example showing the correct installation.

When determining the length of the moving coil's stroke or the length of the magnetic way, consider the total length of the moving coil and the hall sensor unit. Refer to the following table.


<Correct>



<Incorrect>



The total length of moving coil with hall sensor



Moving Coil Model SGLGW-	Length of Moving Coil L1 (mm)	Length of Hall Sensor Unit A (mm)	Total Length L (mm)
30A050□P□	50	0 (Included in the length of moving coil)	50
30A080□P□	80		80
40A140□P□	140	16	156
40A253□P□	252.5		268.5
40A365□P□	365		381
60A140□P□	140	16	156
60A253□P□	252.5		268.5
60A365□P□	365		381
90A200□P□	199	0 (Included in the length of moving coil)	199
90A370□P□	367		367
90A535□P□	535		535

Ratings and Specifications

Time Rating: Continuous
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40˚C
Excitation: Permanent magnet
Withstand Voltage: 1500 VAC for one minute

Enclosure: Self-cooled, air-cooling (Only self-cooled type available for SGLGW-30A linear servomotor)
Ambient Humidity: 20% to 80% (no condensation)
Allowable Winding Temperature: 130˚C (Thermal class B)

●With Standard-force Magnetic Ways

Linear Servomotor Model SGLGW-		30A		40A			60A			90A		
		050C	080C	140C	253C	365C	140C	253C	365C	200C	370C	535C
Peak Speed*	m/s	5	5	5	5	5	4.8	4.8	4.8	4	4	4
Rated Force*	N	12.5	25	47	93	140	70	140	210	325	550	750
Rated Current*	A_{rms}	0.51	0.79	0.8	1.6	2.4	1.2	2.2	3.3	4.4	7.5	10.2
Peak Force*	N	40	80	140	280	420	220	440	660	1300	2200	3000
Peak Current*	A_{rms}	1.62	2.53	2.4	4.9	7.3	3.5	7.0	10.5	17.6	30.0	40.8
Moving Coil Mass	kg	0.10	0.15	0.34	0.60	0.87	0.42	0.76	1.10	2.15	3.6	4.9
Force Constant	N/A_{rms}	26.4	33.9	61.5	61.5	61.5	66.6	66.6	66.6	78.0	78.0	78.0
BEMF Constant	V/(m/s)	8.8	11.3	20.5	20.5	20.5	22.2	22.2	22.2	26.0	26.0	26.0
Motor Constant	$N/\sqrt{W}$	3.7	5.6	7.8	11.0	13.5	11.1	15.7	19.2	26.0	36.8	45.0
Electrical Time Constant	ms	0.2	0.4	0.4	0.4	0.4	0.5	0.5	0.5	1.4	1.4	1.4
Mechanical Time Constant	ms	7.30	4.78	5.59	4.96	4.77	3.41	3.08	2.98	3.18	2.66	2.42
Thermal Resistance (With heat sink)	K/W	5.19	3.11	1.67	0.87	0.58	1.56	0.77	0.51	0.39	0.26	0.22
Thermal Resistance (Without heat sink)	K/W	8.13	6.32	3.02	1.80	1.23	2.59	1.48	1.15	1.09	0.63	0.47
Magnetic Attraction	N	0	0	0	0	0	0	0	0	0	0	0
Applicable SERVOPACK	SGDV	R70A	R90A	R90A	1R6A	2R8A	1R6A	2R8A	5R5A	120A	180A	200A

Notes: 1 The items marked with an * and Force and Speed Characteristics (the table on the next page) are the values at a motor winding temperature of 100˚C during operation in combination with a SERVOPACK. The others are at 20˚C.


2 The above specifications show the values under the cooling condition when a heat sink (aluminium board) listed in the following table is mounted on the moving coil.

Heat Sink Size
200 mm × 300 mm × 12 mm : SGLGW-30A050C, -30A080C, -40A140C, -60A140C
300 mm × 400 mm × 12 mm : SGLGW-40A253C, -60A253C
400 mm × 500 mm × 12 mm : SGLGW-40A365C, -60A365C
800 mm × 900 mm × 12 mm : SGLGW-90A200C, -90A370C, -90A535C


Ratings and Specifications

●Force and Speed Characteristics A : Continuous Duty Zone B : Intermittent Duty Zone


SGLGW-30A050C




SGLGW-30A080C




SGLGW-40A140C




SGLGW-40A253C




SGLGW-40A365C




SGLGW-60A140C




SGLGW-60A253C




SGLGW-60A365C




SGLGW-90A200C



SGLGW-90A370C



SGLGW-90A535C



Notes:
1. When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.
2. The solid, dotted, and dashed-dotted lines of the intermittent duty zone indicate the characteristics when a servomotor runs with the following combinations:
   · The solid line: With a three-phase 200 V or a single-phase 230 V SERVOPACK
   · The dotted line: With a single-phase 200 V SERVOPACK
   · The dashed-dotted line: With a single-phase 100 V SERVOPACK

●With High-force Magnetic Ways

Linear Servomotor Model SGLGW-		40A			60A		
		140C	253C	365C	140C	253C	365C
Peak Speed*	m/s	4.2	4.2	4.2	4.2	4.2	4.2
Rated Force*	N	57	114	171	85	170	255
Rated Current*	A_{rms}	0.8	1.6	2.4	1.2	2.2	3.3
Peak Force*	N	230	460	690	360	720	1080
Peak Current*	A_{rms}	3.2	6.5	9.7	5.0	10.0	14.9
Moving Coil Mass	kg	0.34	0.60	0.87	0.42	0.76	1.10
Force Constant	N/A_{rms}	76.0	76.0	76.0	77.4	77.4	77.4
BEMF Constant	V/(m/s)	25.3	25.3	25.3	25.8	25.8	25.8
Motor Constant	$N/\sqrt{W}$	9.6	13.6	16.7	12.9	18.2	22.3
Electrical Time Constant	ms	0.4	0.4	0.4	0.5	0.5	0.5
Mechanical Time Constant	ms	3.69	3.24	3.12	2.52	2.29	2.21
Thermal Resistance (With heat sink)	K/W	1.67	0.87	0.58	1.56	0.77	0.51
Thermal Resistance (Without heat sink)	K/W	3.02	1.80	1.23	2.59	1.48	1.15
Magnetic Attraction	N	0	0	0	0	0	0
Applicable SERVOPACK	SGDV	1R6A	2R8A	3R8A	1R6A	3R8A	7R6A


Notes: 1 The items marked with an * and Force and Speed Characteristics (the table on the next page) are the values at a motor winding temperature of 100˚C during operation in combination with a SERVOPACK. The others are at 20˚C.

2 The above specifications show the values under the cooling condition when a heat sink (aluminium board) listed in the following table is mounted on the moving coil.

Heat Sink Size
200 mm × 300 mm × 12 mm : SGLGW-40A140C, -60A140C
300 mm × 400 mm × 12 mm : SGLGW-40A253C, -60A253C
400 mm × 500 mm × 12 mm : SGLGW-40A365C, -60A365C

Ratings and Specifications

●Force and Speed Characteristics A : Continuous Duty Zone B : Intermittent Duty Zone



Notes:
1. When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.
2. The solid, dotted, and dashed-dotted lines of the intermittent duty zone indicate the characteristics when a servomotor runs with the following combinations:
   · The solid line: With a three-phase 200 V or a single-phase 230 V SERVOPACK
   · The dotted line: With a single-phase 200 V SERVOPACK
   · The dashed-dotted line: With a single-phase 100 V SERVOPACK

●Mechanical Specifications

(1) Impact Resistance
- Impact acceleration: 196 m/s^2
- Impact occurrences: twice


(2) Vibration Resistance

The linear servomotors will withstand the following vibration acceleration in three directions: Vertical, side to side, and front to back.
- Vibration acceleration: 49 m/s^2


External Dimensions Units: mm

(1) SGLGW-30

● Moving Coil: SGLGW-30A□□□C□ (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor
Connector Specifications




Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector
: 17JE-13090-02 (D8C)
Stud : 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Plug : 350779-1
Pin : 350924-1 or
770672-1
by Tyco Electronics AMP K.K.


The Mating Connector

Cap : 350780-1
Socket : 350925-1 or
770673-1

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG	Green

Hall Sensor Output Signals

When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLGW-	L1	L2	L3	L4	L5	G (Gap)	Approx. Mass* kg
30A050C□	50	48	30	20	20	0.85	0.14
30A080C□	80	72	50	30	25	0.95	0.19


*: The values indicate the mass of moving coil with a hall sensor unit.

External Dimensions Units: mm

● Moving Coil: SGLGW-30A□□□C□D (With a connector by Interconnectron GmbH)



Hall Sensor
Connector Specifications




Pin Connector :
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector
Socket Connector :
17JE-13090-02 (D8C)
Stud : 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications




Extension: SROC06JMSCN169
Pin : 021.423.1020
by Interconnectron GmbH

The Mating Connector
Plug : SPUC06KFSDN236
Socket: 020.030.1020

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	Not used	–
5	Not used	–
6	FG	Green

Hall Sensor Output Signals
When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLGW-	L1	L2	L3	L4	L5	G (Gap)	Approx. Mass* kg
30A050C□D	50	48	30	20	20	0.85	0.14
30A080C□D	80	72	50	30	25	0.95	0.19

*: The values indicate the mass of moving coil with a hall sensor unit.

External Dimensions Units: mm

- Magnetic Way: SGLGM-30□□□A




Magnetic Way Model SGLGM-	L1	L2	N	Approx. Mass kg
30108A	108	54	2	0.6
30216A	216	162	4	1.1
30432A	432	378	8	2.3

Note: If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.


External Dimensions Units: mm

(2) SGLGW-40

● Moving Coil: SGLGW-40A□□□C□ (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor
Connector Specifications




Pin Connector :
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector :
17JE-13090-02 (D8C)
Stud : 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Plug : 350779-1
Pin : 350561-3 or
350690-3 (No.1 to 3)
350654-1
350669-1 (No.4)
by Tyco Electronics AMP K.K.


The Mating Connector

Cap : 350780-1
Socket : 350570-3 or
350689-3

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG	Green

Hall Sensor Output Signals

When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLGW-	L1	L2	L3	L4	L5	L6	N1	N2	Approx. Mass* kg
40A140C□	140	125	90	30	52.5	45	3	4	0.40
40A253C□	252.5	237.5	180	37.5	60	135	5	8	0.66
40A365C□	365	350	315	30	52.5	270	8	14	0.93


*: The values indicate the mass of moving coil with a hall sensor unit.

External Dimensions Units: mm

● Moving Coil: SGLGW-40A□□□C□D (With a connector by Interconnectron GmbH)



Hall Sensor
Connector Specifications




Pin Connector :
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector
Socket Connector :
17JE-13090-02 (D8C)
Stud : 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications




Extension: SROC06JMSCN169
Pin : 021.423.1020
by Interconnectron GmbH

The Mating Connector
Plug : SPUC06KFSDN236
Socket: 020.030.1020

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	Not used	–
5	Not used	–
6	FG	Green

Hall Sensor Output Signals
When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLGW-	L1	L2	L3	L4	L5	L6	N1	N2	Approx. Mass* kg
40A140C□D	140	125	90	30	52.5	45	3	4	0.40
40A253C□D	252.5	237.5	180	37.5	60	135	5	8	0.66
40A365C□D	365	350	315	30	52.5	270	8	14	0.93

*: The values indicate the mass of moving coil with a hall sensor unit.

External Dimensions Units: mm


● Magnetic Way : SGLGM-40□□□C (Without mounting holes on the bottom)
SGLGM-40□□□CT (With mounting holes on the bottom)



Type	Standard-force Magnetic Way Model SGLGM-	L1	L2	N	Approx. Mass kg
Standard Force	40090C or 40090CT	90	45	2	0.8
	40225C or 40225CT	225	180	5	2.0
	40360C or 40360CT	360	315	8	3.1
	40405C or 40405CT	405	360	9	3.5
	40450C or 40450CT	450	405	10	3.9

Note: If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.

● High-force Magnetic Way : SGLGM-40□□□C-M (Without mounting holes on the bottom)
SGLGM-40□□□CT-M (With mounting holes on the bottom)




Type	High-force Magnetic Way Model SGLGM-	L1	L2	N	Approx. Mass kg
High Force	40090C-M or 40090CT-M	90	45	2	1.0
	40225C-M or 40225CT-M	225	180	5	2.6
	40360C-M or 40360CT-M	360	315	8	4.1
	40405C-M or 40405CT-M	405	360	9	4.6
	40450C-M or 40450CT-M	450	405	10	5.1

Note: If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.


External Dimensions Units: mm

(3) SGLGW-60

● Moving Coil: SGLGW-60A□□□C□ (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor
Connector Specifications




Pin Connector :
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector :
17JE-13090-02 (D8C)
Stud : 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Plug : 350779-1
Pin : 350561-3 or
350690-3 (No.1 to 3)
350654-1
350669-1 (No.4)
by Tyco Electronics AMP K.K.


The Mating Connector

Cap : 350780-1
Socket : 350570-3 or
350689-3

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG	Green

Hall Sensor Output Signals

When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLGW-	L1	L2	L3	L4	L5	L6	N1	N2	Approx. Mass* kg
60A140C□	140	125	90	30	52.5	45	3	4	0.48
60A253C□	252.5	237.5	180	37.5	60	135	5	8	0.82
60A365C□	365	350	315	30	52.5	270	8	14	1.16


*: The values indicate the mass of moving coil with a hall sensor unit.

External Dimensions Units: mm

● Moving Coil: SGLGW-60A□□□C□D (With a connector by Interconnectron GmbH)



Hall Sensor
Connector Specifications




Pin Connector :
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector
Socket Connector :
17JE-13090-02 (D8C)
Stud : 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications




Extension: SROC06JMSCN169
Pin : 021.423.1020
by Interconnectron GmbH

The Mating Connector
Plug : SPUC06KFSDN236
Socket: 020.030.1020

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	Not used	–
5	Not used	–
6	FG	Green

Hall Sensor Output Signals

When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLGW-	L1	L2	L3	L4	L5	L6	N1	N2	Approx. Mass* kg
60A140C□D	140	125	90	30	52.5	45	3	4	0.48
60A253C□D	252.5	237.5	180	37.5	60	135	5	8	0.82
60A365C□D	365	350	315	30	52.5	270	8	14	1.16

*: The values indicate the mass of moving coil with a hall sensor unit.

External Dimensions Units: mm


● Magnetic Way : SGLGM-60□□□C (Without mounting holes on the bottom)
SGLGM-60□□□CT (With mounting holes on the bottom)



Type	Standard-force Magnetic Way Model SGLGM-	L1	L2	N	Approx. Mass kg
Standard Force	60090C or 60090CT	90	45	2	1.1
	60225C or 60225CT	225	180	5	2.6
	60360C or 60360CT	360	315	8	4.1
	60405C or 60405CT	405	360	9	4.6
	60450C or 60450CT	450	405	10	5.1

Note: If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.

● High-force Magnetic Way : SGLGM-60□□□C-M (Without mounting holes on the bottom)
SGLGM-60□□□CT-M (With mounting holes on the bottom)




Type	High-force Magnetic Way Model SGLGM-	L1	L2	N	Approx. Mass kg
High Force	60090C-M or 60090CT-M	90	45	2	1.3
	60225C-M or 60225CT-M	225	180	5	3.3
	60360C-M or 60360CT-M	360	315	8	5.2
	60405C-M or 60405CT-M	405	360	9	5.9
	60450C-M or 60450CT-M	450	405	10	6.6

Note: If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.


External Dimensions Units: mm

(4) SGLGW-90

● Moving Coil: SGLGW-90A□□□C□ (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor
Connector Specifications




Pin Connector :
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector :
17JE-13090-02 (D8C)
Stud : 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Plug : 350779-1
Pin : 350218-3 or
350547-3 (No.1 or 3)
350654-1
350669-1 (No.4)
by Tyco Electronics AMP K.K.


The Mating Connector

Cap : 350780-1
Socket : 350536-3 or
350550-3

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG	Green

Hall Sensor Output Signals

When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLGW-	L1	L2	L3	L4	L5	L6	N1	N2	Approx. Mass* kg
90A200C□	199	189	130	40	60	95	3	4	2.2
90A370C□	367	357	260	40	55	285	5	8	3.65
90A535C□	535	525	455	40	60	380	8	10	4.95

*: The values indicate the mass of moving coil with a hall sensor unit.

External Dimensions Units: mm

- Magnetic Way: SGLGM-90□□□A




Magnetic Way SGLGM-	L1	L2	N	Approx. Mass kg
90252A	252	189	4	7.3
90504A	504	441	8	14.7

Note: If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.

Selecting Cables

●Cables Connections



●Cables

Name	Applicable Linear Servomotor Model	Length	Order No.	Specifications	Details
① Linear Servomotor Main Circuit Cables	SGLGW-30,-40,-60	1 m	JZSP-CLN11-01-E	SERVOPACK End / Linear Servomotor End *1	(1)
		3 m	JZSP-CLN11-03-E		
		5 m	JZSP-CLN11-05-E		
		10 m	JZSP-CLN11-10-E		
		15 m	JZSP-CLN11-15-E		
		20 m	JZSP-CLN11-20-E		
	SGLGW-90	1 m	JZSP-CLN21-01-E	SERVOPACK End / Linear Servomotor End *1	(2)
		3 m	JZSP-CLN21-03-E		
		5 m	JZSP-CLN21-05-E		
		10 m	JZSP-CLN21-10-E		
		15 m	JZSP-CLN21-15-E		
		20 m	JZSP-CLN21-20-E		
	SGLGW -30□□□□□□D -40□□□□□□D -60□□□□□□D	1 m	JZSP-CLN14-01-E	SERVOPACK End / Linear Servomotor End *2	(3)
		3 m	JZSP-CLN14-03-E		
		5 m	JZSP-CLN14-05-E		
		10 m	JZSP-CLN14-10-E		
		15 m	JZSP-CLN14-15-E		
		20 m	JZSP-CLN14-20-E		

*1: Connector by Tyco Electronics AMP K.K.
*2: Connector by Interconnectron GmbH

(Cont'd)

NOTE: Shaded items are non-stock.

Selecting Cables


●Cables

Name	Applicable Linear Servomotor Model	Length	Order No.	Specifications	Details
② Cables for Connecting Linear Scales*	All models	1 m	JZSP-CLL00-01-E	Serial Converter Unit End — Linear Scale End	(4)
		3 m	JZSP-CLL00-03-E		
		5 m	JZSP-CLL00-05-E		
		10 m	JZSP-CLL00-10-E		
		15 m	JZSP-CLL00-15-E		
③ Cables for Connecting Serial Converter Units	All models	1 m	JZSP-CLP70-01-E	SERVOPACK End — Serial Converter Unit End	(5)
		3 m	JZSP-CLP70-03-E		
		5 m	JZSP-CLP70-05-E		
		10 m	JZSP-CLP70-10-E		
		15 m	JZSP-CLP70-15-E		
		20 m	JZSP-CLP70-20-E		
④ Cables for Connecting Hall Sensors	All models	1 m	JZSP-CLL10-01-E	Serial Converter Unit End — Hall Sensor Unit End	(6)
		3 m	JZSP-CLL10-03-E		
		5 m	JZSP-CLL10-05-E		
		10 m	JZSP-CLL10-10-E		
		15 m	JZSP-CLL10-15-E		

* When using the serial converter unit, JZDP-G00□-□□□-E, the maximum cable length is 3 m.

(1) Linear Servomotor Main Circuit Cables: JZSP-CLN11-□□-E

· Wiring Specifications



SERVOPACK-end Leads


Wire Color	Signal
Red	Phase U
White	Phase V
Blue	Phase W
Green/yellow	FG

Linear Servomotor-end Connector

Signal	Pin. No.
Phase U	1
Phase V	2
Phase W	3
FG	4

(2) Linear Servomotor Main Circuit Cables: JZSP-CLN21-□□-E

· Wiring Specifications



SERVOPACK-end Leads


Wire Color	Signal
Red	Phase U
White	Phase V
Blue	Phase W
Green/yellow	FG

Linear Servomotor-end Connector

Signal	Pin. No.
Phase U	1
Phase V	2
Phase W	3
FG	4

(3) Linear Servomotor Main Circuit Cables: JZSP-CLN14-□□-E

· Wiring Specifications



SERVOPACK-end Leads


Wire Color	Signal
Black (White 1)	Phase U
Black (White 2)	Phase V
Black (White 3)	Phase W
Green/yellow	FG

Linear Servomotor-end Connector

Signal	Pin No.
Phase U	1
Phase V	2
Phase W	3
—	4
—	5
FG	6

Selecting Cables


(4) Cables for Connecting Linear Scales: JZSP-CLL00-□□-E



· Wiring Specifications

Serial Converter Unit End		Linear Scale End	
Pin No.	Signal	Pin No.	Signal
1	/Cos (V1–)	1	/Cos (V1–)
2	/Sin (V2–)	2	/Sin (V2–)
3	Ref (V0+)	3	Ref (V0+)
4	+5V	4	+5V
5	5Vs	5	5Vs
6	BID	6	BID
7	Vx	7	Vx
8	Vq	8	Vq
9	Cos (V1+)	9	Cos (V1+)
10	Sin (V2+)	10	Sin (V2+)
11	/Ref (V0+)	11	/Ref (V0–)
12	0V	12	0V
13	0Vs	13	0Vs
14	DIR	14	DIR
15	Inner	15	Inner
Case	Shield	Case	Shield


(5) Cables for Connecting Serial Converter Units: JZSP-CLP70-□□-E



· Wiring Specifications

SERVOPACK End			Serial Converter Unit End		
Pin No.	Signal	Wire Color	Pin No.	Signal	Wire Color
1	PG5V	Red	1	+5V	Red
2	PG0V	Black	5	0V	Black
3	–	–	3	–	–
4	–	–	4	–	–
5	PS	Light blue	2	Phase S output	Light blue
6	/PS	Light blue/white	6	Phase /S output	Light blue/white
Shell	Shield	–	Case	Shield	–
			7	–	–
			8	–	–
			9	–	–

(6) Cables for Connecting Hall Sensors: JZSP-CLL10-□□-E




· Wiring Specifications

Serial Converter Unit End		Hall Sensor End	
Pin No.	Signal	Pin No.	Signal
1	+5V	1	+5V
2	Phase U input	2	Phase U input
3	Phase V input	3	Phase V input
4	Phase W input	4	Phase W input
5	0V	5	0V
6	–	6	–
7	–	7	–
8	–	8	–
9	–	9	–
Case	Shield	Case	Shield

Linear Servomotors

SGLFW

(With F-type iron core)



Model Designations

● Moving Coil

SGL F W - 20 A 090 A P □

Linear Σ Series
Linear Servomotor

Servomotor Type

Code	Specifications
F	F-type iron core

W: Moving Coil

Magnet Height

Voltage
A: 200 VAC
D: 400 VAC

Length of Moving Coil

Design Revision Order
A, B, ...

Hall Sensor

Code	Specifications
P	With hall sensor
Blank	Without hall sensor

Connector for Main Circuit Cable

Code	Specifications	Applicable Model
Blank	Connector by Tyco Electronics AMP K.K.	All models
D	Connector by Interconnectron GmbH	SGLFW-35, -50, -1Z□200B, -1ZD380B

◦Magnetic Way

SGL F M - 20 324 A □

Linear Σ Series
Linear Servomotor

Servomotor Type

Code	Specifications
F	F-type iron core

M: Magnetic Way

Magnet Height

Length of Magnetic Way

Design Revision Order
A, B, ...

Options

Code	Specifications
Blank	Standard
C	With magnet cover

NOTE: Shaded items are non-stock.

Features

- Direct-feed mechanism for high-speed and high-precision positioning.
- The magnetic attraction force between the moving and stationary members can be used effectively to increase the rigidity of the linear guidance by preloading the linear motion bearings.
- The magnetic preloading on certain types of compliant linear motion bearings can help increase the system's frequency response, improving its deceleration and settling performances.

Application Examples


- Feeders and loaders
- Semiconductor equipment
- LCD manufacturing equipment

Precautions on Moving Coil with Hall Sensor


When using a moving coil with a hall sensor, the magnetic way must completely cover the bottom of the hall sensor. Refer to the example showing the correct installation.

When determining the length of the moving coil's stroke or the length of the magnetic way, consider the total length of the moving coil and the hall sensor unit. Refer to the following table.


<Correct>



<Incorrect>



The total length of moving coil with hall sensor



Moving Coil Model SGLFW-	Length of Moving Coil L1 (mm)	Length of Hall Sensor Unit A (mm)	Total Length L (mm)
20A090AP□	91	22	113
20A120AP□	127		149
35□120AP□	127	22	149
35□230AP□	235		257
50□200□P□	215	22	237
50□380□P□	395		417
1Z□200□P□	215	22	237
1Z□380□P□	395		417

Ratings and Specifications

Time Rating: Continuous
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40˚C
Excitation: Permanent magnet
Withstand Voltage: 1500 VAC for one minute
Enclosure: Self-cooled
Ambient Humidity: 20% to 80% (no condensation)
Allowable Winding Temperature: 130˚C (Thermal class B)

200-V Class

Linear Servomotor Model		20A		35A		50A		1ZA	
SGLFW-□		090A	120A	120A	230A	200B	380B	200B	380B
Peak Speed	m/s	5.0	5.0	5.0	5.0	5.0	5.0	4.9	4.9
Rated Force*	N	25	40	80	160	280	560	560	1120
Rated Current*	A_{rms}	0.70	0.80	1.4	2.8	5.0	10.0	8.7	17.5
Peak Force*	N	86	125	220	440	600	1200	1200	2400
Peak Current*	A_{rms}	3.0	2.9	4.4	8.8	12.4	25.0	21.6	43.6
Moving Coil Mass	kg	0.7	0.9	1.3	2.3	3.5	6.9	6.4	11.5
Force Constant	N/A_{rms}	36.0	54.0	62.4	62.4	60.2	60.2	69.0	69.0
BEMF Constant	V/(m/s)	12.0	18.0	20.8	20.8	20.1	20.1	23.0	23.0
Motor Constant	$N/\sqrt{W}$	7.9	9.8	14.4	20.4	34.3	48.5	52.4	74.0
Electrical Time Constant	ms	3.2	3.3	3.6	3.6	15.9	15.8	18.3	18.3
Mechanical Time Constant	ms	11.0	9.3	6.2	5.5	3.0	2.9	2.3	2.1
Thermal Resistance (With Heat Sink)	K/W	4.35	3.19	1.57	0.96	0.56	0.38	0.47	0.2
Thermal Resistance (Without Heat Sink)	K/W	7.69	5.02	4.10	1.94	1.65	0.95	1.3	0.73
Magnetic Attraction	N	314	462	809	1590	1650	3260	3300	6520
Applicable SERVOPACK	SGDV-	1R6	1R6	1R6	3R8	5R5	120A	120A	200A

Notes: 1 The items marked with an * and Force and Speed Characteristics (the table on the next page) are the values at a motor winding temperature of 100˚C during operation in combination with a SERVOPACK. The others are at 20˚C.
2 The above specifications show the values under the cooling condition when a heat sink (aluminum board) listed in the following table is mounted on the moving coil.
Heat Sink Size :125 mm × 125 mm × 13 mm: SGLFW-20A090A, -20A120A
254 mm × 254 mm × 25 mm: SGLFW-35A120A, -35A230A
400 mm × 500 mm × 40 mm: SGLFW-50A200B, -50A380B, -1ZA200B
600 mm × 762 mm × 50 mm: SGLFW-1ZA380B

400-V Class


Linear Servomotor Model		35D		50D		1ZD	
SGLFW-□		120A	230A	200B	380B	200B	380B
Peak Speed	m/s	4.5	4.5	5.0	5.0	5.0	5.0
Rated Force*	N	80	160	280	560	560	1120
Rated Current*	A_{rms}	0.6	1.3	2.3	4.5	4.9	9.8
Peak Force*	N	220	440	600	1200	1200	2400
Peak Current*	A_{rms}	2.0	4.0	5.6	11.0	12.3	24.6
Moving Coil Mass	kg	1.3	2.3	3.5	6.9	6.4	11.5
Force Constant	N/A_{rms}	136.0	136.0	134.7	134.7	122.6	122.6
BEMF Constant	V/(m/s)	45.3	45.3	44.9	44.9	40.9	40.9
Motor Constant	$N/\sqrt{W}$	14.2	20.1	33.4	47.2	51.0	72.1
Electrical Time Constant	ms	3.7	3.6	15.0	15.0	17.4	17.2
Mechanical Time Constant	ms	5.2	5.1	3.2	3.2	2.5	2.2
Thermal Resistance (With Heat Sink)	K/W	1.57	0.96	0.56	0.38	0.47	0.2
Thermal Resistance (Without Heat Sink)	K/W	4.1	1.94	1.65	0.95	1.3	0.73
Magnetic Attraction	N	810	1590	1650	3260	3300	6520
Applicable SERVOPACK	SGDV-	1R9D	1R9D	3R5D	5R4D	5R4D	120D

Notes: 1 The items marked with an * and Force and Speed Characteristics (the table on the next page) are the values at a motor winding temperature of 100˚C during operation in combination with a SERVOPACK. The others are at 20˚C.
2 The above specifications show the values under the cooling condition when a heat sink (aluminum board) listed in the following table is mounted on the moving coil.
Heat Sink Size :254 mm × 254 mm × 25 mm: SGLFW-35D120A, -35D230A
400 mm × 500 mm × 40 mm: SGLFW-50D200B, -50D380B, -1ZD200B
600 mm × 762 mm × 50 mm: SGLFW-1ZD380B

Ratings and Specifications


●Force and Speed Characteristics A : Continuous Duty Zone B : Intermittent Duty Zone (Note1)

200-V Class



Notes:
1. When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.
2. The solid, dotted, and dashed-dotted lines of the intermittent duty zone indicate the characteristics when a servomotor runs with the following combinations:
   · The solid line: With a three-phase 200 V or a single-phase 230 V SERVOPACK
   · The dotted line: With a single-phase 200 V SERVOPACK
   · The dashed-dotted line: With a single-phase 100 V SERVOPACK

400-V Class



Notes:
1. When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.
2. The dotted line indicates the characteristics when a 400-VAC linear servomotor is used with 200-V input power supply. In this case, a serial converter unit is required. Contact your Yaskawa representative for details.

●Mechanical Specifications

(1) Impact Resistance

·Impact acceleration: 196 m/s^2
·Impact occurrences: twice


(2) Vibration Resistance

· The linear servomotors will withstand the following vibration acceleration in three directions: Vertical, side to side, and front to back.
· Vibration acceleration: 49 m/s^2


External Dimensions Units: mm

(1) SGLFW-20


● Moving Coil: SGLFW-20A□□□A□ (With a connector by Tyco Electronics AMP K.K.)




①SGLFW-20A090A□



②SGLFW-20A120A□



Hall Sensor
Connector Specifications




Pin Connector :
17JE-13090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Plug:350779-1
Pin :350218-3 or
350547-3(No.1 to 3)
350654-1
350669-1(No.4)
by Tyco Electronics AMP K.K.

The Mating Connector


Cap : 350780-1
Socket: 350536-3 or
350550-3

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Black
4	FG	Green

Note: Models compatible with connectors by Interconnectron GmbH are also available.

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Moving Coil Model SGLFW-	L1	L2	L3	Approx. Mass kg
20A090A□	91	36	72	0.7
20A120A□	127	72	108	0.9

External Dimensions Units: mm

● Magnetic Way: SGLFM-20□□□A



Assembly Dimensions


Notes: 1 Multiple SGLFM-20□□□A magnetic ways can be connected. Connect magnetic ways so that the reference marks match one on the other in the same direction as shown in the figure.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.

Magnetic Way Model SGLFM-	$L1^{-0.1}_{-0.3}$	L2	(L3)	N	Approx. Mass kg
20324A	324	270 (54 × 5)	(331.6)	6	0.9
20540A	540	486 (54 × 9)	(547.6)	10	1.4
20756A	756	702 (54 × 13)	(763.6)	14	2


External Dimensions Units: mm

(2) SGLFW-35


● Moving Coil: SGLFW-35□□□□A□ (With a connector by Tyco Electronics AMP K.K.)




①SGLFW-35□120A□



②SGLFW-35□230A□



Hall Sensor
Connector Specifications




Pin Connector
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02(D8C)
Stud:17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Plug: 350779-1
Pin : 350218-3 or
350547-3 (No.1 to 3)
350654-1
350669-1 (No.4)
by Tyco Electronics AMP K.K.


The Mating Connector

Cap : 350780-1
Socket: 350536-3 or
350550-3

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Black
4	FG	Green

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLFW-	L1	L2	L3	Approx. Mass kg
35□120A□	127	72	108	1.3
35□230A□	235	180	216	2.3

External Dimensions Units: mm


● Moving Coil: SGLFW-35□□□□A□D (With a connector by Interconnectron GmbH)




①SGLFW-35□120A□D



②SGLFW-35□230A□D



Hall Sensor
Connector Specifications



Pin Connector :
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Extension: ARRA06AMRPN182
Pin : 021.279.1020
by Interconnectron GmbH


The Mating Connector

Plug : APRA06BFRDN170
Socket: 020.105.1020

Pin No.	Name
1	Phase U
2	Phase V
4	Phase W
5	Not used
6	Not used
⏚	Ground

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Moving Coil Model SGLFW-	L1	L2	L3	N	Approx. Mass kg
35□120A□D	127	72	108	6	1.3
35□230A□D	235	180	216	12	2.3

External Dimensions Units: mm

● Magnetic Way: SGLFM-35□□□A



Assembly Dimensions


Notes: 1 Multiple SGLFM-35□□□A magnetic ways can be connected. Connect magnetic ways so that the reference marks match one on the other in the same direction as shown in the figure.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.

Magnetic Way Model SGLFM-	L1 -0.1 -0.3	L2	(L3)	N	Approx. Mass kg
35324A	324	270 (54×5)	(334.4)	6	1.2
35540A	540	486 (54×9)	(550.4)	10	2
35756A	756	702 (54×13)	(766.4)	14	2.9


External Dimensions Units: mm

(3) SGLFW-50


● Moving Coil: SGLFW-50□□□□B□ (With a connector by Tyco Electronics AMP K.K.)




①SGLFW-50□200B□



②SGLFW-50□380B□



Hall Sensor
Connector Specifications




Pin Connector :
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Plug:350779-1
Pin :350218-3 or
350547-3(No.1 to 3)
350654-1
350669-1(No.4)
by Tyco Electronics AMP K.K.


The Mating Connector

Cap : 350780-1
Socket: 350536-3 or
350550-3

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Black
4	FG	Green

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLFW-	L1	L2	L3	Approx. Mass kg
50□200B□	215	120	180	3.5
50□380B□	395	300	360	6.9

External Dimensions Units: mm


● Moving Coil: SGLFW-50□□□□B□D (With a connector by Interconnectron GmbH)




①SGLFW-50□200B□D



②SGLFW-50□380B□D



Hall Sensor
Connector Specifications




Pin Connector :
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Extension: ARRA06AMRPN182
Pin : 021.279.1020
by Interconnectron GmbH


The Mating Connector

Plug : APRA06BFRDN170
Socket: 020.105.1020

Pin No.	Name
1	Phase U
2	Phase V
4	Phase W
5	Not used
6	Not used
⏚	Ground

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Moving Coil Model SGLFW-	L1	L2	L3	N	Approx. Mass kg
50□200B□D	215	120	180	6	3.5
50□380B□D	395	300	360	12	6.9

External Dimensions Units: mm

● Magnetic Way: SGLFM-50□□□A



Assembly Dimensions


Notes: 1 Multiple SGLFM-50□□□A magnetic ways can be connected. Connect magnetic ways so that the reference marks match one on the other in the same direction as shown in the figure.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.

Magnetic Way Model SGLFM-	$L1^{-0.1}_{-0.3}$	L2	(L3)	N	Approx. Mass kg
50405A	405	337.5 (67.5×5)	(416.3)	6	2.8
50675A	675	607.5 (67.5×9)	(686.3)	10	4.6
50945A	945	877.5 (67.5×13)	(956.3)	14	6.5


External Dimensions Units: mm

(4) SGLFW-1Z


● Moving Coil: SGLFW-1Z□□□□B□ (With a connector by Tyco Electronics AMP K.K.)




①SGLFW-1Z□200B□



②SGLFW-1Z□380B□



Hall Sensor
Connector Specifications




Pin Connector :
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Plug:350779-1
Pin :350218-3 or
350547-3(No.1 to 3)
350654-1
350669-1(No.4)
by Tyco Electronics AMP K.K.


The Mating Connector

Cap : 350780-1
Socket: 350536-3 or
350550-3

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Black
4	FG	Green

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLFW-	L1	L2	L3	N	Approx. Mass kg
1Z□200B□	215	120	180	9	6.4
1Z□380B□	395	300	360	18	11.5

External Dimensions Units: mm


● Moving Coil: SGLFW-1Z□□□□B□D (With a connector by Interconnectron GmbH)




①SGLFW-1Z□200B□D



②SGLFW-1ZD380B□D



Hall Sensor
Connector Specifications



Pin Connector :
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Extension: ARRA06AMRPN182
Pin : 021.279.1020
by Interconnectron GmbH


The Mating Connector

Plug : APRA06BFRDN170
Socket: 020.105.1020

Pin No.	Name
1	Phase U
2	Phase V
4	Phase W
5	Not used
6	Not used
⏚	Ground

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Moving Coil Model SGLFW-	L1	L2	L3	N	Approx. Mass kg
1Z□200B□D	215	120	180	9	6.4
1ZD380B□D	395	300	360	18	11.5

External Dimensions Units: mm

● Magnetic Way: SGLFM-1Z□□□A




Assembly Dimensions

Notes: 1 Multiple SGLFM-1Z□□□A magnetic ways can be connected. Connect magnetic ways so that the reference marks match one on the other in the same direction as shown in the figure.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.

Magnetic Way Model SGLFM-	$L1^{-0.1}_{-0.3}$	L2	L3	N	Approx. Mass kg
1Z405A	405	337.5 (67.5 × 5)	(423.9)	6	5
1Z675A	675	607.5 (67.5 × 9)	(693.9)	10	8.3
1Z945A	945	877.5 (67.5 × 13)	(963.9)	14	12






Selecting Cables

●Cables Connections



Selecting Cables

●Cables


Name	Applicable Linear Servomotor Model	Length	Order No.	Specifications	Details
① Linear Servomotor Main Circuit Cables	SGLFW-20, -35	1 m	JZSP-CLN11-01-E	SERVOPACK End Linear Servomotor End  *1	(1)
		3 m	JZSP-CLN11-03-E		
		5 m	JZSP-CLN11-05-E		
		10 m	JZSP-CLN11-10-E		
		15 m	JZSP-CLN11-15-E		
		20 m	JZSP-CLN11-20-E		
	SGLFW-50, -1Z	1 m	JZSP-CLN21-01-E	SERVOPACK End Linear Servomotor End  *1	(2)
		3 m	JZSP-CLN21-03-E		
		5 m	JZSP-CLN21-05-E		
		10 m	JZSP-CLN21-10-E		
		15 m	JZSP-CLN21-15-E		
		20 m	JZSP-CLN21-20-E		
	SGLFW-□□A□□□□□D	1 m	JZSP-CLN14-01-E	SERVOPACK End Linear Servomotor End  *2	(3)
		3 m	JZSP-CLN14-03-E		
		5 m	JZSP-CLN14-05-E		
		10 m	JZSP-CLN14-10-E		
		15 m	JZSP-CLN14-15-E		
		20 m	JZSP-CLN14-20-E		
	SGLFW-□□D□□□□□D	1 m	JZSP-CLN15-01-E	SERVOPACK End Linear Servomotor End  *2	(4)
		3 m	JZSP-CLN15-03-E		
		5 m	JZSP-CLN15-05-E		
		10 m	JZSP-CLN15-10-E		
		15 m	JZSP-CLN15-15-E		
		20 m	JZSP-CLN15-20-E		
② Cables for Connecting Linear Scales*3	All models	1 m	JZSP-CLL00-01-E	Serial Converter Unit End Linear Scale End 	(5)
		3 m	JZSP-CLL00-03-E		
		5 m	JZSP-CLL00-05-E		
		10 m	JZSP-CLL00-10-E		
		15 m	JZSP-CLL00-15-E		
③ Cables for Connecting Serial Converter Units	All models	1 m	JZSP-CLP70-01-E	SERVOPACK End Serial Converter Unit End 	(6)
		3 m	JZSP-CLP70-03-E		
		5 m	JZSP-CLP70-05-E		
		10 m	JZSP-CLP70-10-E		
		15 m	JZSP-CLP70-15-E		
		20 m	JZSP-CLP70-20-E		
④ Cables for Connecting Hall Sensors	All models	1 m	JZSP-CLL10-01-E	Serial Converter Unit End Hall Sensor Unit End 	(7)
		3 m	JZSP-CLL10-03-E		
		5 m	JZSP-CLL10-05-E		
		10 m	JZSP-CLL10-10-E		
		15 m	JZSP-CLL10-15-E		

*1: Connector by Tyco Electronics AMP K.K.
*2: Connector by Interconnectron GmbH
*3: When using the serial converter unit, JZDP-G00□-□□□-E, the maximum cable length is 3 m.

NOTE: Shaded items are non-stock.

Selecting Cables


(1) Linear Servomotor Main Circuit Cables: JZSP-CLN11-□□-E



· Wiring Specifications

SERVOPACK-end Leads		Linear Servomotor-end Connector	
Wire Color	Signal	Signal	Pin No.
Red	Phase U	Phase U	1
White	Phase V	Phase V	2
Blue	Phase W	Phase W	3
Green/yellow	FG	FG	4


(2) Linear Servomotor Main Circuit Cables: JZSP-CLN21-□□-E



· Wiring Specifications

SERVOPACK-end Leads		Linear Servomotor-end Connector	
Wire Color	Signal	Signal	Pin No.
Red	Phase U	Phase U	1
White	Phase V	Phase V	2
Blue	Phase W	Phase W	3
Green/yellow	FG	FG	4

(3) Linear Servomotor Main Circuit Cables: JZSP-CLN14-□□-E




· Wiring Specifications

SERVOPACK-end Leads		Linear Servomotor-end Connector	
Wire Color	Signal	Signal	Pin No.
Black (White 1)	Phase U	Phase U	1
Black (White 2)	Phase V	Phase V	2
Black (White 3)	Phase W	Phase W	3
Green/yellow	FG	—	4
		—	5
		FG	6

(4) Linear Servomotor Main Circuit Cables: JZSP-CLN15-□□-E

· Wiring Specifications




SERVOPACK-end Leads

Wire Color	Signal
Red	Phase U
White	Phase V
Black	Phase W
Green/yellow	FG

Linear Servomotor-end Connector

Signal	Pin No.
Phase U	1
Phase V	2
Phase W	3
—	4
—	5
FG	6

(5) Cables for Connecting Linear Scales: JZSP-CLL00-□□-E




· Wiring Specifications

Serial Converter Unit End		Linear Scale End	
Pin No.	Signal	Pin No.	Signal
1	/Cos(V1−)	1	/Cos(V1−)
2	/Sin(V2−)	2	/Sin(V2−)
3	Ref(V0+)	3	Ref(V0+)
4	+5V	4	+5V
5	5Vs	5	5Vs
6	BID	6	BID
7	Vx	7	Vx
8	Vq	8	Vq
9	Cos(V1+)	9	Cos(V1+)
10	Sin(V2+)	10	Sin(V2+)
11	/Ref(V0+)	11	/Ref(V0−)
12	0V	12	0V
13	0Vs	13	0Vs
14	DIR	14	DIR
15	Inner	15	Inner
Case	Shield	Case	Shield

Selecting Cables

(6) Cables for Connecting Serial Converter Units: JZSP-CLP70-□□-E



· Wiring Specifications


SERVOPACK End

Pin No.	Signal	Wire Color
1	PG5V	Red
2	PG0V	Black
3	–	–
4	–	–
5	PS	Light blue
6	/PS	Light blue/white
Shell	Shield	–

Serial Converter Unit End

Pin No.	Signal	Wire Color
1	+5V	Red
5	0V	Black
3	–	–
4	–	–
2	Phase S output	Light blue
6	Phase /S output	Light blue/white
Case	Shield	–
7	–	–
8	–	–
9	–	–

(7) Cables for Connecting Hall Sensors: JZSP-CLL10-□□-E



· Wiring Specifications

Serial Converter Unit End

Pin No.	Signal
1	+5V
2	Phase U input
3	Phase V input
4	Phase W input
5	0V
6	–
7	–
8	–
9	–
Case	Shield


Hall Sensor End

Pin No.	Signal
1	+5V
2	Phase U input
3	Phase V input
4	Phase W input
5	0V
6	–
7	–
8	–
9	–
Case	Shield

Linear Servomotors

SGLTW

(With T-type iron core)



Model Designations

● Moving Coil (All Models are Non-Stock)

SGL T W - 20 A 170 A P □

Linear Σ Series

Servomotor Type

Code	Specifications
T	T-type iron core

W: Moving Coil

Magnet Height

Voltage
A: 200 VAC
D: 400 VAC

Length of Moving Coil

Design Revision Order
A, B, ...
H: High-efficiency Type

Connector for Main Circuit Cable

Code	Specification	Applicable Model
Blank	Connector by Tyco Electronics AMP K.K.	SGLTW -20A□□□□□ -35A□□□□□ -50A□□□□□
	MS connector	SGLTW -40□□□□B□ -80□□□□B□
D	Connector by Interconnectron GmbH	SGLTW -35D□□□H□ -50D□□□H□

Hall Sensor

Code	Specifications
P	With hall sensor
Blank	Without hall sensor

Note: Shaded items are non-stock

● Magnetic Way (All Models are Non-Stock)

SGL T M - 20 324 A □

Linear Σ Series

Linear Servomotor

Servomotor Type

Code	Specifications
T	T-type iron core

M: Magnetic Way

Magnet Height

Length of Magnetic Way

Options

Code	Specifications	Applicable Model
Blank	Standard	All models
C	With magnet cover	Models with core
Y	With base and magnet cover	SGLTM-20, -35, -40, -80(Note)

Note: Not available for these models: the SGLTM-35□□□H and the SGLTM-50□□□H.

Design Revision Order
A, B, ...
H: High-efficiency Type

Features

- Direct-feed mechanism for high-speed and high-precision positioning.
- Yaskawa's unique construction principles of the TW linear motors negate the effects of the magnetic attraction force between the relative motor members.
- Lack of magnetic attraction helps to extend the life of the linear motion guides and to minimize operation noise.
- Very little cogging.

Application Examples


- Feeders and loaders
- Mounters
- Machine tools

● Precautions on Moving Coil with Hall Sensor


When using a moving coil with a hall sensor, the magnetic way must completely cover the bottom of the hall sensor. Refer to the example showing the correct installation.

When determining the length of the moving coil's stroke or the length of the magnetic way, consider the total length of the moving coil and the hall sensor unit. Refer to the following table.


< Correct >



< Incorrect >



The total length of moving coil with hall sensor



Moving Coil Model SGLTW-	Length of Moving Coil L1 (mm)	Length of Hall Sensor Unit A (mm)	Total Length L (mm)
20A170AP□	170	34	204
20A320AP□	315		349
20A460AP□	460		494
35A170AP□	170	34	204
35A320AP□	315		349
35A460AP□	460		494
35□170HP□	170	34	204
35□320HP□	315		349
50□170HP□	170	34	204
50□320HP□	315		349
40A400AP□	395	26	421
40A600AP□	585	36	621
80A400AP□	395	26	421
80A600AP□	585	36	621
40□400BP□	395	26	421
40□600BP□	575		601
80□400BP□	395	26	421
80□600BP□	575		601

Ratings and Specifications

Time Rating: Continuous
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40˚C
Excitation: Permanent magnet
Withstand Voltage: 1500 VAC for one minute
Enclosure: Self-cooled
Ambient Humidity: 20% to 80% (no condensation)
Allowable Winding Temperature: 130˚C (Thermal class B)

200-V Class

Linear Servomotor Model SGLTW-		Standard Type										High-efficiency Type			
		20A			35A			40A		80A		35A		50A	
		170A	320A	460A	170A	320A	460A	400B	600B	400B	600B	170H	320H	170H	320H
Peak Speed	m/s	5	5	5	5	5	5	3.1	3.1	2.5	2.5	4.8	4.8	3.2	3.1
Rated Force*	N	130	250	380	220	440	670	670	1000	1300	2000	300	600	450	900
Rated Current*	A_{rms}	2.3	4.4	6.7	3.5	7	10.7	7.3	10.9	11.1	17.1	5.1	10.1	4.9	9.8
Peak Force*	N	380	760	1140	660	1320	2000	2600	4000	5000	7500	600	1200	900	1800
Peak Current*	A_{rms}	7.7	15.4	23.2	12.1	24.2	36.7	39.4	60.6	57.9	86.9	11.9	23.9	11.5	22.9
Moving Coil Mass	kg	2.5	4.6	6.7	3.7	6.8	10	15	23	24	35	4.9	8.8	6	11
Force Constant	N/A_{rms}	61	61	61	67.5	67.5	67.5	99.1	99.1	126	126	64	64	98.5	98.5
BEMF Constant	V/(m/s)	20.3	20.3	20.3	22.5	22.5	22.5	33	33	42	42	21.3	21.3	32.8	32.8
Motor Constant	$N/\sqrt{w}$	18.7	26.5	32.3	26.7	37.5	46.4	61.4	75.2	94.7	116	37.4	52.9	50.3	71.1
Electrical Time Constant	ms	5.9	5.9	5.9	6.9	6.8	7	15.2	15.2	17	17	15.1	15.1	16.5	16.5
Mechanical Time Constant	ms	7.5	6.5	6.4	5.2	4.8	4.6	4	4	3	3	3.3	3.3	2.8	2.8
Thermal Resistance (With Heat Sink)	K/W	1.01	0.49	0.38	0.76	0.44	0.32	0.24	0.2	0.22	0.18	0.76	0.4	0.61	0.3
Thermal Resistance (Without Heat Sink)	K/W	1.82	1.11	0.74	1.26	0.95	0.61	0.57	0.4	0.47	0.33	1.26	0.83	0.97	0.8
Magnetic Attraction*1	N	0	0	0	0	0	0	0	0	0	0	0	0	0	0
Magnetic Attraction(on one side)*2	N	800	1590	2380	1400	2780	4170	3950	5890	7650	11400	1400	2780	2000	3980
Applicable SERVOPACK	SGDV-	3R8A	7R6A	120A	5R5A	120A	180A	180A	330A	330A	550A	5R5A	120A	5R5A	120A

*1 : The unbalanced magnetic gap resulted from the moving coil installation condition causes a magnetic attraction on the moving coil.
*2 : The value indicates the magnetic attraction generated on one side of the magnetic way.
Notes: 1 The items marked with an * and Force and Speed Characteristics (on the next page) are the values at a motor winding temperature of 100˚C during operation in combination with a SERVOPACK. The others are at 20˚C.
2 The above specifications show the values under the cooling condition when a heat sink (aluminum board) listed in the following table is mounted on the moving coil.
Heat Sink Size 254 mm×254 mm×25 mm : SGLTW-20A170A,-35A170A
400 mm×500 mm×40 mm : SGLTW-20A320A,-20A460A,-35A170H,-35A320A,-35A320H,-35A460A,-50A170H
609 mm×762 mm×50 mm : SGLTW-40A400B,-40A600B,-50A320H,-80A400B,-80A600B

400-V Class

Linear Servomotor Model SGLTW-		Standard Type				High-efficiency Type			
		40D		80D		35D		50D	
		400B	600B	400B	600B	170H	320H	170H	320H
Peak Speed	m/s	3.1	3.1	3.1	3.1	5	5	4	4
Rated Force*	N	670	1000	1300	2000	300	600	450	900
Rated Current*	A_{rms}	3.7	5.5	7.2	11.1	3.2	6.5	3.2	6.3
Peak Force*	N	2600	4000	5000	7500	600	1200	900	1800
Peak Current*	A_{rms}	20.7	30.6	37.6	56.4	7.7	15.5	7.4	14.8
Moving Coil Mass	kg	15	23	24	35	4.7	8.8	6	11
Force Constant	N/A_{rms}	196.1	196.1	194.4	194.4	99.6	99.6	153.3	153.3
BEMF Constant	V/(m/s)	65.4	65.4	64.8	64.8	33.2	33.2	51.1	51.1
Motor Constant	$N/\sqrt{w}$	59.6	73	85.9	105.2	36.3	51.4	48.9	69.1
Electrical Time Constant	ms	14.3	14.4	15.6	15.6	14.3	14.4	15.6	15.6
Mechanical Time Constant	ms	4.3	4.2	3.2	3.2	3.5	3.3	2.5	2.5
Thermal Resistance (With Heat Sink)	K/W	0.24	0.2	0.22	0.18	0.76	0.4	0.61	0.3
Thermal Resistance (Without Heat Sink)	K/W	0.57	0.4	0.47	0.33	1.26	0.83	0.97	0.8
Magnetic Attraction*1	N	0	0	0	0	0	0	0	0
Magnetic Attraction(on one side)*2	N	3950	5890	7650	11400	1400	2780	2000	3980
Applicable SERVOPACK	SGDV-	120D	170D	170D	260D	3R5D	8R4D	3R5D	8R4D

*1 : The unbalanced magnetic gap resulted from the moving coil installation condition causes a magnetic attraction on the moving coil.
*2 : The value indicates the magnetic attraction generated on one side of the magnetic way.
Notes: 1 The items marked with an * and Force and Speed Characteristics (on page 163) are the values at a motor winding temperature of 100˚C during operation in combination with a SERVOPACK. The others are at 20˚C.
2 The above specifications show the values under the cooling condition when a heat sink (aluminum board) listed in the following table is mounted on the moving coil.
Heat Sink Size 400 mm×500 mm×40 mm : SGLTW-35D170H,-35D320H,-50D170H
609 mm×762 mm×50 mm : SGLTW-40D400B,-40D600B,-50D320H,-80D400B,-80D600B


Ratings and Specifications

●Force and Speed Characteristics


A : Continuous Duty Zone B : Intermittent Duty Zone

200-V Class Standard Type


SGLTW-20A170A




SGLTW-20A320A




SGLTW-20A460A




SGLTW-35A170A




SGLTW-35A320A




SGLTW-35A460A




SGLTW-40A400B




SGLTW-40A600B



SGLTW-80A400B




SGLTW-80A600B




200-V Class High-efficiency Type


SGLTW-35A170H




SGLTW-35A320H



SGLTW-50A170H




SGLTW-50A320H




Note: When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.

●Force and Speed Characteristics (cont'd) A : Continuous Duty Zone B : Intermittent Duty Zone

400-V Class Standard Type



400-V Class High-efficiency Type



Notes: 1 When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.
2 The dotted line indicates the characteristics when a 400-VAC linear servomotor is used with 200-V input power supply. In this case, a serial converter unit is required. Contact your Yaskawa representative for details.

●Mechanical Specifications

(1) Impact Resistance

·Impact acceleration: 196 m/s^2

·Impact occurrences: twice

(2) Vibration Resistance


The linear servomotors will withstand the following vibration acceleration in three directions: Vertical, side to side, and front to back.

·Vibration acceleration: 49 m/s^2


External Dimensions Units: mm

(1) Standard Type SGLTW-20

● Moving Coil: SGLTW-20A□□□A□ (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor
Connector Specifications




Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5VDC
2	Phase U
3	Phase V
4	Phase W
5	0V
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Plug: 350779-1
Pin : 350218-3 or
350547-3 (No.1 to 3)
350654-1
350669-1 (No.4)
by Tyco Electronics AMP K.K.


The Mating Connector

Cap : 350780-1
Socket: 350536-3 or
350550-3

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Black
4	Ground	Green

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Moving Coil Model SGLTW-	L1	L2	(L3)	N	Approx. Mass kg
20A170A□	170	144 (48×3)	(16)	8	2.5
20A320A□	315	288 (48×6)	(17)	14	4.6
20A460A□	460	432 (48×9)	(18)	20	6.7

External Dimensions Units: mm

● Magnetic Way : SGLTM-20□□□A□




Assembly Dimensions

Notes: 1 Two magnetic ways for both ends of moving coil make one set. Spacers are mounted on magnetic ways for safety during transportation. Do not remove the spacers until the moving coil is mounted on a machine.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.
3 Two magnetic ways in a set can be connected to each other.
4 The dimensions marked with an * are the dimensions between the magnetic ways. Be sure to follow exactly the dimensions specified in the figure above. Mount magnetic ways as shown in Assembly Dimensions. The values with a ♣ are the dimensions at preshipment.
5 Use socket headed screws of strength class 10.9 minimum for magnetic way mounting screws. Do not use stainless steel screws.

Magnetic Way Model SGLTM-	$L1^{-0.1}_{-0.3}$	L2	N	Approx. Mass kg
20324A□	324	270 (54×5)	6	3.4
20540A□	540	486 (54×9)	10	5.7
20756A□	756	702 (54×13)	14	7.9

External Dimensions Units: mm

● Magnetic Way with Base: SGLTM-20□□□AY




Notes: 1 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.
2 Two magnetic ways in a set can be connected to each other.
3 The characteristics of the magnetic way with base are the same as of the magnetic way without base (SGLTM-20□□□A).

Magnetic Way Model SGLTM-	L1	L2	L3	L4	L5	N1	N2	Approx. Mass kg
20324AY	324	270	310	162	162	6	2	5.1
20540AY	540	486	526	378	189	10	3	8.5
20756AY	756	702	742	594	198	14	4	12


External Dimensions Units: mm

(2) Standard Type SGLTW-35A

● Moving Coil: SGLTW-35A□□□A□ (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor
Connector Specifications




Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5VDC
2	Phase U
3	Phase V
4	Phase W
5	0V
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Plug: 350779-1
Pin : 350218-3 or
350547-3 (No.1 to 3)
350654-1
350669-1 (No.4)
by Tyco Electronics AMP K.K.


The Mating Connector

Cap : 350780-1
Socket: 350536-3 or
350550-3

Pin No.	Signal	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Black
4	Ground	Green

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Moving Coil Model SGLTW-	L1	L2	(L3)	N	Approx. Mass kg
35A170A□	170	144 (48×3)	(16)	8	3.7
35A320A□	315	288 (48×6)	(17)	14	6.8
35A460A□	460	432 (48×9)	(18)	20	10

External Dimensions Units: mm

● Magnetic Way: SGLTM-35□□□A□




Assembly Dimensions


Notes: 1 Two magnetic ways for both ends of moving coil make one set. Spacers are mounted on magnetic ways for safety during transportation. Do not remove the spacers until the moving coil is mounted on a machine.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.
3 Two magnetic ways in a set can be connected to each other.
4 The dimensions marked with an * are the dimensions between the magnetic ways. Be sure to follow exactly the dimensions specified in the figure above. Mount magnetic ways as shown in Assembly Dimensions. The values with a ♣ are the dimensions at preshipment.
5 Use socket headed screws of strength class 10.9 minimum for magnetic way mounting screws. Do not use stainless steel screws.

Magnetic Way Model SGLTM-	$L1^{-0.1}_{-0.3}$	L2	N	Approx. Mass kg
35324A□	324	270 (54×5)	6	4.8
35540A□	540	486 (54×9)	10	8
35756A□	756	702 (54×13)	14	11

External Dimensions Units: mm

● Magnetic Way with Base: SGLTM-35□□□AY






Notes: 1 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.
2 Two magnetic ways in a set can be connected to each other.
3 The characteristics of the magnetic way with base are the same as of the magnetic way without base (SGLTM-35□□□A).

Magnetic Way Model SGLTM-	L1	L2	L3	L4	L5	N1	N2	Approx. Mass kg
35324AY	324	270	310	162	162	6	2	6.4
35540AY	540	486	526	378	189	10	3	11
35756AY	756	702	742	594	198	14	4	15


External Dimensions Units: mm

(3) Standard Type SGLTW-40

● Moving Coil: SGLTW-40□□□□B□ (With an MS connector)



Hall Sensor
Connector Specifications



Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5VDC
2	Phase U
3	Phase V
4	Phase W
5	0V
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Receptacle type: MS3102A-22-22P
□by DDK Ltd.


The Mating Connector

L-shaped plug type : MS3108B22-22S
Straight plug type : MS3106B22-22S
Cable clamp type : MS3057-12A

Pin No.	Signal
A	Phase U
B	Phase V
C	Phase W
D	Ground

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Moving Coil Model SGLTW-	L1	L2	(L3)	N	Approx. Mass kg
40□400B□	395	360(60×6)	(15)	14	15
40□600B□	575	540(60 ×9)	(15)	20	22

External Dimensions Units: mm

● Magnetic Way : SGLTM-40□□□A□




Assembly Dimensions

Notes: 1 Two magnetic ways for both ends of moving coil make one set. Spacers are mounted on magnetic ways for safety during transportation. Do not remove the spacers until the moving coil is mounted on a machine.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.
3 Two magnetic ways in a set can be connected to each other.
4 The dimensions marked with an * are the dimensions between the magnetic ways. Be sure to follow exactly the dimensions specified in the figure above. Mount magnetic ways as shown in Assembly Dimensions. The values with a ♣ are the dimensions at preshipment.
5 Use socket headed screws of strength class 10.9 minimum for magnetic way mounting screws. Do not use stainless steel screws.

Magnetic Way Model SGLTM-	$L1^{-0.1}_{-0.3}$	L2	N	Approx. Mass kg
40405A□	405	337.5 (67.5×5)	6	9
40675A□	675	607.5 (67.5×9)	10	15
40945A□	945	877.5 (67.5×13)	14	21

External Dimensions Units: mm

● Magnetic Way with Base: SGLTM-40□□□AY




Notes: 1 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.
2 Two magnetic ways in a set can be connected to each other.
3 The characteristics of the magnetic way with base are the same as of the magnetic way without base (SGLTM-40□□□A).

Magnetic Way Model SGLTM-	L1	L2	L3	L4	L5	N1	N2	Approx. Mass kg
40405AY	405	337.5	387.5	202.5	202.5	6	2	13
40675AY	675	607.5	657.5	472.5	236.25	10	3	21
40945AY	945	877.5	927.5	742.5	247.5	14	4	30


External Dimensions Units: mm

(4) Standard Type SGLTW-80

● Moving Coil: SGLTW-80□□□□B□ (With an MS connector)



Hall Sensor
Connector Specifications



Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5VDC
2	Phase U
3	Phase V
4	Phase W
5	0V
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Receptacle type: MS3102A-22-22P
by DDK Ltd.


The Mating Connector

L-shaped plug type : MS3108B22-22S
Straight plug type : MS3106B22-22S
Cable clamp type : MS3057-12A

Pin No.	Signal
A	Phase U
B	Phase V
C	Phase W
D	Ground

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Moving Coil Model SGLTW-	L1	L2	L3	N	Approx. Mass kg
80□400B□	395	360(60×6)	(15)	14	24
80□600B□	575	540(60×9)	(15)	20	35

External Dimensions Units: mm

● Magnetic Way : SGLTM-80□□□A□




Notes: 1 Two magnetic ways for both ends of moving coil make one set. Spacers are mounted on magnetic ways for safety during transportation. Do not remove the spacers until the moving coil is mounted on a machine.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.
3 Two magnetic ways in a set can be connected to each other.
4 The dimensions marked with an * are the dimensions between the magnetic ways. Be sure to follow exactly the dimensions specified in the figure above. Mount magnetic ways as shown in Assembly Dimensions. The values with a ♣ are the dimensions at preshipment.
5 Use socket headed screws of strength class 10.9 minimum for magnetic way mounting screws. Do not use stainless steel screws.

Magnetic Way Model SGLTM-	$L1^{-0.1}_{-0.3}$	L2	L3	N1	N2	Approx. Mass kg
80405A□	405	337.5(67.5×5)	337.5(33.75×10)	6	11	14
80675A□	675	607.5(67.5×9)	607.5(33.75×18)	10	19	24
80945A□	945	877.5(67.5×13)	887.5(33.75×26)	14	27	34

External Dimensions Units: mm

- Magnetic Way with Base: SGLTM-80□□□AY




Notes: 1 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.
2 Two magnetic ways in a set can be connected to each other.
3 The characteristics of the magnetic way with base are the same as of the magnetic way without base (SGLTM-80□□□A).

Magnetic Way Model SGLTM-	L1	L2	L3	L4	L5	N1	N2	N3	Approx. Mass kg
80405AY	405	337.5	387.5	202.5	202.5	6	2	11	18
80675AY	675	607.5	657.5	472.5	236.25	10	3	19	31
80945AY	945	877.5	927.5	742.5	247.5	14	4	27	43


External Dimensions Units: mm

(5) High-efficiency Type SGLTW-35A□□□H□

● Moving Coil: SGLTW-35A□□□H□ (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor
Connector Specifications




Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector
Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5VDC
2	Phase U
3	Phase V
4	Phase W
5	0V
6	Not used
7	Not used
8	Not used
9	Not used

Lead Specifications of Moving Coil

・If this cable is bent repetitively, the cable will disconnect.




(View from Top of Moving Coil)

Name	Color	Code	Wire Size
Phase U	Black	U	2 mm²
Phase V		V	
Phase W		W	
Ground	Green	–	2 mm²

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLTW-	L1	L2	(L3)	N	Approx. Mass kg
35A170H□	170	144 (48×3)	(16)	8	4.7
35A320H□	315	288 (48×6)	(17)	14	8.8

External Dimensions Units: mm

● Moving Coil: SGLTW-35D□□□H□D (With a connector by Interconnectron GmbH)



Hall Sensor
Connector Specifications




Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5VDC
2	Phase U
3	Phase V
4	Phase W
5	0V
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Extension : ARRA06AMRPN182
Pin : 021.279.1020
by Interconnectron GmbH


The Mating Connector

Plug : APRA06BFRDN170
Socket : 020.105.1020

Pin No.	Signal
1	Phase U
2	Phase V
4	Phase W
5	Not used
6	Not used
⏚	Ground

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Moving Coil Model SGLTW-	L1	L2	(L3)	N	Approx. Mass kg
35D170H□D	170	144(48× 3)	(16)	8	4.7
35D320H□D	315	288(48×6)	(17)	14	8.8

External Dimensions Units: mm

● Magnetic Way: SGLTM-35□□□H□



Assembly Dimensions


Notes: 1 Two magnetic ways for both ends of moving coil make one set. Spacers are mounted on magnetic ways for safety during transportation. Do not remove the spacers until the moving coil is mounted on a machine.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.
3 Two magnetic ways in a set can be connected to each other.
4 The dimensions marked with an * are the dimensions between the magnetic ways. Be sure to follow exactly the dimensions specified in the figure above. Mount magnetic ways as shown in Assembly Dimensions. The values with a ♣ are the dimensions at preshipment.
5 Use socket headed screws of strength class 10.9 minimum for magnetic way mounting screws. Do not use stainless steel screws.

Magnetic Way Model SGLTM-	$L1^{-0.1}_{-0.3}$	L2	N	Approx. Mass kg
35324H□	324	270 (54×5)	6	4.8
35540H□	540	486 (54×9)	10	8
35756H□	756	702 (54×13)	14	11


External Dimensions Units: mm

(6) High-efficiency Type SGLTW-50

● Moving Coil: SGLTW-50A□□□H□ (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor
Connector Specifications



Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.


The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5VDC
2	Phase U
3	Phase V
4	Phase W
5	0V
6	Not used
7	Not used
8	Not used
9	Not used

Lead Specifications of Moving Coil

• If this cable is bent repetitively, the cable will disconnect.




(View from Top of Moving Coil)

Name	Color	Code	Wire Size
Phase U	Black	U	2 mm²
Phase V		V	
Phase W		W	
Ground	Green	–	2 mm²

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.




Moving Coil Model SGLTW-	L1	L2	(L3)	N	Approx. Mass kg
50A170H□	170	144 (48×3)	(16)	8	6
50A320□□	315	288 (48×6)	(17)	14	11

External Dimensions Units: mm

● Moving Coil: SGLTW-50D□□□H□D (With a connector by Interconnectron GmbH)



Hall Sensor
Connector Specifications




Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Signal
1	+5VDC
2	Phase U
3	Phase V
4	Phase W
5	0V
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor
Connector Specifications



Extension : ARRA06AMRPN182
Pin : 021.279.1020
by Interconnectron GmbH


The Mating Connector

Plug : APRA06BFRDN170
Socket : 020.105.1020

Pin No.	Signal
1	Phase U
2	Phase V
4	Phase W
5	Not used
6	Not used
⏚	Ground

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Moving Coil Model SGLTW-	L1	L2	(L3)	N	Approx. Mass kg
50D170H□D	170	144(48×3)	(16)	8	6
50D320H□D	315	288(48×6)	(17)	14	11

External Dimensions Units: mm

● Magnetic Way: SGLTM-50□□□H□




Assembly Dimensions

Notes: 1 Two magnetic ways for both ends of moving coil make one set. Spacers are mounted on magnetic ways for safety during transportation. Do not remove the spacers until the moving coil is mounted on a machine.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.
3 Two magnetic ways in a set can be connected to each other.
4 The dimensions marked with an * are the dimensions between the magnetic ways. Be sure to follow exactly the dimensions specified in the figure above. Mount magnetic ways as shown in Assembly Dimensions. The values with a ♣ are the dimensions at preshipment.
5 Use socket headed screws of strength class 10.9 minimum for magnetic way mounting screws. Do not use stainless steel screws.





Magnetic Way Model SGLTM-	$L1^{-0.1}_{-0.3}$	L2	N	Approx. Mass kg
50324H□	324	270 (54×5)	6	8
50540H□	540	486 (54×9)	10	13
50756H□	756	702 (54×13)	14	18

Selecting Cables

●Cables Connections



●Cables




Name	Applicable Linear Servomotor Model	Length	Order No.	Specifications	Details
① Linear Servomotor Main Circuit Cables	SGLTW -20, -35, -50	1 m	JZSP-CLN21-01-E		(1)
		3 m	JZSP-CLN21-03-E		
		5 m	JZSP-CLN21-05-E		
		10 m	JZSP-CLN21-10-E		
		15 m	JZSP-CLN21-15-E		
		20 m	JZSP-CLN21-20-E		
	SGLTW-40,-80	1 m	JZSP-CLN39-01-E		(2)
		3 m	JZSP-CLN39-03-E		
		5 m	JZSP-CLN39-05-E		
		10 m	JZSP-CLN39-10-E		
		15 m	JZSP-CLN39-15-E		
		20 m	JZSP-CLN39-20-E		
	SGLTW- □□A□□□□□D	1 m	JZSP-CLN14-01-E		(3)
		3 m	JZSP-CLN14-03-E		
		5 m	JZSP-CLN14-05-E		
		10 m	JZSP-CLN14-10-E		
		15 m	JZSP-CLN14-15-E		
		20 m	JZSP-CLN14-20-E		
	SGLTW- □□D□□□□□D	1 m	JZSP-CLN15-01-E		(4)
		3 m	JZSP-CLN15-03-E		
		5 m	JZSP-CLN15-05-E		
		10 m	JZSP-CLN15-10-E		
		15 m	JZSP-CLN15-15-E		
		20 m	JZSP-CLN15-20-E		

*1: Connector by Tyco Electronics AMP K.K.
*2: MS connector
*3: Connector by Interconnectron GmbH

NOTE: Shaded items are non-stock.


(cont'd)

Selecting Cables

Name	Applicable Linear Servomotor Model	Length	Order No.	Specifications	Details
② Cables for Connecting Linear Scales*	All models	1 m	JZSP-CLL00-01-E		(5)
		3 m	JZSP-CLL00-03-E		
		5 m	JZSP-CLL00-05-E		
		10 m	JZSP-CLL00-10-E		
		15 m	JZSP-CLL00-15-E		
③ Cables for Connecting Serial Converter Units	All models	1 m	JZSP-CLP70-01-E		(6)
		3 m	JZSP-CLP70-03-E		
		5 m	JZSP-CLP70-05-E		
		10 m	JZSP-CLP70-10-E		
		15 m	JZSP-CLP70-15-E		
		20 m	JZSP-CLP70-20-E		
④ Cables for Connecting Hall Sensors	All models	1 m	JZSP-CLL10-01-E		(7)
		3 m	JZSP-CLL10-03-E		
		5 m	JZSP-CLL10-05-E		
		10 m	JZSP-CLL10-10-E		
		15 m	JZSP-CLL10-15-E		

* When using serial converter unit JZSP-GD00□ - □□□ -E, the maximum cable length is 3 m.

(1) Linear Servomotor Main Circuit Cables: JZSP-CLN21-□□-E




● Wiring Specifications

SERVOPACK-end Leads		Linear Servomotor-end Connector	
Wire Color	Signal	Signal	Pin No.
Red	Phase U	Phase U	1
White	Phase V	Phase V	2
Blue	Phase W	Phase W	3
Green/yellow	FG	FG	4

(2) Linear Servomotor Main Circuit Cables: JZSP-CLN39-□□-E

A connector is not provided on the linear-servomotor end of the main circuit cable (JZSP-CLN39-□□-E).
This connector is provided by the customer.




● Wiring Specifications

SERVOPACK-end Leads		Linear Servomotor-end Connector	
Wire Color	Signal	Signal	Pin No.
Red	Phase U	Phase U	1
White	Phase V	Phase V	2
Blue	Phase W	Phase W	3
Green/yellow	FG	FG	4


Selecting Cables

●JZSP-CLN39 Cable Connectors



Applicable Linear Servomotor Model	Attached Connector	Plug		Cable Clamp
		Straight	Straight L-shaped	
SGLTW-40, -80	MS3102A22-22P	MS3106B22-22S or MS3106A22-22A	MS3108B22-22S	MS3057-12A


(a) MS3106B: Straight Plug with Front-shell and Back-shell Separated



Units: mm

Shell Size	Joint Screw A	Joint Length J±0.12	Max. Overall Length L	Outer Diameter of Nut $Q^{+0}_{-0.38}$	Cable Clamp Mounting Screw V	Min. Effective Screw Length W	Max. Width Y
22	1 3/8 -18UNEF	18.26	55.57	40.48	1 3/16 -18UNEF	9.53	50


(b) MS3106A: Straight Plug with Solid Shell



Units: mm

Shell Size	Joint Screw A	Joint Length J±0.12	Overall Length L±0.5	Outer Diameter of Nut $Q^{+0}_{-0.38}$	Outer Diameter N±0.5	Cable Clamp Mounting Screw V	Min. Effective Screw Length W
22	1 3/8 -18UNEF	18.26	54	40.48	34.99	1 3/16-18UNEF	9.53


(c) MS3108B: L-shaped Plug with Front-shell and Back-shell Separated



Units: mm

Shell Size	Joint Screw A	Joint Length J±0.12	Max. Overall Length L	R ±0.5	U ±0.5	Outer Diameter of Nut $Q^{+0}_{-0.38}$	Cable Clamp Mounting Screw V	Min. Effective Screw Length W
22	1 3/8 -18UNEF	18.26	76.98	24.1	33.3	40.48	1 3/16 -18UNEF	9.53

(d) MS3057-12A: Cable Clamp with Rubber Bushing




Units: mm

Applicable Shell Size	Overall Length A±0.7	Effective Screw Length C	E	G±0.7	H	J	Mounting Screw V	Outer Diameter Q±0.7	Rubber Bushing Type
20, 22	23.8	10.3	19.0	37.3	4.0	15.9	1 3/16 -18UNEF	35.0	AN3420 -12

(3) Linear Servomotor Main Circuit Cables: JZSP-CLN14-□□-E

● Wiring Specifications



SERVOPACK-end Leads


Wire Color	Signal
Black (White 1)	Phase U
Black (White 2)	Phase V
Black (White 3)	Phase W
Green / yellow	FG

Linear Servomotor-end Connector

Signal	Pin No.
Phase U	1
Phase V	2
Phase W	3
—	4
—	5
FG	6

(4) Linear Servomotor Main Circuit Cables: JZSP-CLN15-□□-E

● Wiring Specifications




SERVOPACK-end Leads

Wire Color	Signal
Red	Phase U
White	Phase V
Black	Phase W
Green / yellow	FG

Linear Servomotor-end Connector

Signal	Pin No.
Phase U	1
Phase V	2
FG	3
Phase W	4
—	5
—	6

(2) Cables for Connecting Linear Scales: JZSP-CLL00-□□-E



● Wiring Specifications

Serial Converter Unit End


Pin No.	Signal
1	/Cos(V1-)
2	/Sin(V2-)
3	Ref(V0+)
4	+5V
5	5Vs
6	BID
7	Vx
8	Vq
9	Cos(V1+)
10	Sin(V2+)
11	/Ref(V0+)
12	0V
13	0Vs
14	DIR
15	Inner
Case	Shield

Linear Scale End

Pin No.	Signal
1	/Cos(V1-)
2	/Sin(V2-)
3	Ref(V0+)
4	+5V
5	5Vs
6	BID
7	Vx
8	Vq
9	Cos(V1+)
10	Sin(V2+)
11	/Ref(V0-)
12	0V
13	0Vs
14	DIR
15	Inner
Case	Shield

Selecting Cables

(6) Cables for Connecting Serial Converter Units: JZSP-CLP70-□□-E



- Wiring Specifications


SERVOPACK End

Pin No.	Signal	Wire Color
1	PG5V	Red
2	PG0V	Black
3	–	–
4	–	–
5	PS	Light blue
6	/PS	Light blue/white
Shell	Shield	–

Serial Converter Unit End

Pin No.	Signal	Wire Color
1	+5V	Red
5	0V	Black
3	–	–
4	–	–
2	Phase S output	Light blue
6	Phase /S output	Light blue/white
Case	Shield	–
7	–	–
8	–	–
9	–	–

(7) Cables for Connecting Hall Sensors: JZSP-CLL10-□□-E



- Wiring Specifications

Serial Converter Unit End

Pin No.	Signal
1	+5V
2	Phase U input
3	Phase V input
4	Phase W input
5	0V
6	–
7	–
8	–
9	–
Case	Shield

Hall Sensor End

Pin No.	Signal
1	+5V
2	Phase U input
3	Phase V input
4	Phase W input
5	0V
6	–
7	–
8	–
9	–
Case	Shield

Linear Servomotors

SGLC

(Cylinder Type)



Model Designations

● Combination of Moving Coil and Magnetic Way
(Global Support - Refer to Stock Status Definitions - page viii)

SGL C – D16 A 085 A P – 750 A

- SGL: Linear Σ Series Linear Servomotor
- C: Servomotor Model

Code	Specifications
C	Cylinder type

- D16: Outer Diameter of Magnetic Way
  - D16 : 16 mm
  - D20 : 20 mm
  - D25 : 25 mm
  - D32 : 32 mm
- A: Voltage
  - A : 200 VAC
- 085: Length of Moving Coil

Outer Diameter of Magnetic Way Code	Length of Moving Coil Code	Length of Moving Coil mm	Outer Diameter of Magnetic Way Code	Length of Moving Coil Code	Length of Moving Coil mm
D16	085	85	D25	125	125
	115	115		170	170
	145	145		215	215
D20	100	100	D32	165	165
	135	135		225	225
	170	170		285	285

- A: Design Revision Order of Moving Coil
  - A, B···
- P: Hall Sensor
  - P : With hall sensor (all models)
- 750: Length of Magnetic Way (See the next page)
- A: Design Revision Order of Magnetic Way
  - A, B···

● Moving Coil

SGL C W – D16 A 085 A P

- SGL: Linear Σ Series Linear Servomotor
- C: Servomotor Model

Code	Specifications
C	Cylinder type

- W: W : Moving Coil
- D16: Outer Diameter of Magnetic Way
  - D16 : 16 mm
  - D20 : 20 mm
  - D25 : 25 mm
  - D32 : 32 mm
- A: Voltage
  - A : 200 VAC
- 085: Length of Moving Coil (See above table)
- A: Design Revision Order
  - A, B···
- P: Hall Sensor
  - P : With hall sensor (all models)

● Magnetic Way

SGL C M – D16 300 A

- SGL: Linear Σ Series Linear Servomotor
- C: Servomotor Model

Code	Specifications
C	Cylinder type

- M: M : Magnetic Way*
- D16: Outer Diameter of Magnetic Way
  - D16: 16 mm
  - D20: 20 mm
  - D25: 25 mm
  - D32: 32 mm
- 300: Length of Magnetic Way (See the next page)
- A: Design Revision Order
  - A, B…

* Note: Order the moving coil and magnetic way as a set. Contact your Yaskawa representative before ordering them separately.

Features

- Both coil assemblies supported, easy switching from ball screws.
- Compared to ball screw systems, high-speed and high-precision positioning greatly reduces tact time.
- Unlike ball screws, no contact with machines, no lubrication oil, easy maintenance.


Application Examples

- Semiconductor equipment
- Electronic parts assembly
- Food packaging machines
- Metal processing machines
- General handling machines

◆Magnetic Way Lengths (Global Support - Refer to Stock Status Definitions - page viii)

Moving Coil Model SGLCW-		Magnetic Way Dimensions mm					
		Standard Specifications					Special Orders
		Code = ① mm					Length of Magnetic Way mm
		①	②	③	④	⑤	Min. to Max.
D16A	085AP 115AP 145AP	300	85	30	37.5	140	240 to 420 (30 mm increments)
			115			110	
			145			80	
		510	85	45	52.5	320	480 to 750 (30 mm increments)
			115			290	
			145			260	
		750	85			560	
			115			530	
			145			500	
D20A	100AP 135AP 170AP	350	100	35	45	160	280 to 490 (35 mm increments)
			135			125	
			170			90	
		590	100	50	60	370	555 to 870 (35 mm increments)
			135			335	
			170			300	
		870	100			650	
			135			615	
			170			580	
D25A	125AP 170AP 215AP	450	125	45	57.5	210	360 to 630 (45 mm increments)
			170			165	
			215			120	
		750	125	60	72.5	480	705 to 1110 (45 mm increments)
			170			435	
			215			390	
		1110	125			840	
			170			795	
			215			750	
D32A	165AP 225AP 285AP	600	165	60	75	285	480 to 840 (60 mm increments)
			225			225	
			285			165	
		1020	165	90	105	645	960 to 1500 (60 mm increments)
			225			585	
			285			525	
		1500	165			1125	
			225			1065	
			285			1005	

① Length of Magnetic Way
② Length of Moving Coil
③ Position of Support Section
④ Range Outside the Guaranteed Force
⑤ Effective Strokes



Note: ④Range outside the guaranteed force:
If any part of the moving coil is located within this range, characteristics indicated in *Force and Speed Characteristics* on page 190 cannot be satisfied.

< Calculating Length of Magnetic Way >

②Length of Moving Coil (mm)

④Range Outside the Guaranteed Force (mm)

⑤Effective Strokes (mm)

Formula

◆Length of Magnetic Way

【②+④×2+⑤】(mm)

Ratings and Specifications

Time Rating: Continuous
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40˚C
Excitation: Permanent magnet

Withstand Voltage: 1500 VAC for one minute
Enclosure: Self-cooled
Ambient Humidity: 20% to 80% (no condensation)
Allowable Winding Temperature: 130˚C (Thermal class B)

Linear Servomotor Model SGLC-		D16A			D20A			D25A			D32A		
		085A	115A	145A	100A	135A	170A	125A	170A	215A	165A	225A	285A
Peak Speed*3	m / s	4.0	4.0	4.0	4.0	4.0	4.0	4.0	4.0	4.0	4.0	4.0	4.0
Rated Force*1	N	17	25	34	30	45	60	70	105	140	90	135	180
Rated Current*1	A_{rms}	0.59	0.53	0.66	0.98	0.98	1.19	1.42	1.75	3.49	1.57	2.79	2.79
Instantaneous Peak Force*1	N	60	90	120	150	225	300	280	420	560	420	630	840
Instantaneous Peak Current*1	A_{rms}	2.07	2.07	2.52	4.90	4.90	5.95	5.68	6.98	12.96	7.32	13.01	13.01
Moving Coil Mass	kg	0.3	0.4	0.5	0.6	0.8	1.0	1.0	1.4	1.8	1.8	2.5	3.2
Force Constant	N / A_{rms}	31.2	46.8	51.3	33.0	49.5	54.3	53.1	64.8	43.2	61.8	52.2	69.6
BEMF Constant	V/(m/s)	10.4	15.6	17.1	11.0	16.5	18.1	17.7	21.6	14.4	20.6	17.4	23.2
Motor Constant	$N/\sqrt{W}$	4.8	5.9	6.7	7.5	9.2	10.4	10.0	12.4	15.4	16.2	20.0	23.0
Electrical Time Constant	ms	0.18	0.18	0.17	0.38	0.32	0.41	0.18	0.59	0.65	0.76	1.18	1.58
Mechanical Time Constant	ms	13.1	11.7	11.3	10.70	9.50	9.30	10.1	9.2	7.6	6.9	6.3	6.0
Thermal Resistance With Heat Sink	K / W	3.35	2.9	1.64	1.66	1.45	1.29	1.00	0.68	0.61	0.77	0.53	0.49
Thermal Resistance Without Heat Sink	K / W	6.79	5.24	4.26	4.35	3.38	2.76	2.99	2.29	1.81	1.87	1.43	1.16
Magnetic Attraction*2	N	0	0	0	0	0	0	0	0	0	0	0	0
Applicable SERVOPACK	SGDV-	R70A	R70A	R90A	1R6A	1R6A	2R8A	1R6A	2R8A	5R5A	2R8A	5R5A	5R5A


*1: These items and “Force and Speed Characteristics” are the values at a motor winding temperature of 100˚C during operation in combination with a SERVOPACK. The others are at 20˚C.
*2: Logical magnetic attraction acting between the moving coil and the magnetic way. Because of the gap imbalance created after installing the moving coil and the magnetic way, a magnetic attraction is generated.
*3: The rated speed during operation by speed control with an analog voltage reference must be set to 1.5 m/s.
Note: These specifications show the values under the cooling conditions when a heat sink (aluminum board) listed in the following table is mounted on the moving coil.

Linear Servomotor Model SGLC-	Heat Sink Size mm
D16A085A D16A115A	100×200×12
D16A145A D20A100A D20A135A D20A170A	200×300×12
D25A125A D32A165A	300×400×12
D25A170A D25A215A D32A225A D32A285A	400×500×12

Global Support Product (see page viii)

Ratings and Specifications

●Force and Speed Characteristics A: Continuous Duty Zone B: Intermittent Duty Zone (Note)



Note: When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.

●Mechanical Specifications of Linear Servomotors

(1) Impact Resistance

· Impact acceleration: 98 m/s²
· Impact occurrences: twice

(2) Vibration Resistance

The linear servomotors will withstand the following vibration acceleration in three directions: Vertical, side to side, and front to back.


· Vibration acceleration: Moving Coil: 24.5 m/s²
Magnetic Way: 24.5 m/s² in axis direction
4.9 m/s² in vertically and horizontally

Global support Product (see page vii)


External Dimensions Units: mm

(1) SGLC-D16

- Moving Coil: SGLCW-D16A□□□AP (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor Connector Specifications



Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Name
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor Connector Specifications



Plug: 350779-1
Pin : 350690-3 or
350561-3 (No.1 to 3)
770210-1 (No.4)
by Tyco
Electronics AMP K.K.
The Mating Connector

Cap: 350780-1
Socket: 350925-1 or
770673-1


Pin No.	Name	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG	Green

Moving Coil Model SGLCW-	L1	L2	Approx. Mass* kg
D16A085AP	85	75	0.3
D16A115AP	115	105	0.4
D16A145AP	145	135	0.5

*: The values indicate the mass of moving coil with a hall sensor unit.

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Global Support Product (see page viii)

External Dimensions Units: mm

● Magnetic Way: SGLCM-D16□□□A



Notes: 1 The magnetic way will become deformed if a magnetic attraction with the moving coil is generated.
Take measures over the entire driving range to prevent any interference between the magnetic way and the moving coil after installation.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.


Magnetic Way Model SGLCM-	L1	L2	L3	L4	L5	L6	L7	Approx. Mass kg	Remarks
D16240A	240±1.6	30	180	25	37.5±0.3	165±1.2	37.5	0.38	–
D16270A	270±1.6	30	210	25	37.5±0.3	195±1.2	37.5	0.43	
D16300A	300±1.6	30	240	25	37.5±0.3	225±1.2	37.5	0.48	Standard
D16330A	330±1.6	30	270	25	37.5±0.3	255±1.2	37.5	0.53	–
D16360A	360±1.6	30	300	25	37.5±0.3	285±1.2	37.5	0.58	
D16390A	390±1.6	30	330	25	37.5±0.3	315±1.2	37.5	0.63	
D16420A	420±1.6	30	360	25	37.5±0.3	345±1.2	37.5	0.68	
D16480A	480±2.5	45	390	40	52.5±0.3	375±2.1	52.5	0.75	
D16510A	510±2.5	45	420	40	52.5±0.3	405±2.1	52.5	0.80	Standard
D16540A	540±2.5	45	450	40	52.5±0.3	435±2.1	52.5	0.85	–
D16570A	570±2.5	45	480	40	52.5±0.3	465±2.1	52.5	0.90	
D16600A	600±2.5	45	510	40	52.5±0.3	495±2.1	52.5	0.95	
D16630A	630±2.5	45	540	40	52.5±0.3	525±2.1	52.5	1.0	
D16660A	660±2.5	45	570	40	52.5±0.3	555±2.1	52.5	1.05	
D16690A	690±2.5	45	600	40	52.5±0.3	585±2.1	52.5	1.1	
D16720A	720±2.5	45	630	40	52.5±0.3	615±2.1	52.5	1.15	
D16750A	750±3	45	660	40	52.5±0.3	645±2.5	52.5	1.2	Standard

Global Support Product (see page 11)


External Dimensions Units: mm

(2) SGLC-D20

- Moving Coil: SGLCW-D20A□□□AP (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor Connector Specifications



Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket Connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Name
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor Connector Specifications



Plug: 350779-1
Pin : 350690-3 or
350561-3 (No.1 to 3)
770210-1 (No.4)
by Tyco
Electronics AMP K.K.
The Mating Connector

Cap: 350780-1
Socket: 350925-1 or
770673-1


Pin No.	Name	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG	Green

Moving Coil Model SGLCW-	L1	L2	Approx. Mass* kg
D20A100AP	100	90	0.6
D20A135AP	135	125	0.8
D20A170AP	170	160	1.0

*: The values indicate the mass of moving coil with a hall sensor unit.

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Global Support Product (see page viii)

External Dimensions Units: mm

● Magnetic Way: SGLCM-D20□□□A



Notes: 1 The magnetic way will become deformed if a magnetic attraction with the moving coil is generated.
Take measures over the entire driving range to prevent any interference between the magnetic way and the moving coil after installation.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.


Magnetic Way Model SGLCM-	L1	L2	L3	L4	L5	L6	L7	Approx. Mass kg	Remarks
D20280A	280±1.6	35	210	30	45±0.3	190±1.2	45	0.68	–
D20315A	315±1.6	35	245	30	45±0.3	225±1.2	45	0.77	
D20350A	350±1.6	35	280	30	45±0.3	260±1.2	45	0.86	Standard
D20385A	385±1.6	35	315	30	45±0.3	295±1.2	45	0.95	–
D20420A	420±1.6	35	350	30	45±0.3	330±1.2	45	1.0	
D20455A	455±1.6	35	385	30	45±0.3	365±1.2	45	1.1	
D20490A	490±1.6	35	420	30	45±0.3	400±1.2	45	1.2	
D20555A	555±2.5	50	455	45	60±0.3	435±2.1	60	1.35	
D20590A	590±2.5	50	490	45	60±0.3	470±2.1	60	1.45	Standard
D20625A	625±2.5	50	525	45	60±0.3	505±2.1	60	1.55	–
D20660A	660±2.5	50	560	45	60±0.3	540±2.1	60	1.6	
D20695A	695±2.5	50	595	45	60±0.3	575±2.1	60	1.7	
D20730A	730±2.5	50	630	45	60±0.3	610±2.1	60	1.8	
D20765A	765±2.5	50	665	45	60±0.3	645±2.1	60	1.9	
D20800A	800±2.5	50	700	45	60±0.3	680±2.1	60	2.0	
D20835A	835±2.5	50	735	45	60±0.3	715±2.1	60	2.1	
D20870A	870±3	50	770	45	60±0.3	750±2.5	60	2.2	Standard

Global support Product
see page vii


External Dimensions Units: mm

(3) SGLC-D25

- Moving Coil: SGLCW-D25A□□□AP (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor Connector Specifications




Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Name
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor Connector Specifications



Plug: 350779-1
Pin: (No. 1 to 3)
350561-3 or 350690-3
(No. 4)
350654-1 or 350669-1
by Tyco Electronics AMP K.K.

The Mating Connector

Cap : 350780-1
Socket: 350925-1 or
770673-1


Pin No.	Name	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG	Green

Moving Coil Model SGLCW-	L1	L2	Approx. Mass* kg
D25A125AP	125	110	1.0
D25A170AP	170	153	1.4
D25A215AP	215	200	1.8

*: The values indicate the mass of moving coil with a hall sensor unit.

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Global Support Product (See page iii)

External Dimensions Units: mm

● Magnetic Way: SGLCM-D25□□□A



Notes: 1 The magnetic way will become deformed if a magnetic attraction with the moving coil is generated.
Take measures over the entire driving range to prevent any interference between the magnetic way and the moving coil after installation.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.


Magnetic Way Model SGLCM-	L1	L2	L3	L4	L5	L6	L7	Approx. Mass kg	Remarks
D25360A	360±1.6	45	270	37	57.5±0.3	245±1.2	57.5	1.5	–
D25405A	405±1.6	45	315	37	57.5±0.3	290±1.2	57.5	1.65	
D25450A	450±1.6	45	360	37	57.5±0.3	335±1.2	57.5	1.8	Standard
D25495A	495±1.6	45	405	37	57.5±0.3	380±1.2	57.5	1.95	–
D25540A	540±1.6	45	450	37	57.5±0.3	425±1.2	57.5	2.1	
D25585A	585±1.6	45	495	37	57.5±0.3	470±1.2	57.5	2.25	
D25630A	630±1.6	45	540	37	57.5±0.3	515±1.2	57.5	2.4	
D25705A	705±2.5	60	585	52	72.5±0.3	560±2.1	72.5	2.85	
D25750A	750±2.5	60	630	52	72.5±0.3	605±2.1	72.5	3.0	Standard
D25795A	795±2.5	60	675	52	72.5±0.3	650±2.1	72.5	3.15	–
D25840A	840±2.5	60	720	52	72.5±0.3	695±2.1	72.5	3.3	
D25885A	885±2.5	60	765	52	72.5±0.3	740±2.1	72.5	3.45	
D25930A	930±2.5	60	810	52	72.5±0.3	785±2.1	72.5	3.6	
D25975A	975±2.5	60	855	52	72.5±0.3	830±2.1	72.5	3.75	
D251020A	1020±2.5	60	900	52	72.5±0.3	875±2.1	72.5	3.9	
D251065A	1065±2.5	60	945	52	72.5±0.3	920±2.1	72.5	4.05	
D251110A	1110±3	60	990	52	72.5±0.3	965±2.5	72.5	4.2	Standard

Global Support Product
(see page vii)


External Dimensions Units: mm

(4) SGLC-D32

- Moving Coil: SGLCW-D32A□□□AP (With a connector by Tyco Electronics AMP K.K.)



Hall Sensor Connector Specifications



Pin Connector:
17JE-23090-02 (D8C)
by DDK Ltd.

The Mating Connector

Socket connector:
17JE-13090-02 (D8C)
Stud: 17L-002C or
17L-002C1

Pin No.	Name
1	+5V (Power supply)
2	Phase U
3	Phase V
4	Phase W
5	0V (Power supply)
6	Not used
7	Not used
8	Not used
9	Not used

Linear Servomotor Connector Specifications



Plug: 350779-1
Pin: (No. 1 to 3)
350561-3 or 350690-3
(No. 4)
350654-1 or 350669-1
by Tyco Electronics AMP K.K.

The Mating Connector

Cap: 350780-1
Socket: 350925-1 or
770673-1


Pin No.	Name	Wire Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG	Green

Moving Coil Model SGLCW-	L1	L2	N	Approx. Mass* kg
D32A165AP	165	145	4	1.8
D32A225AP	225	205	4	2.5
D32A285AP	285	265	6	3.2

*: The values indicate the mass of moving coil with a hall sensor unit.

Hall Sensor Output Signals


When the moving coil moves in the direction indicated by the arrow in the figure, the relationship between the hall sensor output signals Su, Sv, Sw and the inverse power of each motor phase Vu, Vv, Vw becomes as shown in the figure below.



Global Support Product (see page xiii)

External Dimensions Units: mm

● Magnetic Way: SGLCM-D32□□□A




Notes: 1 The magnetic way will become deformed if a magnetic attraction with the moving coil is generated.
Take measures over the entire driving range to prevent any interference between the magnetic way and the moving coil after installation.
2 If you have a pacemaker or any other electronic medical device, do not go near the magnetic way of the linear servomotor.

Magnetic Way Model SGLCM-	L1	L2	L3	L4	L5	L6	L7	Approx. Mass kg	Remarks
D32480A	480±1.6	60	360	52	75±0.3	330±1.2	75	3.0	–
D32540A	540±1.6	60	420	52	75±0.3	390±1.2	75	3.4	
D32600A	600±1.6	60	480	52	75±0.3	450±1.2	75	3.8	Standard
D32660A	660±1.6	60	540	52	75±0.3	510±1.2	75	4.2	–
D32720A	720±1.6	60	600	52	75±0.3	570±1.2	75	4.6	
D32780A	780±1.6	60	660	52	75±0.3	630±1.2	75	5.0	
D32840A	840±1.6	60	720	52	75±0.3	690±1.2	75	5.4	
D32960A	960±2.5	90	780	82	105±0.3	750±2.1	105	5.9	
D321020A	1020±2.5	90	840	82	105±0.3	810±2.1	105	6.3	Standard
D321080A	1080±2.5	90	900	82	105±0.3	870±2.1	105	6.7	–
D321140A	1140±2.5	90	960	82	105±0.3	930±2.1	105	7.1	
D321200A	1200±2.5	90	1020	82	105±0.3	990±2.1	105	7.5	
D321260A	1260±2.5	90	1080	82	105±0.3	1050±2.1	105	7.9	
D321320A	1320±2.5	90	1140	82	105±0.3	1110±2.1	105	8.3	
D321380A	1380±2.5	90	1200	82	105±0.3	1170±2.1	105	8.7	
D321440A	1440±2.5	90	1260	82	105±0.3	1230±2.1	105	9.1	
D321500A	1500±3	90	1320	82	105±0.3	1290±2.5	105	9.5	Standard

Global Support Program
(see page vii)





Selecting Cables

●Cables Connections



Global Support Product (see page vii)


●Cables

Name	Applicable Linear Servomotor Model	Length	Order No.	Specifications	Details
① Linear Servomotor Main Circuit Cables	All models	1 m	JZSP-CLN11-01-E	SERVOPACK End / Linear Servomotor End 	(1)
		3 m	JZSP-CLN11-03-E		
		5 m	JZSP-CLN11-05-E		
		10 m	JZSP-CLN11-10-E		
		15 m	JZSP-CLN11-15-E		
② Cables for Connecting Linear Scales	All models	1 m	JZSP-CLL00-01-E	Serial Converter Unit End / Linear Scale End 	(2)
		3 m	JZSP-CLL00-03-E		
		5 m	JZSP-CLL00-05-E		
		10 m	JZSP-CLL00-10-E		
		15 m	JZSP-CLL00-15-E		
③ Cables for Connecting Serial Converter Units	All models	1 m	JZSP-CLP70-01-E	SERVOPACK End / Serial Converter Unit End 	(3)
		3 m	JZSP-CLP70-03-E		
		5 m	JZSP-CLP70-05-E		
		10 m	JZSP-CLP70-10-E		
		15 m	JZSP-CLP70-15-E		
		20 m	JZSP-CLP70-20-E		
④ Cables for Connecting Hall Sensors	All models	1 m	JZSP-CLL10-01-E	Serial Converter Unit End / Hall Sensor Unit End 	(4)
		3 m	JZSP-CLL10-03-E		
		5 m	JZSP-CLL10-05-E		
		10 m	JZSP-CLL10-10-E		
		15 m	JZSP-CLL10-15-E		

* When using serial converter unit JZDP-G00□-□□□-E, the maximum cable length is 3 m.

Selecting Cables

(1) Linear Servomotor Main Circuit Cables:
JZSP-CLN11-□□-E



· Wiring Specifications


SERVOPACK-end Leads

Wire Color	Signal
Red	Phase U
White	Phase V
Blue	Phase W
Green/yellow	FG

Linear Servomotor-end Connector

Signal	Pin. No.
Phase U	1
Phase V	2
Phase W	3
FG	4

(2) Cables for Connecting Linear Scales:
JZSP-CLL00-□□-E



· Wiring Specifications


Serial Converter Unit End

Pin No.	Signal
1	/Cos(V1–)
2	/Sin(V2–)
3	Ref(V0+)
4	+5V
5	5Vs
6	BID
7	Vx
8	Vq
9	Cos(V1+)
10	Sin(V2+)
11	/Ref(V0+)
12	0V
13	0Vs
14	DIR
15	Inner
Case	Shield

Linear Scale End

Pin No.	Signal
1	/Cos(V1–)
2	/Sin(V2–)
3	Ref(V0+)
4	+5V
5	5Vs
6	BID
7	Vx
8	Vq
9	Cos(V1+)
10	Sin(V2+)
11	/Ref(V0–)
12	0V
13	0Vs
14	DIR
15	Inner
Case	Shield

(3) Cables for Connecting Serial Converter Units:
JZSP-CLP70-□□-E



· Wiring Specifications


SERVOPACK End

Pin No.	Signal	Wire Color
1	PG5V	Red
2	PG0V	Black
3	-	-
4	-	-
5	PS	Light blue
6	/PS	Light blue/white
Shell	Shield	-

Serial Converter Unit End

Pin No.	Signal	Wire Color
1	+5V	Red
5	0V	Black
3	-	-
4	-	-
2	Phase S output	Light blue
6	Phase /S output	Light blue/white
Case	Shield	-
7	-	-
8	-	-
9	-	-

(4) Cables for Connecting Hall Sensors
JZSP-CLL10-□□-E



· Wiring Specifications

Serial Converter Unit End

Pin No.	Signal
1	+5V
2	Phase U input
3	Phase V input
4	Phase W input
5	0V
6	-
7	-
8	-
9	-
Case	Shield

Hall Sensor End

Pin No.	Signal
1	+5V
2	Phase U input
3	Phase V input
4	Phase W input
5	0V
6	-
7	-
8	-
9	-
Case	Shield

Global Support Product (see page viii)

Serial Converter Unit (Model: JZDP-□00□-□□□-E)

●Characteristics and Specifications

Items		JZDP-D00□-□□□-E	JZDP-G00□-□□□-E
Electrical Characteristics	Power Supply Voltage	+5.0V±5%, ripple content 5% max.	
	Current Consumption*1	120 mA Typ. 350 mA max.	
	Signal Resolution	Input two-phase sine wave: 1/256 pitch	Input two-phase sine wave: 1/4096 pitch
	Max. Response Frequency	250 kHz	100 kHz
	Analog Input Signals*2 (cos, sin, Ref)	Differential input amplitude: 0.4 to 1.2 V Input signal level: 1.5 to 3.5 V	
	Hall Sensor Input Signal	CMOS level	
	Output Signals*3	Position data, hall sensor information, and alarms	
	Output Method	Serial data transmission	
	Output Circuit	Balanced transceiver (SN75LBC176 or the equivalent) Internal terminal resistance: 120 Ω	
Mechanical Characteristics	Approx. Mass	150 g	
	Vibration Resistance	98 m/s^2 max. (10 to 2500 Hz) in three directions	
	Impact Resistance	980 m/s^2, (11 ms) two times in three directions	
Environmental Conditions	Ambient Temperature	0 to 55°C	
	Storage Temperature	−20 to +80°C	
	Humidity	20% to 90% RH (no condensation)	

*1: The current consumption of the linear scale and hall sensor is not included in this value.
The current consumption of linear scale and hall sensor must be taken into consideration for the current capacity of host controller that supplies the power. The current consumption of hall sensor: Approx. 40 mA.




*2: Input a value within the specified range. Otherwise, incorrect position information is output, and the device may be damaged.

*3: The power is turned on, and the transmission is enabled after 100 ms to 300 ms.

Serial Converter Unit (Model: JZDP-□00□-□□□-E)

●Model Designations

JZDP - □00□ - □□□ - E


Serial Converter Unit Model			
Code	Appearance	Applicable Linear Scale	Hall Sensor
D003 G003		Manufactured by HEIDENHAIN Corp.	None
D005 G005		Manufactured by RENISHAW plc.	None
D006 G006		Manufactured by HEIDENHAIN Corp.	Provided
D008 G008		Manufactured by RENISHAW plc.	Provided

Applicable Linear Servomotor					
Servomotor Model		Symbol	Servomotor Model		Symbol
SGLGW- (Coreless) When a standard-force magnetic way is used.	30A050C	250	SGLTW- (Iron core, T-type)	20A170A	011
	30A080C	251		20A320A	012
	40A140C	252		20A460A	013
	40A253C	253		35A170A	014
	40A365C	254		35A320A	015
	60A140C	258		35A460A	016
	60A253C	259		35A170H	105
	60A365C	260		35A320H	106
	90A200C	264		50A170H	108
	90A370C	265		50A320H	109
	90A535C	266		40A400B	185
SGLGW- + SGLGM-□□□-M (Coreless) When a high-force magnetic way is used	40A140C	255		40A600B	186
	40A253C	256		80A400B	187
	40A365C	257		80A600B	188
	60A140C	261		35D170H	193
	60A253C	262		35D320H	194
	60A365C	263		50D170H	195
SGLFW- (Iron core, F-type)	20A090A	017		50D320H	196
	20A120A	018		40D400B	197
	35A120A	019		40D600B	198
	35A230A	020		80D400B	199
	50A200B	181		80D600B	200
	50A380B	182	SGLC-	D16A085AP	354
	1ZA200B	183		D16A115AP	373
	1ZA380B	184		D16A145AP	356
	35D120A	211		D20A100AP	357
	35D230A	212		D20A135AP	358
	50D200B	189		D20A170AP	359
	50D380B	190		D25A125AP	360
	1ZD200B	191		D25A170AP	374
	1ZD380B	192		D25A215AP	362
				D32A165AP	363
				D32A225AP	364
				D32A285AP	365

■ Non-Stock Items
□ Global Stock Items

●Analog Signal Input Timing

The following figure shows the input timing of the analog signals.
When the cos and sin signals are shifted 180 degrees, the differential signals are the /cos and /sin signals.
The specifications of the cos, /cos, sin, and /sin signals are identical except for the phase.
Input the signals Ref and /Ref so that they shall cross each other as shown in the figure because they are input into the converter. When they are crossed, the output data will be counted up.



*:If the analog signal amplitude declines to about 0.35 V because of differential amplitude, the serial converter outputs an alarm.

IMPORTANT

■ Precautions


1 Never perform insulation resistance and withstand voltage tests.
2 When analog signals are input to the serial converter unit, noise influence on the analog signals affects the unit's ability to output correct position information. The analog cable must be as short as possible and shielded.
3 Use the serial converter unit without gases such as H_2S.
4 Do not connect or disconnect the unit while power is being supplied, or the unit may be damaged.
5 When using multiple axes, use a shield cable for each axis. Do not use a shield cable for multiple axes.

Serial Converter Unit (Model: JZDP-□00□-□□□-E) Units: mm

●Without Cable for Hall Sensor (For Linear Scale by HEIDENHAIN Corporation)


Serial Converter Unit Model: JZDP-□003-□□□-E

(1) Connection Example




* When using serial converter unit JZDP-G00□-□□□-E, the maximum cable length is 3 m.

(2) External Dimensions



Pin No.	Signal
1	+5V
2	Phase S output
3	Not used
4	Not used
5	0V
6	Phase /S output
7	Not used
8	Not used
9	Not used
Case	Shield


CN1
SERVOPACK End
Serial Data Output



17-series Connector:
17LE-13090-27-FA
(Socket) by DDK Ltd.

Pin No.	Signal
1	cos input (A+)
2	0V
3	sin input (B+)
4	+5V
5	Not used
6	Not used
7	/Ref input (R−)
8	Not used
9	/cos input (A−)
10	0V sensor
11	/sin input (B−)
12	5V sensor
13	Not used
14	Ref input (R+)
15	Not used
Case	Shield

CN2
Linear Scale End
Analog Signal Input



17-series Connector:
17LE-13150-27-FA
(Socket) by DDK Ltd.


Notes: 1 Do not use the unused pins.
2 Contact HEIDENHAIN Corporation for details of connection cables (analog 1 Vp-p output, D-sub 15-pin, male) by HEIDENHAIN Corporation.
3 Use the same terminal for 5-V sensor and phase-W input.
4 Phase U, V, and W input are internally pulled up at 10 kΩ.

Serial Converter Unit (Model: JZDP-□00□-□□□-E) Units: mm

●Without Cable for Hall Sensor (For Linear Scale by Renishaw plc.)


Serial Converter Unit Model: JZDP-□005-□□□-E

(1) Connection Example



* When using serial converter unit JZDP-G00□-□□□-E, the maximum cable length is 3 m.


(2) External Dimensions



Pin No.	Signal
1	+5V
2	Phase S output
3	Not used
4	Not used
5	0V
6	Phase /S output
7	Not used
8	Not used
9	Not used
Case	Shield

SERVOPACK does not have the function to process Vq signals.


CN1
SERVOPACK End
Serial Data Output



17-series Connector:
17LE-13090-27-FA
(Socket) by DDK Ltd.

Pin No.	Signal
1	cos input (V1−)
2	sin input (V2−)
3	Ref input (V0+)
4	+5V
5	5Vs
6	Not used
7	Not used
8	Not used
9	cos input (V1+)
10	sin input (V2+)
11	/Ref input (V0−)
12	0V
13	0Vs
14	Not used
15	inner (0V)
Case	Shield

CN2
Linear Scale End
Analog Signal Input



17-series Connector:
17JE-13150-02 (D8C) A-CG
(Socket) by DDK Ltd.


Notes: 1 Do not use the unused pins.
2 Contact Renishaw plc. for details of connection cables (analog 1 Vp-p output, D-sub 15-pin, male) by Renishaw plc. However, the BID and DIR signals are not connected.
3 Use the linear scale-end connector to change the zero point specifications of the linear scale.

Serial Converter Unit (Model: JZDP-□00□-□□□-E) Units: mm

●With Cable for Hall Sensor (For Linear Scale by HEIDENHAIN Corporation)


Serial Converter Unit Model: JZDP-□006-□□□-E

(1) Connection Example




* When using serial converter unit JZDP-G00□-□□□-E, the maximum cable length is 3 m.

(2) External Dimensions




CN1
SERVOPACK End
Serial Data Output



17-series Connector:
17LE-13090-27-FA
(Socket) by DDK Ltd.

Pin No.	Signal
1	+5V
2	Phase S output
3	Not used
4	Not used
5	0V
6	Phase /S output
7	Not used
8	Not used
9	Not used
Case	Shield


CN2
Linear Scale End
Analog Signal Input



17-series Connector:
17JE-13150-02 (D8C) A-CG
(Socket) by DDK Ltd.

Pin No.	Signal
1	cos input (A+)
2	0V
3	sin input (B+)
4	+5V
5	Not used
6	Not used
7	/Ref input (R−)
8	Not used
9	/cos input (A−)
10	0V sensor
11	/sin input (B−)
12	5V sensor
13	Not used
14	Ref input (R+)
15	Not used
Case	Shield

CN3
Linear Servomotor End
Hall Sensor Signal Input



17-series Connector:
17JE-13090-02 (D8C) A-CG
by DDK Ltd.

Pin No.	Signal
1	+5V
2	Phase U input
3	Phase V input
4	Phase W input
5	0V
6	Not used
7	Not used
8	Not used
9	Not used
Case	Shield


Notes: 1 Do not use the unused pins.
2 Contact HEIDENHAIN Corporation for details of connection cables (analog 1 Vp-p output, D-sub 15-pin, male) by HEIDENHAIN Corporation.
3 Phase U, V, and W input are internally pulled up at 10 kΩ.

Serial Converter Unit (Model: JZDP-□00□-□□□-E) Units: mm

●With Cable for Hall Sensor (For Linear Scale by Renishaw plc.)


Serial Converter Unit Model: JZDP-□008-□□□-E

(1) Connection Example




* When using serial converter unit JZDP-G00□-□□□-E, the maximum cable length is 3 m.

(2) External Dimensions




CN1
SERVOPACK End
Serial Data Output



17-series Connector:
17LE-13090-27-FA
(Socket) by DDK Ltd.

Pin No.	Signal
1	+5V
2	Phase S output
3	Not used
4	Not used
5	0V
6	Phase /S output
7	Not used
8	Not used
9	Not used
Case	Shield


CN2
Linear Scale End
Analog Signal Input



17-series Connector:
17JE-13150-02 (D8C) A-CG
(Socket) by DDK Ltd.

Pin No.	Signal
1	/cos input (V1−)
2	/sin input (V2−)
3	Ref input (V0+)
4	+5V
5	5Vs
6	Not used
7	Not used
8	Not used
9	cos input (V1+)
10	sin input (V2+)
11	/Ref input (V0−)
12	0 V
13	0 Vs
14	Not used
15	Inner
Case	Shield

CN3
Linear Servomotor End
Hall Sensor Signal Input



17-series Connector:
17JE-13090-02 (D8C) A-CG
by DDK Ltd.

Pin No.	Signal
1	+5V
2	Phase U input
3	Phase V input
4	Phase W input
5	0V
6	Not used
7	Not used
8	Not used
9	Not used
Case	Shield

Notes: 1 Do not use the unused pins.
2 Contact Renishaw plc. for details of connection cables (analog 1 Vp-p output, D-sub 15-pin, male) by Renishaw plc. However, the BID and DIR signals are not connected.
3 Use the linear scale-end connector to change the zero point specifications of the linear scale.
4 Phase U, V, and W input are internally pulled up at 10 kΩ.

Flexible Cables


●Life of Flexible Cable

The flexible cable supports 10,000,000 or more operations of bending life with the recommended bending radius R.
The following table shows the recommended bending radius R of each cable.

Cable Type	Model	Recommended Bending Radius mm
Linear Servomotor Main Circuit Cables	JZSP-CLN11-□□-E	35
	JZSP-CLN21-□□-E	38
	JZSP-CLN39-□□-E	50
	JZSP-CLN14-□□-E	35
Cables for Connecting Linear Scales	JZSP-CLL00-□□-E	57
Cables for Connecting Hall Sensors	JZSP-CLL10-□□-E	46
Cables for Connecting Serial Converter Units	JZSP-CLP70-□□-E	46

●Conditions

1 Repeat moving one end of the cable forward and backward for 320 mm with using the test equipment shown in the following figure.
2 Connect the lead wires in parallel, and count the number of cable return motion times until a lead wire is disconnected. Note that one reciprocating is counted as one test.



Notes: 1 The life of flexible cable differs largely depending on the amount of mechanical shocks, mounting to the cable, and fixing methods.
The life of flexible cable is limited under the specified conditions.
2 The life of flexible cable indicates the number of bending times in which lead wires are electrically conducted and by which no cracks and damages that affects the performance of cable sheathing are caused. Disconnecting the shield wire is not taken into account.

●Wiring Precautions

Even if the recommended bending radius R is respected in the mechanical design, incorrect wiring may cause early disconnection. Observe the following precautions when wiring.

(1) Cable twisting
Straighten the flexible cables before wiring.
Twisted cables cause early disconnection. Check the indication on the cable surface to make sure that the cable is not twisted.

(2) Fixing method
Do not fix the moving points of the flexible cable. Stress on the fixed points may cause early disconnection. Fix the cable at the minimum number of points.


(3) Cable length
If the cable length is too long, it may cause the cable's sagging. Besides the cable length is too short, it may cause the excessive tension on the fixed points that will cause early disconnection. Use a flexible cable with the optimum length.

(4) Interference between cables
Avoid interference between cables.
Interference limits the motion of flexible cable, which causes early disconnection. Keep enough distance between cables, or provide a partition when wiring.

Linear Slides

NEW!

Σ-Trac



Model Designation

SGT 1 F3 1 - 030 AR 20 - 0 4

Σ-Trac Series
Linear Slide

Linear Slide Type
1 : Standard
(Aluminum base)

Mounted Linear Servomotor

Moving Coil Model	Voltage	Code
SGLFW-35A120A	200 V	F3
SGLFW-35A230A		F4
SGLFW-50A200B		F9
SGLFW-50A380B		FA
SGLFW-35D120A	400 V	FD
SGLFW-35D230A		FE
SGLFW-50D200B		FF
SGLFW-50D380B		FG

Number of Tables (per Axis)
1 : 1 table

Stroke Length
007 : 70 mm
to
195 : 1950 mm

Standard

Linear Scale Resolution
20 : 20 μm

Surface Treatment
0 : Aluminum base: Clear anodized

* Options:
4: Cable Track Assembly

* Limit sensors and covers sold separately. See Cables, Connectors, and Accessories.

Features

- Factory assembled, fully integrated linear motor driven slide reduces machine design complexity and commissioning time.
- Automatic motor recognition by Yaskawa amplifiers eliminates need for user to input motor coil parameters.
- Long strokes and high-speed, high accuracy positioning.
- Large integrated cable carrier allows space for peripheral cables and hoses.
- Covers and accessories available as accessories (up to 1 m stroke).
- See www.yaskawa.com for "Quick Ship" program details.


Application Examples

- Pick and Place
- Precision Dispensing
- Vision Inspection
- Laser Cutting/Machining.
- Engraving
- Flat Panel Display Manufacture (LCD Substrate Handling)
- Industrial Laser and Ink Jet Printing
- Electronic Component Assembly
- Insertion Machines (Packaging)

Model Classification

Force

SERVOPACK Model SGDV-			Σ-Trac Series Linear Slides
Single-phase 100 VAC	Three-phase 200 VAC	Three-phase 400 VAC	Model
2R1F	1R6A	–	SGT1F31-□□□
–	–	1R9D	SGT1FD1-□□□
–	3R8A	–	SGT1F41-□□□
–	–	1R9D	SGT1FE1-□□□
–	5R5A	–	SGT1F91-□□□
–	–	3R5D	SGT1FF1-□□□
–	120A	–	SGT1FA1-□□□
–	–	5R4D	SGT1FG1-□□□



Stroke Length

Model	Stroke Length
SGT1F31-□□□ SGT1FD1-□□□	80 mm – 1950 mm
SGT1F41-□□□ SGT1FE1-□□□	180 mm – 1830 mm
SGT1F91-□□□ SGT1FF1-□□□	70 mm – 1830 mm
SGT1FA1-□□□ SGT1FG1-□□□	170 mm – 1650 mm

SGT1F31, SGT1F41, SGT1FD1, and SGT1FE1 Linear Slides

●Ratings and Specifications

Time Rating: Continuous
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40˚C
Excitation: Permanent magnet
Withstand Voltage: 1500 VAC for one minute
Enclosure: Self-cooled
Ambient Humidity: 20% to 80% (no condensation)
Winding Insulation: Class A

Linear Slide Model*1		200 V Models		400 V Models	
		SGT1F31-□□□ AR20-04	SGT1F41-□□□ AR20-04	SGT1FD1-□□□ AR20-04	SGT1FE1-□□□ AR20-04
Mounted Linear Servomotor Model	SGLFW-	35A120AP	35A230AP	35D120AP	35D230AP
Applicable SERVOPACK Model	SGDV-	2R1F, 1R6A	3R8A	1R9A	1R9A
Mounted Serial Converter Unit Model	JZDP-	D008-019	D008-020	D008-211	D008-212
Rated Force	N	80	160	80	160
Peak Force	N	220	440	220	440
Force Constant	N / A_{rms}	62.4	62.4	136	136
Motor Constant	$N / \sqrt{W}$	14.4	20.4	14.2	20.1
Maximum Payload*2, *3	kg	30	70	30	70
Movable Member Mass	kg	4.3	6.6	4.3	6.6
Total Mass	kg	See Table 1 on the next page.	See Table 2 on the next page.	See Table 1 on the next page.	See Table 2 on the next page.
Effective Stroke	mm				
Resolution	μm	0.078 (20 μm / 256)		0.078 (20 μm / 256)	
Repeatability*4	μm	±1.0	±1.0	±1.0	±1.0
Absolute Accuracy	μm	Consult factory		Consult factory	
Straightness and Flatness	μm	Consult factory		Consult factory	


*1: Squares (□□□) are used to indicate the stroke length code shown in Tables 1 and 2.
*2: Values obtained when the acceleration is 4.9 m/s².
*3: Contact your Yaskawa representative if the expected payload exceeds the value indicated in the table.
*4: Values obtained when the ambient temperature is constant.

●Performance Curves


● Force - Speed

A : Continuous Duty Zone
B : Intermittent Duty Zone (Note)

(1) SGT1F31, SGT1FD1




(2) SGT1F41, SGT1FE1




Note: When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.


● Effective Force - Ambient Temperature


When the sensor temperature is 50˚C or less
Average speed (m/s) : 0 — 1 — 2
Note: Average speed=Total movement distance (m)/ cycle time (s)





● Load Mass - Acceleration







SGT1F31, SGT1F41, SGT1FD1, and SGT1FE1 Linear Slides Units: mm

●External Dimensions

(1) SGT1F31, SGT1FD1










Table 1

Stroke Code	Stroke Length	L1 mm	L2 mm	L3 mm	L4 mm	L5 mm	N	Total Mass kg
008	80	360	295	270	45	90	4	10.4
030	300	580	515	440			5	14.4
041	410	690	625	550			6	16.3
052	520	800	735	660			7	18.2
063	630	910	845	770			8	20.0
074	740	1020	955	880			9	21.9
085	850	1130	1065	990			10	23.9
096	960	1240	1175	1100			11	26.0
107	1070	1350	1285	1210	70	110	12	27.8
118	1180	1460	1395	1320			13	29.8
129	1290	1570	1505	1430			14	31.6
140	1400	1680	1615	1540			15	33.5
151	1510	1790	1725	1650			16	35.6
162	1620	1900	1835	1760			17	37.5
173	1730	2010	1945	1870			18	39.4
184	1840	2120	2055	1980			19	41.3
195	1950	2230	2165	2090			20	43.2

(2) SGT1F41, SGT1FE1









Table 2

Stroke Code	Stroke Length	L1 mm	L2 mm	L3 mm	L4 mm	L5 mm	N	Total Mass kg
018	180	580	515	440			5	16.5
029	290	690	625	550			6	18.5
040	400	800	735	660			7	20.4
051	510	910	845	770			8	22.2
062	620	1020	955	880			9	24.2
073	730	1130	1065	990			10	26.1
084	840	1240	1175	1100			11	28.6
095	950	1350	1285	1210	70	110	12	30.1
106	1060	1460	1395	1320			13	32.0
117	1170	1570	1505	1430			14	33.8
128	1280	1680	1615	1540			15	35.8
139	1390	1790	1725	1650			16	37.7
150	1500	1900	1835	1760			17	39.8
161	1610	2010	1945	1870			18	41.6
172	1720	2120	2055	1980			19	43.6
183	1830	2230	2165	2090			20	44.3

Notes: 1 The moving coil moves in the direction indicated by the arrow when current flows in the order of phase U, V, and W.
2 When installing the linear slide, the surface should be flat to the equivalent of a maximum discrepancy of 0.02/200 mm (reference value).

• Connector Specifications for the Σ-Trac Series Linear Slides (All Models)

View X-X



Plug : 350779-1
(by Tyco Electronics AMP K.K.)
Pins : 350924-1 or 770672-1
(by Tyco Electronics AMP K.K.)

For Motor Cable

Pin No.	Signal
1	Phase-U output
2	Phase-V output
3	Phase-W output
4	FG

View Y-Y

Encoder Plug



Plug : 55100-0600
(by Molex.)
Connector (Socket):
54280-0600
(by Molex.)

For Encoder Connection

Pin	Signal	Wire Color
1	PG 5V	Red
2	PG 0V	Black
3	–	–
4	–	–
5	Data +	Light Blue
6	Data -	White/Light Blue

SGT1F91, SGT1FA1, SGT1FF1, and SGT1FG1 Linear Slides

●Ratings and Specifications

Time Rating: Continuous
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0 to 40˚C
Excitation: Permanent magnet
Withstand Voltage: 1500 VAC for one minute
Enclosure: Self-cooled
Ambient Humidity: 20% to 80% (no condensation)
Winding Insulation: Class A

Linear Slide Model*1		200 V Models		400 V Models	
		SGT1F91-□□□ AR20-04	SGT1FA1-□□□ AR20-04	SGT1FF1-□□□ AR20-04	SGT1FG1-□□□ AR20-04
Mounted Linear Servomotor Model	SGLFW-	50A200BP	50A380BP	50D200BP	50D380BP
Applicable SERVOPACK Model	SGDV-	5R5A	120A	3R5D	5R4D
Applicable Serial Converter Unit Model	JZDP-	D008-181	D008-182	D008-189	D008-190
Rated Force	N	280	560	280	560
Peak Force	N	600	1200	600	1200
Force Constant	N / A_{rms}	60.2	60.2	134.7	134.7
Motor Constant	$N / \sqrt{W}$	34.3	48.5	34.4	47.2
Maximum Payload*2, *3	kg	100	215	100	215
Movable Member Mass	kg	8.5	14.5	8.5	14.5
Total Mass	kg	See Table 1 on the next page.	See Table 2 on the next page.	See Table 1 on the next page.	See Table 2 on the next page.
Effective Stroke	mm				
Resolution	μm	0.078 (20 μm / 256)		0.078 (20 μm / 256)	
Repeatability*4	μm	±1.0		±1.0	
Absolute Accuracy	μm	Consult factory		Consult factory	
Straightness and Flatness	μm	Consult factory		Consult factory	


*1: Squares (□□□) are used to indicate the stroke length code shown in Tables 1.
*2: Values obtained when the acceleration is 4.9 m/s².
*3: Contact your Yaskawa representative if the expected payload exceeds the value indicated in the table.
*4: Values obtained when the ambient temperature is constant.

●Performance Curves


● Force - Speed

A : Continuous Duty Zone
B : Intermittent Duty Zone (Note)

(1) SGT1F91, SGT1FF1




(2) SGT1FA1, SGT1FG1




Note: When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.


● Effective Force - Ambient Temperature


When the sensor temperature is 50˚C or less
Average speed (m/s) : 0 — 1 — 2
Note: Average speed=Total movement distance (m)/ cycle time (s)





● Load Mass - Acceleration








SGT1F91, SGT1FA1, SGT1FF1, and SGT1FG1 Linear Slides Units: mm

●External Dimensions

(1) SGT1F91, SGT1FF1









Note: Endplate removed in this view


Table 1

Stroke		L1	L2	L3	L4	L5	N	Total Mass
Code	Length	mm	mm	mm	mm	mm		kg
007	70	440	375	300	70	100	4	17.3
035	350	720	655	540	90	135	5	22.8
048	480	850	785	675	87.5		6	25.6
062	620	990	925	810	90		7	28.4
075	750	1120	1055	945	87.5		8	31.0
089	890	1260	1195	1080	90		9	33.8
102	1020	1390	1325	1215	87.5		10	36.6
116	1160	1530	1465	1350	90		11	39.3
129	1290	1660	1595	1485	87.5		12	41.9
143	1430	1800	1735	1620	90		13	44.7
156	1560	1930	1865	1755	87.5		14	47.5
170	1700	2070	2005	1890	90		15	50.2
183	1830	2200	2135	2025	87.5		16	53.0

(2) SGT1FA1, SGT1FG1








Note: Endplate removed in this view

Table 2

Stroke		L1	L2	L3	L4	L5	N	Total Mass
Code	Length	mm	mm	mm	mm	mm		kg
017	170	720	655	540	90	135	5	28.7
030	300	850	785	675	87.5		6	31.6
044	440	990	925	810	90		7	34.4
057	570	1120	1055	945	87.5		8	37.0
071	710	1260	1195	1080	90		9	39.7
084	840	1390	1325	1215	87.5		10	42.6
098	980	1530	1465	1350	90		11	45.3
111	1110	1660	1595	1485	87.5		12	47.9
125	1250	1800	1735	1620	90		13	50.6
138	1380	1930	1865	1755	87.5		14	53.4
152	1520	2070	2005	1890	90		15	56.2
165	1650	2200	2135	2025	87.5		16	58.9

Notes: 1 The moving coil moves in the direction indicated by the arrow when current flows in the order of phase U, V, and W.
2 When installing the linear Slide, the surface should be flat to the equivalent of a maximum discrepancy of 0.02/200 mm (reference value).

●Connection diagrams



Selecting Cables, Connectors, and Accessories

●Applicable Cables and Connectors

Motor Type	Linear Scale Type	Servo Drive				Motor Cable	Linear Scale Connection Cables	Pulse-train or Analog Voltage Reference		
		Σ-Trac Series Model	SERVOPACK Model SGDV-			SERVOPACK ↔ Motor	[CN2] ↔ Encoder Cable	I/O Signal Connector [CN1]		
			Single-phase 100 V	Three-phase 200 V	Three-phase 400 V	Power Cable (Flexible Type)	Serial Cable (Flexible Type)	Connector Terminal Block Converter Unit	Cable with Loose Wires at One End	Connector Kit (CN1)
Moving Coil (MC)	Incremental	SGT1F31-□□□ AR20-04	2R1F,	-	-	JZSP-CLN11-□□	JZSP-CMP00-□□ (A) The numbers in the boxes(□□) indicate the cable length. 03 = 3 m 05 = 5 m 10 = 10 m 15 = 15 m 20 = 20 m	JUSP-TA50PG-E (with a 0.5 m cable)	JZSP-CSI01-□-E The number in the box (□) indicates the cable length. 1 = 1 m 2 = 2 m 3 = 3 m	JZSP-CSI9-1-E
			-	1R6A	-					
		SGT1FD1-□□□ AR20-04	-	-	1R9D					
		SGT1F41-□□□ AR20-04	-	3R8A	-	JZSP-CLN11-□□				
		SGT1FE1-□□□ AR20-04	-	-	1R9D					
		SGT1F91-□□□ AR20-04	-	5R5A	-	JZSP-CLN21-□□				
		SGT1FF1-□□□ AR20-04	-	-	3R5D					
		SGT1FA1-□□□ AR20-04	-	120A	-	JZSP-CLN21-□□				
		SGT1FG1-□□□ AR20-04	-	-	5R4D					

Motor Type	Linear Scale Type	Servo Drive				MECHATROLINK Communications			Cables for Setting Devices/Monitors	
		Σ-Trac Series Model	SERVOPACK Model SGDV-			I/O Signal Connector [CN1]		MECHATROLINK Communications Connector [CN6A] or [CN6B]	[CN3]↔Setting Devices	[CN5]
			Single-phase 100 V	Three-phase 200 V	Three-phase 400 V	Connector Terminal Block Converter Cable	Connector Kit (CN1)		Personal Computer Cable	Analog Monitor Cable
Moving Coil (MC)	Incremental	SGT1F31-□□□ AR20-04	2R1F,	-	-	JZSP-TA26P-□-E □→None = 0.5 m 1 = 1 m 2 = 2 m	JZSP-CSI9-2-E (DE9411354)	MECHATROLINK communications cable: JEPMC-W6002-□□-E The numbers in the boxes(□□) indicate the cable length. A5 = 0.5 m 01 = 1 m 03 = 3 m 05 = 5 m 10 = 10 m 20 = 20 m 30 = 30 m 40 = 40 m 50 = 50 m MECHATROLINK terminator: JEPMC-W6022-E	JZDP-CMS02-E (2 m)	JZSP-CA01-E (1 m)
			-	1R6A	-					
		SGT1FD1-□□□ AR20-04	-	-	1R9D					
		SGT1F41-□□□ AR20-04	-	3R8A	-					
		SGT1FE1-□□□ AR20-04	-	-	1R9D					
		SGT1F91-□□□ AR20-04	-	5R5A	-					
		SGT1FF1-□□□ AR20-04	-	-	3R5D					
		SGT1FA1-□□□ AR20-04	-	120A	-					
		SGT1FG1-□□□ AR20-04	-	-	5R4D					

●Applicable Accessories

Cover Kits: SGTA-CVR 3 - 030

Stroke Code for Motor Selected

Motor Code	
3	Covers for SGT1F31, SGT1FD1
4	Covers for SGT1F41, SGT1FE1
9	Covers for SGT1F91, SGT1FF1
A	Covers for SGT1FA1, SGT1FG1

Note: Cover kit includes 1 top cover, 2 side covers, and all mounting hardware.

Stroke Codes		Cover Length (mm)
SGT1F31 SGT1FD1	SGT1F41 SGT1FE1	
008	-	372.7
030	018	592.7
041	029	702.7
052	040	812.7
063	051	922.7
074	062	1032.7
085	073	1142.7
096	084	1252.7
107	095	1362.7

Stroke Codes		Cover Length (mm)
SGT1F91 SGT1FF1	SGT1FA1 SGT1FG1	
007	-	452.7
035	017	732.7
048	030	862.7
062	044	1002.7
075	057	1132.7
089	071	1272.7
102	084	1402.7


Limit Sensor Kits: SGTA-LSK□□□

Code	Description
PNO	PNP Normally Open
NNO	NPN Normally Open
NNC	NPN Normally Closed

Kit includes 1 sensor plus mounting screw.

Linear Slides

Σ-Trac-μ



Model Designation

(Global Support - Refer to Stock Status Definitions - page viii)

SGT M M 03 - 065 A H 20 A P

- SGT: Σ-Trac Series Linear Slide
- M: Moving Magnet Type
- M: Integrally Molded Armature Type
- 03: Peak Force
  - 03 : 25 N
  - 01 : 10 N
- 065: Effective Stroke
  - 010 : 10 mm
  - 025 : 25 mm
  - 030 : 30 mm
  - 065 : 65 mm
- A: Linear Scale Output Form
  - A : Analog output 1 Vp-p
- H: Linear Scale Manufacturer
  - H : HEIDENHAIN Corporation
  - M : MicroE International Inc.
- 20: Linear Scale Resolution
  - 20 : 20 μm
  - 04 : 4 μm
- A: Design Revision Order
  - A, B, C, ...
- P: Options
  - P : With hall sensor

Features

- Ultra-flat profile reduces floorspace requirements.
- For applications requiring short strokes (10 mm to 65 mm)
- Vibration-free transmission device enables high-precision positioning with a repetitive positioning accuracy of ±0.5 μm max.
- Locations of armature coils on fixed side of the stationary member reduce effects of heat on table or workpiece.

Application Examples

- Semiconductor mounters
- Equipment for biomedical
- Optical testing devices

Model Classification

(Global Support - Refer to Stock Status Definitions - page viii)

Force

SERVOPACK (Three-phase 200 VAC) Model SGDV-		Σ-Trac-μ Series Linear Slides	
100V	200V	Model	Force 10 N 20 N 30 N
R70F	R70A	SGTMM01	Rated force / Peak force
R90F	R90A	SGTMM03	

Stroke Length

Model	Stroke Length 50mm 100mm 150mm 200mm
SGTMM01	10 mm, 30 mm
SGTMM03	25 mm, 65 mm

●Ratings and Specifications

Time Rating: Continuous
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0˚C to 40˚C
Excitation: Permanent magnet
Dielectric Strength: 1500 VAC for one minute
Protection Method: Self-cooled
Ambient Humidity: 20% to 80% (no condensation)
Allowable Winding Temperature: 130˚C (Thermal class B)

Linear Slide Model		SGTMM01-010AM20A	SGTMM01-030AM20A	SGTMM03-025AH20AP	SGTMM03-025AH04AP	SGTMM03-065AH20A□	SGTMM03-065AH04AP
Applicable SERVOPACK Model	SGDV-	R70F, R70A		R90F, R90A			
Applicable Serial Converter Unit Model	JZDP-	D003-242-E		D00□-221-E		D00□-220-E	
Rated Force	N	3.5	3.5	7	7	7	7
Peak Force	N	10	10	25	25	25	25
Force Constant	N/A_{rms}	9	9	13.2	13.2	12.3	12.3
Motor Constant	$N/\sqrt{W}$	1.78	1.26	2.29	2.29	1.58	1.58
Maximum Payload*1	kg	1	1	3	3	3	3
Effective Stroke	mm	10	30	25	25	65	65
Resolution	μm	0.078 (20 μm/256)			0.016 (4 μm/256)	0.078 (20 μm/256)	0.016 (4 μm/256)
Movable Member Mass	kg	0.1	0.1	0.215	0.215	0.19	0.19
Total Mass (excluding cables)	kg	0.35	0.31	0.62	0.62	0.63	0.63
Repeatability*2	μm	±0.5	±0.5	±0.5	±0.5	±0.5	±0.5

*1: Values obtained when the acceleration is 4.9 m/s2.
*2: Values obtained when the ambient temperature is constant.


●Performance Curves

● Force - Speed
A : Continuous Duty Zone
B : Intermittent Duty Zone (Note)


● Effective Force - Ambient Temperature
When the sensor temperature is 50 ˚C or less.
Ambient temperature

● Load Mass - Acceleration


(1) SGTMM01










(2) SGTMM03-025








(3) SGTMM003-065








Note: When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.

Global Support Product (See page viii)

SGTMM Linear Slides Units: mm

●External Dimensions


(1) SGTMM01



*: See the next page for the connector specifications.

Linear Slide Model SGTMM01-	L1 mm	L2 mm	L3 mm	L4 mm	L5 mm	L6 mm	L7 mm	L8 mm	L9 mm	N
010AM20A	80	75	63	14	42	8	–	11	22.5	3
030AM20A	100	95	83	10.5	16	42	16	10.5	32.5	4

(2) SGTMM03-025AH20AP




*: See the next page for the connector specifications.

Global Support Product (see page viii)


●External Dimensions

(3) SGTMM03-025AH04AP



Note: The magnet moves in the direction indicated by the arrow when current flows in the order of phase U, V, and W.

(4) SGTMM03-065AH20A



Note: The magnet moves in the direction indicated by the arrow when current flows in the order of phase U, V, and W.

Global Support Product (see page iii)

●Connector Specifications for the Σ-Trac-μ Series of Linear Slides (All Models)

For SGTMM01 Linear Sliders

For Motor Cable

Pin No.	Name	Lead Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG	Green

For Encoder Cable

Pin No.	Signal	Pin No.	Signal
1	IW–	9	N/C
2	IW+	10	N/C
3	Test	11	N/C
4	Transmit	12	+5 V
5	Receive	13	GND
6	Reset	14	Cos–
7	Cos+	15	Sin–
8	Sin+		

For SGTMM03 Linear Sliders

For Motor Cable

Pin No.	Name	Lead Color
1	Phase U	Red
2	Phase V	White
3	Phase W	Blue
4	FG	Green

For Encoder Cable

Pin No.	Signal	Pin No.	Signal
1	Cos output (A+)	9	/Cos output (A-)
2	0 V	10	0 V sensor
3	Sin output (B+)	11	/Sin output (B-)
4	+5 V	12	5 V sensor
5	Not used	13	Not used
6	Not used	14	/Ref (R+)
7	/Ref (R-)	15	Not used
8	Not used	Case	Shield


For Hall Sensor Cable

Pin No.	Signal
1	+5V (power supply)
2	Phase-U output
3	Phase-V output
4	Phase-W output
5	0V (power supply)
6	Not used
7	Not used
8	Not used
9	Not used

SGTMM Linear Slides Units: mm


● External Dimensions

(5) SGTMM03-065AH20AP



Note: The magnet moves in the direction indicated by the arrow when current flows in the order of phase U, V, and W.

(6) SGTMM03-065AH04AP




Note: The magnet moves in the direction indicated by the arrow when current flows in the order of phase U, V, and W.

Global Support Product (see page viii)

Selecting Cables and Connectors

●Connection diagrams



Global Support Product (See page xiii)


●Applicable Cables and Connectors

Motor Type	Linear Scale Type	Servo Drive		Motor Cable	Linear Scale Connection Cables		
		Σ-Trac-μ Series Model	SERVOPACK Model SGDV-	SERVOPACK ↔ Motor	Serial Converter Unit Model JZDP-	[CN2]↔Serial Converter Unit	Serial Converter Unit↔Linear Encoder
			Three-phase 200 V	Power Cable (Flexible Type)		Serial Cable (Flexible Type)	Encoder Cable (Flexible Type)
Moving Magnet (MM)	Incremental	SGTMM01-010AM20A	R70A	JZSP-CLN11-□□-E	D003-242-E	JZSP-CLP70-□□-E The numbers in the boxes (□□) indicates the cable length. 01 = 1 m 03 = 3 m 05 = 5 m 10 = 10 m 15 = 15 m 20 = 20 m	JZSP-CLL00-□□-E The numbers in the boxes (□□) indicates the cable length. 01 = 1 m 03 = 3 m 05 = 5 m 10 = 10 m 15 = 15 m Note: For SGTMM01 linear Slides, a JZSP-CLL40 -E cable (length: 0.2 m) is also required.
		SGTMM01-030AM20A	R70A	JZSP-CLN11-□□-E	D003-242-E		
		SGTMM03-025AH20AP	R90A	JZSP-CLN11-□□-E	D006-221-E		
		SGTMM03-025AH04AP	R90A	JZSP-CLN11-□□-E	D006-221-E		
		SGTMM03-065AH20A	R90A	JZSP-CLN11-□□-E	D003-220-E		
		SGTMM03-065AH20AP	R90A	JZSP-CLN11-□□-E	D006-220-E		
		SGTMM03-065AH04AP	R90A	JZSP-CLN11-□□-E	D006-220-E		


Selecting Cables and Connectors

●Detail Drawings: Serial Converter Units for Linear Scales by HEIDENHAIN Corporation

●JZDP-D006-□□□-E
(With Hall Sensor Cable)



●JZDP-D003-□□□-E
(Without Hall Sensor Cable)



●Details on Connectors

CN1



SERVOPACK End
Serial Data Output

by DDK Ltd.
17-series Connector:
17LE-13090-27-FA
(Socket)

Pin No.	Signal	Pin No.	Signal
1	+5V	6	Phase-/S output
2	Phase-S output	7	Not used
3	Not used	8	Not used
4	Not used	9	Not used
5	0V	Case	Shield

CN2



Linear Scale End
Analog Signal Input

by DDK Ltd.
17-series Connector:
17JE-13150-02 (D8C)A-CG
(Socket)

Pin No.	Signal	Pin No.	Signal
1	cos input (A+)	9	/cos input (A-)
2	0V	10	0 V sensor
3	sin input (B+)	11	/sin input (B-)
4	+5V	12	5 V sensor
5	Not used	13	Not used
6	Not used	14	Ref input (R+)
7	/Ref input (R-)	15	Not used
8	Not used	Case	Shield

CN3



Linear Servomotor End
Hall Sensor Signal Input

by DDK Ltd.
17-series Connector:
17JE-13090-02(D8C) A-CG
(Socket)


Pin No.	Signal	Pin No.	Signal
1	+5V	6	Not used
2	Phase-U input	7	Not used
3	Phase-V input	8	Not used
4	Phase-W input	9	Not used
5	0V	Case	Shield

Global Support Product (see page xxx)

	Pulse Train or Analog Voltage Reference			MECHATROLINK Communications			Cables for Setting Devices/Monitors	
Serial Converter Unit↔Hall Sensor	I/O Signal Connector [CN1]			I/O Signal Connector [CN1]		MECHATROLINK Communications Connector [CN6A] or [CN6B]	[CN3]↔Setting Devices	[CN5]
Hall Sensor Cable (Flexible Type)	Connector Terminal Block Converter Unit	Cable with Loose Wires at One End	Connector Kit [CN1]	Connector Terminal Block Converter Cable	Connector Kit [CN1]		Personal Computer Cable	Analog Monitor Cable
JZSP-CLL10-□□-E The numbers in the boxes (□□) indicates the cable length. 01 = 1 m 03 = 3 m 05 = 5 m 10 = 10 m 15 = 15 m	JUSP-TA50PG-E (with a 0.5 m cable)	JZSP-CSI01-□-E The number in the box (□) indicates the cable length. 1 = 1 m 2 = 2 m 3 = 3 m	JZSP-CSI9-1-E	JZSP-TA26P-□-E	JZSP-CSI9-2-E (DE9411354)	MECHATROLINK communications cable: JEPMC-W6002-□□-E The numbers in the boxes(□□) indicates the cable length. A5 = 0.5 m 01 = 1 m 03 = 3 m 05 = 5 m 10 = 10 m 20 = 20 m 30 = 30 m 40 = 40 m 50 = 50 m MECHATROLINK terminator: JEPMC-W6022-E	JZDP-CMS02-E (2m)	JZSP-CA01-E (1m)

Linear Slides

Σ-Trac-MAG



Model Designation (Global Support - Refer to Stock Status Definitions - page viii)

● With Incremental Linear Scales

SGT M F4 A - 027 A H 20 A

Σ-Trac Series
Linear Slide
Moving Magnet Type
Armature Code
(Armature not integrally mounted)
F4 : SGLFW-35A230A-F
F5 : SGLFW-50A380A-F
Table Length
A : Short
B : Long

Armature Code	Table Length	Effective Stroke	Armature Code	Table Length	Effective Stroke
F4	A	100 mm	F5	A	185 mm
	B	65 mm		B	110 mm

Peak Force
027 : 270 N
036 : 360 N
054 : 540 N
072 : 720 N

Linear Scale Output Form
A : Analog output 1 Vp-p

Linear Scale Manufacturer
H : HEIDENHAIN Corporation

Linear Scale Resolution
20 : 20 μm

Design Revision Order
A, B, C

● With Absolute (ABS) Linear Scales

SGT M F4 A - 027 ABS 1 A

Σ-Trac Series
Linear Slide
Moving Magnet Type
Armature Code
(Armature not integrally mounted)
F4 : SGLFW-35A230A-F
F5 : SGLFW-50A380A-F
Table Length
A : Short
B : Long

Armature Code	Table Length	Effective Stroke	Armature Code	Table Length	Effective Stroke
F4	A	100 mm	F5	A	185 mm
	B	65 mm		B	110 mm

Peak Force
027 : 270 N
036 : 360 N
054 : 540 N
072 : 720 N

With an absolute linear scale

Linear Scale Specifications
1 : ST781A (by Mitutoyo Corporation, resolution: 0.5 μm)
2 : ST783A (by Mitutoyo Corporation, resolution: 0.1 μm)

Design Revision Order
A, B, C

Features


- Optimum drive for high-acceleration and high-tact operations because of its lightweight moving member.
- For short strokes (65 mm to 185 mm)
- Cooling units (pipes, etc.) for forced-air or liquid cooling systems can be placed on the fixed side.
- Linear scale options: Incremental or absolute.
- Improved stroke efficiency*

*:Ratio of effective stroke to the total length of drive system

Model Classification (Global Support - Refer to Stock Status Definitions - page viii)

Force

SERVOPACK (Three-phase 200 VAC) Model SGDV-		Σ-Trac-MAG Series Linear Slides	
100V	200V	Model	Force
2R1F	1R6A	SGTMF4A-027	
2R1F	1R6A	SGTMF4B-036	
5R5A		SGTMF5A-054	
5R5A		SGTMF5B-072	



Stroke Length

Model	Stroke Length
SGTMF4A-027	100 mm
SGTMF4B-036	65 mm
SGTMF5A-054	185 mm
SGTMF5B-072	110 mm

●Ratings and Specifications

Time Rating: Continuous
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0˚C to 40˚C
Excitation: Permanent magnet
Dielectric Strength: 1500 VAC for one minute
Protection Methods: Self-cooled
Ambient Humidity: 20% to 80% (no condensation)
Allowable Winding Temperature: 130˚C (Thermal class B)

Linear Slide Model		With Incremental Linear Scales		With Absolute Linear Scales	
		SGTMF4A-027AH20A	SGTMF4B-036AH20A	SGTMF4A-027ABS1A	SGTMF4B-036ABS1A
Applicable SERVOPACK Model	SGDV-	2R1F, 1R6A			
Applicable Serial Converter Unit Model	JZDP-	D003-243-E	D003-244-E	–	–
Rated Force	N	90	120	90	120
Peak Force	N	270	360	270	360
Force Constant	N/A_{rms}	66.9	89.2	66.9	89.2
Motor Constant	$N/\sqrt{W}$	11	14.6	11	14.6
Maximum Payload*1	kg	40	55	40	55
Effective Stroke	mm	100	65	100	65
Resolution	μm	Incremental encoder: 0.078 (20 μm/256)		Absolute encoder*3: 0.5	
Movable Member Mass	kg	1.72	2.52	1.72	2.52
Total Mass (excluding cables)	kg	6.8	8.05	6.8	8.05
Repeatability*2	μm	±1.0	±1.0	±1.0	±1.0

*1: Values obtained when the acceleration is 4.9 m/s².
*2: Values obtained when the ambient temperature is constant.
*3: An absolute encoder with a resolution of 0.1 μm is also available. Contact your Yaskawa representative for details.


●Performance Curves

● Force - Speed
A : Continuous Duty Zone
B : Intermittent Duty Zone (Note)


● Effective Force - Ambient Temperature
When the sensor temperature is 50 ˚C or less
Ambient temperature

● Load Mass - Acceleration


(1) SGTMF4A-027









(2) SGTMF4B-036








Note: When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.

Global Support Product
See page viii

SGTMF4 Linear Slides Units: mm


●External Dimensions

●With Incremental Linear Scale



Linear Slide Model SGTMF	L1 mm	L2 mm	L3 mm	L4 mm	L5 mm	L6 mm	L7 mm	L8 mm	L9 mm	L10 mm	L11 mm	N
4A-027AH20A	107	120	20	40	80	20	–	–	–	–	–	6
4B-036AH20A	71	156	18	40	120	18	41	80	37	5.5	145	12

●With Absolute Linear Scale



Linear Slide Model SGTMF	L1 mm	L2 mm	L3 mm	L4 mm	L5 mm	L6 mm	L7 mm	L8 mm	L9 mm	L10 mm	L11 mm	L12 mm	N
4A-027ABS1A	107	120	20	40	80	–	–	–	–	–	10.5	6.5	6
4B-036ABS1A	71	156	18	40	120	41	80	37	5.5	145	–	–	12

Global Support Product (see page xiii)

●Ratings and Specifications

Time Rating: Continuous
Insulation Resistance: 500 VDC, 10 MΩ min.
Ambient Temperature: 0˚C to 40˚C
Excitation: Permanent magnet
Dielectric Strength: 1500 VAC for one minute
Protection Methods: Self-cooled
Ambient Humidity: 20% to 80% (no condensation)
Allowable Winding Temperature: 130˚C (Thermal class B)

Linear Slide Model		With Incremental Linear Scales		With Absolute Linear Scales	
		SGTMF5A-054AH20A	SGTMF5B-072AH20A	SGTMF5A-054ABS1A	SGTMF5B-072ABS1A
Applicable SERVOPACK Model	SGDV-	5R5A	5R5A	5R5A	5R5A
Applicable Serial Converter Unit Model	JZDP-	D003-245-E	D003-246-E	–	–
Rated Force	N	150	200	150	200
Peak Force	N	540	720	540	720
Force Constant	N/A_{rms}	59.4	79.1	59.4	79.1
Motor Constant	$N/\sqrt{W}$	18.5	24.7	18.5	24.7
Maximum Payload*1	kg	85	110	85	110
Effective Stroke	mm	185	110	185	110
Resolution	μm	Incremental encoder: 0.078 (20 μm/256)		Absolute encoder*3: 0.5	
Movable Member Mass	kg	4.2	6.84	4.2	6.84
Total Mass (excluding cables)	kg	19.8	22.5	19.8	22.5
Repeatability*2	μm	±1.0	±1.0	±1.0	±1.0

*1: Values obtained when the acceleration is 4.9 m/s².
*2: Values obtained when the ambient temperature is constant.
*3: An absolute encoder with a resolution of 0.1 μm is also available. Contact your Yaskawa representative for details.


●Performance Curves


● Force - Speed
A : Continuous Duty Zone
B : Intermittent Duty Zone (Note)


● Effective Force - Ambient Temperature
When the sensor temperature is 50 ˚C or less
Ambient temperature

● Load Mass - Acceleration


(1) SGTMF5A-054









(2) SGTMF5B-072








Note: When the effective force during intermittent duty is within the rated force, the servomotor can be used within the intermittent duty zone.

Global Support Product (see page viii)

SGTMF5 Linear Slides Units: mm


●External Dimensions

● With Incremental Linear Scale



Linear Slide Model SGTMF	L1 mm	L2 mm	L3 mm	L4 mm	L5 mm	L6 mm	L7 mm	N
5A-054AH20A	185	195	220	37.5	60	120	25	6
5B-072AH20A	110	270	145	15	60	240	62.5	10

● With Absolute Linear Scale




Linear Slide Model SGTMF	L1 mm	L2 mm	L3 mm	L4 mm	L5 mm	L6 mm	L7 mm	N
5A-054ABS1A	185	195	37.5	60	120	25	12.5	6
5B-072ABS1A	110	270	15	60	240	62.5	–	10

Global Support Product (see page vii)

Selecting Cables and Connectors

●Connection diagrams



Global Support Product (See page viii)


●Applicable Cables and Connectors

Motor Type	Linear Scale Type	Servo Drive		Motor Cable	Linear Scale Connection Cables		
			SERVOPACK Model SGDV-	SERVOPACK ↔ Motor	Serial Converter Unit Model JZDP-	[CN2]↔Serial Converter Unit	Serial Converter Unit↔Linear Encoder
		Σ-Trac-MAG Series Model	Three-phase 200 V	Power Cable (Flexible Type)		Serial Cable (Flexible Type)	Encoder Cable (Flexible Type)
Moving Magnet (MM)	Incremental	SGTMF4A-027AH20A	1R6A	JZSP-CLN11-□□-E	D003-243-E	JZSP-CLP70-□□-E (The numbers in the boxes(□□) indicates the cable length. 01 = 1 m, 03 = 3 m, 05 = 5 m, 10 = 10 m, 15 = 15 m, 20 = 20 m)	JZSP-CLL00-□□-E (The numbers in the boxes(□□) indicates the cable length. 01 = 1 m, 03 = 3 m, 05 = 5 m, 10 = 10 m, 15 = 15 m)
		SGTMF4B-036AH20A	1R6A	JZSP-CLN11-□□-E	D003-244-E		
		SGTMF5A-054AH20A	5R5A	JZSP-CLN21-□□-E	D003-245-E		
		SGTMF5B-072AH20A	5R5A	JZSP-CLN21-□□-E	D003-246-E		
	Absolute	SGTMF4A-027ABS1A	1R6A	JZSP-CLN11-□□-E	—	JZSP-CLP70□□-E [CN2]↔Linear Scale	—
		SGTMF4B-036ABS1A	1R6A	JZSP-CLN11-□□-E	—		
		SGTMF5A-054ABS1A	5R5A	JZSP-CLN21-□□-E	—		
		SGTMF5B-072ABS1A	5R5A	JZSP-CLN21-□□-E	—		


Selecting Cables and Connectors

●Detail Drawings: Serial Converter Units for Linear Scales by HEIDENHAIN Corporation

●JZDP-D006-□□□-E
(With Hall Sensor Cable)



●JZDP-D003-□□□-E
(Without Hall Sensor Cable)



●Details on Connectors

CN1



SERVOPACK End
Serial Data Output

by DDK Ltd.
17-series Connector:
17LE-13090-27-FA
(Socket)

Pin No.	Signal	Pin No.	Signal
1	+5V	6	Phase-/S output
2	Phase-S output	7	Not used
3	Not used	8	Not used
4	Not used	9	Not used
5	0V	Case	Shield

CN2



Linear Scale End
Analog Signal Input

by DDK Ltd.
17-series Connector:
17JE-13150-02 (D8C)A-CG
(Socket)

Pin No.	Signal	Pin No.	Signal
1	cos input (A+)	9	/cos input (A-)
2	0V	10	0 V sensor
3	sin input (B+)	11	/sin input (B-)
4	+5V	12	5 V sensor
5	Not used	13	Not used
6	Not used	14	Ref input (R+)
7	/Ref input (R-)	15	Not used
8	Not used	Case	Shield

CN3



Linear Servomotor End
Hall Sensor Signal Input

by DDK Ltd.
17-series Connector:
17JE-13090-02(D8C) A-CG
(Socket)

Pin No.	Signal	Pin No.	Signal
1	+5V	6	Not used
2	Phase-U input	7	Not used
3	Phase-V input	8	Not used
4	Phase-W input	9	Not used
5	0V	Case	Shield

Global Support Product (see page xii)

	Pulse Train or Analog Voltage Reference			MECHATROLINK Communications			Cables for Setting Devices/Monitors	
	I/O Signal Connector [CN1]			I/O Signal Connector [CN1]		MECHATROLINK Communications Connector [CN6A] or [CN6B]	[CN3]••Setting Devices	[CN5]
	Connector Terminal Block Converter Unit	Cable with Loose Wires at One End	Connector Kit [CN1]	Connector Terminal Block Converter Cable	Connector Kit [CN1]		Personal Computer Cable	Analog Monitor Cable
	JUSP-TA50PG-E (with a 0.5 m cable)	JZSP-CSI01-□-E The number in the box (□) indicates the cable length. 1 = 1 m 2 = 2 m 3 = 3 m	JZSP-CSI9-1-E	JZSP-TA26P-□-E	JZSP-CSI9-2-E (DE9411354)	MECHATROLINK communications cable: JEPMC-W6002-□□-E The numbers in the boxes (□□) indicates the cable length. A5 = 0.5 m 01 = 1 m 03 = 3 m 05 = 5 m 10 = 10 m 20 = 20 m 30 = 30 m 40 = 40 m 50 = 50 m MECHATROLINK terminator: JEPMC-W6022-E	JZDP-CMS02-E (2 m)	JZSP-CA01-E (1 m)

efesotomasyon.com

Analog Voltage/Pulse Train Reference Type SERVOPACKs

SGDV-□□□□01

(For Rotary Servomotors)

SGDV-□□□□05

(For Linear Servomotors)



Model Designations

SGDV - R70 A 01 A □

- SGDV: Σ-V Series SGDV SERVOPACK
- R70: Current
- A: Voltage
- 01: Interface
- A: Design Revision Order A, B…
- □: Options

Code	Specifications
Blank	Base-mounted (standard)
001000	Rack-mounted*

*: SGDV-470A, -550A, -590A, -780A SERVOPACKs are duct-ventilated.

Code	Specifications
F	100 VAC
A	200 VAC
D	400 VAC

Code	Specifications
01	Analog voltage/pulse train reference type (for rotary servomotors)
05	Analog voltage/pulse train reference type (for linear servomotors)

Code	100 V (Single Phase) Applicable Servomotor Max. Capacity kW	Code	200 V (Three Phase) Applicable Servomotor Max. Capacity kW	Code	400 V (Three Phase) Applicable Servomotor Max. Capacity kW
R70	0.05	R70*	0.05	1R9	0.5
R90	0.1	R90*	0.1	3R5	1.0
2R1	0.2	1R6*	0.2	5R4	1.5
2R8	0.4	2R8*	0.4	8R4	2.0
		3R8	0.5	120	3.0
		5R5*	0.75	170	5.0
		7R6	1.0	210	6.0
		120♣	1.5	260	7.5
		180	2.0	280	11
		200	3.0	370	15
		330	5.0		
		470	6.0		
		550	7.5		
		590	11		
		780	15		

NOTE: Shaded items are non-stock.

* These amplifiers can be powered with single or three-phase.

♣ SGDV-120A□1A008000, a special version of the 1.5kW amplifier can be used for single-phase operation.

Features

- Unprecedented ease-of-use through cutting-edge technology
  - New tuning-less function means no adjustment needed.
  - Impressive load regulation with strengthened vibration suppression function.
- Slashed setup time
  - Setup wizard function and wiring conformation function of engineering tool SigmaWin+ allows easy setup just by watching the monitor.
- High response characteristics at 1 kHz min.
  - New advanced autotuning.
  - Reduced positioning time through model following control, and smooth machine control enabled by vibration suppression function.

Ratings

Single-phase 100 V

SERVOPACK Model SGDV-□□□□		R70F	R90F	2R1F	2R8F
Applicable Servomotor Max. Capacity	kW	0.05	0.1	0.2	0.4
Continuous Output Current	A_{rms}	0.66	0.91	2.1	2.8
Max. Output Current	A_{rms}	2.1	2.9	6.5	9.3
Main Circuit (Single Phase)		100 to 115 VAC+10% to −15% 50/60 Hz			
Control Circuit (Single Phase)		100 to 115 VAC+10% to −15% 50/60 Hz			

Single-phase 200 V

SERVOPACK Model SGDV-□□□□		R70A	R90A	1R6A	2R8A	5R5A	120
Applicable Servomotor Max. Capacity	kW	0.05	0.1	0.2	0.4	0.75	1.5
Continuous Output Current	A_{rms}	0.66	0.91	1.6	2.8	5.5	11.6
Max. Output Current	A_{rms}	2.1	2.9	6.5	9.3	16.9	28
Main Circuit (Single Phase)		220 to 230 VAC +10% to -15% 50/60 Hz					
Control Circuit (Single Phase)		220 to 230 VAC +10% to -15% 50/60 Hz					


Three-phase 200 V

SERVOPACK Model SGDV-□□□□		R70A	R90A	1R6A	2R8A	3R8A	5R5A	7R6A	120A	180A	200A	330A	470A	550A	590A	780A
Applicable Servomotor Max. Capacity	kW	0.05	0.1	0.2	0.4	0.5	0.75	1.0	1.5	2.0	3.0	5.0	6	7.5	11	15
Continuous Output Current	A_{rms}	0.66	0.91	1.6	2.8	3.8	5.5	7.6	11.6	18.5	19.6	32.9	46.9	54.7	58.6	78
Max. Output Current	A_{rms}	2.1	2.9	6.5	9.3	11	16.9	17	28	42	56	84	110	130	140	170
Main Circuit		Three-phase 200 to 230 VAC+10% to −15% 50/60 Hz														
Control Circuit		Single-phase 200 to 230 VAC+10% to −15% 50/60 Hz														

Three-phase 400 V

SERVOPACK Model SGDV-□□□□		1R9D	3R5D	5R4D	8R4D	120D	170D	210D	260D	280D	370D
Applicable Servomotor Max. Capacity	kW	0.5	1.0	1.5	2.0	3.0	5.0	6	7.5	11	15
Continuous Output Current	A_{rms}	1.9	3.5	5.4	8.4	11.9	16.5	20.8	25.4	28.1	37.2
Max. Output Current	A_{rms}	5.5	8.5	14	20	28	42	55	65	70	85
Main Circuit		Three-phase 380 to 480 VAC+10% to −15% 50/60 Hz									
Control Circuit		24 VDC ±15%									

- SERVOPACK Overload Characteristics



Note: Overload characteristics shown above do not guarantee continuous duty of 100% or more output. Use a servomotor with effective torque within the continuous duty zone of Torque-Motor Speed Characteristics.

Specifications

Items			Specifications
Input Power Supply	Main Circuit	100 V	Single-phase 100 to 115 VAC +10% to −15% 50/60 Hz
		200 V	Three-phase 200 to 230 VAC +10% to −15% 50/60 Hz
		400 V	Three-phase 380 to 480 VAC +10% to −15% 50/60 Hz
	Control Circuit	100 V	Single-phase 100 to 115 VAC +10% to −15% 50/60 Hz
		200 V	Single-phase 200 to 230 VAC +10% to −15% 50/60 Hz
		400 V	24 VDC ±15%
Control Method			For 100 V, for 200 V, for 400 V, single-phase or three-phase full-wave rectification IGBT PWM control, sine-wave driven
Feedback	Rotary Servomotors		Serial encoder: 13-bit (incremental encoder) : 17-bit (incremental/absolute encoder) : 20-bit (incremental/absolute encoder)
	Linear Servomotors		Serial converter or serial data
Operating Conditions	Surrounding/Storage Temperature		Surrounding temperature: 0 to +55°C, storage temperature: −20 to +85°C
	Ambient/Storage Humidity		90%RH or less (no condensation)
	Vibration/Shock Resistance		Vibration resistance: 4.9 m/s^2, Shock resistance: 19.6 m/s^2
	Protection class/Pollution degree		Protection class: IP 1X, pollution degree: 2 Do not use SERVOPACKs in the following locations: · Locations subject to corrosive or flammable gasses · Locations subject to exposure to water, oil, or chemicals · Locations subject to dust, including iron dust, and salts
	Others		Do not use SERVOPACKs in the following locations: · Locations subject to static electricity noise, strong electromagnetic/magnetic fields, radioactivity
	Elevation		1000 m or less
Compliant Standards			UL 508C EN50178, EN55011 class A group 1, EN61800-3, EN61800-5-1
Configuration			Base-mounted (Rack-mounting available as an option for some models. 6 kW or more models are duct-ventilated.)
Performance	Speed Control Range		1:5000 (The lowest speed of the speed control range is the speed at which the servomotor will not stop with a rated torque load.)
	Speed Regulation*	Load Regulation	0% to 100% load: ±0.01% max. (at rated speed)
		Voltage Regulation	Rated voltage: ±10% : 0% (at rated speed)
		Temperature Regulation	25±25°C : ±0.1% max. (at rated speed)
	Torque Control Tolerance (Repeatability)		±1%
	Soft Start Time Setting		0 to 10 s (can be set individually for acceleration and deceleration.)
I/O Signals	Encoder Output Pulses		Phase A, phase B, phase C: line driver output The number of dividing pulse: Any setting ratio is available.
Communications	RS-422A Communications	Interface	Digital operator, RS-422A port of personal computers etc.
		1:N communications	RS-422A port: N=15 max. available
		Axis address setting	Set by parameters
		Function	Status display, parameter settings, adjustment functions, utility functions, parameter copy functions
	USB Communications	Interface	Personal computers (application: engineering tool SigmaWin+)
		1:N communications	Compliant with USB1.1 standard
		Function	Status display, parameter settings, adjustment functions, utility functions, parameter copy functions, waveform trace
Display		Power Charge	CHARGE for main circuit power supply input confirmation One LED (orange)
Analog Monitor			Analog monitor connector built in for monitoring speed, torque and other reference signals. Number of points: 2
Protective Functions			Overcurrent, Overvoltage, low voltage, overload, regeneration error
Utility Functions			Alarm history, JOG operation, origin search, etc.
Regenerative Processing			100 VAC model: External regenerative resistor (optional) 200 VAC SGDV-R70A, -R90A, -1R6A, -2R8A: External regenerative resistor (optional) 200 VAC SGDV-470A, -550A, -590A, -780A: External regenerative resistor unit (optional) 200 VAC models other than shown above: Built-in regenerative resistor 400 VAC SGDV-210D, -260D, -280D, -370D: External regenerative resistor unit (optional) 400 VAC models other than shown above: Built-in regenerative resistor
Safety Functions		Input	/HWBB1, /HWBB2: Hard wire base block signal
		Output	EDM1: Status monitor (fixed output) of built-in safety circuit
		Compliant Standards	EN954 category 3 Stop category 0, IEC61508 SIL 2
Option Card Function		Feedback	Serial encoder communications input for fully-closed loop control

*: Speed regulation is defined as follows:

$$\text{Speed regulation} = \frac{\text{No-load motor speed} - \text{Total load motor speed}}{\text{Rated motor speed}} \times 100\%$$

The motor speed may change due to voltage variations or temperature variation. The ratio of speed changes to the rated speed represent speed regulation due to voltage and temperature variations.

Specifications

●Rotary Servomotors

Items			Specifications	
I/O Signal	Encoder Output Pulses		Phase A, phase B, phase C: line driver output The number of dividing pulse: Any setting ratio is available.	
	Sequence Input	Fixed Input	SEN signal	
		Input Signals which can be allocated	Number of Channels	7 channels
			Functions	The signal allocation and positive/negative logic can be modified. Servo On (/S-ON), proportional control (/P-CON), alarm reset (/ALM-RST), forward run prohibited (P-OT), reverse run prohibited (/N-OT), forward torque limit (/P-CL), reverse torque limit(/N-CL), internal set speed selection (/SPD-D, / SPD-A, /SPD-B), control selection (/C-SEL), zero clamping (/ZCLAMP), reference pulse inhibit (/INHIBIT), gain selection (/G-SEL)
	Sequence Output	Fixed Output	Servo alarm (ALM), alarm code (ALO1, ALO2, ALO3) outputs	
		Output Signals which can be allocated	Number of Channels	3 channels
			Functions	The signal allocation and positive/negative logic can be modified. Positioning completion (/COIN), speed coincidence detection (/V-CMP), servomotor rotation detection (/TGON), servo ready (/S-RDY), torque limit detection (/CLT), speed limit detection (/VLT), brake interlock (/BK), warning (/WRAN), near (/NEAR)
Panel Operator		Display	7-segment 5-digit LED (Red)	
		Switch	Push switch: 4 channels	
Torque Control	Analog Input	Reference Voltage	±3 VDC (Variable setting range: ±1 to 10 VDC) at rated torque, max. input voltage: ±12 V	
		Input Impedance	About 14 kΩ min.	
		Circuit Time Constant	16 μs	
Speed Control	Analog Input	Reference Voltage	±6 VDC (variable setting range: ±2 to 10 VDC) at rated speed, max. input voltage: ±12 V	
		Input Impedance	About 14 kΩ min.	
		Circuit Time Constant	30 μs	
	Internal Set Speed Control	Rotation Direction Selection	Switches the direction by /P-CON (/SPD-D)	
		Speed Selection	Speed 1 to 3 selection	
	Function	Soft Start Setting	0 to 10 s (can be set individually for acceleration and deceleration.)	
Position Control	Reference Pulse	Type	Sign + pulse train, 90°phase difference 2-phase pulse (phase A + phase B), or CCW + CW pulse train	
		Form	Non-insulated line driver (+5 V level), open collector	
		Max. Input Pulse Frequency*	Sign+ Pulse train : 4 Mpps CW+ CCW pulse train : 4 Mpps 90° phase difference 2-phase pulse ×1 multiplier : 1 Mpps (before mlutiplier) ×2 multiplier : 1 Mpps (before mlutiplier) ×4 multiplier : 1 Mpps (before mlutiplier) Open collector : 200 kpps	
	Clear Signal	Function	Clears error pulse by external signals.	
		Form	Applicable to line driver, open collector	

*: If the maximum reference frequency exceeds 1 Mpps, use a shielded cable for I/O signals and ground both ends of the shield.
Connect the shield at the SERVOPACK to the connector shell.

Specifications

●Linear Servomotors

Items			Specifications	
I/O Signal	Encoder Output Pulses		Phase A, phase B, phase C: line driver output The number of dividing pulse: Any setting ratio is available.	
	Sequence Input	Input Signals which can be allocated	Number of Channels	7 channels
			Functions	The signal allocation and positive/negative logic can be modified. Servo ON (/S-ON), proportional control (/P-CON), alarm reset (/ALM-RST), forward run prohibited (P-OT), reverse run prohibited (N-OT), forward external force limit (/P-CL), reverse external force limit (/N-CL), internal set speed selection (/SPD-D, /SPD-A, /SPD-B), control selection (/C-SEL), zero clamping (/ZCLAMP), reference pulse inhibit (/INHIBIT), gain selection (/G-SEL), polarity detection (P-DET)
	Sequence Output	Fixed Output	Servo alarm (ALM), alarm code (ALO1, ALO2, ALO3) outputs	
		Output Signals which can be allocated	Number of Channels	3 channels
			Functions	The signal allocation and positive / negative logic can be modified. Positioning completion (/COIN), speed coincidence detection (V/CMP), servomotor movement detection (/TGON), servo ready (/S-RDY), force limit detection (/CLT), speed limit detection (/VLT), brake interlock (/BK), warning (/WARN), near (/NEAR)
Panel Operator		Display	7-segment 5-digit LED (Red)	
		Switch	Push switch: 4 channels	
Force Control	Analog Input	Reference Voltage	±3 VDC (variable setting range: ±1 to 10 VDC), max. input voltage: ±12 V	
		Input Impedance	About 14 kΩ min.	
		Circuit Time Constant	16 μs	
Speed Control	Analog Input	Reference Voltage	±6 VDC (variable setting range: ±2 to 10 VDC) at rated speed, max. input voltage: ±12 V	
		Input Impedance	About 14 kΩ min.	
		Circuit Time Constant	30 μs	
	Internal Set Speed Control	Movement Direction Selection	/P-CON (/SPD-D) signal	
		Speed Selection	Speed 1 to 3 selection	
	Function	Soft Start Setting	0 to 10 s (can be set individually for acceleration and deceleration.)	
Position Control	Reference Pulse	Type	Sign+ pulse train, 90°phase difference 2-phase pulse (phase A+ phase B), or CCW+ CW pulse train	
		Form	Non-insulated line driver (+5 V level), open collector	
		Max. Input Pulse Frequency*	Sign+ Pulse train : 4 Mpps CW+ CCW pulse train : 4 Mpps 90° phase difference 2-phase pulse ×1 multiplier : 1 Mpps (before mlutiplier) ×2 multiplier : 1 Mpps (before mlutiplier) ×4 multiplier : 1 Mpps (before mlutiplier) Open collector : 200 kpps	
	Clear Signal	Function	Clears error pulse by external signals.	
		Form	Applicable to line driver, open collector	

*: If the maximum reference frequency exceeds 1 Mpps, use a shielded cable for I/O signals and ground both ends of the shield.
Connect the shield at the SERVOPACK to the connector shell.

Power Supply Capacities and Power Losses

The following table shows SERVOPACK's power supply capacities and power losses at the rated output.

Main Circuit Power Supply	Applicable Servomotor Max. Capacity kW	SERVOPACK Model SGDV-	Power Supply Capacity kVA	Output Current A	Main Circuit Power Loss W	Regenerative Resistor Power Loss W	Control Circuit Power Loss W	Total Power Loss W
Signal-phase 100 V	0.05	R70F	0.2	0.66	5.4	—	17	22.4
	0.1	R90F	0.3	0.91	7.8			24.8
	0.2	2R1F	0.7	2.1	14.4			31.4
	0.4	2R8F	1.4	2.8	25.6			42.6
Single-phase 200 V	0.05	R70A	0.2	0.66	5.2	—	17	22.2
	0.1	R90A	0.3	0.91	7.4			24.4
	0.2	1R6A	0.7	1.6	13.7			30.7
	0.4	2R8A	1.2	2.8	24.9			41.9
	0.75	5R5A	1.9	5.5	52.7	8		77.7
	1.5	120A	4	11.6	68.2	10	22	100.2
Three-phase 200 V	0.05	R70A	0.2	0.66	5.1	—	17	22.1
	0.1	R90A	0.3	0.91	7.3			24.3
	0.2	1R6A	0.6	1.6	13.5			30.5
	0.4	2R8A	1	2.8	24.0			41.0
	0.5	3R8A	1.4	3.8	20.1	8		45.1
	0.75	5R5A	1.6	5.5	43.8			68.8
	1.0	7R6A	2.3	7.6	53.6			78.6
	1.5	120A	3.2	11.6	65.8	10	22	97.8
	2.0	180A	4	18.5	111.9	16		149.9
	3.0	200A	5.9	19.6	113.8			161.4
	5.0	330A	7.5	32.9	263.7	36	27	326.7
	6.0	470A	10.7	46.9	279.4	(180)*1	33	312.4
	7.5	550A	14.6	54.7	357.8	(350)*2		390.8
	11	590A	21.7	58.6	431.7		48	479.7
	15	780A	29.6	78	599.0			647.0
Three-phase 400 V	0.5	1R9D	1.1	1.9	24.6	14	21	59.6
	1.0	3R5D	2.3	3.5	46.1			81.1
	1.5	5R4D	3.5	5.4	71.3			106.3
	2.0	8R4D	4.5	8.4	77.9	28	25	130.9
	3.0	120D	7.1	11.9	108.7			161.7
	5.0	170D	11.7	16.5	161.1	36	24	221.1
	6.0	210D	12.4	20.8	172.7	(180)*3	27	199.7
	7.5	260D	14.4	25.7	218.6			245.6
	11	280D	21.9	28.1	294.6	(350)*4	30	324.6
	15	370D	30.6	37.2	403.8			433.8


*1: For the optional JUSP-RA04-E regenerative resistor unit.
*2: For the optional JUSP-RA05-E regenerative resistor unit.
*3: For the optional JUSP-RA18-E regenerative resistor unit
*4: For the optional JUSP-RA19-E regenerative resistor unit.

Notes: 1 SGDV-R70F, -R90F, -2R1F, -2R8F, -R70A, -R90A, -1R6A, and -2R8A SERVOPACKs do not have built-in regenerative resistors.
If the regenerative energy exceeds the specified value, connect an external regenerative resistor (optional).
2 SGDV-470A, -550A, -590A, -780A, -210D, -260D, -280D, -370D SERVOPACKs do not have built-in regenerative resistors.
Be sure to connect a regenerative resistor unit (optional) or an external regenerative resistor (optional). For selection details, refer to page 339.
3 Regenerative resistor power losses are allowable losses. Take the following action if this value is exceeded.
· Remove the lead or short bar that is short-circuiting the SERVOPACK main circuit terminal B2 and B3.
(SGDV-3R8A, -5R5A, -7R6A, -120A, -180A, -200A, -330A, or 400-V class SERVOPACKs.)
· Install an external regenerative resistor (optional). For selection details, refer to page 339

External Dimensions Units: mm


●Base-mounted SERVOPACKs

(1) Single-phase 100 VAC, Model: SGDV-R70F0□A, -R90F0□A, and -2R1F0□A




Approx. Mass: 1.1 kg

(2) Single-phase 100 VAC, Model: SGDV-2R8F0□A



Approx. Mass: 1.5 kg


(3) Three-phase 200 VAC, Model: SGDV-R70A0□A, -R90A0□A, and -1R6A0□A



Approx. Mass: 0.9 kg


External Dimensions Units: mm

(4) Three-phase 200 VAC, Model: SGDV-2R8A0□A




Approx. Mass: 1.0 kg

(5) Three-phase 200 VAC, Model: SGDV-3R8A0□A, -5R5A0□A, and 7R6A0□A



Approx. Mass: 1.5 kg


(6) Three-phase 200 VAC, Model: SGDV-120A0□A



Approx. Mass: 2.4 kg


External Dimensions Units: mm

(7) Single-phase 200 VAC, Model: SGDV-120A0□A008000 (1.5 kW, single-phase input type)
Three-phase 200 VAC, Model: SGDV-180A0□A and -200A0□A



Approx. Mass: 2.8 kg


(8) Three-phase 200 VAC, Model: SGDV-330A0□A



Approx. Mass: 4.6 kg


External Dimensions Units: mm

(9) Three-phase 200 VAC, Model: SGDV-470A0□A and -550A0□A



Approx. Mass: 10.2 kg


(10) Three-phase 200 VAC, Model: SGDV-590A0□A and -780A0□A



Approx. Mass: 21.0 kg

External Dimensions Units: mm


(11) Three-phase 400 VAC, Model: SGDV-1R9D0□A, -3R5D0□A, and -5R4D0□A



Mounting Hole Diagram

Approx. Mass: 2.7 kg


(12) Three-phase 400 VAC, Model: SGDV-8R4D0□A and -120D0□A



Mounting Hole Diagram

Approx. Mass: 3.7 kg

(13) Three-phase 400 VAC, Model: SGDV-170D0□A




Mounting Hole Diagram

Approx. Mass: 5.6 kg


External Dimensions Units: mm

(14) Three-phase 400 VAC, Model: SGDV-210D0□A and -260D0□A



Approx. Mass: 11.3 kg

(15) Three-phase 400 VAC, Model: SGDV-280D0□A and -370D0□A



Approx. Mass: 16.2 kg

Connectors for Base-mounted SERVOPACKs


Port	Model	Pin	Manufacturer
CN1	10250-52A2PL	50	Sumitomo 3M Ltd.
CN2	53984-0671	6	Molex Japan Co., Ltd.
CN3	HDR-EC14LFDTN-SLE-PLUS	14	Honda Tsushin Kogyo Co., Ltd.
CN7	MNC23-5K5H00	5	ADVANCED-CONNECTEK INC.
CN8	1981080-1	8	Tyco Electronics AMP K.K.

Note: The connectors above or their equivalents are used for SERVOPACKs.

External Dimensions Units: mm


● Rack-mounted SERVOPACKs (6 kW or more models: duct-ventilated)

(1) Single-phase 100 VAC, Model: SGDV-R70F0□A001, -R90F0□A001, and -2R1F0□A001




Approx. Mass: 1.1 kg

(2) Single-phase 100 VAC, Model: SGDV-2R8F0□A001



Approx. Mass: 1.5 kg


(3) Three-phase 200 VAC, Model: SGDV-R70A0□A001, -R90A0□A001, and -1R6A0□A001



Approx. Mass: 0.9 kg


External Dimensions Units: mm

(4) Three-phase 200 VAC, Model: SGDV-2R8A0□A001




Approx. Mass: 1.0 kg

(5) Three-phase 200 VAC, Model: SGDV-3R8A0□A001, -5R5A0□A001, and -7R6A□0A001



Approx. Mass: 1.5 kg


(6) Three-phase 200 VAC, Model: SGDV-120A0□A001



Approx. Mass: 2.5 kg


External Dimensions Units: mm

(7) Single-phase 200 VAC, Model: SGDV-120A0□A008000 (1.5 kW, single-phase input type)
Three-phase 200 VAC, Model: SGDV-180A0□A001 and -200A0□A001



Approx. Mass: 3.1 kg


(8) Three-phase 200 VAC, Model: SGDV-330A0□A001



Approx. Mass: 6.0 kg


External Dimensions Units: mm

(9) Three-phase 200 VAC, SGDV-470A0□A001 and -550A□A001 (Duct-ventilated type)



Approx. Mass: 8.5 kg


(10) Three-phase 200 VAC, SGDV-590A0□A001 and -780A□A001 (Duct-ventilated type)



Approx. Mass: 16.0 kg


External Dimensions Units: mm

(11) Three-phase 400 VAC, Model: SGDV-1R9D0□A001, -3R5D0□A001, and -5R4D0□A001




Approx. Mass: 2.7 kg

(12) Three-phase 400 VAC, Model: SGDV-8R4D0□A001 and -120D0□A001



Approx. Mass: 3.8 kg


(13) Three-phase 400 VAC, Model: SGDV-170D0□A001



Approx. Mass: 5.7 kg

External Dimensions Units: mm


(14) Three-phase 400 VAC, Model: SGDV-210D0□A001 and -260D0□A001 (Duct-ventilated type)



Mounting Hole Diagram

Approx. Mass: 8.1 kg

(15) Three-phase 400 VAC, Model: SGDV-280D0□A001 and -370D0□A001 (Duct-ventilated type)



Mounting Hole Diagram

Approx. Mass: 13.6 kg


Connectors for Rack-mounted SERVOPACKs



Port	Model	Pin	Manufacturer
CN1	10250-52A2PL	50	Sumitomo 3M Ltd.
CN2	53984-0671	6	Molex Japan Co., Ltd.
CN3	HDR-EC14LFDTN-SLE-PLUS	14	Honda Tsushin Kogyo Co., Ltd.
CN7	MNC23-5K5H00	5	ADVANCED-CONNECTEK INC.
CN8	1981080-1	8	Tyco Electronics AMP K.K.

Note: The connectors above or their equivalents are used for SERVOPACKs.

Selecting Cables

●Cables for CN1 CN3 CN5 CN7 CN8 (Analog Voltage/Pulse Train Reference Type SERVOPACKs)




Name		Length	Order No.	Specifications	Details
CN1 Cables for I/O Signals	Connector Terminal Converter Unit		JUSP-TA50PG-E	Terminal Block and 0.5 m Connection Cable 	(1)
	Cables with Loose Wires at One End	1 m	JZSP-CSI01-1-E	Cable with Loose Wires at Peripheral Devices 	(2)
		2 m	JZSP-CSI01-2-E		
		3 m	JZSP-CSI01-3-E		
CN3	Digital Operator		JUSP-OP05A-1-E	With Connection Cable (1 m) 	(3)
	Digital Operator Converter Cable*1	0.3 m	JZSP-CVS05-A3-E	Cable with Connectors at Both Ends 	(4)
CN7 Connection Cables for Personal Computer		2.5 m	JZSP-CVS06-02-E	Cable with Connctors at Both Ends 	(5)
CN5 Cables for Analog Monitor		1 m	JZSP-CA01-E	SERVOPACK End 	(6)
CN8 Cables for Safety Functions	Cables with Connector*2	3 m	JZSP-CVH03-03-E		(7)
	Connector Kit*3		Contact Tyco Electronics AMP K.K. Product name: Industrial Mini I/O D-shape Type1 Plug Connector Kit Model: 2013595-1		

*1 : A converter cable is required to use Σ-III series digital operators (model: JUSP-OP05A) for Σ-V series SERVOPACKs.
*2 : When using the safety function, connect this cable to the safety devices. Even when not using the safety function, use SERVOPACKs with the Safe Jumper Connector (model: JZSP-CVH05-E) connected.
*3 : Use the connector kit when you make cables yourself.

Selecting Cables

(1) Connector Terminal Converter Unit for CN1


· Configurations




Model	Cable Length (L)
JUSP-TA50PG-E	0.5 m
JUSP-TA50PG-1-E	1 m
JUSP-TA50PG-2-E	2 m

Note: Shaded items are non-stock.

· Dimensional Drawings of Terminal Block (Units: mm)




· Dimensional Drawings of Cable



(2) Cable with Loose Wires at One End for CN1

· Dimensional Drawings of Cable



* : Manufactured by Sumitomo 3M Ltd.

Note : See the next page for the connection diagram.


Model	Cable Length (L)
JZSP-CSI01-1-E	1 m
JZSP-CSI01-2-E	2 m
JZSP-CSI01-3-E	3 m

●Cable with Loose Wires at One End for CN1

Connection Diagram of JZSP-CSI01-□-E Cable

SERVOPACK End

Pin No.	Signal	Wire Color	Marking		Host Controller End Lead Marker
			Color	Dots	
1	SG	Orange	Red	1	1
3	PL1	OrangeGr	Black	1	3
2	SG	ay	Red	1	2
4	SEN	Gray	Black	1	4
5	V-REF	White	Red	1	5
6	SG	White	Black	1	6
7	PULS	Yellow	Red	1	7
8	/PULS	Yellow	Black	1	8
9	T-REF	Pink	Red	1	9
10	SG	Pink	Black	1	10
11	SIGN	Orange	Red	2	11
12	/SIGN	Orange	Black	2	12
13	PL2	Gray	Red	2	13
14	/CLR	White	Red	2	14
15	CLR	White	Black	2	15
16	–	Gray	Black	2	16
17	–	Yellow	Red	2	17
18	PL3	Yellow	Black	2	18
19	PCO	Pink	Red	2	19
20	/PCO	Pink	Black	2	20
21	BAT (+)	Orange	Red	3	21
22	BAT (-)	Orange	Black	3	22
23	–	Gray	Red	3	23
24	–	Gray	Black	3	24
25	/V-CMP+	White	Red	3	25
26	/V-CMP–	White	Black	3	26
27	/TGON+	Yellow	Red	3	27
28	/TGON–	Yellow	Black	3	28
29	/S-RDY+	Pink	Red	3	29
30	/S-RDY–	Pink	Black	3	30
31	ALM+	Orange	Red	4	31
32	ALM–	Orange	Black	4	32
33	PAO	Gray	Red	4	33
34	/PAO	Gray	Black	4	34
35	PBO	White	Red	4	35
36	/PBO	White	Black	4	36
37	ALO1	Yellow	Red	4	37
38	ALO2	Yellow	Black	4	38
39	ALO3	Pink	Red	4	39
40	/S-ON	Pink	Black	4	40
41	/P-CON	Orange	Red	5	41
42	P-OT	Orange	Black	5	42
43	N-OT	Gray	Red	5	43
44	/ALM-RST	Gray	Black	5	44
45	/P-CL	White	Red	5	45
46	/N-CL	White	Black	5	46
47	+24V-IN	Yellow	Red	5	47
48	-	Pink	Red	5	48
49_	-	Pink	Black	5	49
50	-	Yellow	Black	5	50
Case	Shield				



: Represents twisted-pair wires.


●Connector Kit for CN1

Use the following connector and cable to assemble the cable. The CN1 connector kit includes one case and one connector.


Connector Kit Model	Case		Connector	
	Model	Qty	Model	Qty
JZSP-CSI9-1-E	10350-52Z0-008*	1 set	10150-3000PE* (Soldered)	1

* : Manufactured by Sumitomo 3M Ltd.

· Dimensional Drawings of Case



· Dimensional Drawings of Connector




· Cable Size

Item	Specifications
Cable	Use twisted-pair or twisted-pair shielded wire.
Applicable Wires	AWG 24, 26, 28, 30
Cable Finished Diameter	16 dia. max.

Selecting Cables Units: mm


(3) Digital Operator (Model: JUSP-OP05A-1-E)



(4) Digital Operator Converter Cable for CN3
(Model: JZSP-CVS05-A3-E)


A converter cable is required to use Σ-Ⅲ series digital operators (model: JUSP-OP05A) for Σ-Ⅴ series SERVOPACKs.

· Dimensional Drawings



(5) Connection Cable for Personal Computer for CN7
(Model: JZSP-CVS06-02-E)


· Dimensional Drawings




IMPORTANT Use a cable specified by Yaskawa.
When using other cables, operation cannot be guaranteed.

(6) Cable for Analog Monitor for CN5
(Model: JZSP-CA01-E)

· Dimensional Drawings



* : Manufactured by Hirose Electric Corporation.



View from Cable End


· Specifications

Pin No.	Cable Color	Signal	Standard Settings
1	Red	Analog Monitor 2	Motor speed : 1V/1000 min^{-1}
2	White	Analog Monitor 1	Torque reference : 1V/100% rated torque
3, 4	Black (2 cables)	GND(0V)	–

Note : The specifications above are factory settings. Monitor specifications can be changed by changing parameters Pn006 and Pn007.

(7) Cable with Connector for CN8
(Model: JZSP-CVH03-03-E)

· Dimensional Drawings



· Specifications

Pin No.	Signal	Lead Color	Marking Color
1	Not used	–	–
2	Not used	–	–
3	/HWBB1–	White	Black
4	/HWBB1□	White	Red
5	/HWBB2–	Gray	Black
6	/HWBB2□	Gray	Red
7	EDM1–	Orange	Black
8	EDM1□	Orange	Red

efesotomasyon.com

MECHATROLINK-II Communications Reference Type SERVOPACKs



SGDV-□□□□11

(For Rotary Servomotors)

SGDV-□□□□15

(For Linear Servomotors)

Model Designations

SGDV - R70 A 11 A □

Options

Code	Specifications
Blank	Base-mounted (standard)
001000	Rack-mounted*

*: SGDV-470A, -550A, -590A, -780A SERVOPACKs are duct-ventilated.

Design Revision Order
A, B…

Interface

Code	Specifications
11	MECHATROLINK-II communications Reference Type (for rotary servomotors)
15	MECHATROLINK-II communications Reference Type (for linear servomotors)

Voltage

Code	Specifications
F	100 VAC
A	200 VAC
D	400 VAC

Σ-V Series
SGDV SERVOPACK

Current

Code	100 V (Single Phase) Applicable Servomotor Max. Capacity kW	Code	200 V (Three Phase) Applicable Servomotor Max. Capacity kW	Code	400 V (Three Phase) Applicable Servomotor Max. Capacity kW
R70	0.05	R70*	0.05	1R9	0.5
R90	0.1	R90*	0.1	3R5	1.0
2R1	0.2	1R6*	0.2	5R4	1.5
2R8	0.4	2R8*	0.4	8R4	2.0
		3R8	0.5	120	3.0
		5R5*	0.75	170	5.0
		7R6	1.0	210	6.0
		120♣	1.5	260	7.5
		180	2.0	280	11
		200	3.0	370	15
		330	5.0		
		470	6.0		
		550	7.5		
		590	11		
		780	15		

NOTE: Shaded items are non-stock.

* These amplifiers can be powered with single or three-phase.

♣ SGDV-120A□1A008000, a special version of the 1.5kW amplifier can be used for single-phase operation.

Features

●Real-time communications

MECHATROLINK-II communications enable high-speed control for 30 stations at a maximum transmission speed of 10 Mbps in a transmission cycle from 250 μs to 4 ms (user setting). Such a high transmission speed allows real-time transmission of various data required for control.

●Cost savings

Thirty stations can be connected to a single MECHATROLINK-II transmission line, so wiring costs and time are greatly reduced. Also, only one signal connector is required on the host controller. And, the all-digital network eliminates the need for conversion from digital to analog for speed/torque references and for a pulse generator to generate position references.

●High-precision motion control

The SGDV SERVOPACK when connected to the host controller in the MECHATROLINK-II network provides not only torque, position, and speed control but also synchronized phase control that requires advanced control technology. The control mode can be changed online so that the machine can move smoothly in complex motions with great efficiency.

Ratings

Single-phase 100 V

SERVOPACK Model SGDV-□□□□		R70F	R90F	2R1F	2R8F
Applicable Servomotor Max. Capacity	kW	0.05	0.1	0.2	0.4
Continuous Output Current	A_{rms}	0.66	0.91	2.1	2.8
Max. Output Current	A_{rms}	2.1	2.9	6.5	9.3
Main Circuit (Single Phase)		100 to 115 VAC+10% to −15% 50/60 Hz			
Control Circuit (Single Phase)		100 to 115 VAC+10% to −15% 50/60 Hz			

Single-phase 200 V

SERVOPACK Model SGDV-□□□□		R70A	R90A	1R6A	2R8A	5R5A	120
Applicable Servomotor Max. Capacity	kW	0.05	0.1	0.2	0.4	0.75	1.5
Continuous Output Current	A_{rms}	0.66	0.91	1.6	2.8	5.5	11.6
Max. Output Current	A_{rms}	2.1	2.9	6.5	9.3	16.9	28
Main Circuit (Single Phase)		220 to 230 VAC +10% to -15% 50/60 Hz					
Control Circuit (Single Phase)		220 to 230 VAC +10% to -15% 50/60 Hz					


Three-phase 200 V

SERVOPACK Model SGDV-□□□□		R70A	R90A	1R6A	2R8A	3R8A	5R5A	7R6A	120A	180A	200A	330A	470A	550A	590A	780A
Applicable Servomotor Max. Capacity	kW	0.05	0.1	0.2	0.4	0.5	0.75	1.0	1.5	2.0	3.0	5.0	6	7.5	11	15
Continuous Output Current	A_{rms}	0.66	0.91	1.6	2.8	3.8	5.5	7.6	11.6	18.5	19.6	32.9	46.9	54.7	58.6	78
Max. Output Current	A_{rms}	2.1	2.9	6.5	9.3	11	16.9	17	28	42	56	84	110	130	140	170
Main Circuit		Three-phase 200 to 230 VAC+10% to −15% 50/60 Hz														
Control Circuit		Single-phase 200 to 230 VAC+10% to −15% 50/60 Hz														

Three-phase 400 V

SERVOPACK Model SGDV-□□□□		1R9D	3R5D	5R4D	8R4D	120D	170D	210D	260D	280D	370D
Applicable Servomotor Max. Capacity	kW	0.5	1.0	1.5	2.0	3.0	5.0	6	7.5	11	15
Continuous Output Current	A_{rms}	1.9	3.5	5.4	8.4	11.9	16.5	20.8	25.4	28.1	37.2
Max. Output Current	A_{rms}	5.5	8.5	14	20	28	42	55	65	70	85
Main Circuit		Three-phase 380 to 480 VAC+10% to −15% 50/60 Hz									
Control Circuit		24 VDC ±15%									

●SERVOPACK Overload Characteristics



Note: Overload characteristics shown above do not guarantee continuous duty of 100% or more output. Use a servomotor with effective torque within the continuous duty zone of Torque-Motor Speed Characteristics.

Specifications

Items			Specifications
Input Power Supply	Main Circuit	100 V	Single-phase 100 to 115 VAC +10% to −15% 50/60 Hz
		200 V	Three-phase 200 to 230 VAC +10% to −15% 50/60 Hz
		400 V	Three-phase 380 to 480 VAC +10% to −15% 50/60 Hz
	Control Circuit	100 V	Single-phase 100 to 115 VAC +10% to −15% 50/60 Hz
		200 V	Single-phase 200 to 230 VAC +10% to −15% 50/60 Hz
		400 V	24 VDC ±15%
Control Method			For 100 V, for 200 V, for 400 V, single-phase or three-phase full-wave rectification IGBT PWM control, sine-wave driven
Feedback	Rotary Servomotors		Serial encoder: 13-bit (incremental encoder) : 17-bit (incremental/absolute encoder) : 20-bit (incremental/absolute encoder)
	Linear Servomotors		Serial converter or serial data
Operating Conditions	Surrounding/Storage Temperature		Surrounding temperature: 0 to +55°C, storage temperature: −20 to +85°C
	Ambient/Storage Humidity		90%RH or less (no condensation)
	Vibration/Shock Resistance		Vibration resistance: 4.9 m/s^2, Shock resistance: 19.8 m/s^2
	Protection class/Pollution degree		Protection class: IP 1X, pollution degree: 2 Do not use SERVOPACKs in the following locations: ·Locations subject to corrosive or flammable gases ·Locations subject to exposure to water, oil, or chemicals ·Locations subject to dust, including iron dust, and salts
	Others		Do not use SERVOPACKs in the following locations: ·Locations subject to static electricity noise, strong electromagnetic/magnetic fields, radioactivity
	Elevation		1000 m or less
Compliant Standards			UL 508C EN50178, EN55011 class A group 1, EN61800-3, EN61800-5-1
Configuration			Base-mounted (Rack-mounting available as an option for some models. 6 kW or more models are duct-ventilated.)
Performance	Speed Control Range		1:5000 (The lowest speed of the speed control range is the speed at which the servomotor will not stop with a rated torque load.)
	Speed Regulation*	Load Regulation	0% to 100% load: ±0.01% max. (at rated speed)
		Voltage Regulation	Rated voltage: ±10% : 0% (at rated speed)
		Temperature Regulation	25±25°C : ±0.1% max. (at rated speed)
	Torque Control Tolerance (Repeatability)		±1%
	Soft Start Time Setting		0 to 10 s (can be set individually for acceleration and deceleration.)
I/O Signals	Encoder Output Pulses		Phase A, phase B, phase C: line driver output The number of dividing pulse: Any setting ratio is available.
Communications	RS-422A Communications	Interface	Digital operator, RS-422A port of personal computers etc.
		1:N communications	RS-422A port: N=15 max. available
		Axis address setting	Set by parameters
		Function	Status display, parameter settings, adjustment functions, utility functions
	USB Communications	Interface	Personal computers (application: engineering tool SigmaWin+)
		1:N communications	Compliant with USB1.1 standard
		Function	Status display, parameter settings, adjustment functions, utility functions
Display		Power Charge	CHARGE for main circuit power supply input confirmation One LED (orange)
Analog Monitor			Analog monitor connector built in for monitoring speed, torque and other reference signals. Number of points: 2
Protective Functions			Overcurrent, Overvoltage, low voltage, overload, regeneration error
Utility Functions			Alarm history, JOG operation, origin search, etc.
Regenerative Processing			100 VAC model: External regenerative resistor (optional) 200 VAC SGDV-R70A, -R90A, -1R6A, -2R8A: External regenerative resistor (optional) 200 VAC SGDV-470A, -550A, -590A, -780A: External regenerative resistor unit (optional) 200 VAC models other than shown above: Built-in regenerative resistor 400 VAC SGDV-210D, -260D, -280D, -370D: External regenerative resistor unit (optional) 400 VAC models other than shown above: Built-in regenerative resistor
Safety Functions		Input	/HWBB1, /HWBB2: Hard wire base block signal
		Output	EDM1: Status monitor (fixed output) of built-in safety circuit
		Compliant Standards	EN954 category 3 Stop category 0, IEC61508 SIL 2
Option Card Function		Feedback	Serial encoder communications input for fully-closed loop control

*: Speed regulation is defined as follows:

$$\text{Speed regulation} = \frac{\text{No-load motor speed} - \text{Total load motor speed}}{\text{Rated motor speed}} \times 100\%$$

The motor speed may change due to voltage variations or temperature variation. The ratio of speed changes to the rated speed represent speed regulation due to voltage and temperature variations.

Specifications

●Rotary Servomotors

Items			Specifications	
I/O Signal	Encoder Output Pulses		Phase A, phase B, phase C: line driver output The number of dividing pulse: Any setting ratio is available.	
	Sequence Input	Number of Channels	7 channels	
		Function	Signal allocations and positive/negative logics can be modified. Homing deceleration switch signal (/DEC), external latch signal (/EXT1 to 3), forward run prohibited (P-OT), reverse run prohibited (N-OT), forward current limit (/P-CL), reverse current limit (/N-CL)	
	Sequence Output	Fixed Output	Servo alarm (ALM)	
		Output Signals which can be allocated	Number of Channels	3 channels
			Function	Signal allocations and positive/negative logics can be modified. Positioning completion (/COIN), speed coincidence detection (/V-CMP), servomotor rotation detection (/TGON), servo ready (/S-RDY), torque limit detection (/CLT), speed limit detection (/VLT), brake interlock (/BK), warning (/WARN), NEAR (/NEAR)
Panel Operator		Display	7-segment 1-digit LED (red)	
		Switch	Rotary switch: 16 positions, DIP switch: 4 poles	
MECHATROLINK Communications		Communications Protocol	MECHATROLINK-II	MECHATROLINK-I
		Transmission Speed	10 Mbps	4 Mbps
		Transmission Cycle	250 μs, 0.5 to 4.0 ms (multiple of 0.5 ms)	2 ms
		Number of Words for Link Transmission	Can be switched between 17-bytes /station and 32-bytes / station.	17-bytes /station
		Station Address	41H to 5FH (max. number of slaves: 30)	
Command Method		Performance	Position control, speed control, and torque control through MECHATROLINK communications	
		Command Input	MECHATROLINK commands (for sequence, motion, data setting/reference, monitor, adjustment, and other commands.)	

●Linear Servomotors

Items			Specifications	
I/O Signal	Encoder Output Pulses		Phase A, phase B, phase C: line driver output The number of dividing pulse: Any setting ratio is available.	
	Sequence Input	Number of Channels	7 channels	
		Function	Signal allocations and positive/negative logics can be modified. Homing deceleration switch signal (/DEC), external latch signal (/EXT1 to 3), forward run prohibited (P-OT), reverse run prohibited (N-OT), forward current limit (/P-CL), reverse current limit (/N-CL)	
	Sequence Output	Fixed Output	Servo alarm (ALM)	
		Output Signals which can be allocated	Number of Channels	3 channels
			Function	Signal allocations and positive/negative logics can be modified. Positioning completion (/COIN), speed coincidence detection (/V-CMP), servomotor movement detection (/TGON), servo ready (/S-RDY), force limit detection (/CLT), speed limit detection (/VLT), brake interlock (/BK), warning (/WARN), NEAR (/NEAR)
Panel Operator		Display	7-segment 1-digit LED (red)	
		Switch	Rotary switch: 16 positions, piano switch: 4 poles	
MECHATROLINK Communications		Communications Protocol	MECHATROLINK-II	MECHATROLINK-I
		Transmission Speed	10 Mbps	4 Mbps
		Transmission Cycle	250 μs, 0.5 to 4.0 ms (multiple of 0.5 ms)	2 ms
		Number of Words for Link Transmission	Can be switched between 17-bytes /station and 32-bytes / station.	17-bytes /station
		Station Address	41H to 5FH (max. number of slaves: 30)	
Command Method		Performance	Position control, speed control, and force control through MECHATROLINK-II communications	
		Command Input	MECHATROLINK commands and MECHATROLINK-II commands (for sequence, motion, data setting/reference, monitor, adjustment, and other commands.)	

Power Supply Capacities and Power Losses

The following table shows SERVOPACK's power supply capacities and power losses at the rated output.

Main Circuit Power Supply	Applicable Servomotor Max. Capacity kW	SERVOPACK Model SGDV-	Power Supply Capacity kVA	Output Current A	Main Circuit Power Loss W	Regenerative Resistor Power Loss W	Control Circuit Power Loss W	Total Power Loss W
Signal-phase 100 V	0.05	R70F	0.2	0.66	5.4	—	17	22.4
	0.1	R90F	0.3	0.91	7.8			24.8
	0.2	2R1F	0.7	2.1	14.4			31.4
	0.4	2R8F	1.4	2.8	25.6			42.6
Single-phase 200 V	0.05	R70A	0.2	0.66	5.2	—	17	22.2
	0.1	R90A	0.3	0.91	7.4			24.4
	0.2	1R6A	0.7	1.6	13.7			30.7
	0.4	2R8A	1.2	2.8	24.9			41.9
	0.75	5R5A	1.9	5.5	52.7	8		77.7
	1.5	120A	4	11.6	68.2	10	22	100.2
Three-phase 200 V	0.05	R70A	0.2	0.66	5.1	—	17	22.1
	0.1	R90A	0.3	0.91	7.3			24.3
	0.2	1R6A	0.6	1.6	13.5			30.5
	0.4	2R8A	1	2.8	24.0			41.0
	0.5	3R8A	1.4	3.8	20.1	8		45.1
	0.75	5R5A	1.6	5.5	43.8			68.8
	1.0	7R6A	2.3	7.6	53.6			78.6
	1.5	120A	3.2	11.6	65.8	10	22	97.8
	2.0	180A	4	18.5	111.9	16		149.9
	3.0	200A	5.9	19.6	113.8			161.4
	5.0	330A	7.5	32.9	263.7	36	27	326.7
	6.0	470A	10.7	46.9	279.4	(180)*1	33	312.4
	7.5	550A	14.6	54.7	357.8	(350)*2		390.8
	11	590A	21.7	58.6	431.7		48	479.7
	15	780A	29.6	78	599.0			647.0
Three-phase 400 V	0.5	1R9D	1.1	1.9	24.6	14	21	59.6
	1.0	3R5D	2.3	3.5	46.1			81.1
	1.5	5R4D	3.5	5.4	71.3			106.3
	2.0	8R4D	4.5	8.4	77.9	28	25	130.9
	3.0	120D	7.1	11.9	108.7			161.7
	5.0	170D	11.7	16.5	161.1	36	24	221.1
	6.0	210D	12.4	20.8	172.7	(180)*3	27	199.7
	7.5	260D	14.4	25.7	218.6			245.6
	11	280D	21.9	28.1	294.6	(350)*4	30	324.6
	15	370D	30.6	37.2	403.8			433.8


*1: For the optional JUSP-RA04-E regenerative resistor unit.
*2: For the optional JUSP-RA05-E regenerative resistor unit.
*3: For the optional JUSP-RA18-E regenerative resistor unit.
*4: For the optional JUSP-RA19-E regenerative resistor unit.

Notes: 1 SGDV-R70F, -R90F, -2R1F, -2R8F, -R70A, -R90A, -1R6A, and -2R8A SERVOPACKs do not have built-in regenerative resistors.
If the regenerative energy exceeds the specified value, connect an external regenerative resistor (optional).
2 SGDV-470A, -550A, -590A, -780A, -210D, -260D, -280D, -370D SERVOPACKs do not have built-in regenerative resistors.
Be sure to connect a regenerative resistor unit (optional) or an external regenerative resistor (optional). For selection details, refer to page 339.
3 Regenerative resistor power losses are allowable losses. Take the following action if this value is exceeded.
· Remove the lead or short bar that is short-circuiting the SERVOPACK main circuit terminal B2 and B3.
(SGDV-3R8A, -5R5A, -7R6A, -120A, -180A, -200A, -330A, or 400-V class SERVOPACKs.)
· Install an external regenerative resistor (optional). For selection details, refer to page 339.

External Dimensions Units: mm

●Base-mounted SERVOPACKs


(1) Single-phase 100 VAC, Model: SGDV-R70F1□A, -R90F1□A, and -2R1F1□A



Mountiong Hole Diagram

Approx. Mass: 1.0 kg


(2) Single-phase 100 VAC, Model: SGDV-2R8F1□A



Mounting Hole Diagram

Approx. Mass: 1.5 kg

(3) Three-phase 200 VAC, Model: SGDV-R70A1□A, -R90A1□A, and -1R6A1□A




Mounting Hole Diagram

Approx. Mass: 0.9 kg

External Dimensions Units: mm


(4) Three-phase 200 VAC, Model: SGDV-2R8A1□A



Mounting Hole Diagram

Approx. Mass: 1.0 kg


(5) Three-phase 200 VAC, Model: SGDV-3R8A1□A, -5R5A1□A, and -7R6A1□A



Mounting Hole Diagram

Approx. Mass: 1.5 kg

(6) Three-phase 200 VAC, Model: SGDV-120A1□A




Mounting Hole Diagram

Approx. Mass: 2.4 kg


External Dimensions Units: mm

(7) Single-phase 200 VAC, Model: SGDV-120A1□A008000 (1.5 kW, single-phase input type)
Three-phase 200 VAC, Model: SGDV-180A1□A and -200A1□A



Approx. Mass: 2.8 kg


(8) Three-phase 200 VAC, Model: SGDV-330A1□A



Approx. Mass: 4.6 kg


External Dimensions Units: mm

(9) Three-phase 200 VAC, Model: SGDV-470A1□A and -550A1□A



Approx. Mass:10.2 kg


(10) Three-phase 200 VAC, Model: SGDV-590A1□A and -780A1□A



Approx. Mass: 21.0 kg

External Dimensions Units: mm


(11) Three-phase 400 VAC, Model: SGDV-1R9D1□A, -3R5D1□A, and -5R4D1□A



Mounting Hole Diagram

Approx. Mass: 2.7 kg


(12) Three-phase 400 VAC, Model: SGDV-8R4D1□A, and -120D1□A



Mounting Hole Diagram

Approx. Mass: 3.7 kg

(13) Three-phase 400 VAC, Model: SGDV-170D1□A




Mounting Hole Diagram

Approx. Mass: 5.6 kg

External Dimensions Units: mm


(14) Three-phase 400 VAC, Model: SGDV-210D1□A and -260D1□A



Mounting Hole Diagram

Approx. Mass: 11.3 kg

(15) Three-phase 400 VAC, Model: SGDV-280D1□A and -370D1□A



Mounting Hole Diagram

Approx. Mass: 16.2 kg

Connectors for Base-mounted SERVOPACKs


Port	Model	Pin	Manufacturer
CN1	10226-52A2PL	26	Sumitomo 3M Ltd.
CN2	53984-0671	6	Molex Japan Co., Ltd.
CN3	HDR-EC14LFDTN-SLE-PLUS	14	Honda Tsushin Kogyo Co., Ltd.
CN6	1903815-1	8	Tyco Electronics AMP K.K.
CN7	MNC23-5K5H00	5	ADVANCED-CONNECTEK INC.
CN8	1981080-1	8	Tyco Electronics AMP K.K.

Note: The connectors above or their equivalents are used for SERVOPACKs.

External Dimensions Units: mm

● Rack-mounted SERVOPACKs (6 kW or more models: duct-ventilated)


(1) Single-phase 100 VAC, Model: SGDV-R70F1□A001, -R90F1□A001, and -2R1F1□A001



Mountiong Hole Diagram

Approx. Mass: 1.1 kg


(2) Single-phase 100 VAC, Model: SGDV-2R8F1□A001



Mountiong Hole Diagram

Approx. Mass: 1.5 kg

(3) Three-phase 200 VAC, Model: SGDV-R70A1□A001, -R90A1□A001, and -1R6A1□A001




Mounting Hole Diagram

Approx. Mass: 0.9 kg


External Dimensions Units: mm

(4) Three-phase 200 VAC, Model: SGDV-2R8A1□A001




Approx. Mass: 1.0 kg

(5) Three-phase 200 VAC, model: SGDV-3R8A1□A001, -5R5A1□A001, and -7R6A1□A001



Approx. Mass: 1.5 kg


(6) Three-phase 200 VAC, Model: SGDV-120A1□A001



Approx. Mass: 2.5 kg


External Dimensions Units: mm

(7) Single-phase 200 VAC, Model: SGDV-120A1□A008000 (1.5 kW, single-phase input type)
Three-phase 200 VAC, Model: SGDV-180A1□A001 and -200A1□A001



Approx. Mass: 3.1 kg


(8) Three-phase 200 VAC, Model: SGDV-330A1□A001



Approx. Mass: 5.0 kg

External Dimensions Units: mm


(9) Three-phase 200 VAC, Model: SGDV-470A1□A001 and -550A1□A001 (Duct-ventilated type)



Mounting Hole Diagram

Approx. Mass: 8.5 kg

(10) Three-phase 200 VAC, Model: SGDV-580A1□A001 and -780A1□A001 (Duct-ventilated type)




Mounting Hole Diagram

Approx. Mass: 16.0 kg


External Dimensions Units: mm

(11) Three-phase 400 VAC, Model: SGDV-1R9D1□A001, -3R5D1□A001, and -5R4D1□A001




Approx. Mass: 2.7 kg

(12) Three-phase 400 VAC, Model: SGDV-8R4D1□A001 and -120D1□A001



Approx. Mass: 3.8 kg


(13) Three-phase 400 VAC, Model: SGDV-170D1□A001



Approx. Mass: 5.7 kg

External Dimensions Units: mm


(14) Three-phase 400 VAC, Model: SGDV-210D1□A001 and -260D1□A001 (Duct-ventilated type)



Mounting Hole Diagram

Approx. Mass: 8.1 kg

(15) Three-phase 400 VAC, Model: SGDV-280D1□A001 and -370D1□A001 (Duct-ventilated type)



Mounting Hole Diagram

Approx. Mass: 13.6 kg


Connectors for Rack-mounted SERVOPACKs







Port	Model	Pin	Manufacturer
CN1	10226-52A2PL	26	Sumitomo 3M Ltd.
CN2	53984-0671	6	Molex Japan Co., Ltd.
CN3	HDR-EC14LFDTN-SLE-PLUS	14	Honda Tsushin Kogyo Co., Ltd.
CN6	1903815-1	8	Tyco Electronics AMP K.K.
CN7	MNC23-5K5H00	5	ADVANCED-CONNECTEK INC.
CN8	1981080-1	8	Tyco Electronics AMP K.K.

Note: The connectors above or their equivalents are used for SERVOPACKs.

Selecting Cables

● Cables for CN1 CN3 CN5 CN6 CN7 CN8 (MECHATROLINK-II Communications Reference Type SERVOPACKs)



Name		Length	Order No.	Specifications	Details
CN1 Cables for I/O Signals	Connector Kit		JZSP-CSI9-2-E	Soldered 	(1)
	Connector Terminal Converter Unit	0.5 m	SBK-U-VBA-A5	Terminal Block and 0.5 m Connection Cable 	(2)
		1 m	SBK-U-VBA-01		
		3 m	SBK-U-VBA-03		
	Cable with Loose wire at One End	1 m	JZSP-CSI02-1-E		(3)
		2 m	JZSP-CSI02-2-E		
		3 m	JZSP-CSI02-3-E		
CN3	Digital Operator		JUSP-OP05A-1-E	With Connection Cable (1 m) 	(4)
	Digital Operator Converter Cable*1	0.3 m	JZSP-CVS05-A3-E	Cable with Connectors at Both Ends 	(5)
CN7 Connection Cables for Personal Computer		2.5 m	JZSP-CVS06-02-E	Cable with Connectors at Both Ends 	(9)
CN6A CN6B MECHATROLINK-II Communication Cable	Cables with Connectors at Both Ends	0.5 m	JEPMC-W6002-A5-E		(7)
		1 m	JEPMC-W6002-01-E		
		–	JEPMC-W6002-□□-E		
	Terminator		JEPMC-W6022-E		(8)
CN5 Cables for Analog Monitor		1 m	JZSP-CA01-E	SERVOPACK End 	(6)
CN8 Cables for Safety Functions	Cables with Connector*2	3 m	JZSP-CVH03-03-E		(10)
	Connector kit*3		Contact Tyco Electronics AMP K.K. Product name : Industrial Mini I/O D-shape Type1 Plug Connector Kit Model : 2013595-1		

*1 : A converter cable is required to use Σ-Ⅲ series digital operators (model: JUSP-OP05A) for Σ-Ⅴ series SERVOPACKs.
*2 : When using the safety function, connect this cable to the safety devices.
Even when not using the safety function, use SERVOPACKs with the Safe Jumper Connector (model: JZSP-CVH05-E) connected.
*3 : Use the connector kit when you make cables yourself.

Selecting Cables Units: mm

(1) Connector Kit for CN1

Use the following connector and cable to assemble the cable. The CN1 connector kit includes one case and one connector.


Connector Kit Model	Case		Connector	
	Model	Qty	Model	Qty
JZSP-CSI9-2-E	10326-52A0-008*	1 set	10126-3000PE* (Soldered)	1

* : Manufactured by Sumitomo 3M Ltd.


· Cable Size

Item	Specifications
Cable	Use twisted-pair or twisted-pair shielded wire.
Applicable Wires	AWG24, 26, 28, 30
Cable Finished Diameter	16 dia. max.


· Dimensional Drawings of Case





· Dimensional Drawings of Connector



(2) Connector Terminal Converter Unit for CN1 (SBK-U-VBA-xx)








CABLE SPECIFICATION (mm)	
OUTER DIAMETER	6.5 +/- 0.2mm
BENDING RADIUS	6 x O.D. MINIMUM 15 x O.D. FOR LONG TERM RELIABILITY

ITEM#	L = LENGTH (mm)
SBK-U-VBA-A5	500 +/- 38.1
SBK-U-VBA-01	1000 +/- 38.1
SBK-U-VBA-03	3000 +/- 38.1




SBK-U-VBA-xx Function Chart for SGDV Servo Amplifier

Pin No.	SGDV Mechatrolink-II type / SGDV Option type	
	Signal	Function
1	/BK+ (/SO1+)	Brake interlock output (+) (General purpose output 1 (+))
2	/BK- (/SO1-)	Brake interlock output (-) (General purpose output 1 (-))
3	ALM+	Servo alarm output (+)
4	ALM-	Servo alarm output (-)
5	-	
6	+24VIN	Control power supply for sequence signal input
7	P-OT (/SI1)	Forward run prohibited input (General purpose input 1)
8	N-OT (/SI2)	Reverse run prohibited input (General purpose input 2)
9	/DEC (/SI3)	Zero-point return deceleration switch input (General purpose input 3)
10	/EXT1 (/SI4)	External latch signal 1 input (General purpose input 4)
11	/EXT2 (/SI5)	External latch signal 2 input (General purpose input 5)
12	/EXT3 (/SI6)	External latch signal 3 input (General purpose input 6)
13	/SI0	General purpose input 0
14	BAT (+)	Battery (+) input
15	BAT (-)	Battery (-) input
16	SG	Signal ground
17	PAO	Phase-A pulse output (+)
18	/PAO	Phase-A pulse output (-)
19	PBO	Phase-B pulse output (+)
20	/PBO	Phase-B pulse output (-)
21	PCO	Phase-C pulse output (+)
22	/PCO	Phase-C pulse output (-)
23	/SO2+	General purpose output 2 (+)
24	/SO2-	General purpose output 2 (-)
25	/SO3+	General purpose output 3 (+)
26	/SO3-	General purpose output 3 (-)

Note: General purpose input and output signals are shown with their default signals assigned - signal assignment may have been changed by parameter

Selecting Cables Units: mm

(3) Cable with Loose Wires at One End for CN1
Dimensional Drawings of Cable



Model	Cable Length
JZSP-CSI02-1-E	1 m
JZSP-CSI02-2-E	2 m
JZSP-CSI02-3-E	3 m


●Cable with Loose Wires at One End for CN1
Connection Diagram of JZSP-CSI02-□-E Cable

SERVOPACK End / Host Controller End

Pin No.	Signal	Wire Color	Marking Color	Marking Dots	Lead Marker
1	/BK+	Blue	Red	1	1
2	/BK−	Blue	Black	1	2
3	ALM+	Pink	Red	1	3
4	ALM−	Pink	Black	1	4
5	–	Green	Red	1	5
6	+24VIN	Green	Black	1	6
7	P-OT	Orange	Red	1	7
8	N-OT	Orange	Black	1	8
9	/DEC	Gray	Red	1	9
10	/EXT1	Gray	Black	1	10
11	/EXT2	Blue	Red	2	11
12	/EXT3	Blue	Black	2	12
13	/SI0	Pink	Red	2	13
14	BAT (+)	Green	Red	2	14
15	BAT (−)	Green	Black	2	15
16	SG	Pink	Black	2	16
17	PAO	Orange	Red	2	17
18	/PAO	Orange	Black	2	18
19	PBO	Gray	Red	2	19
20	/PBO	Gray	Black	2	20
21	PCO	Blue	Red	3	21
22	/PCO	Blue	Black	3	22
23	/SO2+	Pink	Red	3	23
24	/SO2−	Pink	Black	3	24
25	/SO3+	Green	Red	3	25
26	/SO3−	Green	Black	3	26

: Represents twisted-pair wires.


(4) Digital Operator (Model: JUSP-OP05A-1-E)



(5) Digital Operator Converter Cable for CN3
(Model: JZSP-CVS05-A3-E)


A converter cable is required to use Σ-Ⅲ series digital operators (model: JUSP-OP05A) for Σ-Ⅴ series SERVOPACKs.

· Dimensional Drawings




(6) Cable for Analog Monitor for CN5
(Model: JZSP-CA01-E)

· Dimensional Drawings



* : Manufactured by Hirose Electric Corporation.



View from Cable End

· Specifications


Pin No.	Cable Color	Signal	Standard Settings
1	Red	Analog Monitor 2	Motor speed : 1V/1000 min^{-1}
2	White	Analog Monitor 1	Torque reference : 1V/100% rated torque
3, 4	Black (2 cables)	GND(0V)	–

Note : The specifications above are factory settings. Monitor specifications can be changed by changing parameters Pn006 and Pn007.

(7) MECHATROLINK-II Communications Cable for CN6
(Model: JEPMC-W6002-□□-E)


· Dimensional Drawings

①Cable with Connectors at Both Ends



Model	Cable Length(L)
JEPMC-W6002-A5-E	0.5 m
JEPMC-W6002-01-E	1.0 m
JEPMC-W6002-03-E	3.0 m
JEPMC-W6002-05-E	5.0 m
JEPMC-W6002-10-E	10.0 m
JEPMC-W6002-20-E	20.0 m
JEPMC-W6002-30-E	30.0 m
JEPMC-W6002-40-E	40.0 m
JEPMC-W6002-50-E	50.0 m

②Cable with Ferrite Core




Model	Cable Length (L)
JEPMC-W6003-A5-E	0.5 m
JEPMC-W6003-01-E	1.0 m
JEPMC-W6003-03-E	3.0 m
JEPMC-W6003-05-E	5.0 m
JEPMC-W6003-10-E	10.0 m
JEPMC-W6003-20-E	20.0 m
JEPMC-W6003-30-E	30.0 m
JEPMC-W6003-40-E	40.0 m
JEPMC-W6003-50-E	50.0 m

IMPORTANT Use a MECHATROLINK-II communications cable specified by Yaskawa. When using other cables, noise resistance may be reduced, and operation cannot be guaranteed.

(8) MECHATROLINK-II Terminator for CN6
(Model : JEPMC-W6022-E)


· Dimensional Drawings



Selecting Cables Units: mm

(9) Connection Cable for Personal Computer for CN7
(Model: JZSP-CVS06-02-E)


· Dimensional Drawings



IMPORTANT Use a cable specified by Yaskawa.
When using other cables, operation cannot be guaranteed.

(10) Cable with Connector for CN8
(Model: JZSP-CVH03-03-E)

· Dimensional Drawings



· Specifications

Pin No.	Signal	Lead Color	Marking Color
1	Not used	−	−
2	Not used	−	−
3	/HWBB1−	White	Black
4	/HWBB1+	White	Red
5	/HWBB2−	Gray	Black
6	/HWBB2+	Gray	Red
7	EDM1−	Orange	Black
8	EDM1+	Orange	Red

SERVOPACK with Additional Options



efesotomasyon.com

Model Designations

Limited Stock Items

SGDV R70 A 0 1 A 000 00 0 001

Σ-V Series SGDV SERVOPACK

Current

Voltage	Code	Applicable Servomotor Max. Capacity kW
100 V	R70	0.05
	R90	0.1
	2R1	0.2
	2R8	0.4
200 V	R70*3	0.05
	R90*3	0.1
	1R6*3	0.2
	2R8*3	0.4
	3R8	0.5
	5R5*3	0.75
	7R6	1.0
	120*4	1.5
	180	2.0
	200	3.0
	330	5.0
	470	6.0
	550	7.5
	590	11
	780	15
400V	1R9	0.5
	3R5	1.0
	5R4	1.5
	8R4	2.0
	120	3.0
	170	5.0
	210	6.0
	260	7.5
	280	11
	370	15

*3: These amplifiers can be powered with single or three-phase.

*4: SGDV-120A□1A008000□□□, a special version of the 1.5kW amplifier can be used for single-phase operation.

Voltage

Code	Specifications
F	100 VAC
A	200 VAC
D	400 VAC

Interface Options

Code	Specifications
0	Analog voltage/pulse train reference type
1	MECHATROLINK-II communication reference type
E	Other control architecture type (i.e. MP2600iec)

Motor Type

Code	Specifications
1	Rotary Servomotors
5*5	Linear Servomotors

*5 Fully Closed Loop option not available with linear style amps.

Design Revision Order: A, B…

Options (hardware)

Code	Specifications
000	Base-mounted (standard)

Options (software)

Code	Specifications
00	standard

Options (parameter)

Code	Specifications
0	standard

Option Function

Code	Specifications
300 *2	MP2600iec Single Axis Controller
200 *2	EtherCAT (CoE) communications reference
001 *1	Fully-closed loop
201 *2	EtherCAT (CoE) communications reference and Fully-closed loop control

*1 This option only available with interface types 0 and 1.

*2 This option only available with interface type E

Additional Options

The **MP2600iec Single Axis Controller Option** provides IEC61131-3 standardized programming for the Sigma-5 servo system. This single axis product is completely scaleable with the MP2000iec multi-axis controller platform via the common programming environment, MotionWorks IEC. Built in Ethernet/IP and Modbus TCP/IP (master and slave) allow for connection to most PLC's and expansion I/O. PLCopen function blocks with MotionWorks IEC simplify programming, while a diagnostic web server reduces field maintenance time. An optional OPC server allows for data exchange with Windows based HMI and SCADA systems.

The **Full Closed Loop Option** allows the user to close the position loop around a secondary feedback device placed near the load. This feature can help eliminate the effects of mechanical compliance and thermal variances of mechanical components allowing for more precise control and improved machine performance.

The **EtherCAT (CoE) Network Option** implements the CANopen drive profile (CiA402) in EtherCAT communication (real-time Ethernet communication).

- ***Topology***: Flexible topologies enable the application of various system architectures, such as cascade connection, line connection, star connection, and ring connection.
- ***Synchronization Control***: The distributed clock from the master realizes synchronization. The transmission delay that is set to each slave as offset synchronizes perfectly.

Product Labeling


The three digit option function code allows for expandability of the servo amplifier's functionality. Each digit of the code defines a different type of option

- First Digit (Control Architecture): compatible with various communication interfaces or single-axis control architectures.
- Second Digit (Safety)*: compatible with EN60204-1 stop category 1 and 2
  (stop category 0 is standard)
- Third Digit (Feedback): compatible with fully-closed loop control

*: Under development.

NOTE: Amplifiers with Interface Options 0 and 1 can accommodate option modules that utilize the 2nd and 3rd digits of the Option Module Code (the first digit will always be 0 for these amplifiers). Amplifiers with Interface Option E can accommodate option modules that utilize all 3 digits of the Option Module Code.

Combination Example:



Nameplate for SERVOPACK with Option Module
Model (20 digits) : SGDV□□□□E□A000000201

Nameplate for EtherCAT (CoE) Network Module
Model：SGDV-OCA01A

Nameplate for SERVOPACK
Model：SGDV-□□□□E□A
(Refer to Model Designations provided in the SERVOPACK pages for details.)

Nameplate for Option Module for Fully-closed Loop Control
Model：SGDV-OFA01A
(This model number is shown on the nameplate for option module for fully-closed loop control)

Ratings

Single-phase 100 V

SERVOPACK Model SGDV□□□□		R70F	R90F	2R1F	2R8F
Applicable Servomotor Max. Capacity	kW	0.05	0.1	0.2	0.4
Continuous Output Current	A_{rms}	0.66	0.91	2.1	2.8
Max. Output Current	A_{rms}	2.1	2.9	6.5	9.3
Main Circuit (Single Phase)		100 to 115 VAC +10% to -15% 50/60 Hz			
Control Circuit (Single Phase)		100 to 115 VAC +10% to -15% 50/60 Hz			

Single-phase 200 V

SERVOPACK Model SGDV□□□□		R70A	R90A	1R6A	2R8A	5R5A	120
Applicable Servomotor Max. Capacity	kW	0.05	0.1	0.2	0.4	0.75	1.5
Continuous Output Current	A_{rms}	0.66	0.91	1.6	2.8	5.5	11.6
Max. Output Current	A_{rms}	2.1	2.9	6.5	9.3	16.9	28
Main Circuit (Single Phase)		220 to 230 VAC +10% to -15% 50/60 Hz					
Control Circuit (Single Phase)		220 to 230 VAC +10% to -15% 50/60 Hz					


Three-phase 200 V


SERVOPACK Model SGDV□□□□		R70A	R90A	1R6A	2R8A	3R8A	5R5A	7R6A	120A	180A	200A	330A	470A	550A	590A	780A
Applicable Servomotor Max. Capacity	kW	0.05	0.1	0.2	0.4	0.5	0.75	1.0	1.5	2.0	3.0	5.0	6	7.5	11	15
Continuous Output Current	A_{rms}	0.66	0.91	1.6	2.8	3.8	5.5	7.6	11.6	18.5	19.6	32.9	46.9	54.7	58.6	78
Max. Output Current	A_{rms}	2.1	2.9	6.5	9.3	11	16.9	17	28	42	56	84	110	130	140	170
Main Circuit		Three-phase 200 to 230 VAC +10% to -15% 50/60 Hz														
Control Circuit		Single-phase 200 to 230 VAC +10% to -15% 50/60 Hz														


Three-phase 400 V

SERVOPACK Model SGDV□□□□		1R9D	3R5D	5R4D	8R4D	120D	170D	210D	260D	280D	370D
Applicable Servomotor Max. Capacity	kW	0.5	1.0	1.5	2.0	3.0	5.0	6	7.5	11	15
Continuous Output Current	A_{rms}	1.9	3.5	5.4	8.4	11.9	16.5	20.8	25.4	28.1	37.2
Max. Output Current	A_{rms}	5.5	8.5	14	20	28	42	55	65	70	85
Main Circuit		Three-phase 380 to 480 VAC +10% to -15% 50/60 Hz									
Control Circuit		24 VDC ±15%									

●SERVOPACK Overload Characteristics







Note: Overload characteristics shown above do not guarantee continuous duty of 100% or more output. Use a servomotor with effective torque within the continuous duty zone of *Torque-Motor Speed Characteristics.*

Specifications

Items		Specifications
Control Method		IGBT PWM control, sine-wave driven
Feedback	Rotary Servomotors	Serial encoder: 13-bit (incremental encoder) : 17-bit (incremental/absolute encoder) : 20-bit (incremental/absolute encoder)
	Linear Servomotors *1	Serial converter or serial data
Operating Conditions	Surrounding/Storage Temperature	Surrounding temperature: 0 to +55°C, storage temperature: -20 to +85°C
	Ambient/Storage Humidity	90%RH or less (no condensation)
	Vibration/Shock Resistance	Vibration resistance: 4.9 m/s², Shock resistance: 19.8 m/s²
	Protection class/Pollution degree	Protection class: IP 1X, pollution degree: 2 Do not use SERVOPACKs in the following locations: ·Locations subject to corrosive or flammable gases ·Locations subject to exposure to water, oil, or chemicals ·Locations subject to dust, including iron dust, and salts
	Others	Do not use SERVOPACKs in the following locations: ·Locations subject to static electricity noise, strong electromagnetic/magnetic fields, radioactivity
	Elevation	1000 m or less

Specifications

Items			Specifications	
Compliant Standards			UL508C EN50178, EN55011/A2 group1 classA, EN61000-6-2, EN61800-3, EN61800-5-1, EN954-1, IEC61508-1 to 4	
Configuration			Standard: Base-mounted; Optional: Rack-mounted, Duct-ventilated	
Performance	Speed Control Range		1:5000 (The lowest speed of the speed control range is the speed at which the servomotor will not stop with a rated torque load.)	
	Speed Regulation*2	Load Regulation	0% to 100% load: ±0.01% max. (at rated speed)	
		Voltage Regulation	Rated voltage: ±10% : 0% (at rated speed)	
		Temperature Regulation	25±25°C : ±0.1% max. (at rated speed)	
	Torque Control Tolerance (Repeatability)		±1%	
I/O Signals	Encoder Output Pulses		Phase A, phase B, phase C: line driver output The number of dividing pulse: Any setting ratio is available.	
	Sequence Input	Input Signals which can be allocated	No. of Channels	7 channels
			Functions	The signal allocation and positive/negative logic can be modified. Forward run prohibited (P-OT), reverse run prohibited (N-OT), forward torque limit (/P-CL), reverse torque limit (/N-CL), general-purpose input signal (/SI0 to /SI6)*3
	Sequence Output	Fixed Output	Servo alarm (ALM)	
		Output Signals which can be allocated	No. of Channels	3 channels
			Functions	The signal allocation and positive/negative logic can be modified. Positioning completion (/COIN), speed coincidence detection(/V-CMP), servomotor rotation detection (/TGON), servo ready(/S-RDY), torque limit detection (/CLT), speed limit detection(/VLT), brake (/BK), warning (/WARN), near (/NEAR)
Communications	RS-422A Communications	Interface	Digital operator, RS-422A port of personal computers etc.	
		1:N communications	RS-422A port: N=15 max. available	
		Axis address setting	Set by parameters	
	USB Communications	Interface	Personal computers (application: engineering tool SigmaWin+)	
		Communications Standard	Compliant with USB 1.1 standard (12 Mbps)	
Display			CHARGE and POWER (seven-segment display)	
Analog Monitor			Number of points: 2 Output voltage: ±10 VDC (linearity effective range ±8 V) Resolution: 16 bit Accuracy: ±20 mV (Typ) Max. output current: ±10 mA Settling time (±1%): 1.2 ms (Typ)	
Dynamic Brake (DB)			Activated when the power supply for the main circuit or the SERVOPACK is OFF, when overtravel (OT) or a servo alarm occurs, or during a hardwired base block.	
Regenerative Processing			100 VAC model: External regenerative resistor (optional) 200 VAC SGDV-R70A, -R90A, -1R6A, -2R8A: External regenerative resistor (optional) 200 VAC SGDV-470A, -550A, -590A, -780A: External regenerative resistor unit (optional) 200 VAC models other than shown above: Built-in regenerative resistor 400 VAC SGDV-210D, -260D, -280D, -370D: External regenerative resistor unit (optional) 400 VAC models other than shown above: Built-in regenerative resistor	
Overtravell (OT) Prevention			Dynamic brake stop at P-OT or N-OT, deceleration to a stop, or free run to a stop	
Protective Functions			Overcurrent, Overvoltage, low voltage, overload, regeneration error	
Utility Functions			Gain adjustment, alarm history, JOG operation, origin search, etc.	
Safety Functions		Input	/HWBB1, /HWBB2: Baseblock signal for power module	
		Output	EDM1: Status monitor (fixed output) of built-in safety circuit	
Option Modules			Fully-closed option module, EtherCAT (CoE)	

*1: Under development

*2: Speed regulation is defined as follows:

$$\text{Speed regulation} = \frac{\text{No-load motor speed} - \text{Total load motor speed}}{\text{Rated motor speed}} \times 100\%$$

The motor speed may change due to voltage variations or temperature variation. The ratio of speed changes to the rated speed represent speed regulation due to voltage and temperature variations.

*3: For details on the functions of the general-purpose input signals /SI0 to /SI6, refer to the manual of the command (option) module being used.

Power Supply Capacities and Power Losses

The following table shows SERVOPACK's power supply capacities and power losses at the rated output.

Main Circuit Power Supply	Applicable Servomotor Max. Capacity kW	SERVOPACK Model SGDV	Power Supply Capacity kVA	Output Current A	Main Circuit Power Loss W	Regenerative Resistor Power Loss W	Control Circuit Power Loss W	Total Power Loss W
Signal-phase 100 V	0.05	R70F	0.2	0.66	5.4	—	17	22.4
	0.1	R90F	0.3	0.91	7.8			24.8
	0.2	2R1F	0.7	2.1	14.4			31.4
	0.4	2R8F	1.4	2.8	25.6			42.6
Single-phase 200 V	0.05	R70A	0.2	0.66	5.2	—	17	22.2
	0.1	R90A	0.3	0.91	7.4			24.4
	0.2	1R6A	0.7	1.6	13.7			30.7
	0.4	2R8A	1.2	2.8	24.9			41.9
	0.75	5R5A	1.9	5.5	52.7	8		77.7
	1.5	120A	4	11.6	68.2	10	22	100.2
Three-phase 200 V	0.05	R70A	0.2	0.66	5.1	—	17	22.1
	0.1	R90A	0.3	0.91	7.3			24.3
	0.2	1R6A	0.6	1.6	13.5			30.5
	0.4	2R8A	1	2.8	24.0			41.0
	0.5	3R8A	1.4	3.8	20.1	8		45.1
	0.75	5R5A	1.6	5.5	43.8			68.8
	1.0	7R6A	2.3	7.6	53.6			78.6
	1.5	120A	3.2	11.6	65.8	10	22	97.8
	2.0	180A	4	18.5	111.9	16		149.9
	3.0	200A	5.9	19.6	113.8			161.4
	5.0	330A	7.5	32.9	263.7	36	27	326.7
	6.0	470A	10.7	46.9	279.4	(180)*1	33	312.4
	7.5	550A	14.6	54.7	357.8	(350)*2		390.8
	11	590A	21.7	58.6	431.7		48	479.7
	15	780A	29.6	78	599.0			647.0
Three-phase 400 V	0.5	1R9D	1.1	1.9	24.6	14	21	59.6
	1.0	3R5D	2.3	3.5	46.1			81.1
	1.5	5R4D	3.5	5.4	71.3			106.3
	2.0	8R4D	4.5	8.4	77.9	28	25	130.9
	3.0	120D	7.1	11.9	108.7			161.7
	5.0	170D	11.7	16.5	161.1	36	24	221.1
	6.0	210D	12.4	20.8	172.7	(180)*3	27	199.7
	7.5	260D	14.4	25.7	218.6			245.6
	11	280D	21.9	28.1	294.6	(350)*4	30	324.6
	15	370D	30.6	37.2	403.8			433.8

*1: For the optional JUSP-RA04-E regenerative resistor unit.
*2: For the optional JUSP-RA05-E regenerative resistor unit.
*3: For the optional JUSP-RA18-E regenerative resistor unit.
*4: For the optional JUSP-RA19-E regenerative resistor unit.


Notes: 1 SGDVR70F, R90F, 2R1F, 2R8F, R70A, R90A, 1R6A, and 2R8A SERVOPACKs do not have built-in regenerative resistors.
If the regenerative energy exceeds the specified value, connect an external regenerative resistor (optional).
2 SGDV470A, 550A, 590A, 780A, 210D, 260D, 280D, 370D SERVOPACKs do not have built-in regenerative resistors.
Be sure to connect a regenerative resistor unit (optional) or an external regenerative resistor (optional). For selection details, refer to page 339.
3 Regenerative resistor power losses are allowable losses. Take the following action if this value is exceeded.
· Remove the lead or short bar that is short-circuiting the SERVOPACK main circuit terminal B2 and B3.
(SGDV3R8A, 5R5A, 7R6A, 120A, 180A, 200A, 330A, or 400 V class SERVOPACKs.)
· Install an external regenerative resistor (optional). For selection details, refer to page 339.

External Dimensions Units: mm (for Analog Voltage/Pulse Train Reference Type SERVOPACKs)

The following drawings illustrate the external dimensions of SERVOPACKs with Interface Options 0 and 1 with option modules.
For details on options available with these SERVOPACKs, refer to pages 311-316.


●Base-mounted SERVOPACKs

(1) Single-phase 100 VAC, Model:SGDVR70F0□A0000000□□□, SGDVR90F0□A0000000□□□,
and SGDV2R1F0□A0000000□□□



Approx. Mass: 1.1 kg


(2) Single-phase 100 VAC, Model: SGDV2R8F0□A0000000□□□



Approx. Mass: 1.6 kg


External Dimensions Units: mm (for Analog Voltage/Pulse Train Reference Type SERVOPACKs)

(3) Three-phase 200 VAC, Model: SGDVR70A0□A000000□□□, SGDVR90A0□A000000□□□, and SGDV1R6A0□A000000□□□



Approx. Mass: 1.0 kg


(4) Three-phase 200 VAC, Model: SGDV2R8A0□A000000□□□



Approx. Mass: 1.1 kg


External Dimensions Units: mm (for Analog Voltage/Pulse Train Reference Type SERVOPACKs)

(5) Three-phase 200 VAC, Model: SGDV3R8A0□A000000□□□, SGDV5R5A0□A000000□□□, and SGDV7R6A0□A000000□□□



Approx. Mass: 1.6 kg


(6) Three-phase 200 VAC, Model: SGDV120A0□A000000□□□



Approx. Mass: 2.5 kg


External Dimensions Units: mm (for Analog Voltage/Pulse Train Reference Type SERVOPACKs)

(7) Single-phase 200 VAC, Model: SGDV120A0□A008000□□□ (1.5 kW, single-phase input type)
Three-phase 200 VAC, Model: SGDV180A0□A000000□□□, and SGDV200A0□A000000□□□



Approx. Mass: 2.9 kg


(8) Three-phase 200 VAC, Model: SGDV330A0□A000000□□□



Approx. Mass: 4.7 kg


External Dimensions Units: mm (for Analog Voltage/Pulse Train Reference Type SERVOPACKs)

(9) Three-phase 200 VAC, Model: SGDV470A0□A000000□□□, SGDV550A0□A000000□□□



Approx. Mass: 1.6 kg


(10) Three-phase 200 VAC, Model: SGDV590A0□A000000□□□, SGDV780A0□A000000□□□



Approx. Mass: 2.5 kg


External Dimensions Units: mm (for Analog Voltage/Pulse Train Reference Type SERVOPACKs)

(11) Three-phase 400 VAC, Model: SGDV1R9D0□A000000□□□, 3R5D0□A000000□□□, and 5R4D0□A000000□□□




Approx. Mass: 2.7 kg

(12) Three-phase 400 VAC, Model: SGDV8R4D0□A000000□□□ and 120D0□A000000□□□,



Approx. Mass: 3.7 kg


(13) Three-phase 400 VAC, Model: SGDV170D0□A000000□□□



Approx. Mass: 5.6 kg

External Dimensions Units: mm (for Analog Voltage/Pulse Train Reference Type SERVOPACKs)


(14) Three-phase 400 VAC, Model: SGDV210D0□A000000□□□ and 260D0□A000000□□□



Mounting Hole Diagram

Approx. Mass: 11.3 kg

(15) Three-phase 400 VAC, Model: SGDV280D0□A000000□□□ and 370D0□A000000□□□



Mounting Hole Diagram

Approx. Mass: 16.2 kg

Connectors for Base-mounted SERVOPACKs


Port	Model	Pin	Manufacturer
CN1	10250-52A2PL	50	Sumitomo 3M Ltd.
CN2	53984-0671	6	Molex Japan Co., Ltd.
CN3	HDR-EC14LFDTN-SLE-PLUS	14	Honda Tsushin Kogyo Co., Ltd.
CN7	MNC23-5K5H00	5	ADVANCED-CONNECTEK INC.
CN8	1981080-1	8	Tyco Electronics AMP K.K.

Note: The connectors above or their equivalents are used for SERVOPACKs.

External Dimensions Units: mm (for MECHATROLINK-II Communications Reference Type SERVOPACKs)


●Base-mounted SERVOPACKs

(1) Single-phase 100 VAC, Model: SGDVR70F1□A000000□□□, SGDVR90F1□A000000□□□, and SGDV2R1F1□A000000□□□



Approx. Mass: 1.1 kg


(2) Single-phase 100 VAC, Model: SGDV2R8F1□A000000□□□



Approx. Mass: 1.6 kg


External Dimensions Units: mm (for MECHATROLINK-II Communications Reference Type SERVOPACKs)

(3) Three-phase 200 VAC, Model: SGDV-R70A1□A000000□□□, SGDVR90A1□A000000□□□, and SGDV1R6A1□A000000□□□



Approx. Mass: 1.0 kg


(4) Three-phase 200 VAC, Model: SGDV2R8A1□A000000□□□



Approx. Mass: 1.1 kg


External Dimensions Units: mm (for MECHATROLINK-II Communications Reference Type SERVOPACKs)

(5) Three-phase 200 VAC, Model: SGDV3R8A1□A000000□□□, SGDV5R5A1□A000000□□□, and SGDV7R6A1□A000000□□□



Approx. Mass: 1.6 kg


(6) Three-phase 200 VAC, Model: SGDV120A1□A000000□□□



Approx. Mass: 2.5 kg


External Dimensions Units: mm (for MECHATROLINK-II Communications Reference Type SERVOPACKs)

(7) Single-phase 200 VAC, Model: SGDV120A1□A008000□□□ (1.5 kW, single-phase input type)
Three-phase 200 VAC, Model: SGDV180A1□A000000□□□, and SGDV200A1□A000000□□□



Approx. Mass: 2.9 kg


(8) Three-phase 200 VAC, Model: SGDV330A1□A000000□□□



Approx. Mass: 4.7 kg


External Dimensions Units: mm (for MECHATROLINK-II Communications Reference Type SERVOPACKs)

(9) Three-phase 200 VAC, Model: SGDV470A1□A000000□□□, SGDV550A1□A000000□□□



Approx. Mass: 2.9 kg


(10) Three-phase 200 VAC, Model: SGDV590A1□A000000□□□, SGDV780A1□A000000□□□



Approx. Mass: 4.7 kg


External Dimensions Units: mm (for MECHATROLINK-II Communications Reference Type SERVOPACKs)

(11) Three-phase 400 VAC, Model: SGDV1R9D1□A000000□□□, 3R5D1□A000000□□□, and 5R4D1□A000000□□□



Approx. Mass: 2.7 kg


(12) Three-phase 400 VAC, Model: SGDV8R4D1□A000000□□□ and 120D1□A000000□□□,



Approx. Mass: 3.7 kg


External Dimensions Units: mm (for MECHATROLINK-II Communications Reference Type SERVOPACKs)

(13) Three-phase 400 VAC, Model: SGDV170D1□A000000□□□



Approx. Mass: 5.6 kg


(14) Three-phase 400 VAC, Model: SGDV210D1□A000000□□□ and 260D1□A000000□□□



Approx. Mass: 11.3 kg

External Dimensions Units: mm (for MECHATROLINK-II Communications Reference Type SERVOPACKs)

(15) Three-phase 400 VAC, Model: SGDV280D1□A000000□□□ and 370D1□A000000□□□



Approx. Mass: 16.2 kg

Connectors for Base-mounted SERVOPACKs

Port	Model	Pin	Manufacturer
CN1	10226-52A2PL	26	Sumitomo 3M Ltd.
CN2	53984-0671	6	Molex Japan Co., Ltd.
CN3	HDR-EC14LFDTN-SLE-PLUS	14	Honda Tsushin Kogyo Co., Ltd.
CN6	1903815-1	8	Tyco Electronics AMP K.K.
CN7	MNC23-5K5H00	5	ADVANCED-CONNECTEK INC.
CN8	1981080-1	8	Tyco Electronics AMP K.K.


Note: The connectors above or their equivalents are used for SERVOPACKs.

External Dimensions Units: mm (for Other Control Architecture Type SERVOPACKs)

The following drawings illustrate the external dimensions of SERVOPACKs with Interface Option E with option modules.
For details on options available with these SERVOPACKs, refer to pages 317-324.


●Base-mounted SERVOPACKs

(1) Single-phase 100 VAC, Model: SGDVR70FE□A000000□□□, SGDVR90FE□A000000□□□, and SGDV2R1FE□A000000□□□



Approx. Mass: 1.1 kg


(2) Single-phase 100 VAC, Model: SGDV2R8FE□A000000□□□



Approx. Mass: 1.6 kg


External Dimensions Units: mm (for Other Control Architecture Type SERVOPACKs)

(3) Three-phase 200 VAC, Model: SGDV-R70AE□A000000□□□, SGDVR90AE□A000000□□□, and SGDV1R6AE□A000000□□□



Approx. Mass: 1.0 kg


(4) Three-phase 200 VAC, Model: SGDV2R8AE□A000000□□□



Approx. Mass: 1.1 kg


External Dimensions Units: mm (for Other Control Architecture Type SERVOPACKs)

(5) Three-phase 200 VAC, Model: SGDV3R8AE□A000000□□□, SGDV5R5AE□A000000□□□, and SGDV7R6AE□A000000□□□



Approx. Mass: 1.6 kg


(6) Three-phase 200 VAC, Model: SGDV120AE□A000000□□□



Approx. Mass: 2.5 kg


External Dimensions Units: mm (for Other Control Architecture Type SERVOPACKs)

(7) Single-phase 200 VAC, Model: SGDV120AE□A008000□□□ (1.5 kW, single-phase input type)
Three-phase 200 VAC, Model: SGDV180AE□A000000□□□, and SGDV200AE□A000000□□□



Approx. Mass: 2.9 kg


(8) Three-phase 200 VAC, Model: SGDV330AE□A000000□□□



Approx. Mass: 4.7 kg


External Dimensions Units: mm (for Other Control Architecture Type SERVOPACKs)

(9) Three-phase 200 VAC, Model: SGDV470AE□A000000□□□, SGDV550AE□A000000□□□



Approx. Mass: 1.6 kg


(10) Three-phase 200 VAC, Model: SGDV590AE□A000000□□□, SGDV780AE□A000000□□□



Approx. Mass: 2.5 kg


External Dimensions Units: mm (for Other Control Architecture Type SERVOPACKs)

(11) Three-phase 400 VAC, Model: SGDV1R9DE□A0000000□□, 3R5DE□A000000□□□, and 5R4DE□A000000□□□



Approx. Mass: 2.9 kg


(12) Three-phase 400 VAC, Model: SGDV8R4DE□A000000□□□ and 120DE□A000000□□□,



Approx. Mass: 4.7 kg

External Dimensions Units: mm (for Other Control Architecture Type SERVOPACKs)


(13) Three-phase 400 VAC, Model: SGDV170DE□A000000□□□



Mounting Hole Diagram

Approx. Mass: 1.6 kg

(14) Three-phase 400 VAC, Model: SGDV210DE□A000000□□□ and 260DE□A000000□□□




Mounting Hole Diagram

Approx. Mass: 2.5 kg

External Dimensions Units: mm (for Other Control Architecture Type SERVOPACKs)

(15) Three-phase 400 VAC, Model: SGDV280DE□A000000□□□ and 370DE□A000000□□□



Approx. Mass: 2.9 kg


Connectors for Base-mounted SERVOPACKs

Port	Model	Pin	Manufacturer
CN1	10226-52A2PL	26	Sumitomo 3M Ltd.
CN2	53984-0671	6	Molex Japan Co., Ltd.
CN3	HDR-EC14LFDTN-SLE-PLUS	14	Honda Tsushin Kogyo Co., Ltd.
CN7	MNC23-5K5H00	5	ADVANCED-CONNECTEK INC.
CN8	1981080-1	8	Tyco Electronics AMP K.K.





Note: The connectors above or their equivalents are used for SERVOPACKs.

Selecting Cables

● Cables for CN1 CN3 CN5 CN7 CN8 CN11 for SERVOPACKs with additional options



NOTE: For information about option module cables, refer to the particular option module section of this catalog.

Name		Length	Order No.	Specifications	Details
CN1 Cables for I/O Signals	Connector Kit		JZSP-CSI9-2-E	Soldered 	(1)
	Connector Terminal Converter Unit	0.5 m	SBK-U-VBA-A5	Terminal Block and 0.5 m Connection Cable 	(2)
		1 m	SBK-U-VBA-01		
		3 m	SBK-U-VBA-03		
	Cable with Loose wire at One End	1 m	JZSP-CSI02-1-E		(3)
		2 m	JZSP-CSI02-2-E		
		3 m	JZSP-CSI02-3-E		
CN3	Digital Operator		JUSP-OP05A-1-E	With Connection Cable (1 m) 	(4)
	Digital Operator Converter Cable*1	0.3 m	JZSP-CVS05-A3-E	Cable with Connectors at Both Ends 	(5)
CN7 Connection Cables for Personal Computer		2.5 m	JZSP-CVS06-02-E	Cable with Connectors at Both Ends 	(6)
CN5 Cables for Analog Monitor		1 m	JZSP-CA01-E	SERVOPACK End 	(7)
CN8 Cables for Safety Functions	Cables with Connector*2	3 m	JZSP-CVH03-03-E		(8)
	Connector kit*3		Contact Tyco Electronics AMP K.K. Product name : Industrial Mini I/O D-shape Type1 Plug Connector Kit Model : 2013595-1		
CN11A CN11B Ethernet/EtherCAT Cables for Industrial Use			Category: CAT5e Shield specifications: S/UTP or S/STP Cable length: 50 m maximum		

*1 : A converter cable is required to use Σ-Ⅲ series digital operators (model: JUSP-OP05A) for Σ-Ⅴ series SERVOPACKs.
*2 : When using the safety function, connect this cable to the safety devices.
Even when not using the safety function, use SERVOPACKs with the Safe Jumper Connector (model: JZSP-CVH05-E) connected.
*3 : Use the connector kit when you make cables yourself.

Selecting Cables

(1) Connector Kit for CN1

Use the following connector and cable to assemble the cable. The CN1 connector kit includes one case and one connector.


Connector Kit Model	Case		Connector	
	Model	Qty	Model	Qty
JZSP-CSI9-2-E	10326-52A0-008*	1 set	10126-3000PE* (Soldered)	1

* : Manufactured by Sumitomo 3M Ltd.


· Cable Size

Item	Specifications
Cable	Use twisted-pair or twisted-pair shielded wire.
Applicable Wires	AWG24, 26, 28, 30
Cable Finished Diameter	16 dia. max.


· Dimensional Drawings of Case



· Dimensional Drawings of Connector



(2) Connector Terminal Converter Unit for CN1 (SBK-U-VBA-xx)



CABLE SPECIFICATION (mm)	
OUTER DIAMETER	6.5 +/- 0.2mm
BENDING RADIUS	6 x O.D. MINIMUM 15 x O.D. FOR LONG TERM RELIABILITY

ITEM#	L = LENGTH (mm)
SBK-U-VBA-A5	500 +/- 38.1
SBK-U-VBA-01	1000 +/- 38.1
SBK-U-VBA-03	3000 +/- 38.1


SBK-U-VBA-xx Function Chart for SGDV Servo Amplifier

Pin No.	SGDV Mechatrolink-II type / SGDV Option type	
	Signal	Function
1	/BK+ (/SO1+)	Brake interlock output (+) (General purpose output 1 (+))
2	/BK- (/SO1-)	Brake interlock output (-) (General purpose output 1 (-))
3	ALM+	Servo alarm output (+)
4	ALM-	Servo alarm output (-)
5	-	
6	+24VIN	Control power supply for sequence signal input
7	P-OT (/SI1)	Forward run prohibited input (General purpose input 1)
8	N-OT (/SI2)	Reverse run prohibited input (General purpose input 2)
9	/DEC (/SI3)	Zero-point return deceleration switch input (General purpose input 3)
10	/EXT1 (/SI4)	External latch signal 1 input (General purpose input 4)
11	/EXT2 (/SI5)	External latch signal 2 input (General purpose input 5)
12	/EXT3 (/SI6)	External latch signal 3 input (General purpose input 6)
13	/SI0	General purpose input 0
14	BAT (+)	Battery (+) input
15	BAT (-)	Battery (-) input
16	SG	Signal ground
17	PAO	Phase-A pulse output (+)
18	/PAO	Phase-A pulse output (-)
19	PBO	Phase-B pulse output (+)
20	/PBO	Phase-B pulse output (-)
21	PCO	Phase-C pulse output (+)
22	/PCO	Phase-C pulse output (-)
23	/SO2+	General purpose output 2 (+)
24	/SO2-	General purpose output 2 (-)
25	/SO3+	General purpose output 3 (+)
26	/SO3-	General purpose output 3 (-)

Note: General purpose input and output signals are shown with their default signals assigned - signal assignment may have been changed by parameter

Selecting Cables Units: mm

(3) Cable with Loose Wires at One End for CN1
Dimensional Drawings of Cable



Model	Cable Length
JZSP-CSI02-1-E	1 m
JZSP-CSI02-2-E	2 m
JZSP-CSI02-3-E	3 m

●Cable with Loose Wires at One End for CN1
Connection Diagram of JZSP-CSI02-□-E Cable

SERVOPACK End


Pin No.	Signal	Wire Color	Marking	
			Color	Dots
1	/BK+	Blue	Red	1
2	/BK−	Blue	Black	1
3	ALM+	Pink	Red	1
4	ALM−	Pink	Black	1
5	–	Green	Red	1
6	+24VIN	Green	Black	1
7	P-OT	Orange	Red	1
8	N-OT	Orange	Black	1
9	/DEC	Gray	Red	1
10	/EXT1	Gray	Black	1
11	/EXT2	Blue	Red	2
12	/EXT3	Blue	Black	2
13	/SI0	Pink	Red	2
14	BAT (+)	Green	Red	2
15	BAT (−)	Green	Black	2
16	SG	Pink	Black	2
17	PAO	Orange	Red	2
18	/PAO	Orange	Black	2
19	PBO	Gray	Red	2
20	/PBO	Gray	Black	2
21	PCO	Blue	Red	3
22	/PCO	Blue	Black	3
23	/SO2+	Pink	Red	3
24	/SO2−	Pink	Black	3
25	/SO3+	Green	Red	3
26	/SO3−	Green	Black	3

Host Controller End

Lead Marker
1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26

: Represents twisted-pair wires.

(4) Digital Operator (Model: JUSP-OP05A-1-E)




Connector: HDR-E14MAG1+(Honda Tsushin Kogyo Co., Ltd.)
Case: HDR-E14LPA5(Honda Tsushin Kogyo Co., Ltd.)

(5) Digital Operator Converter Cable for CN3
(Model: JZSP-CVS05-A3-E)

A converter cable is required to use Σ-Ⅲ series digital operators (model: JUSP-OP05A) for Σ-Ⅴ series SERVOPACKs.

· Dimensional Drawings




Connector (14-pole): 10214-6202PL
(Sumitomo 3M Ltd.)
Cover: FA458036
(Yasco Components Co., Ltd.)

Connector (14-pole): HDR-E14MAG1+
(Honda Tsushin Kogyo Co., Ltd.)
Cover: HDR-E14LPA5
(Honda Tsushin Kogyo Co., Ltd.)

Selecting Cables

(6) Connection Cable for Personal Computer for CN7
(Model: JZSP-CVS06-02-E)


· Dimensional Drawings




IMPORTANT Use a cable specified by Yaskawa.
When using other cables, operation cannot be guaranteed.

(7) Cable for Analog Monitor for CN5
(Model: JZSP-CA01-E)

· Dimensional Drawings



* : Manufactured by Hirose Electric Corporation.



View from Cable End


· Specifications

Pin No.	Cable Color	Signal	Standard Settings
1	Red	Analog Monitor 2	Motor speed : 1V/1000 min^{-1}
2	White	Analog Monitor 1	Torque reference : 1V/100% rated torque
3, 4	Black (2 cables)	GND(0V)	−

Note : The specifications above are factory settings. Monitor specifications can be changed by changing parameters Pn006 and Pn007.

(8) Cable with Connector for CN8
(Model: JZSP-CVH03-03-E)

· Dimensional Drawings




· Specifications

Pin No.	Signal	Lead Color	Marking Color
1	Not used	−	−
2	Not used	−	−
3	/HWBB1−	White	Black
4	/HWBB1+	White	Red
5	/HWBB2−	Gray	Black
6	/HWBB2+	Gray	Red
7	EDM1−	Orange	Black
8	EDM1+	Orange	Red

Fully-Closed Loop Control Option

●System Configuration for Fully-Closed Loop Control


When using rotary servomotors with Fully-Closed loop control, use SERVOPACKs with option module for Fully-Closed loop control.



●Model Designations

JZDP - D00□ - 000 - E

Serial Converter Unit Model


Code	Appearance	Applicable External Encoder	Hall Sensor
D003		Manufactured by HEIDENHAIN Corporation	None
D005		Manufactured by Renishaw plc.	None

Heidenhain serial converters are non-stock.


Note: Using the serial converter unit JZDP-A□□□ with SGDV SERVOPACK will void our guarantee.

Option Module for Fully-Closed Loop Control

●External Dimensions Units: mm



Approx. Mass: 0.1 kg



Front View (mounted on analog and pulse train type SERVOPACK)

Connector

Port	Model	Pin	Manufacturer
CN31	53984-0671	6	Molex Japan Co., Ltd.

Note: The connectors above or their equivalents are used for SERVOPACKs.

Connection Cable Between Fully Closed Loop Connector and Serial Converter Unit (see page 314).


●Characteristics and Specifications

Items		Specifications
Electrical Characteristics	Power Supply Voltage	+5.0 V ±5%, ripple content 5% max.
	Current Consumption*1	120 mA typ. 350 mA max.
	Signal Resolution	Input two-phase sine wave: 1/256 pitch
	Max. Response Frequency	250 kHz
	Analog Input Signals*2 (cos, sin, Ref)	Differential input amplitude: 0.4 to 1.2 V Input signal level: 1.5 to 3.5 V
	Output Signal*3	Position data, alarms
	Output Method	Serial data communications [HDLC (High-level Data Link Control) protocol format with Manchester codes]
	Output Circuit	Balanced type transceiver (SN75LBC176 or the equivalent), internal terminating resistor: 120 Ω
Mechanical Characteristics	Approx. Mass	150 g
	Vibration Resistance	98 m/s² max. (10 to 2500 Hz) in three directions
	Impact Resistance	980 m/s², (11 ms) two times in three directions
Environmental Conditions	Surrounding Air Temperature	0 to 55˚C
	Storage Temperature	−20 to 80˚C
	Humidity	20% to 90%RH (no condensation)

*1: The current consumption of the external encoder is not included in this value.
The current consumption of the external encoder must be taken into consideration for the current capacity of host controller that supplies the power.
*2: Input a value within the specified range. Otherwise, incorrect position information is output, and the device may be damaged.
*3: The transmission is enabled 100 to 300 ms after the power turns on.

●Analog Signal Input Timing

The following figure shows the input timing of the analog signals.
When the cos and sin signals are shifted 180 degrees, the differential signals are the /cos and /sin signals.
The specifications of the cos, /cos, sin, and /sin signals are identical except for the phase.
Input the signals Ref and /Ref so that they shall cross each other as shown in the figure because they are input into the converter. When they are crossed, the output data will be counted up.



IMPORTANT


■Precautions

1 Never perform insulation resistance and withstand voltage tests.
2 When analog signals are input to the serial converter unit, noise influence on the analog signals affects the unit's ability to output correct position information. The analog cable must be as short as possible and shielded.
3 Do not connect or disconnect the unit while power is being supplied, or the unit may be damaged.
4 When using multiple axes, use a shield cable for each axis. Do not use a shield cable for multiple axes.


Serial Converter Units Units: mm

●External Dimensions

(1) Model: JZDP-D003-□□□-E



(2) Model: JZDP-D005-□□□-E




●Connection Cables

● Recommended Cables


Name	Application	Model	Length
Cables with Connectors at Both Ends	Connection between SERVOPACK (Option module for Fully-Closed loop control) connector CN31 and serial converter unit	JZSP-CLP70-03-E	3 m
		JZSP-CLP70-05-E	5 m
		JZSP-CLP70-10-E	10 m
		JZSP-CLP70-15-E	15 m
		JZSP-CLP70-20-E	20 m

● Dimensional Drawing




●Connection Examples

(1) Connection Example with External Encoder by HEIDENHAIN Corporation
Model: JZDP-D003-□□□-E



Pin No.	Signal
1	+5V
2	Phase S output
3	Not used
4	Not used
5	0V
6	Phase /S output
7	Not used
8	Not used
9	Not used
Case	Shield


CN1
SERVOPACK End
Serial Data Output



17-series Connector:
17LE-13090-27-FA
(Socket) by DDK Ltd.

Pin No.	Signal
1	cos input (A+)
2	0V
3	sin input (B+)
4	+5V
5	Not used
6	Not used
7	/Ref input (R–)
8	Not used
9	/cos input (A–)
10	0V sensor
11	/sin input (B–)
12	5V sensor
13	Not used
14	Ref input (R+)
15	Not used
Case	Shield


CN2
External Encoder End
Analog Signal Input



17-series Connector:
17LE-13150-27-FA
(Socket) by DDK Ltd.

Notes: 1 Do not use the unused pins.
2 The external encoder (analog 1 Vp-p output, D-sub 15-pin) by HEIDENHAIN Corporation can be directly connected.


(2) Connection Example with External Encoder by Renishaw plc.
Model : JZDP-D005-□□□-E



Pin No.	Signal
1	+5V
2	Phase S output
3	Not used
4	Not used
5	0V
6	Phase /S output
7	Not used
8	Not used
9	Not used
Case	Shield

SERVOPACK does not have the function to process Vq signals.


CN1
SERVOPACK End
Serial Data Output



17-series Connector:
17LE-13090-27-FA
(Socket) by DDK Ltd.

Pin No.	Signal
1	/cos input (V1–)
2	/sin input (V2–)
3	Ref input (V0+)
4	+5V
5	5Vs
6	Not used
7	Not used
8	Not used
9	cos input (V1+)
10	sin input (V2+)
11	/Ref input (V0–)
12	0V
13	0Vs
14	Not used
15	Inner (0V)
Case	Shield

CN2
External Encoder End
Analog Signal Input




17-series Connector:
17JE-13150-02 (D8C) A-CG
(Socket) by DDK Ltd.


Notes: 1 Do not use the unused pins.
2 The external encoder (analog 1 Vp-p output, D-sub 15-pin) by Renishaw plc. can be directly connected. However, the BID and DIR signals are not connected.
3 Use the external encoder-end connector to change the home position specifications of the external encoder.

Serial Converter Units

(3) Connection Example with External Encoder by Mitutoyo Corporation (Model: ABS ST78□A)
When using these external encoders, serial converter units are not required.



● System Configuration for EtherCAT (CoE) Communication Reference



EtherCAT Connector (RJ45)

Connector	Description
CN11A	EtherCAT signal input
CN11B	EtherCAT signal output


- Connector Pin Arrangement

Pin No.	Signal Name	Remarks
1	TD+	Send data
2	TD-	
3	RD+	Receive data
4	–	N.C.*
5	–	N.C.*
6	RD-	Receive data
7	–	N.C.*
8	–	N.C.*


* Pins denoted as N.C. do not connect to any signal.

EtherCAT (CoE) Communication Reference Option

●External Dimensions Units: mm



Approx. Mass: 0.1 kg



Front View: With front cover open

Name	Specifications
CN11A CN11B Ethernet/EtherCAT Cables for Industrial Use	Category: CAT5e Shield specifications: S/UTP or S/STP Cable length: 50 m maximum

Specifications of the EtherCAT(CoE) Communication Reference Option


● Specifications

Items		Specifications
Power Specification	Power Supply Method	Supplied from the control power supply of the servo amplifier
Operating Conditions	Surrounding Air/Storage Temperature	Surrounding air temperature: 0 to 55°C, Storage temperature: –20 to 85°C
	Ambient/Storage Humidity	90% RH or less (with no condensation)
	Vibration/Shock Resistance	Vibration resistance: 4.9 m/s^2, Shock resistance: 19.6 m/s^2
	Protection Class/ Pollution Degree	Protection class: IP10, pollution degree: 2 Do not use SERVOPACKs in the following locations: • Locations subject to corrosive or flammable gases • Locations subject to exposure to water, oil, or chemicals • Locations subject to dust, including iron dust, and salts
	Altitude	1000 m or less
	Others	Do not use SERVOPACKs in the following locations: •Locations subject to static electricity noise, strong electromagnetic/magnetic fields, radioactivity
Conformance Standards		UL508C EN50178, EN55011/A2 Group1 Class A, EN61000-6-2 EN61800-3, EN61800-5-1, EN954-1, IEC61508-1 ~ 4
RoHS Directive		Compliant
Baud Rate		100Mbps
Max. No. of Stations		65536 stations
Transmission Cycle		125 µs or more
Cable Length between Nodes		50 m max
Topology		Cascade, star, ring, line
Connector		RJ-45
Profile		CANopen(CoE) IEC61800-7 CiA402 Drive Profile
Control Mode		• Homing mode • Profile position mode • Interpolated position mode • Profile velocity mode • Profile Torque mode • Cyclic sync position mode • Cyclic sync velocity mode • Cyclic sync torque mode
SERVOPACK Performance and Functions		Response frequency: 1.6 kHz Various adjustment functions are available.
Display		EtherCAT RUN indicator (RUN) × 1 EtherCAT ERR indicator (ERR) × 1 EtherCAT Link/Activity indicator × 2
Rotary Switch		Secondary Address : × 2


MP2600iec Single-Axis Motion Controller Option

The MP2600iec Single Axis Motion Controller Option for the Sigma-5 amplifier provides a compact, all-in-one, servo/controller package with the following features:

- IEC61131-3 standardized programming environment with PLCopen function blocks for motion control.
- Self-tuning, anti-vibration, and other high performance, easy-to-implement servo control features
- Ethernet/IP, Modbus TCP/IP, and OPC Server, which provide connectivity to PLCs, HMIs, SCADA, MES, and ERP
- Scaleability with the multi-axis MP2000iec controller platform via the common programming environment, MotionWorks IEC
- Web server that allows for maintenance diagnostics and troubleshooting
- I/O features:
  - 15 digital inputs
  - 11 digital outputs
  - 1 analog input
  - 1 analog outpu
  - 1 external encoder input
  - 1 external encoder latch



●External Dimensions Units: mm



Dimensions in mm.

Specifications of the MP2600iec Single Axis Machine Controller Option

● General Specifications

Items		Specifications
Environmental Conditions	Ambient Operating Temperature	0 to 55°C
	Ambient Storage Temperature	-20°C to +85°C
	Ambient Operating Humidity	90% RH or less (with no condensation)
	Ambient Storage Humidity	90% RH or less (with no condensation)
	Protection Class/Pollution Degree	Protection class: IP10, Pollution degree: 2 An environment that satisfies the following conditions. • Free of corrosive or explosive gases • Free of exposure to water, oil or chemicals • Free of dust, salts or iron dust
	Operating Altitude	1,000 m above sea level or lower
Mechanical Operating Conditions	Vibration Resistance	4.9 m/s^2
	Shock Resistance	19.6 m/s^2
	Others	Free of static electricity, strong electromagnetic fields, magnetic fields or exposure to radioactivity


● Hardware Specifications

Items				Specifications
CPU				200 MHz, 32 bit, ARM 9
Memory		SDRAM		32 MB
		SRAM		512 kB with battery backup
		Flash		4 MB flash. Code and parameter storage
Operator interface		LED		10 LEDs (red and green - operating mode, communication and error status
		User Configuration		6x DIP switch (operating mode and communication configuration
User I/O	Controller Side (CN13)	Network		2x 100baseTX Ethernet
		Digital input		8 programmable inputs
		Digital output		8 programmable outputs
		Analog input		1 ch., +/- 10V, 16 bit
		Analog output		1 ch., +/- 10V, 16 bit
		Pulse Counter		RS-422-compatible pulse counter input (quadrature, pulse and direction, and up/down counter modes) with 5, 12, and 24V position latch inputs
	Servo Side (CN1)	Sequence Input	Allocated	Number of Inputs: 7
				Functions: The signal allocation and positive/negative logic can be modified. Forward run prohibited (P-OT), reverse run prohibited (N-OT), forward torque limit (/P-CL), reverse torque limit (/N-CL), general-purpose input signal (/SI0 to /SI6)
		Sequence Input	Fixed	Servo Alarm (ALM)
			Allocated	Number of Outputs: 3
				Functions: The signal allocation and positive/negative logic can be modified. Positioning completion (/COIN), speed coincidence detection(/V-CMP), servomotor rotation detection (/TGON), servo ready (/S-RDY), torque limit detection (/CLT), speed limit detection (VLT), brake (/BK), warning (/WARN), near (/NEAR)
Network capability				OPC (Client and Server required)
				Ethernet/IP
				Modbus/TCP
Programming standards				IEC61131/PLCopen
Diagnostic and configuration interface				Web interface
Motion control performance				1 controlled axis and one external position input at a trajectory update rate of 1 kHz
Servo-Side Safety Functions	Input			/HWBB1, /HWBB2: Baseblock signal for power module
	Output			EDM1: Status monitor (fixed output) of built-in safety circuit

* Allocated I/O can also be used as programmable I/O.

Selecting Cables

●Cable Selection

Name		Length	Order No.	Specifications	Details
CN13 Cables for I/O Signals	Connector Kit		JZSP-CSI9-1-E	Soldered 	(1)
	Connector Terminal Converter Unit	0.5 m	CBK-U-MP2B-A5	Terminal Block and 0.5 m Connection Cable 	(2)
		1 m	CBK-U-MP2B-01		
		3 m	CBK-U-MP2B-03		
	Flying Lead Cable	0.5 m	CFC-U-MP2B-A5		(3)
		1 m	CFC-U-MP2B-01		
		3 m	CFC-U-MP2B-03		
CN11A CN11B Ethernet/EtherCAT Cables for Industrial Use			Category: CAT5e Shield specifications: S/UTP or S/STP Cable length: 50 m maximum		

(1) Connector Kit for CN13

Use the following connector and cable to assemble the cable. The CN13 connector kit includes one case and one connector.


Connector Kit Model	Case		Connector	
	Model	Qty	Model	Qty
JZSP-CSI9-1-E	10350-52Z0-008*	1 set	10150-3000PE* (Soldered)	1

* : Manufactured by Sumitomo 3M Ltd.


· Cable Size

Item	Specifications
Cable	Use twisted-pair or twisted-pair shielded wire.
Applicable Wires	AWG 24, 26, 28, 30
Cable Finished Diameter	16 dia. max.

· Dimensional Drawings of Case




· Dimensional Drawings of Connector



Selecting Cables

(2) Connector Terminal Converter Unit for CN13



ITEM#	L = LENGTH (mm)
CBK-U-MP2B-A5	500 +/- 38.1
CBK-U-MP2B-01	1000 +/- 38.1
CBK-U-MP2B-03	3000 +/- 38.1


CABLE SPECIFICATION (mm)	
OUTER DIAMETER	8.5 +/- 0.1mm
BENDING RADIUS	6 x O.D. MINIMUM 15 x O.D. FOR LONG TERM RELIABILITY

CBK-U-MP2B-XX Function Chart for MP2600iec

Pin No.	Signal Name	I/O	Function
1	AO	O	Analog output
2	AI	I	Analog input
3	-	-	-
4	PA+	I	Phase A pulse (+)
5	PA-	I	Phase A pulse (-)
6	GND	P	Encoder input ground
7	BAT+	P	Controller SRAM Battery (+)
8	-	-	-
9	PILC5V	I	Phase-C latch pulse (-) for 5VDC input
10	PILC24V	I	Phase-C latch pulse (-) for 24VDC input
11	DO_00-	O	Digital output 0 (-)
12	DO_02-	O	Digital output 2 (-)
13	DICOM	I	Digital input common
14	DI_00	I	Digital input 0
15	DI_02	I	Digital input 2
16	DI_04	I	Digital input 4
17	DI_06	I	Digital input 6
18	DO_04-	O	Digital output 4 (-)
19	DO_06-	O	Digital output 6 (-)
20	-	-	-
21	DO_00+	O	Digital output 0 (+)
22	DO_02+	O	Digital output 2 (+)
23	DO_04+	O	Digital output 4 (+)
24	DO_06+	O	Digital output 6 (+)
25	-	-	-
26	AO_GND	O	Analog output ground
27	AI_GND	I	Analog input ground
28	-	-	-
29	PB+	I	Phase B pulse (+)
30	PB-	I	Phase B pulse (-)
31	GND	P	Encoder input ground
32	BAT-	P	Controller SRAM Battery (-)
33	-	-	-
34	PILC12V	I	Phase-C latch pulse (-) for 12VDC input
35	PIL	I	Phase-C latch pulse (+)
36	DO_01-	O	Digital output 1 (-)
37	DO_03-	O	Digital output 3 (-)
38	DICOM	I	Digital input common
39	DI_01	I	Digital input 1 - shared with pulse latch input
40	DI_03	I	Digital input 3
41	DI_05	I	Digital input 5
42	DI_07	I	Digital input 7
43	DO_05-	O	Digital output 5 (-)
44	DO_07-	O	Digital output 7 (-)
45	-	-	-
46	DO_01+	O	Digital output 1 (+)
47	DO_03+	O	Digital output 3 (+)
48	DO_05+	O	Digital output 5 (+)
49	DO_07+	O	Digital output 7 (+) - shared w/ position agreement COIN signal
50	-	-	-

I = Input, O = Output, P = Power

(3) Flying Lead Cable for CN13



ITEM NUMBER	X = LENGTH (mm)
CFC-U-MP2B-A5	500
CFC-U-MP2B-01	1000
CFC-U-MP2B-03	3000

CABLE SPECIFICATION (mm)	
OUTER DIAMETER	8.1
BENDING RADIUS	12 O.D.

CFC-U-MP2B-XX Function Chart for MP2600iec

Pin No.	Color (Solid/Band)	Signal Name		Function
1	BLK/RED	AO	O	Analog output
2	BLK/WHT	AI	I	Analog input
3	RED/GRN	-	-	-
4	BLK/BLU	PA+	I	Phase A pulse (+)
5	BLU/BLK	PA-	I	Phase A pulse (-)
6	RED/BLU	GND	P	Encoder input ground
7	RED/WHT	BAT+	P	Controller SRAM Battery (+)
8	BLK/GRN	-	-	-
9	BLK/YEL	PILC5V	I	Phase-C latch pulse (-) for 5VDC input
10	BLK/ORG	PILC24V	I	Phase-C latch pulse (-) for 24VDC input
11	RED/YEL	DO_00-	O	Digital output 0 (-)
12	RED/BRN	DO_02-	O	Digital output 2 (-)
13	RED/ORG	DICOM	I	Digital input common
14	GRN/WHT	DI_00	I	Digital input 0
15	GRN/BLU	DI_02	I	Digital input 2
16	GRN/YEL	DI_04	I	Digital input 4
17	GRN/BRN	DI_06	I	Digital input 6
18	GRN/ORG	DO_04-	O	Digital output 4 (-)
19	WHT/BLU	DO_06-	O	Digital output 6 (-)
20	WHT/YEL	-	-	-
21	YEL/RED	DO_00+	O	Digital output 0 (+)
22	BRN/RED	DO_02+	O	Digital output 2 (+)
23	ORG/GRN	DO_04+	O	Digital output 4 (+)
24	BLU/WHT	DO_06+	O	Digital output 6 (+)
25	WHT/BRN	-	-	-
26	RED/BLK	AO_GND	O	Analog output ground
27	WHT/BLK	AI_GND	I	Analog input ground
28	GRN/RED	-	-	-
29	BLK/BRN	PB+	I	Phase B pulse (+)
30	BRN/BLK	PB-	I	Phase B pulse (-)
31	BLU/RED	GND	P	Encoder input ground
32	WHT/RED	BAT-	P	Controller SRAM Battery (-)
33	GRN/BLK	-	-	-
34	ORG/BLK	PILC12V	I	Phase-C latch pulse (-) for 12VDC input
35	YEL/BLK	PIL	I	Phase-C latch pulse (+)
36	WHT/ORG	DO_01-	O	Digital output 1 (-)
37	BLU/YEL	DO_03-	O	Digital output 3 (-)
38	ORG/RED	DICOM	I	Digital input common
39	WHT/GRN	DI_01	I	Digital input 1 - shared with pulse latch input
40	BLU/GRN	DI_03	I	Digital input 3
41	YEL/GRN	DI_05	I	Digital input 5
42	BRN/GRN	DI_07	I	Digital input 7
43	BLU/BRN	DO_05-	O	Digital output 5 (-)
44	BLU/ORG	DO_07-	O	Digital output 7 (-)
45	YEL/WHT	-	-	-
46	ORG/WHT	DO_01+	O	Digital output 1 (+)
47	YEL/BLU	DO_03+	O	Digital output 3 (+)
48	BRN/BLU	DO_05+	O	Digital output 5 (+)
49	ORG/BLU	DO_07+	O	Digital output 7 (+) - shared w/ position agreement COIN signal
50	BRN/WHT	-	-	-

I = Input, O = Output, P = Power

efesotomasyon.com

Wiring Main Circuit


●Typical Main Circuit Wiring Examples

This section describes the typical main circuit wiring examples.

WARNING


After turning OFF the power, do not touch the power terminals while charge indicator is still ON. High residual voltage may still remain in the SERVOPACK. When the voltage is discharged, the charge indicator will turn OFF. Make sure the charge indicator is OFF before starting wiring or inspection.

●Single-phase 100 V



1QF : Molded-case circuit breaker
FIL : Noise filter
1KM : Magnetic contactor (for control power supply)
2KM : Magnetic contactor (for main circuit power supply)
1Ry : Relay
1PL : Indicator lamp
1SA : Surge absorber
2SA : Surge absorber
3SA : Surge absorber
1D : Flywheel diode

●Three-phase 200 V




1QF : Molded-case circuit breaker
FIL : Noise filter
1KM : Magnetic contactor (for control power supply)
2KM : Magnetic contactor (for main circuit power supply)
1Ry : Relay
1PL : Indicator lamp
1SA : Surge absorber
2SA : Surge absorber
3SA : Surge absorber
1D : Flywheel diode

Note: Every SERVOPACK of SGDV-470A, -550A□-590A□and -780A requires a specified external regenerative unit.

Wiring Main Circuit

● Three-phase 400 V



1QF : Molded-case circuit breaker
FIL : Noise filter
1KM : Magnetic contactor (for control power supply)
2KM : Magnetic contactor (for main circuit power supply)
1Ry : Relay
1PL : Indicator lamp
1SA : Surge absorber
2SA : Surge absorber
3SA : Surge absorber
1D : Flywheel diode
Note: Every SERVOPACK of SGDV-210D, -260D□-280D□and -370D requires a specified external regenerative unit.

● General Precautions for Wiring

IMPORTANT

- Use a molded-case circuit breaker (QF) or fuse to protect the Main Circuit.
  The SERVOPACK connects directly to a commercial power supply; it is not isolated by a transformer or other device.
  Always use a molded-case circuit breaker (QF) or fuse to protect the servo system from accidents involving different power system voltages or other accidents.
- Install a ground fault detector.
  The SERVOPACK does not have a built-in protective circuit for grounding. To configure a safer system, install a ground fault detector against overloads and short-circuiting, or install a ground fault detector combined with a molded-case circuit breaker.
- Do not turn power ON and OFF frequently.
  The power supply in the SERVOPACK contains a capacitor, which causes a high charging current to flow when power is turned ON. Frequently turning power ON and OFF will causes the main circuit elements in the SERVOPACK to deteriorate.

To ensure safe, stable application of the servo system, observe the following precautions when wiring.

Observe the following precautions when wiring the main circuit.

- Use shielded twisted-pair wires or shielded multi-core twisted-pair wires for signal lines and encoder lines.
- The maximum wiring length is 3 m for signal lines and 50 m for encoder lines.

Observe the following precautions when wiring the ground.

- Use a cable as thick as possible (at least 2.0 mm2)
- Ground the 100-V and the 200-V SERVOPACK to a resistance of 100 Ω or less. Ground the 400-V SERVOPACK to a resistance of 10 Ω or less.
- Be sure to ground at only one point.
- Ground the servomotor directly if the servomotor is insulated from the machine.

The signal cable conductors are as thin as 0.2 mm or 0.3 mm. Do not impose excessive bending force or tension.

● Precautions When Using the SERVOPACK with a DC Power Input


When using the SERVOPACK with a DC power input, *refer to 3.1.5 Precautions When using the SERVOPACK with a DC power input on "AC Servodrive Σ-V Series USER'S MANUAL Design and Maintenance."* (manual no. SIEP S800000 45)

●Precautions When Using More Than One SERVOPACK

This section shows an example of the wiring when more than one SERVOPACK is used and the precautions.

●Wiring Example

Connect the alarm output (ALM) terminals for the three SERVOPACKs in series to enable alarm detection relay 1RY to operate.
When a SERVOPACK alarm is activated, the ALM output signal transistor is turned OFF.



●Precautions

Multiple servos can share a single molded-case circuit breaker (QF) or noise filter. Always select a QF or noise filter that has enough capacity for the total power capacity (load conditions) of those servos.

SERVOPACK Main Circuit Wire

●Single-phase, 100 V

Cables	Terminal Symbol	SERVOPACK Model SGDV-			
		R70F	R90F	2R1F	2R8F
Main Circuit Power Cable	L1, L2	HIV1.25		HIV2.0	
Servomotor Main Circuit Cable	U, V, W	HIV1.25			
Control Power Cable	L1C, L2C	HIV1.25			
External Regenerative Resistor Cable	B1/⊕, B2	HIV1.25			
Ground Cable	⏚	HIV2.0 min.			

●Three-phase, 200 V

Cables	Terminal Symbol	SERVOPACK Model SGDV-													
		R70A	R90A	1R6A	2R8A	3R8A	5R5A	7R6A	120A	180A	200A	330A	470A	550A	590A	780A
Main Circuit Power Cable	L1, L2, L3	HIV1.25			HIV2.0					HIV3.5		HIV5.5	HIV8	HIV14	HIV22	
Servomotor Main Circuit Cable	U, V, W	HIV1.25			HIV2.0					HIV3.5	HIV5.5	HIV8.0	HIV14		HIV22	
Control Power Cable	L1C, L2C	HIV1.25														
External Regenerative Resistor Cable	B1/⊕, B2	HIV1.25								HIV2.0	HIV3.5	HIV5.5	HIV8		HIV22	
Ground Cable	⏚	HIV2.0 min.														

●Three-phase, 400 V

Cables	Terminal Symbol	SERVOPACK Model SGDV-									
		1R9D	3R5D	5R4D	8R4D	120D	170D	210D	260D	280D	370D
Main Circuit Power Cable	L1, L2, L3	HIV1.25			HIV2.0		HIV3.5		HIV5.5	HIV8	HIV14
Servomotor Main Circuit Cable	U, V, W	HIV1.25			HIV2.0		HIV3.5	HIV5.5		HIV8	HIV14
Control Power Cable	24V, 0V	HIV1.25									
External Regenerative Resistor Cable	B1/⊕, B2	HIV1.25					HIV2.0	HIV3.5		HIV5.5	HIV8
Ground Cable	⏚	HIV2.0 min.									

●Wire Type

Wire Type		Allowable Conductor Temperature
Code	Name	˚C
PVC	Polyvinyl chloride insulated wire	–
IV	600 V polyvinyl chloride insulated wire	60
HIV	600 V grade heat-resistant polyvinyl chloride insulated wire	75

●HIV Conversion Chart

HIV	Cross-Sectional Area (mm^2) *1	AWG
HIV 1.25	1.25	16
HIV 2.0	2.0	14
HIV 3.5	3.5	12
HIV 5.5	5.5	10
HIV 8.0	8.0	8
HIV 14	14	6
HIV 22	22	4

*1 Cross-sectional area applies to solid wires

SERVOPACK Main Circuit Wire

The following table shows the size and allowable currents for the wires. Use a wire whose specifications meet or are less than the values in the table.

● 600 V grade heat-resistant polyvinyl chloride insulated wires

Nominal Cross Section Diameter mm^2	AWG size	Allowable Current at Ambient Temperatures A		
		30°C	40°C	50°C
0.5	20	6.6	5.6	4.5
0.75	–	8.8	7.0	5.5
0.9	18	9.0	7.7	6.0
1.25	17 to 16	12.0	11.0	8.5
2.0	14	23	20	16
3.5	12 to 11	33	29	24
5.5	10 to 9	43	38	31
8.0	8	55	49	40
14.0	6 to 5	79	70	57
22.0	4 to 3	91	81	66

Note: The values in the table are only for reference.

IMPORTANT

1 Wire sizes are selected for three cables per bundle at 40˚C ambient temperature with the rated current.
2 Use a wire with a minimum withstand voltage of 600 V for the main circuit.
3 If wires are bundled in PVC or metal ducts, take into account the reduction of the allowable current.
4 Use a heat-resistant wire under high ambient or panel temperatures, where polyvinyl chloride insulated wires will rapidly deteriorate.

Molded-case Circuit Breaker and Fuse Capacity

Main Circuit Power Supply	Applicable Servomotor Max. Capacity kW	SERVOPACK Model SGDV-	Power Supply Capacity per SERVOPACK kVA	Current Capacity		Inrush Current	
				Main Circuit A_{rms}	Control Circuit A_{rms}	Main Circuit A_{0-p}	Control Circuit A_{0-p}
Single-phase 100 V	0.05	R70F	0.2	1.5	0.38	16.5	35
	0.1	R90F	0.3	2.5			
	0.2	2R1F	0.7	5			
	0.4	2R8F	1.4	10			
Three-phase 200 V	0.05	R70A	0.2	1.0	0.2	33	70
	0.1	R90A	0.3	1.0			
	0.2	1R6A	0.6	2.0			
	0.4	2R8A	1	3.0			
	0.5	3R8A	1.4	3.0			33
	0.75	5R5A	1.6	6.0			
	1.0	7R6A	2.3	6.0			
	1.5	120A	3.2	7.3	0.25		
	2.0	180A	4	9.7			
	3.0	200A	5.9	15			
	5.0	330A	7.5	25	0.3	65.5	
	6.0	470A	10.7	29			
	7.5	550A	14.6	37			
	11	590A	21.7	54	0.45	109	48
	15	780A	29.6	73			
Three-phase 400 V	0.5	1R9D	1.1	1.4	1.2	17	–
	1.0	3R5D	2.3	2.9			
	1.5	5R4D	3.5	4.3			
	2.0	8R4D	4.5	5.8	1.4	34	
	3.0	120D	7.1	8.6			
	5.0	170D	11.7	14.5		57	
	6.0	210D	12.4	17.4	1.5	34	
	7.5	260D	14.4	21.7			
	11	280D	21.9	31.8	1.7	68	
	15	370D	30.6	43.4			

Notes: 1 To comply with the low voltage directive, connect a fuse to the input side. Select the fuse or molded-case circuit breaker for the input side from among models that are compliant with UL standards.
The table above also provides the net values of current capacity and inrush current. Select a fuse and a molded-case circuit breaker which meet the breaking characteristics shown below.
· Main circuit, control circuit: No breaking at three-times the current values of the table for 5 s.
· Inrush current: No breaking at the same current values of the table for 20 ms.
2 In accordance with UL standards, the following restrictions apply. Install fuses or circuit breakers listed in accordance with the guidelines of NEC.

SERVOPACK SGDV-	Restrictions
180A,200A	Available rated current for molded-case circuit breaker: 40 A or less
330A	· Available rated current for non-time delay fuse: 70 A or less · Available rated current for time delay fuse: 40 A or less · Do not use single wires.
470A, 550A	· Available rated current for molded-case circuit breaker: 60A or less · Available rated current for non-time delay fuse: 60 A or less
590A, 780A	· Available rated current for molded-case circuit breaker: 100 A or less · Available rated current for non-time delay fuse or time delay fuse: 100 A or less (Available rated current for class J non-time delay or faster fuse: 125 A or less)
210D, 260D	· Available rated current for molded-case circuit breaker: 60 A or less · Available rated current for non-time delay fuse: 60 A or less · Available rated current for time delay fuse: 35 A or less
280D, 370D	· Available rated current for molded-case circuit breaker: 80 A or less · Available rated current for non-time delay fuse: 125 A or less · Available rated current for time delay fuse: 75 A or less

Noise Filters

●Noise Filter Selection

Main Circuit Power Supply	SERVOPACK Model SGDV-	Recommended Noise Filter			Details
		Model	Specifications	Leakage Current	
Single-phase 100 V	R70F,R90F	FN2070-6/07	Single-phase 250V 6A	0.734 mA 230VAC/50Hz	(1)
	2R1F	FN2070-10/07	Single-phase 250V 10A		
	2R8F	FN2070-16/07	Single-phase 250V 16A		
Single-phase 200 V	R70A, R90A, 1R6A	FN2070-6/07	Single-phase 250V 6A	0.734 mA 230VAC/50Hz	
	2R8A	FN2070-10/07	Single-phase 250V 10A		
	5R5A	FN2070-16/07	Single-phase 250V 16A		
	120A	FN350-30/33	Single-phase 250V 30A	5.4 mA 230VAC/50Hz	
Three-phase 200 V	R70A,R90A,1R6A 2R8A,3R8A	FN258L-7/07	Three-phase 480V 7A	0.5 mA 440VAC/50Hz	(2)
	5R5A,7R6A	FN258L-16/07	Three-phase 480V 16A	0.8 mA 440VAC/50Hz	
	120A,180A	HF3020C-UQC	Three-phase 480V 20A	10 mA 440VAC/50Hz	
	200A	HF3030C-UQC	Three-phase 480V 30A		
	330A, 470A	HF3050C-UQC	Three-phase 480V 50A		
	550A	HF3060C-UQC	Three-phase 480V 60A		
	590A, 780A	HF3100C-UQB	Three-phase 480V 100A		(3)
Three- phase 400 V	1R9D,3R5D,5R4D	FN258L-7/07	Three-phase 480V 7A	0.8 mA 440VAC/50Hz	(2)
	8R4D,120D	FN258L-16/07	Three-phase 480V 16A		
	170D	FMAC-0934-5010	Three-phase 480V 35A	160 mA 440VAC/50Hz	(3)
	210D, 260D	HF3050C-UQC	Three-phase 480V 50A	10 mA 440VAC/50Hz	(2)
	280D, 370D	HF3080C-UQB	Three-phase 480V 80A		(3)

Note: RoHS-compliant models are not available. Contact the manufactures when in need of an RoHS-compliant model.


IMPORTANT


Some noise filters have large leakage currents. The grounding measures taken also affect the extent of the leakage current. If necessary, select an appropriate leakage current detector or leakage current breaker taking into account the grounding measures that are used and leakage current from the noise filter. Contact the manufacturer of the noise filter for details

Noise Filters



● External Dimensions (Units: mm)

(1) FN Type (by Schaffner EMC, Inc.)



Model		FN2070-6/07	FN2070-10/07	FN2070-16/07
Dimensional Drawings				
External Dimensions	Code	Dimensions		
	A	113.5±1	156±1	119±0.5
	B	57.5±1		85.5±1
	C	45.4±1.2		57.6±1
	D	94±1	130.5±1	98.5±1
	F	103±0.3	143±0.3	109±0.3
	J	25±0.2		40±0.2
	K	8.4±0.5		8.6±0.5
	L	32.4±0.5		–
	M	4.4±0.1	5.3±0.1	4.4±0.1
	N	6±0.1		7.4±0.1
	P	0.9±0.1		1.2±0.1
	Q	–		66±0.3
	R	–		51±0.2
	S	38±0.5		–

Model	FN350-30/33
Dimensional Drawings	

(2) FN Type and HF Type

Model		FN Type [by Schaffner EMC, Inc.]		HF Type [by SOSHIN ELECTRIC CO., LTD.]	
		FN258L-7/07	FN258L-16/07	HF3020C-UQC HF3030C-UQC	HF3050C-UQC HF3060C-UQC
Dimensional Drawings					
External Dimensions mm	Code	Dimensions		Dimensions	
	A	225±1	305±1	236	256
	B	126±0.8	142±0.8	221	241
	C	50±0.6	55±0.6	206	226
	D	225±0.8	275±0.8	184	204
	E	240±0.5	290±0.5	105	115
	F	25±0.3	30±0.3	90	100
	G	6.5±0.2		76	86
	H	300±10		122	127
	J	1±0.1		5.5×7 Dia.	5.5×7 Dia.
	K	–		M5	M5
	L	9±1		M5	M5
	M	–		16	16
	N	–		13	13
	O	M5		51.4	51.4
	P	AWG16	AWG14	13	13
	Q	–		61.1	61.1

(3) HF Type and FS Type

Model	HF Type [by SOSHIN ELECTRIC CO., LTD.]	FMAC Type [by Schurter, Inc.]
	HF3080C-UQB HF3100C-UQB	FMAC-0934-5010
External Dimensions mm		

Surge Absorber



●Surge Absorber Selection

The surge absorber (for lightning surge) absorbs lightning surge and prevents faulty operation in or damage to electronic circuits.

Main Circuit Power Supply	SERVOPACK Model SGDV-	Recommended Surge Absorber
Single-phase 100 V	□□□F	LT-C12G801WS
Three-phase 200 V	□□□A	LT-C32G801WS
Three-phase 400 V	□□□D	LT-C35G102WS

●External Dimensions (Units: mm)

Model: LT-C32G801WS, LT-C35G102WS, LT-C12G801WS [by SOSHIN ELECTRIC CO., LTD.]

External Dimensions	Internal Connection Diagram
	

*: No L2 is on the LT-C12G801WS surge absorber.

●Magnetic Contactor Selection


A magnetic contactor is required to make the AC power to SERVOPACK ON/OFF sequence externally. Be sure to attach a surge absorber (for switching surge) (surge absorber unit etc.) to the excitation coil of the magnetic contactor.


Main Circuit Power Supply	SERVOPACK Model SGDV-	Magnetic Contactor	
		Model	Specifications
Single-phase 100 V	R70F,R90F,2R1F	SC-03	(RoHS)
	2R8F	SC-4-1	(RoHS)
Three-phase 200 V	R70A,R90A,1R6A,2R8A,3R8A	SC-03	(RoHS)
	5R5A,7R6A,120A	SC-4-1	(RoHS)
	180A,200A	SC-5-1	(RoHS)
	330A, 470A	SC-N1	(RoHS)
	550A	SC-N2	(RoHS)
	590A	SC-N2S	(RoHS)
	780A	SC-N3	(RoHS)
Three-phase 400 V	1R9D,3R5D,5R4D	SC-4-1/G	Coil 24 VDC (RoHS)
	8R4D,120D	SC-5-1/G	Coil 24 VDC (RoHS)
	170D, 260D	SC-N1/G	Coil 24 VDC (RoHS)
	280D, 370D	SC-N2S/G	Coil 24 VDC (RoHS)

Note: Contact Fuji Electric FA Components & Systems Co., Ltd.


●External Dimensions (Units: mm)



· SC-03





Mounting Hole Dimensions




Aux. Contact	Structure
1a	
1b	


- Mounting methods : The following methods ①,②,③ are available.
  ①…34 × (48 to) 52
  ②…30 × 48
  ③…35 × 60
- Mounting screw : 2-M4

Use the two mounting holes on the diagonal line to mount a contactor.


Approx. Mass : 0.32 kg



· SC-4-1





Mounting Hole Dimensions



Aux. Contact	Structure
1a	
1b	


- Mounting methods : The following methods ①,w are available.
  ①…34 × (48 to) 52
  w…35 × 60
- Mounting screw : 2-M4


Use the two mounting holes on the diagonal line to mount a contactor.

Approx. Mass : 0.36 kg


Magnetic Contactor




· SC-5-1





Mounting Hole Dimensions




Aux. Contact	Structure
2a	
1a1b	
2b	


- Mounting methods : The following methods ①,② are available.
  ①…54 × (56 to) 60
  ②…50 × 60
- Mounting screw : 2-M4

Use the two mounting holes on the diagonal line to mount a contactor.


Approx. Mass: 0.38 kg



· SC-4-1/G





Mounting Hole Dimensions




Aux. Contact	Structure
1a	
1b	


- Mounting methods : The following methods ①,② are available.
  ①…34 × (48 to) 52
  ②…35 × 60
- Mounting screw : 2-M4

Use the two mounting holes on the diagonal line to mount a contactor.


Approx. Mass : 0.6 kg



· SC-5-1/G





Mounting Hole Dimensions




Aux. Contact	Structure
2a	
1a1b	
2b	


- Mounting methods : The following methods ①,② are available.
  ①…54 × (56 to) 60
  ②…50 × 60
- Mounting screw : 2-M4

Use the two mounting holes on the diagonal line to mount a contactor.

Approx. Mass : 0.62 kg


· SC-N2S/G






∗: For two side mounting,
aux. contact blocks are attached.

Mounting Hole Dimensions



Structure





Approx. Mass: 1.4 kg

- Mounting methods : The following methods ①,w are available.
  ①…70 × 75 w…(55 to) 65 × 90
- Mounting screw : 2-M4

Use the two mounting holes on the diagonal line to mount a contactor.


· SC-N1, SC-N2





*: For two side mounting,
aux. contact blocks attached.


Mounting Hole Dimensions



- Mounting methods :
  The following methods ①,② are available.
  ①…70 × 75 ②…(55 to) 65 × 90
- Mounting screw : 2-M4

Use the two mounting holes on the diagonal line to mount a contactor.

Structure





*: These contacts are used if the auxiliary contacts consist of four normally open (NO) and four normally close (NC) contacts.

Note: The terminals of the auxiliary contacts are numbered differently than conventional terminals. The numbers in parentheses use the conventional method.

Approx. Mass: 0.59 kg


· SC-N2S, SC-N3





∗: For two side mounting,
aux. contact blocks attached.


Mounting Hole Dimensions



- Mounting methods :
  The following methods ①,② are available.
  ①…70 × 75 ②…(55 to) 60 × 90
- Mounting screw : 2-M4

Use the two mounting holes on the diagonal line to mount a contactor.

Structure





*: These contacts are used if the auxiliary contacts consist of four normally open (NO) and four normally close (NC) contacts.

Note: The terminals of the auxiliary contacts are numbered differently than conventional terminals. The numbers in parentheses use the conventional method.

Approx. Mass: 1.1 kg


· SC-N1/G





∗: For two side mounting,
aux. contact blocks attached.


Mounting Hole Dimensions



- Mounting methods :
  The following methods ①,② are available
  ①…(60 to)65 × 70 ②…45(to 50) × 70
- Mounting screw : 2-M4

Use the two mounting holes on the diagonal line to mount a contactor.

Structure



*: These contacts are used if the auxiliary contacts consist of four normally open (NO) and four normally close (NC) contacts.

Note: The terminals of the auxiliary contacts are numbered differently than conventional terminals. The numbers in parentheses use the conventional method.

Approx. Mass: 0.82 kg

AC/DC Reactors

●Selection


If power supply harmonic suppression is needed, connect a DC reactor between the three-phase 200 V or three-phase 400 V SERVOPACK main circuit terminals⊖1 and⊖2. Also, connect an AC reactor to single-phase 100 V SERVOPACK main circuit terminal L1 in series.

Select AD/DC reactors according to the SERVOPACK ratings.

Main Circuit Power Supply	SERVOPACK SGDV-	AC/DC Reactor Model	Inductance mH	Rated Current A
Single-phase 100 V	R70F	X5053	20.0	2.0
	R90F			
	2R1F	X5054	5.0	3.0
	2R8F	X5056	2.0	5.0
Three-phase 200 V	R70A	X5061	2.0	4.8
	R90A			
	1R6A			
	2R8A			
	3R8A			
	5R5A			
	7R6A			
	120A	X5060	1.5	8.8
	180A			
	200A	X5059	1.0	14.0
	330A	X5068	0.47	26.8
	470A	–	–	–
	550A			
	590A			
	780A			
Three-phase 400 V	1R9D	X5074	4.7	1.5
	3R5D	X5075	3.3	4.5
	5R4D			
	8R4D	X5076	2.2	8.6
	120D			
	170D	X5077	1.5	14.1
	210D	–	–	–
	260D			
	280D			
	370D			

Note: RoHS-compliant models are not available. The last digit of an RoHS-compliant model number is R. Contact the manufacturers when selecting an RoHS- compliant model.

●External Dimensions (Units: mm)



AC/DC Reactor Model	External Dimensions									Approx. Mass kg
	A	B	C	D	E	F	G	H Dia.	I Dia.	
X5053	35	52	90	105	35	45	50	4	4.3	0.6
X5054	35	52	80	95	30	40	45	4	4.5	0.4
X5056	35	52	80	95	30	40	45	4	4.3	0.4
X5059	50	74	125	140	35	45	60	5	5.3	1.1
X5060	40	59	105	140	35	45	60	5	5.3	1.1
X5061	35	52	80	95	35	45	50	4	4.3	0.5
X5068	50	74	125	155	53	66	75	5	6.4	1.9
X5074	30	47	70	85	28	38	45	4	4.3	0.3
X5075	40	59	100	120	40	50	55	4	4.3	0.9
X5076	50	74	125	140	35	45	60	5	4.3	1.1
X5077	50	74	125	155	53	66	75	5	5.3	1.9

Holding Brake Power Supply Unit

●Holding Brake Power Supply Unit

IMPORTANT


- We recommend opening or closing the circuit for the holding brake's power supply so that switching will occur on the AC side of the holding brake power supply unit. This will reduce brake operation time compared to switching on the DC side.
- When switching on the DC side, install an extra surge absorber (for lightning surge) apart from the surge absorber (for lightning surge) built in the brake circuit near the brake coil, in order to prevent damage to the brake coil from surge voltage.
- Holding brake power supply units for 24 VDC are not provided by Yaskawa. Please obtain these from other manufacturers. Do not connect holding brake power supply units for different output voltages to SERVOPACKs. Overcurrent may result in burning.

- Model
  200 V input: LPSE-2H01-E
  100 V input: LPDE-1H01-E

- Specifications
  Rated output voltage: 90 VDC
  Maximum output current: DC 1.0 A
  Lead wire length: 500 mm each
  Maximum ambient temperature: 60°C
  Lead wires: Color coded (refer to the table below)


AC input		Brake end
100 V	200 V	
Blue/white	Yellow/white	Red/black

- External Dimensions (Units: mm)




- Internal Circuits
  We recommend opening or closing the circuit for the holding brake's power supply so that switching will occur on the AC side of the holding brake power supply unit. This will reduce brake operation time compared to switching on the DC side.
  When switching on the DC side, install an extra surge absorber apart from the surge absorber built in the brake circuit near the brake coil, in order to prevent damage to the brake coil from surge voltage.

  Brake Power Supply for 200 VAC
  Internal Circuit for Model: LPSE-2H01-E



  Brake Power Supply for 100 VAC
  Internal Circuit for Model: LPDE-1H01-E



Regenerative Resistors

●Regenerative Power and Regenerative Resistance


The rotational energy of driven machine such as servomotor is returned to the SERVOPACK. This is called regenerative power. The regenerative power is absorbed by charging the smoothing capacitor, but when the chargeable energy is exceeded, the regenerative power is further consumed by the regenerative resistor.

The servomotor is driven in regeneration state in the following circumstances:


- While decelerating to a stop during acceleration and deceleration operation.
- Continuous operation on the vertical axis.
- During continuous operation with the servomotor rotated from the load side (negative load).

A servomotor may not be operated with an overhanging load, which tends to continuously rotate the motor. following figures show a typical example of such a load.

- DO NOT use the servomotor with the Vertical Axis Motor Drive without Counterweight



- DO NOT use the servomotor with the Feeding Motor Drive



IMPORTANT

- Never operate servomotors with an overhanging load. Doing so will cause the SERVOPACKs' regenerative brake to be applied continuously and the regenerative energy of the load may exceed the allowable range causing damage to the SERVOPACK.
- The regenerative brake capacity of the SGDV SERVOPACKs is rated for short-term operation approximately equivalent to the time it takes to decelerate to a stop.

External regenerative resistors are sometimes required by the AC servo drive capacity selection program SigmaJunmaSize+. When using an external regenerative resistor, parameter Pn600 must be set.

For details, refer to 3.6.2 Setting Regenerative Resistor Capacity on *"Σ-V Series User's Manual Design and Maintenance."* (manual no. SIEP S800000 45)

●Regenerative Resistor Selection

Select regenerative resistors in the following manner. External resistors are to be provided by users.

Voltage	SERVOPACK Model SGDV-	Built-in Regenerative Resistor	Necessity of External Regenerative Resistors	Necessity of External Regenerative Resistors
Single-phase 100 V	□□□F	None	Basically Not Required	No built-in regenerative resistor is provided, however, normally an external regenerative resistor is not required. Install external regenerative resistors when the smoothing capacitor in SERVOPACK cannot process all the regenerative power.
Three-phase 200 V	R70A, R90A, 1R6A, 2R8A			
	3R8A, 5R5A, 7R6A 120A, 180A, 200A, 330A	Standard Equipment*1	Basically Not Required	A built-in regenerative resistor is provided as standard. Install external regenerative resistors when the built-in regenerative resistor cannot process all the regenerative power.
	470A, 550A 590A, 780A	None	Required*2	No built-in regenerative resistor is provided, so the external regenerative resistor is required. If the external resistor is not connected with the SERVOPACK, the alarm 300 is detected as a regeneration error alarm.
Three-phase 400 V	1R9D, 3R5D, 5R4D 8R4D, 120D, 170D	Standard Equipment*1	Basically Not Required	A built-in regenerative resistor is provided as standard. Install external regenerative resistors when the built-in regenerative resistor cannot process all the regenerative power.
	210D, 260D, 280D, 370D	None	Required*2	No built-in regenerative resistor is provided, so the external regenerative resistor is required. If the external resistor is not connected with the SERVOPACK, the alarm 300 is detected as a regeneration error alarm.

*1: For specifications of built-in regenerative resistors, refer to the next page.
*2: Regenerative resistor units are available. For details, refer to page 337.

Regenerative Resistors

●Specifications of Built-in Regenerative Resistor

The following table shows the specifications of the SERVOPACK's built-in resistor and the amount of regenerative power (average values) that it can process.

Applicable SERVOPACK SGDV-		Specifications of Built-in Resistor		Regenerative Power Processed by Built-in Resistor*1	Minimum Allowable Resistance
		Resistance Ω	Capacity W	W	Ω
Single-phase 100 V	□□□F	–	–	–	40
Three-phase 200 V	R70A,R90A, 1R6A,2R8A	–	–	–	40
	3R8A, 5R5A, 7R6A	50	40	8	40
	120A	20	50	10	20
	180A, 200A	12	80	16	12
	330A	8	180	36	8
	470A	(6.25)*2	(880)*2	(180)*2	5.8
	550A, 590A, 780A	(3.13)*3	(1760)*3	(350)*3	2.9
Three-phase 400 V	1R9D, 3R5D, 5R4D	108	70	14	73
	8R4D, 120D	45	140	28	44
	170D	32	180	36	28
	210D,260D	(18)*4	(880)*4	(180)*4	18
	280D,370D	(14.25)*5	(1760)*5	(350)*5	14.25

*1: The average regenerative power that can be handled is 20% of the rated capacity of the regenerative resistor built into the SERVOPACK.
*2: For the optional JUSP-RA04-E regenerative resistor unit.
*3: For the optional JUSP-RA05-E regenerative resistor unit.
*4: For the optional JUSP-RA18-E regenerative resistor unit.
*5: For the optional JUSP-RA19-E regenerative resistor unit.

●References for External Resistor (by Iwaki Musen Kenkyusho Co., Ltd.)

Model	Specifications
RH120	70 W,1 to 100 Ω
RH150	90 W,1 to 100 Ω
RH220□	120 W,1 to 100 Ω
RH300C	200 W,1 to 10 kΩ
RH500	300 W,1 to 30 Ω

Notes: 1 Contact the manufacturers when in need of an RoHS-compliant model.
2 When using an external regenerative resistor, parameter Pn600 must be set.
For details, refer to 3.6.2 Setting Regenerative Resistor Capacity on "Σ-V Series User's Manual Design and Maintenance." (manual no. SIEP S800000 45)

RH120(N) 10Ω K

Model
N: Noniductive Winding

Resistance


Tolerance	
Code	Tolerance
K	±10%
J	±5%
H	±3%

● Specifications

Resistance Tolerance	K : ±10% J : ±5% H : ±3%
Temperature Resistance Characteristics	±400PPM / ℃ (20 Ω max.), ±260PPM / ℃ (20 Ω min.)
Withstand Voltage	2000 VAC / min. ΔR: ± (0.1%+0.05 Ω)
Insulation Resistance	500 VDC,20 MΩ min.
Short-time Overload	When 10 times of rated power is applied for five seconds, ΔR: ±(2%+0.05 Ω)
Life	1000 hours of repeating the operation ON for 90 minutes and OFF for 30 minutes, ΔR: ±(5%+0.05 Ω)
Heat Resistance	Not ignite after having applied 10 times of rated power for one minute
Operating temperature	−25℃ to +150℃

● External Dimensions (Units: mm)

RH120, 150, 220




Lead wire length L = 300

Model	Rated Power	Resistance
RH120	70 W	1Ω to 100Ω
RH150	90 W	1Ω to 100Ω
RH220	120 W	1Ω to 100Ω


Dimensions	A	B	C	D	E	F	G
RH120	182	150	172	16	42	22	20
RH150	212	180	202	16	44	24	30
RH220	230	200	220	15	60	24	20

RH220B




Lead wire length : L = 500
Rated power : 120 W
Resistance : 1 Ω to 100 Ω

RH300C



Lead wire length : L = 300
Rated power : 200 W
Resistance : 1 Ω to 10 kΩ

RH500



Lead wire length : L =450
Rated power : 300 W
Resistance : 1 Ω to 30 Ω

External Regenerative Resistor


●Regenerative Resistor Unit

SERVOPACK Model SGDV-	Regenerative Resistor Unit Model	Specifications	Allowable Power Loss
470A	JUSP-RA04-E	6.25 Ω,880 W	180 W
550A, 590A, 780A	JUSP-RA05-E	3.13 Ω,1760 W	350 W
210D, 260D	JUSP-RA18-E	18 Ω,880 W	180 W
280D, 370D	JUSP-RA19-E	14.25 Ω,1760 W	350 W

Note: Only when using the regenerative resistors above, parameter Pn600 does not need to be set.

● External Dimensions


(1) JUSP-RA04-E, -RA05-E




Units: mm

Model	W	H	D	M1	M2	Approx. Mass
JUSP-RA04-E	220	350	92	180	335	4 kg
JUSP-RA05-E	300	350	95	250	335	7 kg

(2) JUSP-RA18-E



(3) JUSP-RA19-E




Servomotor Capacity Selection Examples

Use the AC servo drive capacity selection program SigmaJunmaSize+ to select servomotor capacity.
The program can be downloaded for free from our web site (http://www.e-mechatronics.com/).


●Selection Example for Speed Control

Mechanical Specifications



- Load speed: $\upsilon_L = 15$ m/min
- Linear motion section mass: $m = 250$ kg
- Ball screw length: $\ell_B = 1.0$ m
- Ball screw diameter: $d_B = 0.02$ m
- Ball screw lead: $P_B = 0.01$ m
- Ball screw material density: ρ =7.87×103 kg/m^3
- Gear ratio: 1/2 (R = 2)
- Gear + coupling moment of inertia : $J_G = 0.40\times10^{-4}$ kg·m^2
- Feeding times: $n = 40$ times/min
- Feeding distance: $\ell = 0.275$ m
- Feeding time: $tm = 1.2$ s max.
- Friction coefficient: $\mu = 0.2$
- Mechanical efficiency: $\eta = 0.9$ (90%)

(1) Speed Diagram



$$t = \frac{60}{n} = \frac{60}{40} = 1.5\ (s)$$

where $ta = td$

$$ta = tm - \frac{60\ell}{\upsilon_L} = 1.2 - \frac{60\times0.275}{15} = 1.2 - 1.1 = 0.1\ (s)$$

$$tc = 1.2 - 0.1\times2 = 1.0\ (s)$$

(2) Rotation Speed

·Load axis rotation speed $n_L = \frac{\upsilon_L}{P_B} = \frac{15}{0.01} = 1500\ (\text{min}^{-1})$

·Motor shaft rotation speed Gear ratio 1/R = 1/2 (R=2)
Therefore, $n_M = n_L \cdot R = 1500 \times 2 = 3000\ (\text{min}^{-1})$

(3) Load torque

$$T_L = \frac{9.8\mu \cdot m \cdot P_B}{2\pi R \cdot \eta} = \frac{9.8\times0.2\times250\times0.01}{2\pi\times2\times0.9} = 0.43\ (\text{N}\cdot\text{m})$$

(4) Load Moment of Inertia

·Linear motion section $J_{L1} = m\left(\frac{P_B}{2\pi R}\right)^2 = 250\times\left(\frac{0.01}{2\pi\times2}\right)^2 = 1.58\times10^{-4}\ (\text{kg}\cdot\text{m}^2)$

·Ball screw $J_B = \frac{\pi}{32}\rho\cdot\ell_B\cdot d_B{}^4\cdot\frac{1}{R^2} = \frac{\pi}{32}\times7.87\times10^3\times1.0\times(0.02)^4\cdot\frac{1}{2^2} = 0.31\times10^{-4}\ (\text{kg}\cdot\text{m}^2)$

·Coupling $J_G = 0.40\times10^{-4}\ (\text{kg}\cdot\text{m}^2)$

·Load moment of inertia at motor shaft $J_L = J_{L1} + J_B + J_G = (1.58 + 0.31 + 0.40)\times10^{-4} = 2.29\times10^{-4}\ (\text{kg}\cdot\text{m}^2)$

(5) Load Moving Power

$$P_O = \frac{2\pi n_M \cdot T_L}{60} = \frac{2\pi\times3000\times0.43}{60} = 135(\text{W})$$

Servomotor Capacity Selection Examples

(6) Load Acceleration Power

$$Pa = \left(\frac{2\pi}{60}\ n_M\right)^2 \frac{J_L}{ta} = \left(\frac{2\pi}{60} \times 3000\right)^2 \times \frac{2.29 \times 10^{-4}}{0.1} = 226\ (\mathrm{W})$$

(7) Servomotor Provisional Selection

(a) Selecting Conditions

- $T_L \leqq$ Motor rated torque
- $\dfrac{(P_o + P_a)}{2} <$ Provisionally selected servomotor rated output $< (P_o + P_a)$
- $n_M \leqq$ Motor rated speed
- $J_L \leqq$ Allowable load moment of inertia

The followings satisfy the conditions.
·Servomotor SGMJV-02A

(b) Specifications of the Provisionally Selected Servomotor

·Rated output	: 200 (W)
·Rated motor speed	: 3000 ($\mathrm{min^{-1}}$)
·Rated torque	: 0.637 (N·m)
·Instantaneous peak torque	: 2.23 (N·m)
·Servomotor moment of inertia	: 0.259×10^{-4} ($\mathrm{kg \cdot m^2}$)
·Allowable load moment of inertia	: $0.259 \times 10^{-4} \times 15 = 3.885 \times$ 10-4 ($\mathrm{kg \cdot m^2}$)

(8) Verification on the Provisionally Selected Servomotor

·Required acceleration torque: $T_P = \dfrac{2\pi n_M (J_M + J_L)}{60ta} + T_L = \dfrac{2\pi \times 3000 \times (0.259 + 2.29) \times 10^{-4}}{60 \times 0.1} + 0.43$

$\fallingdotseq$ 1.23 (N·m) < Instantaneous peak torque · · · Satisfactory

·Required deceleration torque: $T_S = \dfrac{2\pi n_M (J_M + J_L)}{60td} - T_L = \dfrac{2\pi \times 3000 \times (0.259 + 2.29) \times 10^{-4}}{60 \times 0.1} - 0.43$


$\fallingdotseq$ 0.37 (N·m) < Instantaneous peak torque · · · Satisfactory

·Torque effective value: $Trms = \sqrt{\dfrac{T_P^2 \cdot ta + T_L^2 \cdot tc + Ts^2 \cdot td}{t}} = \sqrt{\dfrac{(1.23)^2 \times 0.1 + (0.43)^2 \times 1.0 + (0.37)^2 \times 0.1}{1.5}}$

$\fallingdotseq$ 0.483 (N·m) < Rated torque · · · Satisfactory

(9) Result

The provisionally selected servomotor is confirmed to be applicable.
The torque diagram is shown below.




Servomotor Capacity Selection Examples

Use the AC servo drive capacity selection program SigmaJunmaSize+ to select servomotor capacity.
The program can be downloaded for free from our web site (http://www.e-mechatronics.com/).


●Selection Example for Position Control

Mechanical Specifications



- Load speed: $\upsilon_L = 15$ m/min
- Linear motion section mass: $m = 80$ kg
- Ball screw length: $\ell_B = 0.8$ m
- Ball screw diameter: $d_B = 0.016$ m
- Ball screw lead: $P_B = 0.005$ m
- Ball screw material density: $\rho = 7.87 \times 103$ kg/m^3
- Coupling mass: $mc = 0.3$ kg
- Coupling outer diameter: $dc = 0.03$ m
- Positioning times: $n = 40$ times/min
- Positioning distance: $\ell = 0.25$ m
- Positioning time: $tm = 1.2$ s max.
- Electrical stop accuracy: $\delta = \pm 0.01$ mm
- Friction coefficient: $\mu = 0.2$
- Mechanical efficiency: $\eta = 0.9$ (90%)

(1) Speed Diagram



$$t = \frac{60}{n} = \frac{60}{40} = 1.5(\text{s})$$

Where $ta = td$, $ts = 0.1$(s)

$$ta = tm - ts - \frac{60\ell}{\upsilon_L} = 1.2 - 0.1 - \frac{60 \times 0.25}{15} = 0.1(\text{s})$$

$$tc = 1.2 - 0.1 \times 2 = 1.0(\text{s})$$

(2) Rotation Speed

·Load axis rotation speed $n_L = \frac{\upsilon_L}{P_B} = \frac{15}{0.005} = 3000(\text{min}^{-1})$

·Motor shaft rotation speed with direct coupling: Gear ratio 1/R = 1/1

Therefore, $n_M = n_L \cdot R = 3000 \times 1 = 3000$ (min^{-1})

(3) Load Torque

$$T_L = \frac{9.8\mu \cdot m \cdot P_B}{2\pi R \cdot \eta} = \frac{9.8 \times 0.2 \times 80 \times 0.005}{2\pi \times 1 \times 0.9} = 0.139(\text{N}\cdot\text{m})$$

(4) Load Moment of Inertia

·Liner motion section $J_{L1} = m\left(\frac{P_B}{2\pi R}\right)^2 = 80 \times \left(\frac{0.005}{2\pi \times 1}\right)^2 = 0.507 \times 10^{-4}(\text{kg}\cdot\text{m}^2)$

·Ball screw $J_B = \frac{\pi}{32}\rho \cdot \ell_B \cdot d_B^4 = \frac{\pi}{32} \times 7.87 \times 10^3 \times 0.8 \times (0.0016)^4 = 0.405 \times 10^{-4}(\text{kg}\cdot\text{m}^2)$

·Coupling $Jc = \frac{1}{8} mc \cdot dc^4 = \frac{1}{8} \times 0.3 \times (0.03)^2 = 0.338 \times 10^{-4}(\text{kg}\cdot\text{m}^2)$

·Load moment of inertia at the motor shaft

$J_L = J_{L1} + J_B + Jc = 1.25 \times 10^{-4}$ (kg · m^2)

Servomotor Capacity Selection Examples

(5) Load Moving Power

$$P_O = \frac{2\pi n_M \cdot T_L}{60} = \frac{2\pi \times 3000 \times 0.139}{60} = 43.7(\mathrm{W})$$

(6) Load Acceleration Power

$$Pa = \left(\frac{2\pi}{60}\ n_M\right)^2 \frac{J_L}{ta} = \left(\frac{2\pi}{60} \times 3000\right)^2 \times \frac{1.25 \times 10^{-4}}{0.1} = 123.4(\mathrm{W})$$

(7) Provisionally Servomotor Selection

(a) Selecting Conditions

- $T_L \leqq$ Motor rated torque
- $\frac{(P_o + P_a)}{2} <$ Provisionally selected servomotor rated output $< (P_o + P_a)$
- $n_M \leqq$ Motor rated speed
- $J_L \leqq$ Allowable load moment of inertia

The followings satisfy the conditions.
·Servomotor SGMJV-01A

(b) Specifications of Servomotor

·Rated output	: 100 (W)
·Rated motor speed	: 3000 ($\mathrm{min^{-1}}$)
·Rated torque	: 0.318 (N·m)
·Instantaneous peak torque	: 1.11 (N·m)
·Servomotor rotor moment of inertia	: 0.0665×10^{-4} ($\mathrm{kg \cdot m^2}$)
·Allowable load moment of inertia	: $0.0665 \times 10^{-4} \times 20 = 1.33 \times 10^{-4}$ ($\mathrm{kg \cdot m^2}$)
·Encoder resolution	: 20 bit (1048576P/rev)

(8) Verification on Provisionally Selected Servomotor

·Required acceleration torque: $T_P = \frac{2\pi n_M (J_M + J_L)}{60ta} + T_L = \frac{2\pi \times 3000 \times (0.0665 + 1.25) \times 10^{-4}}{60 \times 0.1} + 0.139$

$\fallingdotseq$ 0.552 (N·m) < Instantaneous peak torque · · · Satisfactory

·Required deceleration torque: $T_S = \frac{2\pi n_M (J_M + J_L)}{60td} - T_L = \frac{2\pi \times 3000 \times (0.0665 + 1.25) \times 10^{-4}}{60 \times 0.1} - 0.139$

$\fallingdotseq$ 0.275 (N·m) < Instantaneous peak torque · · · Satisfactory

·Torque effective value: $Trms = \sqrt{\frac{T_P^2 \cdot ta + T_L^2 \cdot tc + Ts^2 \cdot td}{t}} = \sqrt{\frac{(0.552)^2 \times 0.1 + (0.139)^2 \times 0.9 + (0.275)^2 \times 0.1}{1.5}}$

$\fallingdotseq$ 0.192 (N·m) < Rated torque · · · Satisfactory

The above confirms that the provisionally selected servomotor is sufficient. In the next step, their performance in position control are checked.

(9) PG Feedback Pulse Dividing Ratio: Setting of Electronic Gear Ratio $\left(\frac{B}{A}\right)$

As the electrical stop accuracy $\delta = \pm 0.01$mm, take the position detection unit $\Delta\ell = 0.01$mm/pulse.

$$\frac{P_B}{\Delta\ell} \times \left(\frac{B}{A}\right) = \frac{5}{0.01} \times \left(\frac{B}{A}\right) = 1048576$$

$$k = \left(\frac{B}{A}\right) = \frac{1048576}{500}$$

(10) Reference Pulse Frequency

$$vs = \frac{1000 v_L}{60 \times \Delta\ell} = \frac{1000 \times 15}{60 \times 0.01} = 25{,}000(\text{pps})$$

(11) Error Counter Pulses

Position loop gain $K_P = 40$ (1/s)

$$\varepsilon = \frac{vs}{K_P} = \frac{25{,}000}{40} = 625(\text{pulse})$$

(12) Electrical Stop Accuracy

$$\pm\Delta\varepsilon = \pm \frac{\varepsilon}{(\text{SERVOPACK control range}) \times \frac{n_M}{n_R}} = \pm \frac{625}{5000 \times \frac{3000}{3000}} \fallingdotseq \pm 0.125 < \pm 1(\text{pulse}) = \pm 0.01(\text{mm})$$

The above results confirm that the selected servomotor is applicable for the position control.

Selecting Regenerative Resistors

(1) Simple Calculation

When driving a servomotor with the horizontal axis, check the external regenerative resistor requirements using the calculation method shown below.

(a) SGDV-□□□F, -R70A, -R90A, -1R6A, and -2R8A SERVOPACKs

These SERVOPACKs do not have built-in regenerative resistors. The energy that can be charged with capacitors is shown in the following table. If the rotational energy in the servomotor exceeds these values, then connect an external regenerative resistor.

Voltage	Applicable SERVOPACK	Regenerative Energy that Can be Processed (joules)	Remarks
Single-phase 100 V	SGDV-R70F, R90F, 2R1F	26.4	Value when main circuit input voltage is 100 VAC
	SGDV-2R8F	44.1	
Three-phase 200V	SGDV-R70A, -R90A, -1R6A	24.2	Value when main circuit input voltage is 200 VAC
	SGDV-2R8A	31.7	

Calculate the rotational energy (Es) in the servomotor from the following equation:

$Es = J \times (n_M)^2/182$ (joules)

· $J = J_M + J_L$

· J_M: Servomotor rotor moment of inertia (kg·m^2)

· J_L: Load converted to shaft moment of inertia (kg·m^2)

· n_M: Rotation speed used by servomotor (min^{-1})

(b) SERVOPACKs other than (a)


SERVOPACKs other than SGDV-□□□F, -R70A, -R90A, -1R6A, and -2R8A have built-in regenerative resistors. The allowable frequencies for just the servomotor in acceleration and deceleration operation, during the rotation speed cycle from 0 (min^{-1}) to the maximum rotation speed to 0, are summarized in the following table.

Convert the data into the values obtained with actual rotation speed and load moment of inertia to determine whether an external regenerative resistor is needed.

Voltage	Servomotor Model	Allowable Frequencies in Regenerative Mode (time/min)													
		03	05	06	08	09	10	13	15	20	25	30	40	44	50
Three-phase 200 V	SGMJV-□□	–	–	–	15	–	–	–	–	–	–	–	–	–	–
	SGMAV-□□	–	–	74	31	–	20	–	–	–	–	–	–	–	–
	SGMPS-□□	–	–	–	11	–	–	–	7	–	–	–	–	–	–
	SGMGV-□□A	39	29	–	–	6	–	6	–	7	–	9*	–	6	–
	SGMSV-□□A	–	–	–	–	–	13	–	21	28	21	10	16	–	12
Three-phase 400V	SGMGV-□□D	68	51	–	–	10	–	8	–	13	–	7	–	6	–
	SGMSV-□□D	–	–	–	–	–	24	–	30	49	38	17	16	–	12

*: This value is "4," when used in combination with SGDV-200A SERVOPACK.

Operating Conditions for Allowable Regenerative Frequency Calculation



Use the following equation to calculate the allowable frequency for regeneration mode operation

$$\text{Allowable frequency} = \frac{\text{Allowable frequency for Seromotor only}}{(1+n)} \times \left(\frac{\text{Max. rotation speed}}{\text{Rotation speed}}\right)^2 \text{(time/min)}$$

· $n = J_L / J_M$

· J_M: Servomotor rotor moment of inertia (kg·m^2)

· J_L: Load converted to shaft moment of inertia (kg·m^2)

(c) SGDV-470A, -550A, -590A, -780A SERVOPACKs

These SERVOPACKs do not have built-in regenerative resistors. The following table shows the allowable regenerative frequencies when the JUSP-RA04-E or JUSP-RA05-E regenerative resistor is used together with an applicable SERVOPACK.


The servomotor driving conditions and the conversion equation for the allowable regenerative frequencies to the rotation speed and load moment of inertia are the same as that shown in (b) on the previous page.

Voltage	Servomotor Model	Allowable Frequencies in Regenerative Mode (time/min)				
		55	70	75	1A	1E
Three-phase 200 V	SGMGV-□□A	24	–	34	39	31
	SGMSV-□□A	–	124	–	–	–

Selecting Regenerative Resistors

(2) Calculating the Regenerative Energy

This section shows the procedure for calculating the regenerative resistor capacity when acceleration and deceleration operation is as shown in the following diagram



● Calculation Procedure

The procedure for calculating the regenerative capacity is as follows:

Step	Item	Symbol	Equation
1	Calculate the rotational energy of the servomotor.	E_S	$E_S = Jn_M^2/182$
2	Calculate the energy consumed by load loss during the deceleration period	E_L	$E_L = (\pi/60)n_M T_L t_D$
3	Calculate the energy lost from servomotor winding resistance.	E_M	(Value calculated from (4) Servomotor Winding Resistance Loss diagrams) × t_D
4	Calculate the SERVOPACK energy that can be absorbed.	E_C	Calculate from (3) SERVOPACK's Absorbable Energy diagrams.
5	Calculate the energy consumed by the regenerative resistor.	E_K	$E_K = E_S - (E_L + E_M + E_C)$
6	Calculate the required regenerative resistor capacity (W).	W_K	$W_K = E_K/(0.2 \times T)$

Note: 1 The "0.2" in the equation for calculating W_K is the value for when the regenerative resistor's utilized load ratio is 20%.

2 The units for the various symbols are as follows:

E_S to E_K: Energy joules (J)
W_K: Regenerative resistor required capacity (W)
J: $(= J_M + J_L)$(kg·m^2)
n_M: Servomotor rotation speed (min^{-1})
T_L: Load torque (N·m)
t_D: Deceleration stopping time (s)
T: Servomotor repeat operation period (s)

If the above calculation determines that the amount of regenerative power (W_K) processed by the built-in resistor is not exceeded, then an external regenerative resistor is not required. Refer to Specifications of Built-in Regenerative Resistor on page 336 for regenerative resistors built into SERVOPACKs. If the amount of regenerative power that can be processed by the built-in resistor is exceeded, then install an external regenerative resistor for the capacity obtained from the above calculation.

If the energy consumed by load loss (in step 2 above) is unknown, then perform the calculation using $E_L = 0$.

When the operation period in regeneration mode is continuous, add the following items to the above calculation procedure in order to find the required capacity (W) for the regenerative resistor.


· Energy for continuous regeneration mode operation period: E_G (joules)
· Energy consumed by regenerative resistor: $E_K = E_S - (E_L + E_M + E_C) + E_G$
· Required capacity of regenerative resistor: $W_K = E_K/(0.2 \times T)$


Here, $E_G = (2\pi/60)\, n_{MG} T_G t_G$


· T_G : Servomotor's generated torque in continuous regeneration mode operation period (N·m)
· n_{MG} : Servomotor rotation speed for same operation period as above (min^{-1})
· t_G : Same operation period as above(s)


(3) SERVOPACK's Absorbable Energy


The following diagrams show the relationship between the SERVOPACK's input power supply voltage and its absorbable energy.












Selecting Regenerative Resistors


(4) Servomotor Winding Resistance Loss


The following diagrams show the relationship, for each servomotor, between the servomotor's generated torque and the winding resistance loss.

(a) SGMJV Rotary Servomotors




(b) SGMAV Rotary Servomotors








(c) SGMPS Rotary Servomotors




(d) SGMGV Rotary Servomotors












(e) SGMSV Rotary Servomotors







Selecting Regenerative Resistors


(f) SGMCS Direct Drive Servomotors








(g) SGLGW Linear Servomotors
















(h) SGLFW Linear Servomotors


Model: SGLFW-20A




Model: SGLFW-35A




Model: SGLFW-50A




Model: SGLFW-1ZA




Model: SGLFW-35D



Model: SGLFW-50D





Model: SGLFW-1ZD





Selecting Regenerative Resistors


(i) SGLTW Linear Servomotors


















(i) SGLTW Linear Servomotors (cont'd)













(j) SGLCW Cylinder Type Linear Servomotors













Selecting Regenerative Resistors

(k) SGT Linear Sliders











Example of Connection to Machine Controller MP2□□□



*: The ALM signal is output for five seconds or less when the power is turned ON. Take this into consideration when designing the power ON sequence. The ALM signal actuates the alarm detection relay "1Ry" to stop the main circuit power supply to the SERVOPACK.

Notes: 1 Only signals applicable to Machine Controller MP2□□□ and Yaskawa's SGDV SERVOPACK are shown in the diagram.
2 The main circuit power supply is a three-phase 200 VAC SERVOPACK input in the example.
3 Note that incorrect connection will cause damage to the Machine Controller and SERVOPACK. Take particular care to wire correctly.
4 Open the signal lines not to be used.
5 The above connection diagram shows only X-axis connection. When using another axes, make connection to the SERVOPACK in the same way.
6 The normally closed (N.C.) input terminals not to be used at the Machine Controller I/O connector section must be short-circuited at the connector.
7 Make the setting so that the servo can be turned ON/OFF by the /S-ON signal.
8 The SERVOPACK has a built-in safety function to protect prevent anyone in the vicinity from being injured by unexpected motion. But, in order to use the function, the circuit for CN8 is required to be configured. When not using the function, use SERVOPACKs with the Safety Jumper Connector connected.


Example of Connection to MP2200 / MP2300 Motion Module SVA-01



*: represents twisted-pair wires.

Notes:
1 Connection cables (model: JEPMC-W 2040-□□) to connect the SERVOPACK to the MP2200/MP2300 are provided by Yaskawa. For details, see “Machine Controller MP2200/MP2300 Motion Module User’s Manual” (manual no. YEA-SIEPC88070016).
2 Only signals applicable to MP2200 / MP2300 Motion Module SVA-01 and Yaskawa’s SGDV SERVOPACK are shown in the diagram.
3 The main circuit power supply is a three-phase 200 VAC SERVOPACK input in the example.
4 Note that incorrect connection will cause damage to the Machine Controller and SERVOPACK. Take particular care to wire correctly.
5 Open the signal lines not to be used.
6 The above connection diagram shows only X-axis connection. When using another axes, make connection to the SERVOPACK in the same way.
7 The normally closed (N.C.) input terminals not to be used at the Machine Controller I/O connector section must be short-circuited at the connector.
8 Make the setting so that the servo can be turned ON/OFF by the /S-ON signal.
9 The SERVOPACK has a built-in safety function to protect prevent anyone in the vicinity from being injured by unexpected motion. But, in order to use the function, the circuit for CN8 is required to be configured. When not using the function, use SERVOPACKs with the Safety Jumper Connector connected.


Example of Connection to MP920 4-axis Analog Module SVA-01



*: represents twisted-pair wires.

Notes:
1 Connection cables (model: JEPMC-W6050-□□) to connect the SERVOPACK to the MP920 are provided by Yaskawa. For details, see "Machine Controller MP920 User's Manual Design and Maintenance" (manual no. SIEZ-C887-2.1).
2 Only signals applicable to MP920 4-axes Analog Module SVA-01 and Yaskawa's SGDV SERVOPACK are shown in the diagram.
3 The main circuit power supply is a three-phase 200 VAC SERVOPACK input in the example.
4 Note that incorrect connection will cause damage to the Machine Controller and SERVOPACK. Take particular care to wire correctly.
5 Open the signal lines not to be used.
6 The above connection diagram shows only X-axis connection. When using another axes, make connection to the SERVOPACK in the same way.
7 The normally closed (N.C.) input terminals not to be used at the Machine Controller I/O connector section must be short-circuited at the connector.
8 Make the setting so that the servo can be turned ON/OFF by the /S-ON signal.
9 The SERVOPACK has a built-in safety function to protect prevent anyone in the vicinity from being injured by unexpected motion. But, in order to use the function, the circuit for CN8 is required to be configured. When not using the function, use SERVOPACKs with the Safety Jumper Connector connected.

Example of Connection to OMRON's Motion Control Unit




*1: Use a battery when using an absolute encoder.
No battery is needed for CN1 (between21, 22) when using an encoder cable with a battery.
· Battery for CN1 : ER6VC3N (3.6 V, 2000 mA)
· Battery for battery unit : JUSP-BA01-E (3.6 V, 1000 mA)

*2: represents twisted-pair wires.

Notes: 1 Only signals applicable to OMRON Corporation's MC unit and Yaskawa's SGDV SERVOPACK are shown in the diagram.
2 The main circuit power supply is a three-phase 200 VAC SERVOPACK input in the example.
3 Note that incorrect connection will cause damage to the MC unit and SERVOPACK.
Take particular care to wire correctly.
4 Open the signal lines not to be used.
5 The above connection diagram shows only X-axis connection. When using another axes, make connection to the SERVOPACK in the same way.
6 The normally closed (N.C.) input terminals not to be used at the motion control unit I/O connector section must be short-circuited at the connector.
7 Make the setting so that the servo can be turned ON/OFF by the /S-ON signal.
8 The SERVOPACK has a built-in safety function to prevent anyone in the vicinity from being injured by unexpected motion. But, in order to use the function, the circuit for CN8 is required to be configured. When not using the function, use SERVOPACKs with the Safety Jumper Connector connected.

Example of Connection to OMRON's Position Control Unit




*1: The ALM signal is output for five seconds or less when the power is turned ON. Take this into consideration when designing the power ON sequence. The ALM signal actuates the alarm detection relay "1Ry" to stop the main circuit power supply to the SERVOPACK.
*2: Set parameter Pn200.0 = 1 or 6.
*3: Connect the shield wire to the connector shell.

*4 represents twisted-pair wires.

Notes: 1 Only signals applicable to OMRON Corporation's position control unit and Yaskawa's SGDV SERVOPACK are shown in the diagram.
2 The main circuit power supply is a three-phase 200 VAC SERVOPACK input in the example.
3 Note that incorrect connection will cause damage to the position control unit and SERVOPACK. Take particular care to wire correctly.
4 Open the signal lines not to be used.
5 The above connection diagram shows only X-axis connection. When using another axes, make connection to the SERVOPACK in the same way.
6 The normally closed (N.C.) input terminals not to be used at the position control unit I/O connector section must be short-circuited at the connector.
7 Make the setting so that the servo can be turned ON/OFF by the /S-ON signal.
8 The SERVOPACK has a built-in safety function to prevent anyone in the vicinity from being injured by unexpected motion. But, in order to use the function, the circuit for CN8 is required to be configured. When not using the function, use SERVOPACKs with the Safety Jumper Connector connected.

Example of Connection to Mitsubishi's AD72 Positioning Unit (SERVOPACK in Speed Control)




*1: The ALM signal is output for five seconds or less when the power is turned ON. Take this into consideration when designing the power ON sequence. The ALM signal actuates the alarm detection relay "1Ry" to stop the main circuit power supply to the SERVOPACK.
*2: Pin numbers are the same both for X-axis and Y-axis.
*3: Connect the shield wire to the connector shell.

*4: represents twisted-pair wires.

Notes: 1 Only signals applicable to Mitsubishi Electric Corporation's AD72 positioning unit and Yaskawa's SGDV SERVOPACK are shown in the diagram.
2 The main circuit power supply is a three-phase 200 VAC SERVOPACK input in the example.
3 Note that incorrect connection will cause damage to the positioning unit and SERVOPACK. Take particular care to wire correctly.
4 Open the signal lines not to be used.
5 The above connection diagram shows only X-axis connection. When using another axes, make connection to the SERVOPACK in the same way.
6 The normally closed (N.C.) input terminals not to be used at the positioning unit I/O connector section must be short-circuited at the connector.
7 Make the setting so that the servo can be turned ON/OFF by the /S-ON signal.
8 The SERVOPACK has a built-in safety function to prevent anyone in the vicinity from being injured by unexpected motion. But, in order to use the function, the circuit for CN8 is required to be configured. When not using the function, use SERVOPACKs with the Safety Jumper Connector connected.

Example of Connection to Mitsubishi's AD75 Positioning Unit (SERVOPACK in Position Control)




*1: represents twisted-pair wires.

*2: The ALM signal is output for five seconds or less when the power is turned ON. Take this into consideration when designing the power ON sequence. The ALM signal actuates the alarm detection relay "1Ry" to stop the main circuit power supply to the SERVOPACK.

Notes: 1 Only signals applicable to Mitsubishi Electric Corporation's AD75 positioning unit and Yaskawa's SGDV SERVOPACK are shown in the diagram.
2 The main circuit power supply is a three-phase 200 VAC SERVOPACK input in the example.
3 Note that incorrect connection will cause damage to the positioning unit and SERVOPACK. Take particular care to wire correctly.
4 Open the signal lines not to be used.
5 The above connection diagram shows only X-axis connection. When using another axes, make connection to the SERVOPACK in the same way.
6 The normally closed (N.C.) input terminals not to be used at the positioning unit I/O connector section must be short-circuited at the connector.
7 Make the setting so that the servo can be turned ON/OFF by the /S-ON signal.
8 The SERVOPACK has a built-in safety function to prevent anyone in the vicinity from being injured by unexpected motion. But, in order to use the function, the circuit for CN8 is required to be configured. When not using the function, use SERVOPACKs with the Safety Jumper Connector connected.

Example of Connection to Mitsubishi's QD75D□ Positioning Unit (SERVOPACK in Positioning Control)



*1: represents twisted-pair wires.

*2: The ALM signal is output for five seconds or less when the power is turned ON. Take this into consideration when designing the power ON sequence. The ALM signal actuates the alarm detection relay "1Ry" to stop the main circuit power supply to the SERVOPACK.

Notes: 1 Only signals applicable to Mitsubishi Electric Corporation's QD75D□ positioning unit and Yaskawa's SGDV SERVOPACK are shown in the diagram.
2 The main circuit power supply is a three-phase 200 VAC SERVOPACK input in the example.
3 Note that incorrect connection will cause damage to the positioning unit and SERVOPACK. Take particular care to wire correctly.
4 Open the signal lines not to be used.
5 The above connection diagram shows only X-axis connection. When using another axes, make connection to the SERVOPACK in the same way.
6 The normally closed (N.C.) input terminals not to be used at the positioning unit I/O connector section must be short-circuited at the connector.
7 Make the setting so that the servo can be turned ON/OFF by the /S-ON signal.
8 The SERVOPACK has a built-in safety function to prevent anyone in the vicinity from being injured by unexpected motion. But, in order to use the function, the circuit for CN8 is required to be configured. When not using the function, use SERVOPACKs with the Safety Jumper Connector connected.



Yaskawa America, Inc.
Drives & Motion Division

2121 Norman Drive South
Waukegan, IL 60085
Tel: 1-800-YASKAWA (927-5292) • Fax: 1-847-887-7310
MotionSupport@yaskawa.com • www.yaskawa.com

Document YEA-KAEPS80000042 • Rev: F-4 • 04/13/11 • © 2011